



## OVP Guide to Using Processor Models

### Model Specific Information for variant ARM\_Cortex-A72MPx4

#### Imperas Software Limited

Imperas Buildings, North Weston  
Thame, Oxfordshire, OX9 2HA, UK  
docs@imperas.com



Author	Imperas Software Limited
Version	0.5
Filename	OVP_Model_Specific_Information_arm_Cortex-A72MPx4.pdf
Created	3 October 2017
Status	OVP Standard Release

## **Copyright Notice**

All rights reserved. This software and documentation contain information that is the property of Imperas Software Limited. The software and documentation are furnished under a license agreement and may be used or copied only in accordance with the terms of the license agreement. No part of the software and documentation may be reproduced, transmitted, or translated, in any form or by any means, electronic, mechanical, manual, optical, or otherwise, without prior written permission of Imperas Software Limited, or as expressly provided by the license agreement.

## **Right to Copy Documentation**

The license agreement with Imperas permits licensee to make copies of the documentation for its internal use only. Each copy shall include all copyrights, trademarks, service marks, and proprietary rights notices, if any.

## **Destination Control Statement**

All technical data contained in this publication is subject to the export control laws of the United States of America. Disclosure to nationals of other countries contrary to United States law is prohibited. It is the reader's responsibility to determine the applicable regulations and to comply with them.

## **Disclaimer**

IMPERAS SOFTWARE LIMITED., AND ITS LICENSORS MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

## **Model Release Status**

This model is released as part of OVP releases and is included in OVPworld packages. Please visit [OVPworld.org](http://OVPworld.org).

## Table of Contents

1 Overview.....	5
1.1 Description.....	5
1.2 Licensing.....	5
1.3 Limitations.....	6
1.4 Verification.....	6
1.5 Features.....	6
1.5.1 Core Features.....	6
1.5.2 Memory System.....	6
1.5.3 Advanced SIMD and Floating-Point Features.....	7
1.5.4 Generic Timer.....	7
1.5.5 Generic Interrupt Controller.....	7
1.6 Integration Support.....	7
1.6.1 Memory Transaction Query.....	7
1.6.2 Page Table Walk Query.....	7
1.6.3 Artifact Page Table Walks.....	8
1.6.4 MMU and Page Table Walk Events.....	8
1.6.5 Artifact Address Translations.....	8
1.6.6 Halt Reason Introspection.....	8
1.6.7 System Register Access Monitor.....	8
1.6.8 System Register Implementation.....	9
2 Configuration.....	9
2.1 Location.....	9
2.2 GDB Path.....	9
2.3 Semi-Host Library.....	9
2.4 Processor Endian-ness.....	9
2.5 QuantumLeap Support.....	9
2.6 Processor ELF Code.....	9
3 Other Variants in this Model.....	9
4 Bus Ports.....	11
5 Net Ports.....	12
6 FIFO Ports.....	17
7 Parameters.....	17
8 Execution Modes.....	22
9 Exceptions.....	23
10 Hierarchy of the model.....	24
10.1 Level 1: MPCORE.....	24
10.2 Level 2: CPU.....	24
11 Model Commands.....	26
11.1 Level 1: MPCORE.....	26
11.2 Level 2: CPU.....	26
12 Registers.....	26
12.1 Level 1: MPCORE.....	26

12.2 Level 2: CPU.....	26
12.2.1 Core.....	26
12.2.2 Core_AAarch64.....	27
12.2.3 Control.....	27
12.2.4 User.....	28
12.2.5 FIQ.....	28
12.2.6 IRQ.....	28
12.2.7 Supervisor.....	29
12.2.8 Monitor.....	29
12.2.9 Hypervisor.....	29
12.2.10 Undefined.....	29
12.2.11 Abort.....	29
12.2.12 SIMD_VFP.....	30
12.2.13 SIMD_VFP_SYS.....	30
12.2.14 SIMD_FP_AAarch64.....	31
12.2.15 AAarch32_32_bit_system.....	32
12.2.16 AAarch32_32_bit_secure_system.....	39
12.2.17 AAarch32_32_bit_non_secure_system.....	39
12.2.18 AAarch32_64_bit_system.....	40
12.2.19 AAarch32_64_bit_secure_system.....	41
12.2.20 AAarch32_64_bit_non_secure_system.....	41
12.2.21 AAarch64_system.....	41
12.2.22 AAarch64_secure_system.....	50
12.2.23 AAarch64_non_secure_system.....	50
12.2.24 AAarch64_SYS_instruction_registers.....	50
12.2.25 Integration_support.....	52
12.2.26 MPCore_distributor.....	53
12.2.27 MPCore_physical_redistributor.....	58
12.2.28 MPCore_processor_interface.....	59
12.2.29 MPCore_virtual_interface_control.....	59
12.2.30 MPCore_virtual_processor_interface.....	60
12.2.31 MPCore_ITS.....	61

## 1 Overview

This document provides the details of an OVP Fast Processor Model variant.

OVP Fast Processor Models are written in C and provide a C API for use in C based platforms. The models also provide a native interface for use in SystemC TLM2 platforms.

The models are written using the OVP VMI API that provides a Virtual Machine Interface that defines the behavior of the processor. The VMI API makes a clear line between model and simulator allowing very good optimization and world class high speed performance.

Most models are provided as a binary shared object and also as source. This allows the download and use of the model binary or the use of the source to explore and modify the model.

The models are run through an extensive QA and regression testing process and most model families are validated using technology provided by the processor IP owners.

There is a companion document (OVP Guide to Using Processor Models) which explains the general concepts of OVP Fast Processor Models and their use. It is downloadable from the OVPworld website documentation pages.

### 1.1 Description

ARM Processor Model

### 1.2 Licensing

Usage of binary model under license governing simulator usage.

Note that for models of ARM CPUs the license includes the following terms:

Licensee is granted a non-exclusive, worldwide, non-transferable, revocable licence to:

If no source is being provided to the Licensee: use and copy only (no modifications rights are granted) the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used to emulate an ARM based system to run application software in a production or live environment.

If source code is being provided to the Licensee: use, copy and modify the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used to emulate an ARM based system to run application software in a production or live environment.

In the case of any Licensee who is either or both an academic or educational institution the purposes shall be limited to internal use.

Except to the extent that such activity is permitted by applicable law, Licensee shall not reverse engineer, decompile, or disassemble this model. If this model was provided to Licensee in Europe, Licensee shall not reverse engineer, decompile or disassemble the Model for the purposes of error correction.

The License agreement does not entitle Licensee to manufacture in silicon any product based on this model.

The License agreement does not entitle Licensee to use this model for evaluating the validity of any ARM patent.

Source of model available under separate Imperas Software License Agreement.

ARMv8 architecture models additionally require a run time model license - contact Imperas for more information.

### ***1.3 Limitations***

Instruction pipelines are not modeled in any way. All instructions are assumed to complete immediately. This means that instruction barrier instructions (e.g. ISB, CP15ISB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. The model does not implement speculative fetch behavior. The branch cache is not modeled.

Caches and write buffers are not modeled in any way. All loads, fetches and stores complete immediately and in order, and are fully synchronous (as if the memory was of Strongly Ordered or Device-nGnRnE type). Data barrier instructions (e.g. DSB, CP15DSB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. Cache manipulation instructions are implemented as NOPs, with the exception of any undefined instruction behavior, which is modeled.

Real-world timing effects are not modeled: all instructions are assumed to complete in a single cycle.

Performance Monitors are implemented as a register interface only.

TLBs are architecturally-accurate but not device accurate. This means that all TLB maintenance and address translation operations are fully implemented but the cache is larger than in the real device.

Debug registers are implemented but non-functional (which is sufficient to allow operating systems such as Linux to boot). Debug state is not implemented.

The GICv3 block is implemented without any ITS. Implementation-defined GICR registers for control of LPIs (GICR\_SETLPIR, GICR\_CLRLPIR, GICR\_INVLPIR, GICR\_INVALLR and GICR\_SYNCR) are all implemented.

The optional SIMD Cryptographic Extension instructions are not supported. AES, SHA1 and SHA2 fields in ID\_AA64ISAR0\_EL1 and ID\_ISAR5\_EL1 registers must be zero.

### ***1.4 Verification***

Models have been extensively tested by Imperas. ARM Cortex-A models have been successfully used by customers to simulate SMP Linux, Ubuntu Desktop, VxWorks and ThreadX on Xilinx Zynq virtual platforms.

### ***1.5 Features***

#### ***1.5.1 Core Features***

AArch64 is implemented at EL3, EL2, EL1 and EL0.

AArch32 is implemented at EL3, EL2, EL1 and EL0.

#### ***1.5.2 Memory System***

Security extensions are implemented (also known as TrustZone). To make non-secure accesses visible externally, override ID\_AA64MMFR0\_EL1.PARange to specify the required physical bus size (32, 36, 40, 42, 44, 48 or 52 bits) and connect the processor to a bus one bit wider (33, 37, 41, 43, 45, 49 or 53 bits, respectively). The extra most-significant bit is the NS bit, indicating a non-secure access. If non-secure accesses are not required to be made visible externally, connect the processor to a bus of exactly the size implied by ID\_AA64MMFR0\_EL1.PARange.

VMSA EL1, EL2 and EL3 stage 1 address translation is implemented. VMSA stage 2 address translation is implemented.

LPA (large physical address extension) is implemented as standard in ARMv8.

### ***1.5.3 Advanced SIMD and Floating-Point Features***

SIMD and VFP instructions are implemented.

The model implements trapped exceptions if FPTrap is set to 1 in MVFR0 (for AArch32) or MVFR0\_EL1 (for AArch64). When floating point exception traps are taken, cumulative exception flags are not updated (in other words, cumulative flag state is always the same as prior to instruction execution, even for SIMD instructions). When multiple enabled exceptions are raised by a single floating point operation, the exception reported is the one in least-significant bit position in FPSCR (for AArch32) or FPCR (for AArch64). When multiple enabled exceptions are raised by different SIMD element computations, the exception reported is selected from the lowest-index-number SIMD operation. Contact Imperas if requirements for exception reporting differ from these.

Trapped exceptions not are implemented in this variant (FPTrap=0)

### ***1.5.4 Generic Timer***

Generic Timer is present. Use parameter override\_timerScaleFactor to specify the counter rate as a fraction of the processor MIPS rate (e.g. 10 implies Generic Timer counters increment once every 10 processor instructions).

### ***1.5.5 Generic Interrupt Controller***

GIC block is implemented (GICv3, including security extensions). Accesses to GIC registers can be viewed externally by connecting to the 32-bit GICRegisters and GICDRegisters bus ports. Secure register accesses are at offset 0x0 on these busses; for example, a secure access to GICD register GICD\_CTLR can be observed by monitoring address 0x00000000 of bus GICDRegisters. Non-secure accesses are at offset 0x80000000 on these busses; for example, a non-secure access to GICD register GICD\_CTLR can be observed by monitoring address 0x80000000 of bus GICDRegisters

The internal GIC block can be disabled by raising signal GICCDISABLE, in which case the GIC needs to be modeled using a platform component instead. Input signals vfiq\_CPU<N> and virq\_CPU<N> can be used by this component to raise virtual FIQ and IRQ interrupts on cores in the cluster if required.

## ***1.6 Integration Support***

This model implements a number of non-architectural pseudo-registers and other features to facilitate integration.

### ***1.6.1 Memory Transaction Query***

Two registers are intended for use within memory callback functions to provide additional information about the current memory access. Register transactPL indicates the processor execution level of the current access (0-3). Note that for load/store translate instructions (e.g. LDRT, STRT) the reported execution level will be 0, indicating an EL0 access. Register transactAT indicates the type of memory access: 0 for a normal read or write; and 1 for a physical access resulting from a page table walk.

### ***1.6.2 Page Table Walk Query***

A banked set of registers provides information about the most recently completed page table walk. There are up to six banks of registers: bank 0 is for stage 1 walks, bank 1 is for stage 2 walks, and banks 2-5 are for stage 2 walks initiated by stage 1 level 0-3 entry lookups,

respectively. Banks 1-5 are present only for processors with virtualization extensions. The currently active bank can be set using register PTWBankSelect. Register PTWBankValid is a bitmask indicating which banks contain valid data: for example, the value 0xb indicates that banks 0, 1 and 3 contain valid data.

Within each bank, there are registers that record addresses and values read during that page table walk. Register PTWBase records the table base address. Registers PTWAddressL0-PTWAddressL3 record the addresses of level 0 to level 3 entries read, respectively, and register PTWAddressValid is a bitmask indicating which address registers contain valid data: for example, the value 0xe indicates that PTWAddressL1-PTWAddressL3 are valid but PTWAddressL0 is not. Registers PTWValueL0-PTWValueL3 contain entry values read at level 0 to level 3. Register PTWInput contains the input address that starts a walk and Register PTWOutput contains the result address (valid only if the page table walk completes). Register PTWValueValid is a bitmask indicating which value registers contain valid data: bits 0-3 indicate PTWValueL0-PTWValueL3, respectively, bit 4 indicates PTWBase, bit 5 indicates PTWInput and bit 6 indicates PTWOutput.

### ***1.6.3 Artifact Page Table Walks***

Registers are also available to enable a simulation environment to initiate an artifact page table walk (for example, to determine the ultimate PA corresponding to a given VA). Register PTWI\_EL1S initiates a secure EL1 table walk for a fetch. Register PTWD\_EL1S initiates a secure EL1 table walk for a load or store (note that current ARM processors have unified TLBs, so these registers are synonymous). Registers PTW[ID]\_EL1NS initiate walks for non-secure EL1 accesses. Registers PTW[ID]\_EL2 initiate EL2 walks. Registers PTW[ID]\_S2 initiate stage 2 walks. Registers PTW[ID]\_EL3 initiate AArch64 EL3 walks. Finally, registers PTW[ID]\_current initiate current-mode walks (useful in a memory callback context). Each walk fills the query registers described above.

### ***1.6.4 MMU and Page Table Walk Events***

Two events are available that allow a simulation environment to be notified on MMU and page table walk actions. Event mmuEnable triggers when any MMU is enabled or disabled. Event pageTableWalk triggers on completion of any page table walk (including artifact walks).

### ***1.6.5 Artifact Address Translations***

A simulation environment can trigger an artifact address translation operation by writing to the architectural address translation registers (e.g. ATS1CPR). The results of such translations are written to an integration support register artifactPAR, instead of the architectural PAR register. This means that such artifact writes will not perturb architectural state.

### ***1.6.6 Halt Reason Introspection***

An artifact register HaltReason can be read to determine the reason or reasons that a processor is halted. This register is a bitfield, with the following encoding: bit 0 indicates the processor has executed a wait-for-event (WFE) instruction; bit 1 indicates the processor has executed a wait-for-interrupt (WFI) instruction; and bit 2 indicates the processor is held in reset.

### ***1.6.7 System Register Access Monitor***

If parameter enableSystemMonitorBus is True, an artifact 32-bit bus "SystemMonitor" is enabled for each PE. Every system register read or write by that PE is then visible as a read or write on this artifact bus, and can therefore be monitored using callbacks installed in the client environment (use opBusReadMonitorAdd/opBusWriteMonitorAdd



or `icmAddBusReadCallback/icmAddBusWriteCallback`, depending on the client API). The format of the address on the bus is as follows:

bits 31:26 - zero

bit 25 - 1 if AArch64 access, 0 if AArch32 access

bit 24 - 1 if non-secure access, 0 if secure access

bits 23:20 - CRm value

bits 19:16 - CRn value

bits 15:12 - op2 value

bits 11:8 - op1 value

bits 7:4 - op0 value (AArch64) or coprocessor number (AArch32)

bits 3:0 - zero

As an example, to view non-secure writes to writes to `CNTFRQ_EL0` in AArch64 state, install a write monitor on address range `0x020e0330:0x020e0333`.

### ***1.6.8 System Register Implementation***

If parameter `enableSystemBus` is `True`, an artifact 32-bit bus "System" is enabled for each PE. Slave callbacks installed on this bus can be used to implement modified system register behavior (use `opBusSlaveNew` or `icmMapExternalMemory`, depending on the client API). The format of the address on the bus is the same as for the system monitor bus, described above.

## **2 Configuration**

### ***2.1 Location***

The model source and object file is found in the VLNV tree at:

`arm.ovpworld.org/processor/arm/1.0`

### ***2.2 GDB Path***

The default GDB for this model is found at:

`$IMPERAS_HOME/lib/$IMPERAS_ARCH/gdb/aarch64-none-elf-gdb`

### ***2.3 Semi-Host Library***

The default semi-host library file is found in the VLNV tree at :

`arm.ovpworld.org/semihosting/armAngel/1.0`

### ***2.4 Processor Endian-ness***

This model can be set to either endian-ness (normally by a pin, or the ELF code).

### ***2.5 QuantumLeap Support***

This processor is qualified to run in a QuantumLeap enabled simulator.

### ***2.6 Processor ELF Code***

ELF codes supported by this model are: , `0xb7` and `0x28`.

## **3 Other Variants in this Model**

Table 1.

<b>Variant</b>
ARMv4T
ARMv4xM
ARMv4
ARMv4TxM
ARMv5xM
ARMv5
ARMv5TxM
ARMv5T
ARMv5TExP
ARMv5TE
ARMv5TEJ
ARMv6
ARMv6K
ARMv6T2
ARMv6KZ
ARMv7
ARM7TDMI
ARM7EJ-S
ARM720T
ARM920T
ARM922T
ARM926EJ-S
ARM940T
ARM946E
ARM966E
ARM968E-S
ARM1020E
ARM1022E
ARM1026EJ-S
ARM1136J-S
ARM1156T2-S
ARM1176JZ-S
Cortex-R4
Cortex-R4F
Cortex-A5UP
Cortex-A5MPx1
Cortex-A5MPx2
Cortex-A5MPx3
Cortex-A5MPx4
Cortex-A8

Cortex-A9UP
Cortex-A9MPx1
Cortex-A9MPx2
Cortex-A9MPx3
Cortex-A9MPx4
Cortex-A7UP
Cortex-A7MPx1
Cortex-A7MPx2
Cortex-A7MPx3
Cortex-A7MPx4
Cortex-A15UP
Cortex-A15MPx1
Cortex-A15MPx2
Cortex-A15MPx3
Cortex-A15MPx4
Cortex-A17MPx1
Cortex-A17MPx2
Cortex-A17MPx3
Cortex-A17MPx4
AArch32
AArch64
Cortex-A53MPx1
Cortex-A53MPx2
Cortex-A53MPx3
Cortex-A53MPx4
Cortex-A57MPx1
Cortex-A57MPx2
Cortex-A57MPx3
Cortex-A57MPx4
Cortex-A72MPx1
Cortex-A72MPx2
Cortex-A72MPx3
Cortex-A72MPx4
MultiCluster

## 4 Bus Ports

Table 2.

Type	Name	min	max	Description
master (initiator)	INSTRUCTION	32	53	
master (initiator)	DATA	32	53	
master (initiator)	GICRegisters	32	32	GIC memory-mapped register block
master (initiator)	GICDRegisters	32	32	GICD memory-mapped register block

## 5 Net Ports

Table 3.

Name	Type	Description
SPI32	input	Shared peripheral interrupt
SPI33	input	Shared peripheral interrupt
SPI34	input	Shared peripheral interrupt
SPI35	input	Shared peripheral interrupt
SPI36	input	Shared peripheral interrupt
SPI37	input	Shared peripheral interrupt
SPI38	input	Shared peripheral interrupt
SPI39	input	Shared peripheral interrupt
SPI40	input	Shared peripheral interrupt
SPI41	input	Shared peripheral interrupt
SPI42	input	Shared peripheral interrupt
SPI43	input	Shared peripheral interrupt
SPI44	input	Shared peripheral interrupt
SPI45	input	Shared peripheral interrupt
SPI46	input	Shared peripheral interrupt
SPI47	input	Shared peripheral interrupt
SPI48	input	Shared peripheral interrupt
SPI49	input	Shared peripheral interrupt
SPI50	input	Shared peripheral interrupt
SPI51	input	Shared peripheral interrupt
SPI52	input	Shared peripheral interrupt
SPI53	input	Shared peripheral interrupt
SPI54	input	Shared peripheral interrupt
SPI55	input	Shared peripheral interrupt
SPI56	input	Shared peripheral interrupt
SPI57	input	Shared peripheral interrupt
SPI58	input	Shared peripheral interrupt
SPI59	input	Shared peripheral interrupt
SPI60	input	Shared peripheral interrupt
SPI61	input	Shared peripheral interrupt
SPI62	input	Shared peripheral interrupt
SPI63	input	Shared peripheral interrupt
SPI64	input	Shared peripheral interrupt
SPI65	input	Shared peripheral interrupt
SPI66	input	Shared peripheral interrupt
SPI67	input	Shared peripheral interrupt
SPI68	input	Shared peripheral interrupt
SPI69	input	Shared peripheral interrupt

SPI70	input	Shared peripheral interrupt
SPI71	input	Shared peripheral interrupt
SPI72	input	Shared peripheral interrupt
SPI73	input	Shared peripheral interrupt
SPI74	input	Shared peripheral interrupt
SPI75	input	Shared peripheral interrupt
SPI76	input	Shared peripheral interrupt
SPI77	input	Shared peripheral interrupt
SPI78	input	Shared peripheral interrupt
SPI79	input	Shared peripheral interrupt
SPI80	input	Shared peripheral interrupt
SPI81	input	Shared peripheral interrupt
SPI82	input	Shared peripheral interrupt
SPI83	input	Shared peripheral interrupt
SPI84	input	Shared peripheral interrupt
SPI85	input	Shared peripheral interrupt
SPI86	input	Shared peripheral interrupt
SPI87	input	Shared peripheral interrupt
SPI88	input	Shared peripheral interrupt
SPI89	input	Shared peripheral interrupt
SPI90	input	Shared peripheral interrupt
SPI91	input	Shared peripheral interrupt
SPI92	input	Shared peripheral interrupt
SPI93	input	Shared peripheral interrupt
SPI94	input	Shared peripheral interrupt
SPI95	input	Shared peripheral interrupt
SPIVector	input	Shared peripheral interrupt vectorized input
periphReset	input	Peripheral reset (active high)
GICCDISABLE	input	GIC CPU interface logic disable (active high, sampled on rising edge of periphReset)
EVENTI	input	Event input signal, active on rising edge
EVENTO	output	Event output signal, active on rising edge
PPI16_CPU0	input	Private peripheral interrupt
PPI17_CPU0	input	Private peripheral interrupt
PPI18_CPU0	input	Private peripheral interrupt
PPI19_CPU0	input	Private peripheral interrupt
PPI20_CPU0	input	Private peripheral interrupt
PPI21_CPU0	input	Private peripheral interrupt
PPI22_CPU0	input	Private peripheral interrupt
PPI23_CPU0	input	Private peripheral interrupt
PPI24_CPU0	input	Private peripheral interrupt
PPI25_CPU0	input	Private peripheral interrupt

PPI26_CPU0	input	Private peripheral interrupt
PPI27_CPU0	input	Private peripheral interrupt
PPI28_CPU0	input	Private peripheral interrupt
PPI29_CPU0	input	Private peripheral interrupt
PPI30_CPU0	input	Private peripheral interrupt
PPI31_CPU0	input	Private peripheral interrupt
CNTVIRQ_CPU0	output	Virtual timer event (active high)
CNTPSIRQ_CPU0	output	Secure physical timer event (active high)
CNTPNSIRQ_CPU0	output	Non-secure physical timer event (active high)
CNTPHIRQ_CPU0	output	Hypervisor physical timer event (active high)
IRQOUT_CPU0	output	IRQ wakeup
FIQOUT_CPU0	output	FIQ wakeup
CLUSTERIDAFF1	input	Configure MPIDR.Aff1
CLUSTERIDAFF2	input	Configure MPIDR.Aff2
VINITHI_CPU0	input	Configure HIVECS mode (SCTLR.V)
CFGEND_CPU0	input	Configure exception endianness (SCTLR.EE)
CFGTE_CPU0	input	Configure exception state at reset (SCTLR.TE)
reset_CPU0	input	Processor reset, active high
fiq_CPU0	input	FIQ interrupt, active high (negation of nFIQ)
irq_CPU0	input	IRQ interrupt, active high (negation of nIRQ)
sei_CPU0	input	System error interrupt, active high
vfiq_CPU0	input	Virtual FIQ interrupt, active high (negation of nVFIQ)
virq_CPU0	input	Virtual IRQ interrupt, active high (negation of nVIRQ)
vsei_CPU0	input	Virtual system error interrupt, active high
AXI_SLVERR_CPU0	input	AXI external abort type (DECERR=0, SLVERR=1)
CP15SDISABLE_CPU0	input	CP15SDISABLE (active high)
SMPEN_CPU0	output	CPUECTLR.SMPEN current value
PPI16_CPU1	input	Private peripheral interrupt
PPI17_CPU1	input	Private peripheral interrupt
PPI18_CPU1	input	Private peripheral interrupt
PPI19_CPU1	input	Private peripheral interrupt
PPI20_CPU1	input	Private peripheral interrupt
PPI21_CPU1	input	Private peripheral interrupt
PPI22_CPU1	input	Private peripheral interrupt
PPI23_CPU1	input	Private peripheral interrupt
PPI24_CPU1	input	Private peripheral interrupt
PPI25_CPU1	input	Private peripheral interrupt
PPI26_CPU1	input	Private peripheral interrupt
PPI27_CPU1	input	Private peripheral interrupt
PPI28_CPU1	input	Private peripheral interrupt

PPI29_CPU1	input	Private peripheral interrupt
PPI30_CPU1	input	Private peripheral interrupt
PPI31_CPU1	input	Private peripheral interrupt
CNTVIRQ_CPU1	output	Virtual timer event (active high)
CNTPSIRQ_CPU1	output	Secure physical timer event (active high)
CNTPNSIRQ_CPU1	output	Non-secure physical timer event (active high)
CNTPHPIRQ_CPU1	output	Hypervisor physical timer event (active high)
IRQOUT_CPU1	output	IRQ wakeup
FIQOUT_CPU1	output	FIQ wakeup
VINITHI_CPU1	input	Configure HIVECS mode (SCTLR.V)
CFGEND_CPU1	input	Configure exception endianness (SCTLR.EE)
CFGTE_CPU1	input	Configure exception state at reset (SCTLR.TE)
reset_CPU1	input	Processor reset, active high
fiq_CPU1	input	FIQ interrupt, active high (negation of nFIQ)
irq_CPU1	input	IRQ interrupt, active high (negation of nIRQ)
sei_CPU1	input	System error interrupt, active high
vfiq_CPU1	input	Virtual FIQ interrupt, active high (negation of nVFIQ)
virq_CPU1	input	Virtual IRQ interrupt, active high (negation of nVIRQ)
vsei_CPU1	input	Virtual system error interrupt, active high
AXI_SLVERR_CPU1	input	AXI external abort type (DECERR=0, SLVERR=1)
CP15SDISABLE_CPU1	input	CP15SDISABLE (active high)
SMPEN_CPU1	output	CPUECTLR.SMPEN current value
PPI16_CPU2	input	Private peripheral interrupt
PPI17_CPU2	input	Private peripheral interrupt
PPI18_CPU2	input	Private peripheral interrupt
PPI19_CPU2	input	Private peripheral interrupt
PPI20_CPU2	input	Private peripheral interrupt
PPI21_CPU2	input	Private peripheral interrupt
PPI22_CPU2	input	Private peripheral interrupt
PPI23_CPU2	input	Private peripheral interrupt
PPI24_CPU2	input	Private peripheral interrupt
PPI25_CPU2	input	Private peripheral interrupt
PPI26_CPU2	input	Private peripheral interrupt
PPI27_CPU2	input	Private peripheral interrupt
PPI28_CPU2	input	Private peripheral interrupt
PPI29_CPU2	input	Private peripheral interrupt
PPI30_CPU2	input	Private peripheral interrupt
PPI31_CPU2	input	Private peripheral interrupt
CNTVIRQ_CPU2	output	Virtual timer event (active high)
CNTPSIRQ_CPU2	output	Secure physical timer event (active high)

CNTPNSIRQ_CPU2	output	Non-secure physical timer event (active high)
CNTPHIRQ_CPU2	output	Hypervisor physical timer event (active high)
IRQOUT_CPU2	output	IRQ wakeup
FIQOUT_CPU2	output	FIQ wakeup
VINITHI_CPU2	input	Configure HIVECS mode (SCTLR.V)
CFGEND_CPU2	input	Configure exception endianness (SCTLR.EE)
CFGTE_CPU2	input	Configure exception state at reset (SCTLR.TE)
reset_CPU2	input	Processor reset, active high
fiq_CPU2	input	FIQ interrupt, active high (negation of nFIQ)
irq_CPU2	input	IRQ interrupt, active high (negation of nIRQ)
sei_CPU2	input	System error interrupt, active high
vfiq_CPU2	input	Virtual FIQ interrupt, active high (negation of nVFIQ)
virq_CPU2	input	Virtual IRQ interrupt, active high (negation of nVIRQ)
vsei_CPU2	input	Virtual system error interrupt, active high
AXI_SLVERR_CPU2	input	AXI external abort type (DECERR=0, SLVERR=1)
CP15SDISABLE_CPU2	input	CP15SDISABLE (active high)
SMPEN_CPU2	output	CPUECTLR.SMPEN current value
PPI16_CPU3	input	Private peripheral interrupt
PPI17_CPU3	input	Private peripheral interrupt
PPI18_CPU3	input	Private peripheral interrupt
PPI19_CPU3	input	Private peripheral interrupt
PPI20_CPU3	input	Private peripheral interrupt
PPI21_CPU3	input	Private peripheral interrupt
PPI22_CPU3	input	Private peripheral interrupt
PPI23_CPU3	input	Private peripheral interrupt
PPI24_CPU3	input	Private peripheral interrupt
PPI25_CPU3	input	Private peripheral interrupt
PPI26_CPU3	input	Private peripheral interrupt
PPI27_CPU3	input	Private peripheral interrupt
PPI28_CPU3	input	Private peripheral interrupt
PPI29_CPU3	input	Private peripheral interrupt
PPI30_CPU3	input	Private peripheral interrupt
PPI31_CPU3	input	Private peripheral interrupt
CNTVIRQ_CPU3	output	Virtual timer event (active high)
CNTPSIRQ_CPU3	output	Secure physical timer event (active high)
CNTPNSIRQ_CPU3	output	Non-secure physical timer event (active high)
CNTPHIRQ_CPU3	output	Hypervisor physical timer event (active high)
IRQOUT_CPU3	output	IRQ wakeup
FIQOUT_CPU3	output	FIQ wakeup
VINITHI_CPU3	input	Configure HIVECS mode (SCTLR.V)



CFGEND_CPU3	input	Configure exception endianness (SCTLR.EE)
CFGTE_CPU3	input	Configure exception state at reset (SCTLR.TE)
reset_CPU3	input	Processor reset, active high
fiq_CPU3	input	FIQ interrupt, active high (negation of nFIQ)
irq_CPU3	input	IRQ interrupt, active high (negation of nIRQ)
sei_CPU3	input	System error interrupt, active high
vfiq_CPU3	input	Virtual FIQ interrupt, active high (negation of nVFIQ)
virq_CPU3	input	Virtual IRQ interrupt, active high (negation of nVIRQ)
vsei_CPU3	input	Virtual system error interrupt, active high
AXI_SLVERR_CPU3	input	AXI external abort type (DECERR=0, SLVERR=1)
CP15SDISABLE_CPU3	input	CP15SDISABLE (active high)
SMPEN_CPU3	output	CPUECTLR.SMPEN current value

## 6 FIFO Ports

No FIFO Ports in this model.

## 7 Parameters

Table 4.

Name	Type	Description
verbose	Boolean	Specify verbosity of output
showHiddenRegs	Boolean	Show hidden registers during register tracing
UAL	Boolean	Disassemble using UAL syntax
disableGICModel	Boolean	Disable the internal GIC model entirely
enableGICv3	Boolean	Enable GICv3 (default: GICv2 only)
enableVFPAAtReset	Boolean	Enable vector floating point (SIMD and VFP) instructions at reset. (Enables cp10/11 in CPACR and sets FPEXC.EN)
enableSystemBus	Boolean	Add 32-bit artifact System bus port, allowing system registers to be externally implemented
enableSystemMonitorBus	Boolean	Add 32-bit artifact SystemMonitor bus port, allowing system register accesses to be externally monitored
distinctMTCores	Boolean	For multi-threaded (MT) processors, simulate threads as separate cores (otherwise, simulate MT threads as a single entity)
compatibility	Enumeration	Specify compatibility mode ISA=0 gdb=1 nopSVC=2
override_debugMask	Uns32	Specifies debug mask, enabling debug output for model components
override_numCPUs	Uns32	Specify the number of cores in a multiprocessor (maximum of 8 for GICv1/ GICv2)

override_affinityMask	Uns32	Specify bitmask of implemented affinity bits in format Aff3:Aff2:Aff1:Aff0 (each a byte)
override_MPIDR_MT	Boolean	Specifies that processor is multithreaded
override_MPIDR_Aff0	Uns32	Override Aff0 field in MPIDR/MPIDR_EL1 register
override_MPIDR_Aff1	Uns32	Override Aff1 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF1 configuration net)
override_MPIDR_Aff2	Uns32	Override Aff2 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF2 configuration net)
override_fcsePresent	Boolean	Specifies that FCSE is present (if true)
override_fpexcDexPresent	Boolean	Specifies that the FPEXC.DEX register field is implemented (if true)
override_advSIMDPresent	Boolean	Specifies that Advanced SIMD extensions are present (if true)
override_vfpPresent	Boolean	Specifies that VFP extensions are present (if true)
override_physicalBits	Uns32	Specifies the implemented physical bus bits (defaults to connected physical bus width)
override_timerScaleFactor	Uns32	Specifies the fraction of MIPS rate to use for MPCore timers (generic timers or global/local/watchdogs depending on implementation). Defaults to 20 for generic timers, 2 for others
override_GICD_NSACRPresent	Boolean	Specifies that optional GICD_NSACR distributor registers are present (GICv2 only)
override_GICD_PPISRPresent	Boolean	Specifies that implementation-specific GICD_PPISR distributor register is present (GICv1 ICDPPIS/ICPPISR, GICv1 and GICv2 only)
override_GICD_SPISRPresent	Boolean	Specifies that implementation-specific GICD_SPISR distributor registers are present (GICv1 ICDSPIS/ICSPISR)
override_GICv3_DistributorBase	Uns64	Specify distributor register block base address (GICv3 only)
override_GICv3_E1NWFPresent	Boolean	Specifies that GICR_CTLR.E1NWF is implemented (GICv3 only)
override_GIC_PPIMask	Uns32	Specify bitmask of implemented PPIs in the GIC (e.g. ID16 is 0x0001, ID31 is 0x8000)
override_GICCDISABLE	Boolean	Specify initial value of GICCDISABLE
override_SCTLR_V	Boolean	Override SCTLR.V with the passed value (enables high vectors)
override_SCTLR_CP15BEN_Present	Boolean	Enable ARMv7 SCTLR.CP15BEN bit (CP15 barrier enable)
override_MIDR	Uns32	Override MIDR/MIDR_EL1 register
override_CTR	Uns32	Override CTR/CTR_EL0 register

override_TLBTR	Uns32	Override TLBTR register
override_CLIDR	Uns32	Override CLIDR/CLIDR_EL1 register
override_AIDR	Uns32	Override AIDR/AIDR_EL1 register
override_CBAR	Uns32	Override Configuration Base Address Register (Corresponds to value on PERIPHBASE input pins)
override_PFR0	Uns32	Override ID_PFR0/ID_PFR0_EL1 register
override_PFR1	Uns32	Override ID_PFR1/ID_PFR1_EL1 register
override_DFR0	Uns32	Override ID_DFR0/ID_DFR0_EL1 register
override_AFR0	Uns32	Override ID_AFR0/ID_AFR0_EL1 register
override_MMFR0	Uns32	Override ID_MMFR0/ID_MMFR0_EL1 register
override_MMFR1	Uns32	Override ID_MMFR1/ID_MMFR1_EL1 register
override_MMFR2	Uns32	Override ID_MMFR2/ID_MMFR2_EL1 register
override_MMFR3	Uns32	Override ID_MMFR3/ID_MMFR3_EL1 register
override_MMFR4	Uns32	Override ID_MMFR4/ID_MMFR4_EL1 register
override_ISAR0	Uns32	Override ID_ISAR0/ID_ISAR0_EL1 register
override_ISAR1	Uns32	Override ID_ISAR1/ID_ISAR1_EL1 register
override_ISAR2	Uns32	Override ID_ISAR2/ID_ISAR2_EL1 register
override_ISAR3	Uns32	Override ID_ISAR3/ID_ISAR3_EL1 register
override_ISAR4	Uns32	Override ID_ISAR4/ID_ISAR4_EL1 register
override_ISAR5	Uns32	Override ID_ISAR5/ID_ISAR5_EL1 register
override_PMCR	Uns32	Override PMCR/PMCR_EL0 register (not functionally significant in the model)
override_PMCEID0	Uns64	Override PMCEID0/PMCEID0_EL0 register (not functionally significant in the model)
override_PMCEID1	Uns64	Override PMCEID1/PMCEID1_EL0 register (not functionally significant in the model)
override_DBGDIDR	Uns32	Override DBGDIDR register (not functionally significant in the model)
override_FPSID	Uns32	Override SIMD/VFP FPSID register
override_MVFR0	Uns32	Override SIMD/VFP MVFR0/MVFR0_EL1 register
override_MVFR1	Uns32	Override SIMD/VFP MVFR1/MVFR1_EL1 register
override_MVFR2	Uns32	Override SIMD/VFP MVFR2/MVFR2_EL1 register
override_FPEXC	Uns32	Override SIMD/VFP FPEXC/FPEXC32_EL2 register
override_GICC_IIDR	Uns32	Override GICC_IIDR register (GICv1 ICCIIDR)

override_GICD_TYPER	Uns32	Override GICD_TYPER register (GICv1 ICDICTR)
override_GICD_TYPER_ITLines	Uns32	Override ITLinesNumber field of GICD_TYPER register (GICv1 ICDICTR)
override_GICD_ICFGRN	Uns32	Override reset value of GICD_ICFGR2...GICD_ICFGRn (GICv1 ICDICFR2...ICDICFRn)
override_GICD_IIDR	Uns32	Override GICD_IIDR register (GICv1 ICDIIDR)
override_GICH_VTR	Uns32	Override GICH_VTR register
override_GICR_IIDR	Uns32	Override GICR_IIDR register (GICv3 and later)
override_GITS_IIDR	Uns32	Override GITS_IIDR register (GICv3 and later)
override_GITS_TYPER	Uns64	Override GITS_TYPER register (GICv3 and later)
override_ICCPMRBits	Uns32	Specify the number of writable bits in GICC_PMR (GICv1 ICCPMR)
override_minICCBPR	Uns32	Specify the minimum possible value for GICC_BPR (GICv1 ICCBPR)
override_ERG	Uns32	Specifies exclusive reservation granule
override_CCSIDR_1I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 1 instruction)
override_CCSIDR_1D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 1 data)
override_CCSIDR_2I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 2 instruction)
override_CCSIDR_2D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 2 data)
override_CCSIDR_3I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 3 instruction)
override_CCSIDR_3D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 3 data)
override_CCSIDR_4I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 4 instruction)
override_CCSIDR_4D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 4 data)
override_CCSIDR_5I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 5 instruction)
override_CCSIDR_5D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 5 data)
override_CCSIDR_6I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 6 instruction)
override_CCSIDR_6D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 6 data)
override_CCSIDR_7I	Uns32	Override CCSIDR/CCSIDR_EL1 (level 7 instruction)

override_CCSIDR_7D	Uns32	Override CCSIDR/CCSIDR_EL1 (level 7 data)
override_RMR	Uns32	Override RMR register alias at highest-implemented exception level
override_RVBAR	Uns64	Override RVBAR register alias at highest-implemented exception level
override_AA64PFR0_EL1	Uns64	Override ID_AA64PFR0_EL1 register
override_AA64PFR1_EL1	Uns64	Override ID_AA64PFR1_EL1 register
override_AA64DFR0_EL1	Uns64	Override ID_AA64DFR0_EL1 register
override_AA64DFR1_EL1	Uns64	Override ID_AA64DFR1_EL1 register
override_AA64AFR0_EL1	Uns64	Override ID_AA64AFR0_EL1 register
override_AA64AFR1_EL1	Uns64	Override ID_AA64AFR1_EL1 register
override_AA64ISAR0_EL1	Uns64	Override ID_AA64ISAR0_EL1 register
override_AA64ISAR1_EL1	Uns64	Override ID_AA64ISAR1_EL1 register
override_AA64MMFR0_EL1	Uns64	Override ID_AA64MMFR0_EL1 register
override_AA64MMFR1_EL1	Uns64	Override ID_AA64MMFR1_EL1 register
override_AA64MMFR2_EL1	Uns64	Override ID_AA64MMFR2_EL1 register
override_DCZID_EL0	Uns32	Override DCZID_EL0 register
override_LORID_EL1	Uns32	Override LORID_EL1 register (ARMv8.1 only)
override_STRoffsetPC12	Boolean	Specifies that STR/STR of PC should do so with 12:byte offset from the current instruction (if true), otherwise an 8:byte offset is used
override_fcseRequiresMMU	Boolean	Specifies that FCSE is active only when MMU is enabled (if true)
override_ignoreBadCp15	Boolean	Specifies whether invalid coprocessor 15 access should be ignored (if true) or cause Invalid Instruction exceptions (if false)
override_SGIDisable	Boolean	Override whether GIC SGIs may be disabled (if true) or are permanently enabled (if false)
override_condUndefined	Boolean	Force undefined instructions to take Undefined Instruction exception even if they are conditional
override_deviceStrongAligned	Boolean	Force accesses to Device and Strongly Ordered regions to be aligned
override_stage1SZMinFault	Boolean	Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ < minimum (by default, clamp to minimum)
override_stage1SZMaxFault	Boolean	Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ > maximum (by default, clamp to maximum)
override_stage2SZMinFault	Boolean	Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ < minimum (by default, clamp to minimum)

override_stage2SZMaxFault	Boolean	Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ > maximum (by default, clamp to maximum)
override_mask_ACTLR_EL1	Uns64	Override mask of writable bits in AArch64 ACTLR_EL1 register, or AArch32 non-secure ACTLR/ACTLR2 pair, if implemented
override_mask_ACTLR_EL2	Uns64	Override mask of writable bits in AArch64 ACTLR_EL2 register, or AArch32 HACTLR/HACTLR2 pair, if implemented
override_mask_ACTLR_EL3	Uns64	Override mask of writable bits in AArch64 ACTLR_EL3 register, or AArch32 secure ACTLR/ACTLR2 pair, if implemented
override_Control_V	Boolean	Override SCTLR.V with the passed value (deprecated, use override_SCTLR_V)
override_MainId	Uns32	Override MIDR register (deprecated, use override_MIDR)
override_CacheType	Uns32	Override CTR register (deprecated, use override_CTR)
override_TLBType	Uns32	Override TLBTR register (deprecated, use override_TLBTR)
override_InstructionAttributes0	Uns32	Override ID_ISAR0 register (deprecated, use override_ISAR0)
override_InstructionAttributes1	Uns32	Override ID_ISAR1 register (deprecated, use override_ISAR1)
override_InstructionAttributes2	Uns32	Override ID_ISAR2 register (deprecated, use override_ISAR2)
override_InstructionAttributes3	Uns32	Override ID_ISAR3 register (deprecated, use override_ISAR3)
override_InstructionAttributes4	Uns32	Override ID_ISAR4 register (deprecated, use override_ISAR4)
override_InstructionAttributes5	Uns32	Override ID_ISAR5 register (deprecated, use override_ISAR5)

## 8 Execution Modes

Table 5.

Name	Code
EL0t	0
EL1t	4
EL1h	5
EL2t	8
EL2h	9
EL3t	12
EL3h	13
User	16
FIQ	17

IRQ	18
Supervisor	19
Monitor	22
Abort	23
Hypervisor	26
Undefined	27
System	31

## 9 Exceptions

Table 6.

<b>Name</b>	<b>Code</b>
Reset	0
Undefined	1
SupervisorCall	2
SecureMonitorCall	3
HypervisorCall	4
PrefetchAbort	5
DataAbort	6
HypervisorTrap	7
IRQ	8
FIQ	9
IllegalState	10
MisalignedPC	11
MisalignedSP	12
SError	13

## 10 Hierarchy of the model

A CPU core may allow the user to configure it to instance many processors of a Symmetrical Multi Processor (SMP). A CPU core may also have sub elements within a processor, for example hardware threading blocks.

OVP processor models can be written to include SMP blocks and to have many levels of hierarchy.

Some OVP CPU models may have a fixed hierarchy, and some may be configured by settings in a configuration register. Please see the register definitions of this model.

This model documentation shows the settings and hierarchy of the default settings for this model variant.

### 10.1 Level 1: MPCORE

This level in the model hierarchy has 2 commands.

This level in the model hierarchy has no register groups.

This level in the model hierarchy has 4 children:

CPU0, CPU1, CPU2 and CPU3

### 10.2 Level 2: CPU

This level in the model hierarchy has 5 commands.

This level in the model hierarchy has 31 register groups:

Table 7.

Group name	Registers
Core	15
Core_AAarch64	33
Control	3
User	7
FIQ	8
IRQ	3
Supervisor	3
Monitor	3
Hypervisor	3
Undefined	3
Abort	3
SIMD_VFP	32
SIMD_VFP_SYS	6
SIMD_FP_AAarch64	32
AArch32_32_bit_system	272
AArch32_32_bit_secure_system	32
AArch32_32_bit_non_secure_system	32



AArch32_64_bit_system	20
AArch32_64_bit_secure_system	4
AArch32_64_bit_non_secure_system	4
AArch64_system	257
AArch64_secure_system	5
AArch64_non_secure_system	5
AArch64_SYS_instruction_registers	55
Integration_support	31
MPCore_distributor	179
MPCore_physical_redistributor	43
MPCore_processor_interface	16
MPCore_virtual_interface_control	11
MPCore_virtual_processor_interface	31
MPCore_ITS	14

This level in the model hierarchy has no children.

## 11 Model Commands

### 11.1 Level 1: MPCORE

Table 8.

Name	Arguments
isync	specify instruction address range for synchronous execution
itrace	enable or disable instruction tracing

### 11.2 Level 2: CPU

Table 9.

Name	Arguments
debugflags	
dumpTLB	[-all]
isync	specify instruction address range for synchronous execution
itrace	enable or disable instruction tracing
validateTLB	[-all] [-verbose]

## 12 Registers

### 12.1 Level 1: MPCORE

No registers.

### 12.2 Level 2: CPU

#### 12.2.1 Core

Table 10.

Name	Bits	Initial value (Hex)		alias	Description
r0	32	0	rw		
r1	32	0	rw		
r2	32	0	rw		
r3	32	0	rw		
r4	32	0	rw		
r5	32	0	rw		
r6	32	0	rw		
r7	32	0	rw		
r8	32	0	rw		
r9	32	0	rw		
r10	32	0	rw		
r11	32	0	rw		frame pointer
r12	32	0	rw		

sp	32	0	rw		stack pointer
lr	32	0	rw		

### 12.2.2 Core\_AAarch64

Table 11.

Name	Bits	Initial value (Hex)		alias	Description
x0	64	0		rw	
x1	64	0		rw	
x2	64	0		rw	
x3	64	0		rw	
x4	64	0		rw	
x5	64	0		rw	
x6	64	0		rw	
x7	64	0		rw	
x8	64	0		rw	
x9	64	0		rw	
x10	64	0		rw	
x11	64	0		rw	
x12	64	0		rw	
x13	64	0		rw	
x14	64	0		rw	
x15	64	0		rw	
x16	64	0		rw	
x17	64	0		rw	
x18	64	0		rw	
x19	64	0		rw	
x20	64	0		rw	
x21	64	0		rw	
x22	64	0		rw	
x23	64	0		rw	
x24	64	0		rw	
x25	64	0		rw	
x26	64	0		rw	
x27	64	0		rw	
x28	64	0		rw	
x29	64	0		rw	frame pointer
x30	64	0		rw	
sp	64	0		rw	stack pointer
pc	64	0		rw	program counter

### 12.2.3 Control

Table 12.

Name	Bits	Initial value (Hex)		alias	Description
fps	32	0	rw		archaic FPSCR view (for gdb)
cpsr	32	3cd	rw		
spsr	32	0	rw		

#### 12.2.4 User

Table 13.

Name	Bits	Initial value (Hex)		alias	Description
r8_usr	32	0	rw		
r9_usr	32	0	rw		
r10_usr	32	0	rw		
r11_usr	32	0	rw		
r12_usr	32	0	rw		
sp_usr	32	0	rw		
lr_usr	32	0	rw		

#### 12.2.5 FIQ

Table 14.

Name	Bits	Initial value (Hex)		alias	Description
r8_fiq	32	0	rw		
r9_fiq	32	0	rw		
r10_fiq	32	0	rw		
r11_fiq	32	0	rw		
r12_fiq	32	0	rw		
sp_fiq	32	0	rw		
lr_fiq	32	0	rw		
spsr_fiq	32	0	rw		

#### 12.2.6 IRQ

Table 15.

Name	Bits	Initial value (Hex)		alias	Description
sp_irq	32	0	rw		
lr_irq	32	0	rw		
spsr_irq	32	0	rw		

### 12.2.7 Supervisor

Table 16.

Name	Bits	Initial value (Hex)		alias	Description
sp_svc	32	0	rw		
lr_svc	32	0	rw		
spsr_svc	32	0	rw		

### 12.2.8 Monitor

Table 17.

Name	Bits	Initial value (Hex)		alias	Description
sp_mon	32	0	rw		
lr_mon	32	0	rw		
spsr_mon	32	0	rw		

### 12.2.9 Hypervisor

Table 18.

Name	Bits	Initial value (Hex)		alias	Description
sp_hyp	32	0	rw		
elr_hyp	32	0	rw		
spsr_hyp	32	0	rw		

### 12.2.10 Undefined

Table 19.

Name	Bits	Initial value (Hex)		alias	Description
sp_undef	32	0	rw		
lr_undef	32	0	rw		
spsr_undef	32	0	rw		

### 12.2.11 Abort

Table 20.

Name	Bits	Initial value (Hex)		alias	Description
sp_abt	32	0	rw		
lr_abt	32	0	rw		
spsr_abt	32	0	rw		

**12.2.12 SIMD\_VFP**

Table 21.

Name	Bits	Initial value (Hex)		alias	Description
d0	64	0		rw	
d1	64	0		rw	
d2	64	0		rw	
d3	64	0		rw	
d4	64	0		rw	
d5	64	0		rw	
d6	64	0		rw	
d7	64	0		rw	
d8	64	0		rw	
d9	64	0		rw	
d10	64	0		rw	
d11	64	0		rw	
d12	64	0		rw	
d13	64	0		rw	
d14	64	0		rw	
d15	64	0		rw	
d16	64	0		rw	
d17	64	0		rw	
d18	64	0		rw	
d19	64	0		rw	
d20	64	0		rw	
d21	64	0		rw	
d22	64	0		rw	
d23	64	0		rw	
d24	64	0		rw	
d25	64	0		rw	
d26	64	0		rw	
d27	64	0		rw	
d28	64	0		rw	
d29	64	0		rw	
d30	64	0		rw	
d31	64	0		rw	

**12.2.13 SIMD\_VFP\_SYS**

Table 22.

Name	Bits	Initial value (Hex)		alias	Description
FPSID	32	41034080	r-		floating-point system ID

FPSCR	32	0	rw		floating-point status/control
FPEXC	32	700	rw		floating-point exception
MVFR0	32	10110222	r-		Media/VFP feature 0
MVFR1	32	12111111	r-		Media/VFP feature 1
MVFR2	32	43	r-		Media/VFP feature 2

### 12.2.14 SIMD\_FP\_AArch64

Table 23.

Name	Bits	Initial value (Hex)		alias	Description
v0	128	-		rw	
v1	128	-		rw	
v2	128	-		rw	
v3	128	-		rw	
v4	128	-		rw	
v5	128	-		rw	
v6	128	-		rw	
v7	128	-		rw	
v8	128	-		rw	
v9	128	-		rw	
v10	128	-		rw	
v11	128	-		rw	
v12	128	-		rw	
v13	128	-		rw	
v14	128	-		rw	
v15	128	-		rw	
v16	128	-		rw	
v17	128	-		rw	
v18	128	-		rw	
v19	128	-		rw	
v20	128	-		rw	
v21	128	-		rw	
v22	128	-		rw	
v23	128	-		rw	
v24	128	-		rw	
v25	128	-		rw	
v26	128	-		rw	
v27	128	-		rw	
v28	128	-		rw	
v29	128	-		rw	
v30	128	-		rw	
v31	128	-		rw	

**12.2.15 AArch32\_32\_bit\_system**

Table 24.

Name	Bits	Initial value (Hex)		alias	Description
ACTLR	32	0	rw		Auxiliary Control
ADFSR	32	0	rw		Auxiliary Data Fault Status
AIDR	32	0	r-		Auxiliary ID
AIFSR	32	0	rw		Auxiliary Instruction Fault Status
AMAIRO	32	0	rw		Auxiliary Memory Attribute Indirection 0
AMAIR1	32	0	rw		Auxiliary Memory Attribute Indirection 1
ATS1CPR	32	-	-w		Address Translate Stage 1 Current State EL1 Read
ATS1CPW	32	-	-w		Address Translate Stage 1 Current State EL1 Write
ATS1CUR	32	-	-w		Address Translate Stage 1 Current State Unprivileged Read
ATS1CUW	32	-	-w		Address Translate Stage 1 Current State Unprivileged Write
ATS1HR	32	-	-w		Address Translate Stage 1 Hyp Mode Read
ATS1HW	32	-	-w		Address Translate Stage 1 Hyp Mode Write
ATS12NSOPR	32	-	-w		Address Translate Stages 1 and 2 Non-Secure Only EL1 Read
ATS12NSOPW	32	-	-w		Address Translate Stages 1 and 2 Non-Secure Only EL1 Write
ATS12NSOUR	32	-	-w		Address Translate Stages 1 and 2 Non-Secure Only Unprivileged Read
ATS12NSOUW	32	-	-w		Address Translate Stages 1 and 2 Non-Secure Only Unprivileged Write
BPIALL	32	-	-w		Branch Predictor Invalidate All
BPIALLIS	32	-	-w		Branch Predictor Invalidate All (IS)
BPIMVA	32	-	-w		Branch Predictor Invalidate by VA
CBAR	32	13080000	rw		Configuration Base Address
CCSIDR	32	701fe00a	r-		Cache Size ID
CLIDR	32	a200023	r-		Cache Level ID
CNTFRQ	32	4c4b40	rw		Counter Frequency
CNTHCTL	32	3	rw		Timer EL2 Control
CNTHP_CTL	32	0	rw		Counter-Timer Hyp Physical Timer Control
CNTHP_TVAL	32	0	rw		Counter-Timer Hyp Physical Timer TimerValue
CNTKCTL	32	0	rw		Timer EL1 Control
CNTP_CTL	32	0	rw		Counter-Timer Physical Timer Control
CNTP_TVAL	32	0	rw		Counter-Timer Physical Timer TimerValue
CNTV_CTL	32	0	rw		Counter-Timer Virtual Timer Control
CNTV_TVAL	32	0	rw		Counter-Timer Virtual Timer TimerValue



CONTEXTIDR	32	0	rw	Context ID
CP15DMB	32	-	-w	CP15 Data Memory Barrier
CP15DSB	32	-	-w	CP15 Data Synchronization Barrier
CP15ISB	32	-	-w	CP15 Instruction Synchronization Barrier
CPACR	32	0	rw	Coprocessor Access Control
CSSCLR	32	0	rw	Cache Size Selection
CTR	32	8444c004	r-	Cache Type
DACR	32	0	rw	Domain Access Control
DBGAUTHSTATUS	32	aa	r-	Debug Authentication Status
DBGBCR0	32	0	rw	Debug Breakpoint Control 0
DBGBCR1	32	0	rw	Debug Breakpoint Control 1
DBGBCR2	32	0	rw	Debug Breakpoint Control 2
DBGBCR3	32	0	rw	Debug Breakpoint Control 3
DBGBCR4	32	0	rw	Debug Breakpoint Control 4
DBGBCR5	32	0	rw	Debug Breakpoint Control 5
DBGBVR0	32	0	rw	Debug Breakpoint Value 0
DBGBVR1	32	0	rw	Debug Breakpoint Value 1
DBGBVR2	32	0	rw	Debug Breakpoint Value 2
DBGBVR3	32	0	rw	Debug Breakpoint Value 3
DBGBVR4	32	0	rw	Debug Breakpoint Value 4
DBGBVR5	32	0	rw	Debug Breakpoint Value 5
DBGBXVR0	32	0	rw	Debug Breakpoint Extended Value 0
DBGBXVR1	32	0	rw	Debug Breakpoint Extended Value 1
DBGBXVR2	32	0	rw	Debug Breakpoint Extended Value 2
DBGBXVR3	32	0	rw	Debug Breakpoint Extended Value 3
DBGBXVR4	32	0	rw	Debug Breakpoint Extended Value 4
DBGBXVR5	32	0	rw	Debug Breakpoint Extended Value 5
DBGCLAIMCLR	32	0	rw	Debug Claim Tag Clear
DBGCLAIMSET	32	0	rw	Debug Claim Tag Set
DBGDCCINT	32	0	rw	DCC Interrupt Enable
DBGDIDR	32	3516d000	r-	Debug ID
DBGDRAR	32	0	r-	Debug ROM Address (32-bit)
DBGDSCRext	32	0	rw	Debug Status and Control
DBGDSCRint	32	0	r-	Debug Status and Control, Internal View
DBGDTRRext	32	0	rw	Debug Data Transfer, Receive, External View
DBGDTRRXint	32	0	rw	Debug Data Transfer, Transmit/Receive
DBGDTRTText	32	0	rw	Debug Data Transfer, Transmit, External View
DBGOSDLR	32	0	rw	Debug OS Double Lock
DBGOSECCR	32	0	rw	Debug OS Lock Exception Catch Control
DBGOSLAR	32	-	-w	Debug OS Lock Access
DBGOSLSR	32	a	r-	Debug OS Lock Status
DBGPRCR	32	0	rw	Debug Power Control

DBGVCR	32	0	rw	Debug Vector Catch
DBGWCR0	32	0	rw	Debug Watchpoint Control 0
DBGWCR1	32	0	rw	Debug Watchpoint Control 1
DBGWCR2	32	0	rw	Debug Watchpoint Control 2
DBGWCR3	32	0	rw	Debug Watchpoint Control 3
DBGWVR0	32	0	rw	Debug Watchpoint Value 0
DBGWVR1	32	0	rw	Debug Watchpoint Value 1
DBGWVR2	32	0	rw	Debug Watchpoint Value 2
DBGWVR3	32	0	rw	Debug Watchpoint Value 3
DCCIMVAC	32	-	-w	Data Cache Line Clean and Invalidate by VA to PoC
DCCISW	32	-	-w	Data Cache Line Clean and Invalidate by Set/Way
DCCMVAC	32	-	-w	Data Cache Line Clean by VA to PoC
DCCMVAU	32	-	-w	Data Cache Line Clean by VA to PoU
DCCSW	32	-	-w	Data Cache Line Clean by Set/Way
DCIMVAC	32	-	-w	Data Cache Line Invalidate by VA to PoC
DCISW	32	-	-w	Data Cache Line Invalidate by Set/Way
DFAR	32	0	rw	Data Fault Address
DFSR	32	0	rw	Data Fault Status
DL1DATA0	32	0	rw	Data L1 Data 0
DL1DATA1	32	0	rw	Data L1 Data 1
DL1DATA2	32	0	rw	Data L1 Data 2
DL1DATA3	32	0	rw	Data L1 Data 3
DL1DATA4	32	0	rw	Data L1 Data 4
DLR	32	0	rw	Debug Link
DSPSR	32	0	rw	Debug Saved Program Status
DTLBIALL	32	-	-w	Invalidate Entire Data TLB
DTLBIASID	32	-	-w	Invalidate Data TLB by ASID
DTLBIMVA	32	-	-w	Invalidate Data TLB by VA
HACR	32	0	rw	Hyp Auxiliary Configuration
HACTLR	32	0	rw	Hyp Auxiliary Control
HADFSR	32	0	rw	Hyp Auxiliary Data Fault Status
HAIFSR	32	0	rw	Hyp Auxiliary Instruction Fault Status
HAMAIRO	32	0	rw	Hyp Auxiliary Memory Attribute Indirection 0
HAMAIR1	32	0	rw	Hyp Auxiliary Memory Attribute Indirection 1
HCPtr	32	33ff	rw	Hyp Coprocessor Trap
HCR	32	0	rw	Hyp Configuration
HCR2	32	0	rw	Hyp Configuration 2
HDCR	32	6	rw	Hyp Debug Configuration
HDFAR	32	0	rw	Hyp Data Fault Address
HIFAR	32	0	rw	Hyp Instruction Fault Address

HMAIR0	32	0	rw	Hyp Memory Attribute Indirection 0
HMAIR1	32	0	rw	Hyp Memory Attribute Indirection 1
HPFAR	32	0	rw	Hyp IPA Fault Address
HSCTLR	32	30c50838	rw	Hyp System Control
HSR	32	0	rw	Hyp Syndrome
HSTR	32	0	rw	Hyp System Trap
HTCR	32	80800000	rw	Hyp Translation Control
HTPIDR	32	0	rw	Hyp Thread and Process ID
HVBAR	32	0	rw	Hyp Vector Base Address
ICC_AP0R0	32	0	rw	Interrupt Controller Active Priorities Group 0, 0
ICC_AP1R0	32	0	rw	Interrupt Controller Active Priorities Group 1, 0
ICC_BPR0	32	2	rw	Interrupt Controller Binary Point 0
ICC_BPR1	32	3	rw	Interrupt Controller Binary Point 1
ICC_CTLR	32	400	rw	Interrupt Controller Control
ICC_DIR	32	-	-w	Interrupt Controller Deactivate Interrupt
ICC_EOIR0	32	-	-w	Interrupt Controller End of Interrupt 0
ICC_EOIR1	32	-	-w	Interrupt Controller End of Interrupt 1
ICC_HPPIR0	32	3ff	r-	Interrupt Controller Highest Priority Pending Interrupt 0
ICC_HPPIR1	32	3ff	r-	Interrupt Controller Highest Priority Pending Interrupt 1
ICC_HSRE	32	0	rw	Interrupt Controller Hyp System Register Enable
ICC_IAR0	32	3ff	r-	Interrupt Controller Interrupt Acknowledge 0
ICC_IAR1	32	3ff	r-	Interrupt Controller Interrupt Acknowledge 1
ICC_IGRPEN0	32	0	rw	Interrupt Controller Interrupt Group 0 Enable
ICC_IGRPEN1	32	0	rw	Interrupt Controller Interrupt Group 1 Enable
ICC_MCTLR	32	400	rw	Interrupt Controller Monitor Control
ICC_MGRPEN1	32	0	rw	Interrupt Controller Monitor Interrupt Group 1 Enable
ICC_MSRE	32	0	rw	Interrupt Controller Monitor System Register Enable
ICC_PMR	32	0	rw	Interrupt Controller Priority Mask
ICC_RPR	32	ff	r-	Interrupt Controller Running Priority
ICC_SRE	32	0	rw	Interrupt Controller System Register Enable
ICH_AP0R0	32	0	rw	Interrupt Controller Hyp Active Priorities Group 0 (Word 0)
ICH_AP1R0	32	0	rw	Interrupt Controller Hyp Active Priorities Group 1 (Word 0)
ICH_EISR	32	0	r-	Interrupt Controller End of Interrupt Status
ICH_ELRSR	32	f	r-	Interrupt Controller Empty List Register Status
ICH_HCR	32	0	rw	Interrupt Controller Hypervisor Control
ICH_LR0	32	0	rw	Interrupt Controller List 0 (Bits 31:0)

ICH_LR1	32	0	rw	Interrupt Controller List 1 (Bits 31:0)
ICH_LR2	32	0	rw	Interrupt Controller List 2 (Bits 31:0)
ICH_LR3	32	0	rw	Interrupt Controller List 3 (Bits 31:0)
ICH_LRC0	32	0	rw	Interrupt Controller List 0 (Bits 63:32)
ICH_LRC1	32	0	rw	Interrupt Controller List 1 (Bits 63:32)
ICH_LRC2	32	0	rw	Interrupt Controller List 2 (Bits 63:32)
ICH_LRC3	32	0	rw	Interrupt Controller List 3 (Bits 63:32)
ICH_MISR	32	0	r-	Interrupt Controller Maintenance Interrupt State
ICH_VMCR	32	4c0000	rw	Interrupt Controller Virtual Machine Control
ICH_VTR	32	90100003	r-	Interrupt Controller VGIC Type
ICIALLU	32	-	-w	Instruction Cache Invalidate All
ICIALUIS	32	-	-w	Instruction Cache Invalidate All (IS)
ICIMVAU	32	-	-w	Instruction Cache Invalidate by VA
ID_AFR0	32	0	r-	Auxiliary Feature 0
ID_DFR0	32	3010066	r-	Debug Feature 0
ID_ISAR0	32	2101110	r-	Instruction Set Attribute 0
ID_ISAR1	32	13112111	r-	Instruction Set Attribute 1
ID_ISAR2	32	21232042	r-	Instruction Set Attribute 2
ID_ISAR3	32	1112131	r-	Instruction Set Attribute 3
ID_ISAR4	32	11142	r-	Instruction Set Attribute 4
ID_ISAR5	32	1	r-	Instruction Set Attribute 5
ID_MMFR0	32	10201105	r-	Memory Model Feature 0
ID_MMFR1	32	40000000	r-	Memory Model Feature 1
ID_MMFR2	32	1260000	r-	Memory Model Feature 2
ID_MMFR3	32	2102211	r-	Memory Model Feature 3
ID_PFR0	32	131	r-	Processor Feature 0
ID_PFR1	32	10011011	r-	Processor Feature 1
IFAR	32	0	rw	Instruction Fault Address
IFSR	32	0	rw	Instruction Fault Status
IL1DATA0	32	0	rw	Instruction L1 Data 0
IL1DATA1	32	0	rw	Instruction L1 Data 1
IL1DATA2	32	0	rw	Instruction L1 Data 2
IL1DATA3	32	0	rw	Instruction L1 Data 3
ISR	32	0	r-	Interrupt Status
ITLBIALL	32	-	-w	Invalidate Entire Instruction TLB
ITLBIASID	32	-	-w	Invalidate Instruction TLB by ASID
ITLBIMVA	32	-	-w	Invalidate Instruction TLB by VA
JIDR	32	0	rw	Jazelle ID
JMCR	32	0	rw	Jazelle Main Configuration
JOSCR	32	0	rw	Jazelle OS Control
L2ACTLR	32	0	rw	L2 Auxiliary Control
L2CTLR	32	3000000	rw	L2 Control

L2ECTLR	32	0	rw	L2 Extended Control
MAIR0	32	98aa4	rw	Memory Attribute Indirection 0
MAIR1	32	44e048e0	rw	Memory Attribute Indirection 1
MIDR	32	410fd081	r-	Main ID
MPIDR	32	80000000	r-	Multiprocessor Affinity
MVBAR	32	0	rw	Monitor Vector Base Address
NMRR	32	44e048e0	rw	Normal Memory Remap
NSACR	32	c00	rw	Non-Secure Access Control
PAR	32	0	rw	Physical Address
PMCCFILTR	32	0	rw	Performance Monitors Cycle Count Filter
PMCCNTR	32	0	rw	Performance Monitors Cycle Count
PMCEID0	32	7fff0f3f	r-	Performance Monitors Common Event ID 0
PMCEID1	32	0	r-	Performance Monitors Common Event ID 1
PMCNTENCLR	32	0	rw	Performance Monitors Count Enable Clear
PMCNTENSET	32	0	rw	Performance Monitors Count Enable Set
PMCR	32	41023000	rw	Performance Monitors Control
PMEVCNTR0	32	0	rw	Performance Monitors Event Count 0
PMEVCNTR1	32	0	rw	Performance Monitors Event Count 1
PMEVCNTR2	32	0	rw	Performance Monitors Event Count 2
PMEVCNTR3	32	0	rw	Performance Monitors Event Count 3
PMEVCNTR4	32	0	rw	Performance Monitors Event Count 4
PMEVCNTR5	32	0	rw	Performance Monitors Event Count 5
PMEVTYPER0	32	0	rw	Performance Monitors Event Type 0
PMEVTYPER1	32	0	rw	Performance Monitors Event Type 1
PMEVTYPER2	32	0	rw	Performance Monitors Event Type 2
PMEVTYPER3	32	0	rw	Performance Monitors Event Type 3
PMEVTYPER4	32	0	rw	Performance Monitors Event Type 4
PMEVTYPER5	32	0	rw	Performance Monitors Event Type 5
PMINTENCLR	32	0	rw	Performance Monitors Interrupt Enable Clear
PMINTENSET	32	0	rw	Performance Monitors Interrupt Enable Set
PMOVSRR	32	0	rw	Performance Monitors Overflow Flag Status
PMOVSSET	32	0	rw	Performance Monitors Overflow Flag Status Set
PMSELR	32	0	rw	Performance Monitors Event Counter Selection
PMSWINC	32	-	-w	Performance Monitors Software Increment
PMUSERENR	32	0	rw	Performance Monitors User Enable
PMXVCNTR	32	0	rw	Performance Monitors Selected Event Count
PMXEVTYPER	32	0	rw	Performance Monitors Selected Event Type
PRRR	32	98aa4	rw	Primary Region Remap
RAMINDEX	32	-	-w	RAM Index
REVIDR	32	0	r-	Revision ID
RMR	32	1	rw	Reset Management
SCR	32	0	rw	Secure Configuration

SCTLR	32	c50838	rw		System Control
SDCR	32	0	rw		Secure Debug Configuration
SDER	32	0	rw		Secure Debug Enable
TCMTR	32	0	r-		TCM Type
TLBIALL	32	-	-w		Invalidate Entire Unified TLB
TLBIALLH	32	-	-w		Invalidate Entire Hyp Unified TLB
TLBIALLHIS	32	-	-w		Invalidate Entire Hyp TLB (IS)
TLBIALLIS	32	-	-w		Invalidate Entire Unified TLB (IS)
TLBIALLNSNH	32	-	-w		Invalidate Entire Non-Secure Non-Hyp Unified TLB
TLBIALLNSNHIS	32	-	-w		Invalidate Entire Non-Secure Non-Hyp Unified TLB (IS)
TLBIASID	32	-	-w		Invalidate Unified TLB by ASID
TLBIASIDIS	32	-	-w		Invalidate Unified TLB by ASID (IS)
TLBIIPAS2	32	-	-w		Invalidate by IPA, Stage 2
TLBIIPAS2IS	32	-	-w		Invalidate by IPA, Stage 2 (IS)
TLBIIPAS2L	32	-	-w		Invalidate by IPA, Stage 2, Last level
TLBIIPAS2LIS	32	-	-w		Invalidate by IPA, Stage 2, Last level (IS)
TLBIMVA	32	-	-w		Invalidate Unified TLB by VA
TLBIMVAA	32	-	-w		Invalidate Unified TLB by VA, all ASID
TLBIMVAAIS	32	-	-w		Invalidate Unified TLB by VA, all ASID (IS)
TLBIMVAAL	32	-	-w		Invalidate Unified TLB by VA, all ASID, Last level
TLBIMVAALIS	32	-	-w		Invalidate Unified TLB by VA, all ASID, Last level (IS)
TLBIMVAH	32	-	-w		Invalidate Hyp Unified TLB by VA
TLBIMVAHIS	32	-	-w		Invalidate Hyp Unified TLB by VA (IS)
TLBIMVAIS	32	-	-w		Invalidate Unified TLB by VA (IS)
TLBIMVAL	32	-	-w		Invalidate Unified TLB by VA, Last level
TLBIMVALH	32	-	-w		Invalidate Hyp Unified TLB by VA, Last level
TLBIMVALHIS	32	-	-w		Invalidate Hyp Unified TLB by VA, Last level (IS)
TLBIMVALIS	32	-	-w		Invalidate Unified TLB by VA, Last level (IS)
TLBTR	32	0	r-		TLB Type
TPIDRPRW	32	0	rw		PL0 Read/Write Software Thread ID
TPIDRURO	32	0	rw		PL0 Read-Only Software Thread ID
TPIDRURW	32	0	rw		PL1 Software Thread ID
TTBCR	32	0	rw		Translation Table Base Control
TTBR0	32	0	rw		Translation Table Base 0
TTBR1	32	0	rw		Translation Table Base 1
VBAR	32	0	rw		Vector Base Address
VMPIDR	32	80000000	rw		Virtualization Multiprocessor ID
VPIDR	32	410fd081	rw		Virtualization Processor ID

VTCR	32	80000000	rw		Virtualization Translation Control
------	----	----------	----	--	------------------------------------

### 12.2.16 AArch32\_32\_bit\_secure\_system

Table 25.

Name	Bits	Initial value (Hex)		alias	Description
ACTLR_S	32	0	rw		Auxiliary Control
ADFSR_S	32	0	rw		Auxiliary Data Fault Status
AIFSR_S	32	0	rw		Auxiliary Instruction Fault Status
AMAIRO_S	32	0	rw		Auxiliary Memory Attribute Indirection 0
AMAIR1_S	32	0	rw		Auxiliary Memory Attribute Indirection 1
CNTP_CTL_S	32	0	rw		Counter-Timer Physical Timer Control
CNTP_TVAL_S	32	0	rw		Counter-Timer Physical Timer TimerValue
CONTEXTIDR_S	32	0	rw		Context ID
CSSELR_S	32	0	rw		Cache Size Selection
DACR_S	32	0	rw		Domain Access Control
DFAR_S	32	0	rw		Data Fault Address
DFSR_S	32	0	rw		Data Fault Status
ICC_AP1R0_S	32	0	rw		Interrupt Controller Active Priorities Group 1, 0
ICC_BPR1_S	32	2	rw		Interrupt Controller Binary Point 1
ICC_CTLR_S	32	400	rw		Interrupt Controller Control
ICC_IGRPEN1_S	32	0	rw		Interrupt Controller Interrupt Group 1 Enable
ICC_SRE_S	32	0	rw		Interrupt Controller System Register Enable
IFAR_S	32	0	rw		Instruction Fault Address
IFSR_S	32	0	rw		Instruction Fault Status
MAIRO_S	32	98aa4	rw		Memory Attribute Indirection 0
MAIR1_S	32	44e048e0	rw		Memory Attribute Indirection 1
NMRR_S	32	44e048e0	rw		Normal Memory Remap
PAR_S	32	0	rw		Physical Address
PRRR_S	32	98aa4	rw		Primary Region Remap
SCTLR_S	32	c50838	rw		System Control
TPIDRPRW_S	32	0	rw		PL0 Read/Write Software Thread ID
TPIDRURO_S	32	0	rw		PL0 Read-Only Software Thread ID
TPIDRURW_S	32	0	rw		PL1 Software Thread ID
TTBCR_S	32	0	rw		Translation Table Base Control
TTBR0_S	32	0	rw		Translation Table Base 0
TTBR1_S	32	0	rw		Translation Table Base 1
VBAR_S	32	0	rw		Vector Base Address

### 12.2.17 AArch32\_32\_bit\_non\_secure\_system

Table 26.

Name	Bits	Initial value (Hex)		alias	Description
ACTLR_NS	32	0		rw	Auxiliary Control
ADFSR_NS	32	0		rw	Auxiliary Data Fault Status
AIFSR_NS	32	0		rw	Auxiliary Instruction Fault Status
AMAIRO_NS	32	0		rw	Auxiliary Memory Attribute Indirection 0
AMAIR1_NS	32	0		rw	Auxiliary Memory Attribute Indirection 1
CNTP_CTL_NS	32	0		rw	Counter-Timer Physical Timer Control
CNTP_TVAL_NS	32	0		rw	Counter-Timer Physical Timer TimerValue
CONTEXTIDR_NS	32	0		rw	Context ID
CSSELR_NS	32	0		rw	Cache Size Selection
DACR_NS	32	0		rw	Domain Access Control
DFAR_NS	32	0		rw	Data Fault Address
DFSR_NS	32	0		rw	Data Fault Status
ICC_AP1R0_NS	32	0		rw	Interrupt Controller Active Priorities Group 1, 0
ICC_BPR1_NS	32	3		rw	Interrupt Controller Binary Point 1
ICC_CTLR_NS	32	400		rw	Interrupt Controller Control
ICC_IGRPEN1_NS	32	0		rw	Interrupt Controller Interrupt Group 1 Enable
ICC_SRE_NS	32	0		rw	Interrupt Controller System Register Enable
IFAR_NS	32	0		rw	Instruction Fault Address
IFSR_NS	32	0		rw	Instruction Fault Status
MAIRO_NS	32	98aa4		rw	Memory Attribute Indirection 0
MAIR1_NS	32	44e048e0		rw	Memory Attribute Indirection 1
NMRR_NS	32	44e048e0		rw	Normal Memory Remap
PAR_NS	32	0		rw	Physical Address
PRRR_NS	32	98aa4		rw	Primary Region Remap
SCTLR_NS	32	c50838		rw	System Control
TPIDRPRW_NS	32	0		rw	PL0 Read/Write Software Thread ID
TPIDRURO_NS	32	0		rw	PL0 Read-Only Software Thread ID
TPIDRURW_NS	32	0		rw	PL1 Software Thread ID
TTBCR_NS	32	0		rw	Translation Table Base Control
TTBR0_NS	32	0		rw	Translation Table Base 0
TTBR1_NS	32	0		rw	Translation Table Base 1
VBAR_NS	32	0		rw	Vector Base Address

### 12.2.18 AArch32\_64\_bit\_system

Table 27.

Name	Bits	Initial value (Hex)		alias	Description
CNTHP_CVAL	64	0		rw	Counter-Timer Hyp Physical Timer CompareValue
CNTPCT	64	0		r-	Counter-Timer Physical Count



CNTP_CVAL	64	0		rw		Counter-Timer Physical Timer CompareValue
CNTVCT	64	0		r-		Counter-Timer Virtual Count
CNTVOFF	64	0		rw		Virtual Offset
CNTV_CVAL	64	0		rw		Counter-Timer Virtual Timer CompareValue
CPUACTLR	64	0		rw		CPU Auxiliary Control
CPUECTLR	64	0		rw		CPU Extended Control
CPUMERRSR	64	0		rw		CPU Memory Error Syndrome
DBGDRAR64	64	0		r-		Debug ROM Address (64-bit)
HTTBR	64	0		rw		Hyp Translation Table Base
ICC_ASGI1R	64	-		-w		Interrupt Controller Alias SGI Group 1
ICC_SGI0R	64	-		-w		Interrupt Controller SGI Group 0
ICC_SGI1R	64	-		-w		Interrupt Controller SGI Group 1
L2MERRSR	64	0		rw		L2 Memory Error Syndrome
PARLPA	64	0		rw		Physical Address
PMCCNTR64	64	0		rw		Performance Monitors Cycle Count (64-bit)
TTBR0LPA	64	0		rw		Translation Table Base 0
TTBR1LPA	64	0		rw		Translation Table Base 1
VTTBR	64	0		rw		Virtualization Translation Table Base

### 12.2.19 AArch32\_64\_bit\_secure\_system

Table 28.

Name	Bits	Initial value (Hex)		alias	Description
CNTP_CVAL_S	64	0		rw	Counter-Timer Physical Timer CompareValue
PARLPA_S	64	0		rw	Physical Address
TTBR0LPA_S	64	0		rw	Translation Table Base 0
TTBR1LPA_S	64	0		rw	Translation Table Base 1

### 12.2.20 AArch32\_64\_bit\_non\_secure\_system

Table 29.

Name	Bits	Initial value (Hex)		alias	Description
CNTP_CVAL_NS	64	0		rw	Counter-Timer Physical Timer CompareValue
PARLPA_NS	64	0		rw	Physical Address
TTBR0LPA_NS	64	0		rw	Translation Table Base 0
TTBR1LPA_NS	64	0		rw	Translation Table Base 1

### 12.2.21 AArch64\_system

Table 30.

Name	Bits	Initial value (Hex)		alias	Description
------	------	---------------------	--	-------	-------------

ACTLR_EL1	64	0	rw	Auxiliary Control (EL1)
ACTLR_EL2	64	0	rw	Auxiliary Control (EL2)
ACTLR_EL3	64	0	rw	Auxiliary Control (EL3)
AFSR0_EL1	32	0	rw	Auxiliary Fault Status 0 (EL1)
AFSR0_EL2	32	0	rw	Auxiliary Fault Status 0 (EL2)
AFSR0_EL3	32	0	rw	Auxiliary Fault Status 0 (EL3)
AFSR1_EL1	32	0	rw	Auxiliary Fault Status 1 (EL1)
AFSR1_EL2	32	0	rw	Auxiliary Fault Status 1 (EL2)
AFSR1_EL3	32	0	rw	Auxiliary Fault Status 1 (EL3)
AIDR_EL1	32	0	r-	Auxiliary ID
AMAIR_EL1	64	0	rw	Auxiliary Memory Attribute Indirection (EL1)
AMAIR_EL2	64	0	rw	Auxiliary Memory Attribute Indirection (EL2)
AMAIR_EL3	64	0	rw	Auxiliary Memory Attribute Indirection (EL3)
CBAR_EL1	64	13080000	r-	Configuration Base Address
CCSIDR_EL1	32	701fe00a	r-	Current Cache Size ID
CLIDR_EL1	32	a200023	r-	Cache Level ID
CNTFRQ_EL0	32	4c4b40	rw	Counter-Timer Frequency
CNTHCTL_EL2	32	3	rw	Counter-Timer Hypervisor Control
CNTHP_CTL_EL2	32	0	rw	Counter-Timer Hypervisor Physical Timer Control
CNTHP_CVAL_EL2	64	0	rw	Counter-Timer Hypervisor Physical Timer CompareValue
CNTHP_TVAL_EL2	32	0	rw	Counter-Timer Hypervisor Physical Timer TimerValue
CNTKCTL_EL1	32	0	rw	Counter-Timer Kernel Control
CNTPCT_EL0	64	0	r-	Counter-Timer Physical Count
CNTPS_CTL_EL1	32	0	rw	Counter-Timer Physical Secure Timer Control
CNTPS_CVAL_EL1	64	0	rw	Counter-Timer Physical Secure Timer CompareValue
CNTPS_TVAL_EL1	32	0	rw	Counter-Timer Physical Secure Timer TimerValue
CNTP_CTL_EL0	32	0	rw	Counter-Timer Physical Timer Control
CNTP_CVAL_EL0	64	0	rw	Counter-Timer Physical Timer CompareValue
CNTP_TVAL_EL0	32	0	rw	Counter-Timer Physical Timer TimerValue
CNTVCT_EL0	64	0	r-	Counter-Timer Virtual Count
CNTVOFF_EL2	64	0	rw	Counter-Timer Virtual Offset

CNTV_CTL_EL0	32	0	rw	Counter-Timer Virtual Timer Control
CNTV_CVAL_EL0	64	0	rw	Counter-Timer Virtual Timer CompareValue
CNTV_TVAL_EL0	32	0	rw	Counter-Timer Virtual Timer TimerValue
CONTEXTIDR_EL1	32	0	rw	Context ID (EL1)
CPACR_EL1	32	0	rw	Architectural Feature Access Control
CPTR_EL2	32	33ff	rw	Architectural Feature Trap (EL2)
CPTR_EL3	32	0	rw	Architectural Feature Trap (EL3)
CPUACTLR_EL1	64	0	rw	CPU Auxiliary Control
CPUECTLR_EL1	64	0	rw	CPU Extended Control
CPUMERRSR_EL1	64	0	rw	CPU Memory Error Syndrome
CSSELR_EL1	32	0	rw	Current Size Selection
CTR_EL0	32	8444c004	r-	Cache Type
CurrentEL	32	c	r-	Current Exception Level
DACR32_EL2	32	0	rw	Domain Access Control
DAIF	32	3c0	rw	Interrupt Mask Bits
DBGAUTHSTATUS_EL1	32	aa	r-	Debug Authentication Status
DBGBCR0_EL1	32	0	rw	Debug Breakpoint Control 0
DBGBCR1_EL1	32	0	rw	Debug Breakpoint Control 1
DBGBCR2_EL1	32	0	rw	Debug Breakpoint Control 2
DBGBCR3_EL1	32	0	rw	Debug Breakpoint Control 3
DBGBCR4_EL1	32	0	rw	Debug Breakpoint Control 4
DBGBCR5_EL1	32	0	rw	Debug Breakpoint Control 5
DBGBVR0_EL1	64	0	rw	Debug Breakpoint Value 0
DBGBVR1_EL1	64	0	rw	Debug Breakpoint Value 1
DBGBVR2_EL1	64	0	rw	Debug Breakpoint Value 2
DBGBVR3_EL1	64	0	rw	Debug Breakpoint Value 3
DBGBVR4_EL1	64	0	rw	Debug Breakpoint Value 4
DBGBVR5_EL1	64	0	rw	Debug Breakpoint Value 5
DBGCLAIMCLR_EL1	32	0	rw	Debug Claim Tag Clear
DBGCLAIMSET_EL1	32	0	rw	Debug Claim Tag Set
DBGDTRTRX_EL0	32	0	rw	Debug Data Transfer, Transmit/Receive
DBGDTR_EL0	64	0	rw	Debug Data Transfer
DBGPRCR_EL1	32	0	rw	Debug Power Control
DBGVCR32_EL2	32	0	rw	Debug Vector Catch
DBGWCR0_EL1	32	0	rw	Debug Watchpoint Control 0
DBGWCR1_EL1	32	0	rw	Debug Watchpoint Control 1

DBGWCR2_EL1	32	0	rw	Debug Watchpoint Control 2
DBGWCR3_EL1	32	0	rw	Debug Watchpoint Control 3
DBGWVR0_EL1	64	0	rw	Debug Watchpoint Value 0
DBGWVR1_EL1	64	0	rw	Debug Watchpoint Value 1
DBGWVR2_EL1	64	0	rw	Debug Watchpoint Value 2
DBGWVR3_EL1	64	0	rw	Debug Watchpoint Value 3
DCZID_EL0	32	4	r-	Data Cache Zero ID
DL1DATA0_EL1	32	0	rw	Data L1 Data 0
DL1DATA1_EL1	32	0	rw	Data L1 Data 1
DL1DATA2_EL1	32	0	rw	Data L1 Data 2
DL1DATA3_EL1	32	0	rw	Data L1 Data 3
DL1DATA4_EL1	32	0	rw	Data L1 Data 4
DLR_EL0	64	0	rw	Debug Link
DSPSR_EL0	32	0	rw	Debug Saved Program Status
ELR_EL1	64	0	rw	Exception Link (EL1)
ELR_EL2	64	0	rw	Exception Link (EL2)
ELR_EL3	64	0	rw	Exception Link (EL3)
ESR_EL1	32	0	rw	Exception Syndrome (EL1)
ESR_EL2	32	0	rw	Exception Syndrome (EL2)
ESR_EL3	32	0	rw	Exception Syndrome (EL3)
FAR_EL1	64	0	rw	Fault Address (EL1)
FAR_EL2	64	0	rw	Fault Address (EL2)
FAR_EL3	64	0	rw	Fault Address (EL3)
FPCR	32	0	rw	Floating Point Control
FPEXC32_EL2	32	700	rw	Floating Point Exception Control
FPSR	32	0	rw	Floating Point Status
HACR_EL2	32	0	rw	Hypervisor Auxiliary Control
HCR_EL2	64	0	rw	Hypervisor Configuration
HPFAR_EL2	64	0	rw	Hypervisor IPA Fault Address
HSTR_EL2	32	0	rw	Hypervisor System Trap
ICC_AP0R0_EL1	32	0	rw	Interrupt Controller Active Priorities Group 0, 0
ICC_AP1R0_EL1	32	0	rw	Interrupt Controller Active Priorities Group 1, 0
ICC_ASGI1R_EL1	64	-	-w	Interrupt Controller Alias SGI Group 1
ICC_BPR0_EL1	32	2	rw	Interrupt Controller Binary Point 0
ICC_BPR1_EL1	32	2	rw	Interrupt Controller Binary Point 1
ICC_CTLR_EL1	32	400	rw	Interrupt Controller Control (EL1)

ICC_CTLR_EL3	32	400	rw		Interrupt Controller Control (EL3)
ICC_DIR_EL1	32	-	-w		Interrupt Controller Deactivate Interrupt
ICC_EOIR0_EL1	32	-	-w		Interrupt Controller End of Interrupt 0
ICC_EOIR1_EL1	32	-	-w		Interrupt Controller End of Interrupt 1
ICC_HPPIR0_EL1	32	3ff	r-		Interrupt Controller Highest Priority Pending Interrupt 0
ICC_HPPIR1_EL1	32	3ff	r-		Interrupt Controller Highest Priority Pending Interrupt 1
ICC_IAR0_EL1	32	3ff	r-		Interrupt Controller Interrupt Acknowledge 0
ICC_IAR1_EL1	32	3ff	r-		Interrupt Controller Interrupt Acknowledge 1
ICC_IGRPEN0_EL1	32	0	rw		Interrupt Controller Interrupt Group 0 Enable
ICC_IGRPEN1_EL1	32	0	rw		Interrupt Controller Interrupt Group 1 Enable
ICC_IGRPEN1_EL3	32	0	rw		Interrupt Controller Interrupt Group 1 Enable (EL3)
ICC_PMR_EL1	32	0	rw		Interrupt Controller Priority Mask
ICC_RPR_EL1	32	ff	r-		Interrupt Controller Running Priority
ICC_SGI0R_EL1	64	-	-w		Interrupt Controller SGI Group 0
ICC_SGI1R_EL1	64	-	-w		Interrupt Controller SGI Group 1
ICC_SRE_EL1	32	0	rw		Interrupt Controller System Register Enable (EL1)
ICC_SRE_EL2	32	0	rw		Interrupt Controller System Register Enable (EL2)
ICC_SRE_EL3	32	0	rw		Interrupt Controller System Register Enable (EL3)
ICH_AP0R0_EL2	32	0	rw		Interrupt Controller Hyp Active Priorities Group 0 (Word 0)
ICH_AP1R0_EL2	32	0	rw		Interrupt Controller Hyp Active Priorities Group 1 (Word 0)
ICH_EISR_EL2	32	0	r-		Interrupt Controller End of Interrupt Status
ICH_ELRSR_EL2	32	f	r-		Interrupt Controller Empty List Register Status
ICH_HCR_EL2	32	0	rw		Interrupt Controller Hypervisor Control
ICH_LR0_EL2	64	0	rw		Interrupt Controller List 0

ICH_LR1_EL2	64	0	rw	Interrupt Controller List 1
ICH_LR2_EL2	64	0	rw	Interrupt Controller List 2
ICH_LR3_EL2	64	0	rw	Interrupt Controller List 3
ICH_MISR_EL2	32	0	r-	Interrupt Controller Maintenance Interrupt State
ICH_VMCR_EL2	32	4c0000	rw	Interrupt Controller Virtual Machine Control
ICH_VTR_EL2	32	90100003	r-	Interrupt Controller VGIC Type
ID_AA64AFR0_EL1	64	0	r-	AArch64 Auxiliary Feature 0
ID_AA64AFR1_EL1	64	0	r-	AArch64 Auxiliary Feature 1
ID_AA64DFR0_EL1	64	10305106	r-	AArch64 Debug Feature 0
ID_AA64DFR1_EL1	64	0	r-	AArch64 Debug Feature 1
ID_AA64ISAR0_EL1	64	0	r-	AArch64 Instruction Set Attribute 0
ID_AA64ISAR1_EL1	64	0	r-	AArch64 Instruction Set Attribute 1
ID_AA64MMFR0_EL1	64	1124	r-	AArch64 Memory Model Feature 0
ID_AA64MMFR1_EL1	64	0	r-	AArch64 Memory Model Feature 1
ID_AA64PFR0_EL1	64	1002222	r-	AArch64 Processor Feature 0
ID_AA64PFR1_EL1	64	0	r-	AArch64 Processor Feature 1
ID_AFR0_EL1	32	0	r-	Auxiliary Feature 0
ID_DFR0_EL1	32	3010066	r-	Debug Feature 0
ID_ISAR0_EL1	32	2101110	r-	Instruction Set Attribute 0
ID_ISAR1_EL1	32	13112111	r-	Instruction Set Attribute 1
ID_ISAR2_EL1	32	21232042	r-	Instruction Set Attribute 2
ID_ISAR3_EL1	32	1112131	r-	Instruction Set Attribute 3
ID_ISAR4_EL1	32	11142	r-	Instruction Set Attribute 4
ID_ISAR5_EL1	32	1	r-	Instruction Set Attribute 5
ID_MMFR0_EL1	32	10201105	r-	Memory Model Feature 0
ID_MMFR1_EL1	32	40000000	r-	Memory Model Feature 1
ID_MMFR2_EL1	32	1260000	r-	Memory Model Feature 2
ID_MMFR3_EL1	32	2102211	r-	Memory Model Feature 3
ID_PFR0_EL1	32	131	r-	Processor Feature 0
ID_PFR1_EL1	32	10011011	r-	Processor Feature 1
IFSR32_EL2	32	0	rw	Instruction Fault Status (EL2)
IL1DATA0_EL1	32	0	rw	Instruction L1 Data 0
IL1DATA1_EL1	32	0	rw	Instruction L1 Data 1
IL1DATA2_EL1	32	0	rw	Instruction L1 Data 2
IL1DATA3_EL1	32	0	rw	Instruction L1 Data 3
ISR_EL1	32	0	r-	Interrupt Status
L2ACTLR_EL1	32	0	rw	L2 Auxiliary Control

L2CTLR_EL1	32	3000000	rw		L2 Control
L2ECTLR_EL1	32	0	rw		L2 Extended Control
L2MERRSR_EL1	64	0	rw		L2 Memory Error Syndrome
MAIR_EL1	64	44e048e000098aa4	rw		Memory Attribute Indirection (EL1)
MAIR_EL2	64	0	rw		Memory Attribute Indirection (EL2)
MAIR_EL3	64	44e048e000098aa4	rw		Memory Attribute Indirection (EL3)
MDCCINT_EL1	32	0	rw		Monitor DCC Interrupt Enable
MDCCSR_EL0	32	0	r-		Monitor DCC Status
MDCR_EL2	32	6	rw		Monitor Debug Configuration (EL2)
MDCR_EL3	32	0	rw		Monitor Debug Configuration (EL3)
MDRAR_EL1	64	0	r-		Monitor Debug ROM Address
MDSCR_EL1	32	0	rw		Monitor Debug System Control
MIDR_EL1	32	410fd081	r-		Main ID
MPIDR_EL1	64	80000000	r-		Multiprocessor Affinity
MVFR0_EL1	32	10110222	r-		Media and VFP Feature 0
MVFR1_EL1	32	12111111	r-		Media and VFP Feature 1
MVFR2_EL1	32	43	r-		Media and VFP Feature 2
NZCV	32	0	rw		Condition Flags
OSDLR_EL1	32	0	rw		OS Double Lock
OSDTRRX_EL1	32	0	rw		OS Lock Data Transfer, Receive
OSDTRTX_EL1	32	0	rw		OS Lock Data Transfer, Transmit
OSECRR_EL1	32	0	rw		OS Lock Exception Catch Control
OSLAR_EL1	32	-	-w		OS Lock Access
OSLSR_EL1	32	a	r-		OS Lock Status
PAR_EL1	64	0	rw		Physical Address
PMCCFILTR_EL0	32	0	rw		Performance Monitors Cycle Count Filter
PMCCNTR_EL0	64	0	rw		Performance Monitors Cycle Count
PMCEID0_EL0	32	7fff0f3f	r-		Performance Monitors Common Event ID 0
PMCEID1_EL0	32	0	r-		Performance Monitors Common Event ID 1
PMCNTENCLR_EL0	32	0	rw		Performance Monitors Count Enable Clear

PMCNTENSET_EL0	32	0	rw		Performance Monitors Count Enable Set
PMCR_EL0	32	41023000	rw		Performance Monitors Control
PMEVCNTR0_EL0	32	0	rw		Performance Monitors Event Count 0
PMEVCNTR1_EL0	32	0	rw		Performance Monitors Event Count 1
PMEVCNTR2_EL0	32	0	rw		Performance Monitors Event Count 2
PMEVCNTR3_EL0	32	0	rw		Performance Monitors Event Count 3
PMEVCNTR4_EL0	32	0	rw		Performance Monitors Event Count 4
PMEVCNTR5_EL0	32	0	rw		Performance Monitors Event Count 5
PMEVTYPER0_EL0	32	0	rw		Performance Monitors Event Type 0
PMEVTYPER1_EL0	32	0	rw		Performance Monitors Event Type 1
PMEVTYPER2_EL0	32	0	rw		Performance Monitors Event Type 2
PMEVTYPER3_EL0	32	0	rw		Performance Monitors Event Type 3
PMEVTYPER4_EL0	32	0	rw		Performance Monitors Event Type 4
PMEVTYPER5_EL0	32	0	rw		Performance Monitors Event Type 5
PMINTENCLR_EL1	32	0	rw		Performance Monitors Interrupt Enable Clear
PMINTENSET_EL1	32	0	rw		Performance Monitors Interrupt Enable Set
PMOVSCLR_EL0	32	0	rw		Performance Monitors Overflow Flag Status Clear
PMOVSSET_EL0	32	0	rw		Performance Monitors Overflow Flag Status Set
PMSELR_EL0	32	0	rw		Performance Monitors Event Counter Selection
PMSWINC_EL0	32	-	-w		Performance Monitors Software Increment
PMUSERENR_EL0	32	0	rw		Performance Monitors User Enable
PMXEVCNTR_EL0	32	0	rw		Performance Monitors Selected Event Count
PMXEVTYPER_EL0	32	0	rw		Performance Monitors Selected Event Type
RAMINDEX_EL1	32	-	-w		RAM Index
REVIDR_EL1	32	0	r-		Revision ID



RMR_EL3	32	1	rw		Reset Management (EL3)
RVBAR_EL3	64	0	r-		Reset Vector Base Address (EL3)
SCR_EL3	32	0	rw		Secure Configuration
SCTLR_EL1	32	c50838	rw		System Control Register (EL1)
SCTLR_EL2	32	30c50838	rw		System Control Register (EL2)
SCTLR_EL3	32	c50838	rw		System Control (EL3)
SDER32_EL3	32	0	rw		AArch32 Secure Debug Enable
SPSR_EL1	32	0	rw		Saved Program Status (EL1)
SPSR_EL2	32	0	rw		Saved Program Status (EL2)
SPSR_EL3	32	0	rw		Saved Program Status (EL3)
SPSR_abt	32	0	rw		Saved Program Status (Abort Mode)
SPSR_fiq	32	0	rw		Saved Program Status (FIQ Mode)
SPSR_irq	32	0	rw		Saved Program Status (IRQ Mode)
SPSR_und	32	0	rw		Saved Program Status (Undefined Mode)
SPSel	32	1	rw		Stack Pointer Select
SP_EL0	64	0	rw		Stack Pointer (EL0)
SP_EL1	64	0	rw		Stack Pointer (EL1)
SP_EL2	64	0	rw		Stack Pointer (EL2)
SP_EL3	64	0	rw	y	Stack Pointer (EL3)
TCR_EL1	64	0	rw		Translation Control (EL1)
TCR_EL2	32	80800000	rw		Translation Control (EL2)
TCR_EL3	32	0	rw		Translation Control (EL3)
TPIDRRO_EL0	64	0	rw		Thread Pointer/ID, Read-Only (EL0)
TPIDR_EL0	64	0	rw		Thread Pointer/ID (EL0)
TPIDR_EL1	64	0	rw		Thread Pointer/ID (EL1)
TPIDR_EL2	64	0	rw		Thread Pointer/ID (EL2)
TPIDR_EL3	64	0	rw		Thread Pointer/ID (EL3)
TTBR0_EL1	64	0	rw		Translation Table Base 0 (EL1)
TTBR0_EL2	64	0	rw		Translation Table Base 0 (EL2)
TTBR0_EL3	64	0	rw		Translation Table Base 0 (EL3)
TTBR1_EL1	64	0	rw		Translation Table Base 1 (EL1)
VBAR_EL1	64	0	rw		Vector Base Address (EL1)
VBAR_EL2	64	0	rw		Vector Base Address (EL2)

VBAR_EL3	64	0	rw		Vector Base Address (EL3)
VMPIDR_EL2	64	80000000	rw		Virtualization Multiprocessor ID
VPIDR_EL2	32	410fd081	rw		Virtualization Processor ID
VTCR_EL2	32	80000000	rw		Virtualization Translation Control
VTTBR_EL2	64	0	rw		Virtualization Translation Table Base

### 12.2.22 AArch64\_secure\_system

Table 31.

Name	Bits	Initial value (Hex)		alias	Description
ICC_AP1R0_EL1_S	32	0	rw		Interrupt Controller Active Priorities Group 1, 0
ICC_BPR1_EL1_S	32	2	rw		Interrupt Controller Binary Point 1
ICC_CTLR_EL1_S	32	400	rw		Interrupt Controller Control (EL1)
ICC_IGRPEN1_EL1_S	32	0	rw		Interrupt Controller Interrupt Group 1 Enable
ICC_SRE_EL1_S	32	0	rw		Interrupt Controller System Register Enable (EL1)

### 12.2.23 AArch64\_non\_secure\_system

Table 32.

Name	Bits	Initial value (Hex)		alias	Description
ICC_AP1R0_EL1_NS	32	0	rw		Interrupt Controller Active Priorities Group 1, 0
ICC_BPR1_EL1_NS	32	3	rw		Interrupt Controller Binary Point 1
ICC_CTLR_EL1_NS	32	400	rw		Interrupt Controller Control (EL1)
ICC_IGRPEN1_EL1_NS	32	0	rw		Interrupt Controller Interrupt Group 1 Enable
ICC_SRE_EL1_NS	32	0	rw		Interrupt Controller System Register Enable (EL1)

### 12.2.24 AArch64\_SYS\_instruction\_registers

Table 33.

Name	Bits	Initial value (Hex)		alias	Description
ALLE1	64	-	-w		
ALLE1IS	64	-	-w		
ALLE2	64	-	-w		
ALLE2IS	64	-	-w		
ALLE3	64	-	-w		
ALLE3IS	64	-	-w		
ASIDE1	64	-	-w		

ASIDE1IS	64	-	-W		
CISW	32	-	-W		
CIVAC	64	-	-W		
CSW	32	-	-W		
CVAC	64	-	-W		
CVAU	64	-	-W		
IALLU	32	-	-W		
IALLUIS	32	-	-W		
IPAS2E1	64	-	-W		
IPAS2E1IS	64	-	-W		
IPAS2LE1	64	-	-W		
IPAS2LE1IS	64	-	-W		
ISW	32	-	-W		
IVAC	64	-	-W		
IVAU	64	-	-W		
S1E0R	64	-	-W		
S1E0W	64	-	-W		
S1E1R	64	-	-W		
S1E1W	64	-	-W		
S1E2R	64	-	-W		
S1E2W	64	-	-W		
S1E3R	64	-	-W		
S1E3W	64	-	-W		
S12E0R	64	-	-W		
S12E0W	64	-	-W		
S12E1R	64	-	-W		
S12E1W	64	-	-W		
VAAE1	64	-	-W		
VAAE1IS	64	-	-W		
VAALE1	64	-	-W		
VAALE1IS	64	-	-W		
VAE1	64	-	-W		
VAE1IS	64	-	-W		
VAE2	64	-	-W		
VAE2IS	64	-	-W		
VAE3	64	-	-W		
VAE3IS	64	-	-W		
VALE1	64	-	-W		
VALE1IS	64	-	-W		
VALE2	64	-	-W		
VALE2IS	64	-	-W		
VALE3	64	-	-W		

VALE3IS	64	-	-w		
VMALLE1	64	-	-w		
VMALLE1IS	64	-	-w		
VMALLS12E1	64	-	-w		
VMALLS12E1IS	64	-	-w		
ZVA	32	-	-w		

### 12.2.25 Integration\_support

Table 34.

Name	Bits	Initial value (Hex)		alias	Description
transactPL	32	3	r-		privilege level of current memory transaction
transactAT	32	0	r-		current memory transaction type: PA=1, VA=0
artifactPAR	64	0	r-		result of address translation for artifact write to ATS1CPR etc
PTWBankSelect	8	0	rw		select PTW bank (0 is stage 1, 1 is stage 2, 2-5 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively)
PTWBankValid	8	0	r-		bitmask of valid banks (0x01 is stage 1, 0x02 is stage 2, 0x04-0x20 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively)
PTWAddressValid	8	0	r-		bitmask of valid bits for each of PTWAddressL0...PTWAddressL3, PTWBase, PTWInput and PTWOutput in current bank
PTWValueValid	8	0	r-		bitmask of valid bits for each of PTWValueL0...PTWValueL3 in current bank
PTWAddressL0	64	0	r-		current bank PTW address, level 0
PTWAddressL1	64	0	r-		current bank PTW address, level 1
PTWAddressL2	64	0	r-		current bank PTW address, level 2
PTWAddressL3	64	0	r-		current bank PTW address, level 3
PTWValueL0	64	0	r-		current bank PTW value, level 0
PTWValueL1	64	0	r-		current bank PTW value, level 1
PTWValueL2	64	0	r-		current bank PTW value, level 2
PTWValueL3	64	0	r-		current bank PTW value, level 3
PTWBase	64	0	r-		current bank PTW table base address
PTWInput	64	0	r-		current bank PTW input address
PTWOutput	64	0	r-		current bank PTW output address
PTWI_EL1S	64	-	-w		perform EL1(S) stage 1 page table walk for fetch, filling PTW query registers

PTWD_EL1S	64	-	-w	perform EL1(S) stage 1 page table walk for load/store, filling PTW query registers
PTWI_EL1NS	64	-	-w	perform EL1(NS) stage 1 page table walk for fetch, filling PTW query registers
PTWD_EL1NS	64	-	-w	perform EL1(NS) stage 1 page table walk for load/store, filling PTW query registers
PTWI_EL2	64	-	-w	perform EL2 page table walk for fetch, filling PTW query registers
PTWD_EL2	64	-	-w	perform EL2 page table walk for load/store, filling PTW query registers
PTWI_S2	64	-	-w	perform stage 2 page table walk for fetch, filling PTW query registers
PTWD_S2	64	-	-w	perform stage 2 page table walk for load/store, filling PTW query registers
PTWI_EL3	64	-	-w	perform EL3 page table walk for fetch, filling PTW query registers
PTWD_EL3	64	-	-w	perform EL3 page table walk for load/store, filling PTW query registers
PTWI_current	64	-	-w	perform current mode page table walk for fetch, filling PTW query registers
PTWD_current	64	-	-w	perform current mode page table walk for load/store, filling PTW query registers
HaltReason	8	0	r-	bit field indicating halt reason

### 12.2.26 MPCore\_distributor

Table 35.

Name	Bits	Initial value (Hex)	alias	Description
GICD_CIDR0	32	d	r-	Component ID 0
GICD_CIDR1	32	f0	r-	Component ID 1
GICD_CIDR2	32	5	r-	Component ID 2
GICD_CIDR3	32	b1	r-	Component ID 3
GICD_CLRSPI_NSR	32	0	-w	Clear SPI
GICD_CLRSPI_SR	32	0	-w	Clear SPI, Secure
GICD_CPENSGIR0	32	0	rw	SGI Clear-Pending 0
GICD_CPENSGIR1	32	0	rw	SGI Clear-Pending 1
GICD_CPENSGIR2	32	0	rw	SGI Clear-Pending 2
GICD_CPENSGIR3	32	0	rw	SGI Clear-Pending 3
GICD_CTLR	32	0	rw	Distributor Control
GICD_ICACTIVER0	32	0	rw	Interrupt Clear-Active 0
GICD_ICACTIVER1	32	0	rw	Interrupt Clear-Active 1
GICD_ICACTIVER2	32	0	rw	Interrupt Clear-Active 2

GICD_ICENABLER0	32	fff	rw	Interrupt Clear-Enable 0
GICD_ICENABLER1	32	0	rw	Interrupt Clear-Enable 1
GICD_ICENABLER2	32	0	rw	Interrupt Clear-Enable 2
GICD_ICFGR0	32	aaaaaaaa	rw	Interrupt Configuration 0
GICD_ICFGR1	32	55540000	rw	Interrupt Configuration 1
GICD_ICFGR2	32	0	rw	Interrupt Configuration 2
GICD_ICFGR3	32	0	rw	Interrupt Configuration 3
GICD_ICFGR4	32	0	rw	Interrupt Configuration 4
GICD_ICFGR5	32	0	rw	Interrupt Configuration 5
GICD_ICPENDR0	32	0	rw	Interrupt Clear-Pending 0
GICD_ICPENDR1	32	0	rw	Interrupt Clear-Pending 1
GICD_ICPENDR2	32	0	rw	Interrupt Clear-Pending 2
GICD_IGROUPR0	32	0	rw	Interrupt Group 0
GICD_IGROUPR1	32	0	rw	Interrupt Group 1
GICD_IGROUPR2	32	0	rw	Interrupt Group 2
GICD_IGRPMODR0	32	0	rw	Interrupt Group Modifier 0
GICD_IGRPMODR1	32	0	rw	Interrupt Group Modifier 1
GICD_IGRPMODR2	32	0	rw	Interrupt Group Modifier 2
GICD_IIDR	32	102043b	r-	Distributor Implementor ID
GICD_IPRIORITYR0	32	0	rw	Interrupt Priority 0
GICD_IPRIORITYR1	32	0	rw	Interrupt Priority 1
GICD_IPRIORITYR2	32	0	rw	Interrupt Priority 2
GICD_IPRIORITYR3	32	0	rw	Interrupt Priority 3
GICD_IPRIORITYR4	32	0	rw	Interrupt Priority 4
GICD_IPRIORITYR5	32	0	rw	Interrupt Priority 5
GICD_IPRIORITYR6	32	0	rw	Interrupt Priority 6
GICD_IPRIORITYR7	32	0	rw	Interrupt Priority 7
GICD_IPRIORITYR8	32	0	rw	Interrupt Priority 8
GICD_IPRIORITYR9	32	0	rw	Interrupt Priority 9
GICD_IPRIORITYR10	32	0	rw	Interrupt Priority 10
GICD_IPRIORITYR11	32	0	rw	Interrupt Priority 11
GICD_IPRIORITYR12	32	0	rw	Interrupt Priority 12
GICD_IPRIORITYR13	32	0	rw	Interrupt Priority 13
GICD_IPRIORITYR14	32	0	rw	Interrupt Priority 14
GICD_IPRIORITYR15	32	0	rw	Interrupt Priority 15
GICD_IPRIORITYR16	32	0	rw	Interrupt Priority 16
GICD_IPRIORITYR17	32	0	rw	Interrupt Priority 17
GICD_IPRIORITYR18	32	0	rw	Interrupt Priority 18
GICD_IPRIORITYR19	32	0	rw	Interrupt Priority 19
GICD_IPRIORITYR20	32	0	rw	Interrupt Priority 20
GICD_IPRIORITYR21	32	0	rw	Interrupt Priority 21
GICD_IPRIORITYR22	32	0	rw	Interrupt Priority 22

GICD_IPRIORITYR23	32	0	rw	Interrupt Priority 23
GICD_IROUTER32	64	0	rw	Interrupt Routing 32
GICD_IROUTER33	64	0	rw	Interrupt Routing 33
GICD_IROUTER34	64	0	rw	Interrupt Routing 34
GICD_IROUTER35	64	0	rw	Interrupt Routing 35
GICD_IROUTER36	64	0	rw	Interrupt Routing 36
GICD_IROUTER37	64	0	rw	Interrupt Routing 37
GICD_IROUTER38	64	0	rw	Interrupt Routing 38
GICD_IROUTER39	64	0	rw	Interrupt Routing 39
GICD_IROUTER40	64	0	rw	Interrupt Routing 40
GICD_IROUTER41	64	0	rw	Interrupt Routing 41
GICD_IROUTER42	64	0	rw	Interrupt Routing 42
GICD_IROUTER43	64	0	rw	Interrupt Routing 43
GICD_IROUTER44	64	0	rw	Interrupt Routing 44
GICD_IROUTER45	64	0	rw	Interrupt Routing 45
GICD_IROUTER46	64	0	rw	Interrupt Routing 46
GICD_IROUTER47	64	0	rw	Interrupt Routing 47
GICD_IROUTER48	64	0	rw	Interrupt Routing 48
GICD_IROUTER49	64	0	rw	Interrupt Routing 49
GICD_IROUTER50	64	0	rw	Interrupt Routing 50
GICD_IROUTER51	64	0	rw	Interrupt Routing 51
GICD_IROUTER52	64	0	rw	Interrupt Routing 52
GICD_IROUTER53	64	0	rw	Interrupt Routing 53
GICD_IROUTER54	64	0	rw	Interrupt Routing 54
GICD_IROUTER55	64	0	rw	Interrupt Routing 55
GICD_IROUTER56	64	0	rw	Interrupt Routing 56
GICD_IROUTER57	64	0	rw	Interrupt Routing 57
GICD_IROUTER58	64	0	rw	Interrupt Routing 58
GICD_IROUTER59	64	0	rw	Interrupt Routing 59
GICD_IROUTER60	64	0	rw	Interrupt Routing 60
GICD_IROUTER61	64	0	rw	Interrupt Routing 61
GICD_IROUTER62	64	0	rw	Interrupt Routing 62
GICD_IROUTER63	64	0	rw	Interrupt Routing 63
GICD_IROUTER64	64	0	rw	Interrupt Routing 64
GICD_IROUTER65	64	0	rw	Interrupt Routing 65
GICD_IROUTER66	64	0	rw	Interrupt Routing 66
GICD_IROUTER67	64	0	rw	Interrupt Routing 67
GICD_IROUTER68	64	0	rw	Interrupt Routing 68
GICD_IROUTER69	64	0	rw	Interrupt Routing 69
GICD_IROUTER70	64	0	rw	Interrupt Routing 70
GICD_IROUTER71	64	0	rw	Interrupt Routing 71
GICD_IROUTER72	64	0	rw	Interrupt Routing 72

GICD_IROUTER73	64	0	rw	Interrupt Routing 73
GICD_IROUTER74	64	0	rw	Interrupt Routing 74
GICD_IROUTER75	64	0	rw	Interrupt Routing 75
GICD_IROUTER76	64	0	rw	Interrupt Routing 76
GICD_IROUTER77	64	0	rw	Interrupt Routing 77
GICD_IROUTER78	64	0	rw	Interrupt Routing 78
GICD_IROUTER79	64	0	rw	Interrupt Routing 79
GICD_IROUTER80	64	0	rw	Interrupt Routing 80
GICD_IROUTER81	64	0	rw	Interrupt Routing 81
GICD_IROUTER82	64	0	rw	Interrupt Routing 82
GICD_IROUTER83	64	0	rw	Interrupt Routing 83
GICD_IROUTER84	64	0	rw	Interrupt Routing 84
GICD_IROUTER85	64	0	rw	Interrupt Routing 85
GICD_IROUTER86	64	0	rw	Interrupt Routing 86
GICD_IROUTER87	64	0	rw	Interrupt Routing 87
GICD_IROUTER88	64	0	rw	Interrupt Routing 88
GICD_IROUTER89	64	0	rw	Interrupt Routing 89
GICD_IROUTER90	64	0	rw	Interrupt Routing 90
GICD_IROUTER91	64	0	rw	Interrupt Routing 91
GICD_IROUTER92	64	0	rw	Interrupt Routing 92
GICD_IROUTER93	64	0	rw	Interrupt Routing 93
GICD_IROUTER94	64	0	rw	Interrupt Routing 94
GICD_IROUTER95	64	0	rw	Interrupt Routing 95
GICD_ISACTIVER0	32	0	rw	Interrupt Set-Active 0
GICD_ISACTIVER1	32	0	rw	Interrupt Set-Active 1
GICD_ISACTIVER2	32	0	rw	Interrupt Set-Active 2
GICD_ISENBALER0	32	fff	rw	Interrupt Set-Enable 0
GICD_ISENBALER1	32	0	rw	Interrupt Set-Enable 1
GICD_ISENBALER2	32	0	rw	Interrupt Set-Enable 2
GICD_ISPENDR0	32	0	rw	Interrupt Set-Pending 0
GICD_ISPENDR1	32	0	rw	Interrupt Set-Pending 1
GICD_ISPENDR2	32	0	rw	Interrupt Set-Pending 2
GICD_ITARGETSR0	32	1010101	rw	Interrupt Processor Targets 0
GICD_ITARGETSR1	32	1010101	rw	Interrupt Processor Targets 1
GICD_ITARGETSR2	32	1010101	rw	Interrupt Processor Targets 2
GICD_ITARGETSR3	32	1010101	rw	Interrupt Processor Targets 3
GICD_ITARGETSR4	32	0	rw	Interrupt Processor Targets 4
GICD_ITARGETSR5	32	0	rw	Interrupt Processor Targets 5
GICD_ITARGETSR6	32	1010100	rw	Interrupt Processor Targets 6
GICD_ITARGETSR7	32	1010101	rw	Interrupt Processor Targets 7
GICD_ITARGETSR8	32	0	rw	Interrupt Processor Targets 8
GICD_ITARGETSR9	32	0	rw	Interrupt Processor Targets 9



GICD_ITARGETSR10	32	0	rw	Interrupt Processor Targets 10
GICD_ITARGETSR11	32	0	rw	Interrupt Processor Targets 11
GICD_ITARGETSR12	32	0	rw	Interrupt Processor Targets 12
GICD_ITARGETSR13	32	0	rw	Interrupt Processor Targets 13
GICD_ITARGETSR14	32	0	rw	Interrupt Processor Targets 14
GICD_ITARGETSR15	32	0	rw	Interrupt Processor Targets 15
GICD_ITARGETSR16	32	0	rw	Interrupt Processor Targets 16
GICD_ITARGETSR17	32	0	rw	Interrupt Processor Targets 17
GICD_ITARGETSR18	32	0	rw	Interrupt Processor Targets 18
GICD_ITARGETSR19	32	0	rw	Interrupt Processor Targets 19
GICD_ITARGETSR20	32	0	rw	Interrupt Processor Targets 20
GICD_ITARGETSR21	32	0	rw	Interrupt Processor Targets 21
GICD_ITARGETSR22	32	0	rw	Interrupt Processor Targets 22
GICD_ITARGETSR23	32	0	rw	Interrupt Processor Targets 23
GICD_NSACR0	32	0	rw	Interrupt Non-secure Access Control 0
GICD_NSACR1	32	0	rw	Interrupt Non-secure Access Control 1
GICD_NSACR2	32	0	rw	Interrupt Non-secure Access Control 2
GICD_NSACR3	32	0	rw	Interrupt Non-secure Access Control 3
GICD_NSACR4	32	0	rw	Interrupt Non-secure Access Control 4
GICD_NSACR5	32	0	rw	Interrupt Non-secure Access Control 5
GICD_PIDR0	32	92	r-	Peripheral ID 0
GICD_PIDR1	32	b4	r-	Peripheral ID 1
GICD_PIDR2	32	3b	r-	Peripheral ID 2
GICD_PIDR3	32	0	r-	Peripheral ID 3
GICD_PIDR4	32	44	r-	Peripheral ID 4
GICD_PIDR5	32	0	r-	Peripheral ID 5
GICD_PIDR6	32	0	r-	Peripheral ID 6
GICD_PIDR7	32	0	r-	Peripheral ID 7
GICD_SETSPI_NSR	32	0	-w	Set SPI
GICD_SETSPI_SR	32	0	-w	Set SPI, Secure
GICD_SGIR	32	0	-w	Software-Generated Interrupt
GICD_SPENDSGIR0	32	0	rw	SPI Set-Pending 0
GICD_SPENDSGIR1	32	0	rw	SPI Set-Pending 1
GICD_SPENDSGIR2	32	0	rw	SPI Set-Pending 2
GICD_SPENDSGIR3	32	0	rw	SPI Set-Pending 3
GICD_SPISR0	32	0	r-	SPI Status 0
GICD_SPISR1	32	0	r-	SPI Status 1

GICD_STATUSR	32	0	rw	Distributor Status
GICD_TYPER	32	7b0462	r-	Interrupt Controller Type

### 12.2.27 MPCore\_physical\_redistributor

Table 36.

Name	Bits	Initial value (Hex)		alias	Description
GICR_CIDR0	32	d	r-		Redistributor Component ID 0
GICR_CIDR1	32	f0	r-		Redistributor Component ID 1
GICR_CIDR2	32	5	r-		Redistributor Component ID 2
GICR_CIDR3	32	b1	r-		Redistributor Component ID 3
GICR_CLRLPIR	64	0	-w		Clear LPI Pending
GICR_CTLR	32	0	rw		Redistributor Control
GICR_ICACTIVER0	32	0	rw		Interrupt Clear-Active 0
GICR_ICENABLER0	32	ffff	rw		Interrupt Clear-Enable 0
GICR_ICFGR0	32	aaaaaaaa	rw		Interrupt Configuration 0
GICR_ICFGR1	32	55540000	rw		Interrupt Configuration 1
GICR_ICPENDR0	32	0	rw		Interrupt Clear-Pending 0
GICR_IGROUPR0	32	0	rw		Interrupt Group 0
GICR_IGRPMODR0	32	0	rw		Interrupt Group Modifier 0
GICR_IIDR	32	43b	r-		Redistributor Implementer Identification
GICR_INVALLR	64	0	-w		Redistributor Invalidate All
GICR_INVLPIR	64	0	-w		Redistributor Invalidate LPI
GICR_IPRIORITYR0	32	0	rw		Interrupt Priority 0
GICR_IPRIORITYR1	32	0	rw		Interrupt Priority 1
GICR_IPRIORITYR2	32	0	rw		Interrupt Priority 2
GICR_IPRIORITYR3	32	0	rw		Interrupt Priority 3
GICR_IPRIORITYR4	32	0	rw		Interrupt Priority 4
GICR_IPRIORITYR5	32	0	rw		Interrupt Priority 5
GICR_IPRIORITYR6	32	0	rw		Interrupt Priority 6
GICR_IPRIORITYR7	32	0	rw		Interrupt Priority 7
GICR_ISACTIVER0	32	0	rw		Interrupt Set-Active 0
GICR_ISENBALER0	32	ffff	rw		Interrupt Set-Enable 0
GICR_ISPENDR0	32	0	rw		Interrupt Set-Pending 0
GICR_NSACR	32	0	rw		Interrupt Non-secure Access Control
GICR_PENDBASER	64	0	rw		Redistributor LPI Pending Table Base Address
GICR_PIDR0	32	93	r-		Redistributor Peripheral ID 0
GICR_PIDR1	32	b4	r-		Redistributor Peripheral ID 1
GICR_PIDR2	32	3b	r-		Redistributor Peripheral ID 2
GICR_PIDR3	32	0	r-		Redistributor Peripheral ID 3

GICR_PIDR4	32	44	r-		Redistributor Peripheral ID 4
GICR_PIDR5	32	0	r-		Redistributor Peripheral ID 5
GICR_PIDR6	32	0	r-		Redistributor Peripheral ID 6
GICR_PIDR7	32	0	r-		Redistributor Peripheral ID 7
GICR_PROPBASER	64	0	rw		Redistributor Properties Base Address
GICR_SETLPIR	64	0	-w		Set LPI Pending
GICR_STATUSR	32	0	rw		Redistributor Status
GICR_SYNCR	32	0	r-		Redistributor Synchronize
GICR_TYPER	64	9	r-		Redistributor Type
GICR_WAKER	32	6	rw		Redistributor Wake

### 12.2.28 MPCore\_processor\_interface

Table 37.

Name	Bits	Initial value (Hex)		alias	Description
GICC_ABPR	32	3	rw		Aliased Binary Point
GICC_AEOIR	32	0	-w		Aliased End of Interrupt
GICC_AHPPIR	32	3ff	r-		Aliased Highest Priority Pending Interrupt
GICC_AIAR	32	3ff	r-		Aliased Interrupt Acknowledge
GICC_APR0	32	0	rw		Active Priorities 0
GICC_BPR	32	2	rw		Binary Point
GICC_CTLR	32	0	rw		CPU Interface Control
GICC_DIR	32	0	-w		Deactivate Interrupt
GICC_EOIR	32	0	-w		End of Interrupt
GICC_HPPIR	32	3ff	r-		Highest Priority Pending Interrupt
GICC_IAR	32	3ff	r-		Interrupt Acknowledge
GICC_IIDR	32	4043b	r-		CPU Interface ID
GICC_NSAPR0	32	0	rw		Non-secure Active Priorities 0
GICC_PMR	32	0	rw		Interrupt Priority Mask
GICC_RPR	32	ff	r-		Running Priority
GICC_STATUSR	32	0	rw		CPU Interface Status

### 12.2.29 MPCore\_virtual\_interface\_control

Table 38.

Name	Bits	Initial value (Hex)		alias	Description
GICH_APR0	32	0	rw		Active Priorities 0
GICH_EISR0	32	0	r-		End of Interrupt Status 0
GICH_ELRSR0	32	f	r-		Empty List Register Status 0

GICH_HCR	32	0	rw		Hypervisor Control
GICH_LR0	32	0	rw		List 0
GICH_LR1	32	0	rw		List 1
GICH_LR2	32	0	rw		List 2
GICH_LR3	32	0	rw		List 3
GICH_MISR	32	0	r-		Maintenance Interrupt Status
GICH_VMCR	32	4c0000	rw		Virtual Machine Control
GICH_VTR	32	90000003	r-		VGIC Type

### 12.2.30 MPCore\_virtual\_processor\_interface

Table 39.

Name	Bits	Initial value (Hex)		alias	Description
GICV_ABPR	32	3	rw		VM Aliased Binary Point
GICV_AEOIR	32	0	-w		VM Aliased End of Interrupt
GICV_AHPPIR	32	3ff	r-		VM Aliased Highest Priority Pending Interrupt
GICV_AIAR	32	3ff	r-		VM Aliased Interrupt Acknowledge
GICV_APR0	32	0	rw		VM Active Priorities 0
GICV_BPR	32	2	rw		VM Binary Point
GICV_CTLR	32	0	rw		Virtual Machine Control
GICV_DIR	32	0	-w		VM Deactivate Interrupt
GICV_EOIR	32	0	-w		VM End of Interrupt
GICV_HPPIR	32	3ff	r-		VM Highest Priority Pending Interrupt
GICV_IAR	32	3ff	r-		VM Interrupt Acknowledge
GICV_IIDR	32	4043b	r-		VM CPU Interface ID
GICV_PMR	32	0	rw		VM Priority Mask
GICV_RPR	32	ff	r-		VM Running Priority
GICV_STATUSR	32	0	rw		VM CPU Interface Status
ICV_AP0R0_EL1	32	0	rw		VM Group 0 Active Priorities 0
ICV_AP1R0_EL1	32	0	rw		VM Group 1 Active Priorities 0
ICV_BPR0_EL1	32	2	rw		VM Group 0 Binary Point
ICV_BPR1_EL1	32	3	rw		VM Group 1 Binary Point
ICV_CTLR_EL1	32	400	rw		Virtual Machine Control
ICV_DIR_EL1	32	0	-w		VM Deactivate Interrupt
ICV_EOIR0_EL1	32	0	-w		VM Group 0 End of Interrupt
ICV_EOIR1_EL1	32	0	-w		VM Group 1 End of Interrupt
ICV_HPPIR0_EL1	32	3ff	r-		VM Group 0 Highest Priority Pending Interrupt
ICV_HPPIR1_EL1	32	3ff	r-		VM Group 1 Highest Priority Pending Interrupt
ICV_IAR0_EL1	32	3ff	r-		VM Group 0 Interrupt Acknowledge
ICV_IAR1_EL1	32	3ff	r-		VM Group 1 Interrupt Acknowledge
ICV_IGRPEN0_EL1	32	0	rw		VM Group 0 Interrupt Enable
ICV_IGRPEN1_EL1	32	0	rw		VM Group 1 Interrupt Enable

ICV_PMR_EL1	32	0	rw		VM Priority Mask
ICV_RPR_EL1	32	ff	r-		VM Running Priority

### 12.2.31 MPCore ITS

Table 40.

Name	Bits	Initial value (Hex)		alias	Description
GITS_BASER0	64	0		rw	ITS Translation Table Descriptor 0
GITS_BASER1	64	0		rw	ITS Translation Table Descriptor 1
GITS_BASER2	64	0		rw	ITS Translation Table Descriptor 2
GITS_BASER3	64	0		rw	ITS Translation Table Descriptor 3
GITS_BASER4	64	0		rw	ITS Translation Table Descriptor 4
GITS_BASER5	64	0		rw	ITS Translation Table Descriptor 5
GITS_BASER6	64	0		rw	ITS Translation Table Descriptor 6
GITS_BASER7	64	0		rw	ITS Translation Table Descriptor 7
GITS_CBASER	64	0		rw	ITS Command Queue Descriptor
GITS_CREADR	64	0		rw	ITS Read
GITS_CTLR	32	80000000		rw	ITS Control
GITS_CWRITER	64	0		rw	ITS Write
GITS_IIDR	32	43b		r-	ITS Identification
GITS_TYPER	64	9ef79		r-	ITS Type

#