



OVP Guide to Using Processor Models

Model specific information for ARM_Cortex-A72MPx3

Imperas Software Limited
Imperas Buildings, North Weston
Thame, Oxfordshire, OX9 2HA, U.K.
docs@imperas.com



| | |
|----------|-------------------------------------------------------|
| Author | Imperas Software Limited |
| Version | 0.6 |
| Filename | OVP_Model_Specific_Information_arm_Cortex-A72MPx3.pdf |
| Created | 18 July 2018 |
| Status | OVP Standard Release |

Copyright Notice

Copyright (c) 2018 Imperas Software Limited. All rights reserved. This software and documentation contain information that is the property of Imperas Software Limited. The software and documentation are furnished under a license agreement and may be used or copied only in accordance with the terms of the license agreement. No part of the software and documentation may be reproduced, transmitted, or translated, in any form or by any means, electronic, mechanical, manual, optical, or otherwise, without prior written permission of Imperas Software Limited, or as expressly provided by the license agreement.

Right to Copy Documentation

The license agreement with Imperas permits licensee to make copies of the documentation for its internal use only. Each copy shall include all copyrights, trademarks, service marks, and proprietary rights notices, if any.

Destination Control Statement

All technical data contained in this publication is subject to the export control laws of the United States of America. Disclosure to nationals of other countries contrary to United States law is prohibited. It is the readers responsibility to determine the applicable regulations and to comply with them.

Disclaimer

IMPERAS SOFTWARE LIMITED, AND ITS LICENSORS MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Model Release Status

This model is released as part of OVP releases and is included in OVPworld packages. Please visit OVPworld.org.

Contents

| | | |
|----------|-------------------------------------------------|----------|
| 1 | Overview | 1 |
| 1.1 | Description | 1 |
| 1.2 | Licensing | 1 |
| 1.3 | Limitations | 2 |
| 1.4 | Verification | 3 |
| 1.5 | Features | 3 |
| 1.5.1 | Core Features | 3 |
| 1.5.2 | Memory System | 3 |
| 1.5.3 | Advanced SIMD and Floating-Point Features | 3 |
| 1.5.4 | Generic Timer | 4 |
| 1.5.5 | Generic Interrupt Controller | 4 |
| 1.6 | Debug Mask | 4 |
| 1.7 | AArch32 Unpredictable Behavior | 5 |
| 1.7.1 | Equal Target Registers | 5 |
| 1.7.2 | Floating Point Load/Store Multiple Lists | 5 |
| 1.7.3 | Floating Point VLD[2-4]/VST[2-4] Range Overflow | 5 |
| 1.7.4 | If-Then (IT) Block Constraints | 5 |
| 1.7.5 | Use of R13 | 5 |
| 1.7.6 | Use of R15 | 5 |
| 1.8 | Integration Support | 6 |
| 1.8.1 | Memory Transaction Query | 6 |
| 1.8.2 | Page Table Walk Query | 6 |
| 1.8.3 | Artifact Page Table Walks | 7 |
| 1.8.4 | MMU and Page Table Walk Events | 7 |
| 1.8.5 | Artifact Address Translations | 7 |
| 1.8.6 | Halt Reason Introspection | 7 |
| 1.8.7 | System Register Access Monitor | 7 |
| 1.8.8 | System Register Implementation | 8 |
| 2 | Configuration | 9 |
| 2.1 | Location | 9 |
| 2.2 | GDB Path | 9 |
| 2.3 | Semi-Host Library | 9 |
| 2.4 | Processor Endian-ness | 9 |
| 2.5 | QuantumLeap Support | 9 |
| 2.6 | Processor ELF code | 9 |

| | | |
|-----------|-----------------------------------|-----------|
| 3 | All Variants in this model | 10 |
| 4 | Bus Master Ports | 13 |
| 5 | Bus Slave Ports | 14 |
| 6 | Net Ports | 15 |
| 7 | FIFO Ports | 20 |
| 8 | Formal Parameters | 21 |
| 9 | Execution Modes | 26 |
| 10 | Exceptions | 27 |
| 11 | Hierarchy of the model | 28 |
| 11.1 | Level 1: MPCORE | 28 |
| 11.2 | Level 2: CPU | 28 |
| 12 | Model Commands | 30 |
| 12.1 | Level 1: MPCORE | 30 |
| 12.1.1 | isync | 30 |
| 12.1.2 | itrace | 30 |
| 12.2 | Level 2: CPU | 30 |
| 12.2.1 | debugflags | 30 |
| 12.2.2 | dumpTLB | 31 |
| 12.2.3 | isync | 31 |
| 12.2.4 | itrace | 31 |
| 12.2.5 | validateTLB | 31 |
| 13 | Registers | 33 |
| 13.1 | Level 1: MPCORE | 33 |
| 13.2 | Level 2: CPU | 33 |
| 13.2.1 | Core | 33 |
| 13.2.2 | Core_AAarch64 | 33 |
| 13.2.3 | Control | 34 |
| 13.2.4 | User | 34 |
| 13.2.5 | FIQ | 35 |
| 13.2.6 | IRQ | 35 |
| 13.2.7 | Supervisor | 35 |
| 13.2.8 | Monitor | 35 |
| 13.2.9 | Hypervisor | 35 |
| 13.2.10 | Undefined | 36 |
| 13.2.11 | Abort | 36 |
| 13.2.12 | SIMD_VFP | 36 |
| 13.2.13 | SIMD_VFP_SYS | 37 |
| 13.2.14 | SIMD_FP_AAarch64 | 37 |
| 13.2.15 | AArch32_32_bit_system | 38 |

| | |
|------------------------------------------------------|----|
| 13.2.16 AArch32_32_bit_secure_system | 43 |
| 13.2.17 AArch32_32_bit_non_secure_system | 44 |
| 13.2.18 AArch32_64_bit_system | 44 |
| 13.2.19 AArch32_64_bit_secure_system | 45 |
| 13.2.20 AArch32_64_bit_non_secure_system | 45 |
| 13.2.21 AArch64_system | 45 |
| 13.2.22 AArch64_secure_system | 50 |
| 13.2.23 AArch64_non_secure_system | 50 |
| 13.2.24 AArch64_SYS_instruction_registers | 51 |
| 13.2.25 Integration_support | 52 |
| 13.2.26 MPCore_distributor | 53 |
| 13.2.27 MPCore_physical_redistributor | 56 |
| 13.2.28 MPCore_processor_interface | 57 |
| 13.2.29 MPCore_virtual_interface_control | 57 |
| 13.2.30 MPCore_virtual_processor_interface | 58 |
| 13.2.31 MPCore_ITS | 58 |

Chapter 1

Overview

This document provides the details of an OVP Fast Processor Model variant.

OVP Fast Processor Models are written in C and provide a C API for use in C based platforms. The models also provide a native interface for use in SystemC TLM2 platforms.

The models are written using the OVP VMI API that provides a Virtual Machine Interface that defines the behavior of the processor. The VMI API makes a clear line between model and simulator allowing very good optimization and world class high speed performance. Most models are provided as a binary shared object and also as source. This allows the download and use of the model binary or the use of the source to explore and modify the model.

The models are run through an extensive QA and regression testing process and most model families are validated using technology provided by the processor IP owners. There is a companion document (OVP Guide to Using Processor Models) which explains the general concepts of OVP Fast Processor Models and their use. It is downloadable from the OVPworld website documentation pages.

1.1 Description

ARM Processor Model

1.2 Licensing

Usage of binary model under license governing simulator usage.

Note that for models of ARM CPUs the license includes the following terms:

Licensee is granted a non-exclusive, worldwide, non-transferable, revocable licence to:

If no source is being provided to the Licensee: use and copy only (no modifications rights are granted) the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used

to emulate an ARM based system to run application software in a production or live environment.

If source code is being provided to the Licensee: use, copy and modify the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used to emulate an ARM based system to run application software in a production or live environment.

In the case of any Licensee who is either or both an academic or educational institution the purposes shall be limited to internal use.

Except to the extent that such activity is permitted by applicable law, Licensee shall not reverse engineer, decompile, or disassemble this model. If this model was provided to Licensee in Europe, Licensee shall not reverse engineer, decompile or disassemble the Model for the purposes of error correction.

The License agreement does not entitle Licensee to manufacture in silicon any product based on this model.

The License agreement does not entitle Licensee to use this model for evaluating the validity of any ARM patent.

Source of model available under separate Imperas Software License Agreement.

1.3 Limitations

Instruction pipelines are not modeled in any way. All instructions are assumed to complete immediately. This means that instruction barrier instructions (e.g. ISB, CP15ISB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. The model does not implement speculative fetch behavior. The branch cache is not modeled.

Caches and write buffers are not modeled in any way. All loads, fetches and stores complete immediately and in order, and are fully synchronous (as if the memory was of Strongly Ordered or Device-nGnRnE type). Data barrier instructions (e.g. DSB, CP15DSB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. Cache manipulation instructions are implemented as NOPs, with the exception of any undefined instruction behavior, which is modeled.

Real-world timing effects are not modeled: all instructions are assumed to complete in a single cycle.

Performance Monitors are implemented as a register interface only except for the cycle counter, which is implemented assuming one instruction per cycle.

TLBs are architecturally-accurate but not device accurate. This means that all TLB maintenance and address translation operations are fully implemented but the cache is larger than in the real device.

Debug registers are implemented but non-functional (which is sufficient to allow operating systems such as Linux to boot). Debug state is not implemented.

The GICv3 block is implemented without any ITS. Implementation-defined GICR registers

for control of LPIs (GICR_SETLPIR, GICR_CLRLPIR, GICR_INVLPIR, GICR_INVALLR and GICR_SYNCR) are all implemented.

The optional SIMD Cryptographic Extension instructions are not supported. AES, SHA1 and SHA2 fields in ID_AA64ISAR0_EL1 and ID_ISAR5_EL1 registers must be zero.

The optional Scalable Vector Extension is under development and should not be enabled (ensure AA64PFR0_EL1.SVE=0).

1.4 Verification

Models have been extensively tested by Imperas. ARM Cortex-A models have been successfully used by customers to simulate SMP Linux, Ubuntu Desktop, VxWorks and ThreadX on Xilinx Zynq virtual platforms.

1.5 Features

1.5.1 Core Features

AArch64 is implemented at EL3, EL2, EL1 and EL0.

AArch32 is implemented at EL3, EL2, EL1 and EL0.

1.5.2 Memory System

Security extensions are implemented (also known as TrustZone). To make non-secure accesses visible externally, override ID_AA64MMFR0_EL1.PARange to specify the required physical bus size (32, 36, 40, 42, 44, 48 or 52 bits) and connect the processor to a bus one bit wider (33, 37, 41, 43, 45, 49 or 53 bits, respectively). The extra most-significant bit is the NS bit, indicating a non-secure access. If non-secure accesses are not required to be made visible externally, connect the processor to a bus of exactly the size implied by ID_AA64MMFR0_EL1.PARange.

VMSA EL1, EL2 and EL3 stage 1 address translation is implemented. VMSA stage 2 address translation is implemented.

LPA (large physical address extension) is implemented as standard in ARMv8.

1.5.3 Advanced SIMD and Floating-Point Features

SIMD and VFP instructions are implemented.

The model implements trapped exceptions if FPTrap is set to 1 in MVFR0 (for AArch32) or MVFR0_EL1 (for AArch64). When floating point exception traps are taken, cumulative exception flags are not updated (in other words, cumulative flag state is always the same as prior to instruction execution, even for SIMD instructions). When multiple enabled exceptions are raised by a single floating point operation, the exception reported is the one in least-significant bit position in FPSCR

(for AArch32) or FPCR (for AArch64). When multiple enabled exceptions are raised by different SIMD element computations, the exception reported is selected from the lowest-index-number SIMD operation. Contact Imperas if requirements for exception reporting differ from these.

Trapped exceptions not are implemented in this variant (FPTrap=0)

1.5.4 Generic Timer

Generic Timer is present. Use parameter “override_timerScaleFactor” to specify the counter rate as a fraction of the processor MIPS rate (e.g. 10 implies Generic Timer counters increment once every 10 processor instructions).

1.5.5 Generic Interrupt Controller

GIC block is implemented (GICv3, including security extensions). Accesses to GIC registers can be viewed externally by connecting to the 32-bit GICRegisters and GICDRegisters bus ports. Secure register accesses are at offset 0x0 on these busses; for example, a secure access to GICD register GICD_CTLR can be observed by monitoring address 0x00000000 of bus GICDRegisters. Non-secure accesses are at offset 0x80000000 on these busses; for example, a non-secure access to GICD register GICD_CTLR can be observed by monitoring address 0x80000000 of bus GICDRegisters

The internal GIC block can be disabled by raising signal GICCDISABLE, in which case the GIC needs to be modeled using a platform component instead. Input signals vfiq_CPU<N> and virq_CPU<N> can be used by this component to raise virtual FIQ and IRQ interrupts on cores in the cluster if required.

1.6 Debug Mask

It is possible to enable model debug messages in various categories. This can be done statically using the “override_debugMask” parameter, or dynamically using the “debugflags” command. Enabled messages are specified using a bitmask value, as follows:

Value 0x004: enable debugging of MMU/MPU mappings

Value 0x020: enable debugging of reads and writes of GIC block registers.

Value 0x040: enable debugging of exception routing via the GIC model component.

Value 0x080: enable debugging of all system register accesses.

Value 0x100: enable debugging of all traps of system register accesses.

Value 0x200: enable verbose debugging of other miscellaneous behavior (for example, the reason why a particular instruction is undefined).

Value 0x400: enable debugging of Performance Monitor timers

All other bits in the debug bitmask are reserved and must not be set to non-zero values.

1.7 AArch32 Unpredictable Behavior

Many AArch32 instruction behaviors are described in the ARM ARM as `CONSTRAINED UNPREDICTABLE`. This section describes how such situations are handled by this model.

1.7.1 Equal Target Registers

Some instructions allow the specification of two target registers (for example, double-width `SMULL`, or some `VMOV` variants), and such instructions are `CONSTRAINED UNPREDICTABLE` if the same target register is specified in both positions. In this model, such instructions are treated as `UNDEFINED`.

1.7.2 Floating Point Load/Store Multiple Lists

Instructions that load or store a list of floating point registers (e.g. `VSTM`, `VLDM`, `VPUSH`, `VPOP`) are `CONSTRAINED UNPREDICTABLE` if either the uppermost register in the specified range is greater than 32 or (for 64-bit registers) if more than 16 registers are specified. In this model, such instructions are treated as `UNDEFINED`.

1.7.3 Floating Point VLD[2-4]/VST[2-4] Range Overflow

Instructions that load or store a fixed number of floating point registers (e.g. `VST2`, `VLD2`) are `CONSTRAINED UNPREDICTABLE` if the upper register bound exceeds the number of implemented floating point registers. In this model, these instructions load and store using modulo 32 indexing (consistent with AArch64 instructions with similar behavior).

1.7.4 If-Then (IT) Block Constraints

Where the behavior of an instruction in an if-then (IT) block is described as `CONSTRAINED UNPREDICTABLE`, this model treats that instruction as `UNDEFINED`.

1.7.5 Use of R13

In architecture variants before ARMv8, use of R13 was described as `CONSTRAINED UNPREDICTABLE` in many circumstances. From ARMv8, most of these situations are no longer considered unpredictable. This model allows R13 to be used like any other GPR, consistent with the ARMv8 specification.

1.7.6 Use of R15

Use of R15 is described as `CONSTRAINED UNPREDICTABLE` in many circumstances. This model allows such use to be configured using the parameter “unpredictable” as follows:

Value “undefined”: any reference to R15 in such a situation is treated as `UNDEFINED`;

Value “nop”: any reference to R15 in such a situation causes the instruction to be treated as a NOP;

Value “raz_wi”: any reference to R15 in such a situation causes the instruction to be treated as a RAZ/WI (that is, R15 is read as zero and write-ignored);

Value “execute”: any reference to R15 in such a situation is executed using the current value of R15 on read, and writes to R15 are allowed (but are not interworking).

Value “assert”: any reference to R15 in such a situation causes the simulation to halt with an assertion message (allowing any such unpredictable uses to be easily identified).

In this variant, the default is “undefined”.

1.8 Integration Support

This model implements a number of non-architectural pseudo-registers and other features to facilitate integration.

1.8.1 Memory Transaction Query

Two registers are intended for use within memory callback functions to provide additional information about the current memory access. Register `transactPL` indicates the processor execution level of the current access (0-3). Note that for load/store translate instructions (e.g. LDRT, STRT) the reported execution level will be 0, indicating an EL0 access. Register `transactAT` indicates the type of memory access: 0 for a normal read or write; and 1 for a physical access resulting from a page table walk.

1.8.2 Page Table Walk Query

A banked set of registers provides information about the most recently completed page table walk. There are up to six banks of registers: bank 0 is for stage 1 walks, bank 1 is for stage 2 walks, and banks 2-5 are for stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively. Banks 1-5 are present only for processors with virtualization extensions. The currently active bank can be set using register `PTWBankSelect`. Register `PTWBankValid` is a bitmask indicating which banks contain valid data: for example, the value 0xb indicates that banks 0, 1 and 3 contain valid data.

Within each bank, there are registers that record addresses and values read during that page table walk. Register `PTWBase` records the table base address. Registers `PTWAddressL0`-`PTWAddressL3` record the addresses of level 0 to level 3 entries read, respectively, and register `PTWAddressValid` is a bitmask indicating which address registers contain valid data: for example, the value 0xe indicates that `PTWAddressL1`-`PTWAddressL3` are valid but `PTWAddressL0` is not. Registers `PTWValueL0`-`PTWValueL3` contain entry values read at level 0 to level 3. Register `PTWInput` contains the input address that starts a walk and Register `PTWOutput` contains the result address (valid only if the page table walk completes). Register `PTWValueValid` is a bitmask indicating which value registers contain valid data: bits 0-3 indicate `PTWValueL0`-`PTWValueL3`, respectively, bit 4 indicates `PTWBase`, bit 5 indicates `PTWInput` and bit 6 indicates `PTWOutput`.

1.8.3 Artifact Page Table Walks

Registers are also available to enable a simulation environment to initiate an artifact page table walk (for example, to determine the ultimate PA corresponding to a given VA). Register `PTWI_EL1S` initiates a secure EL1 table walk for a fetch. Register `PTWD_EL1S` initiates a secure EL1 table walk for a load or store (note that current ARM processors have unified TLBs, so these registers are synonymous). Registers `PTW[ID]_EL1NS` initiate walks for non-secure EL1 accesses. Registers `PTW[ID]_EL2` initiate EL2 walks. Registers `PTW[ID]_S2` initiate stage 2 walks. Registers `PTW[ID]_EL3` initiate AArch64 EL3 walks. Finally, registers `PTW[ID]_current` initiate current-mode walks (useful in a memory callback context). Each walk fills the query registers described above.

1.8.4 MMU and Page Table Walk Events

Two events are available that allow a simulation environment to be notified on MMU and page table walk actions. Event `mmuEnable` triggers when any MMU is enabled or disabled. Event `pageTableWalk` triggers on completion of any page table walk (including artifact walks).

1.8.5 Artifact Address Translations

A simulation environment can trigger an artifact address translation operation by writing to the architectural address translation registers (e.g. `ATS1CPR`). The results of such translations are written to an integration support register `artifactPAR`, instead of the architectural `PAR` register. This means that such artifact writes will not perturb architectural state.

1.8.6 Halt Reason Introspection

An artifact register `HaltReason` can be read to determine the reason or reasons that a processor is halted. This register is a bitfield, with the following encoding: bit 0 indicates the processor has executed a wait-for-event (WFE) instruction; bit 1 indicates the processor has executed a wait-for-interrupt (WFI) instruction; and bit 2 indicates the processor is held in reset.

1.8.7 System Register Access Monitor

If parameter “`enableSystemMonitorBus`” is `True`, an artifact 32-bit bus “`SystemMonitor`” is enabled for each PE. Every system register read or write by that PE is then visible as a read or write on this artifact bus, and can therefore be monitored using callbacks installed in the client environment (use `opBusReadMonitorAdd/opBusWriteMonitorAdd` or `icmAddBusReadCallback/icmAddBusWriteCallback`, depending on the client API). The format of the address on the bus is as follows:

bits 31:26 - zero

bit 25 - 1 if AArch64 access, 0 if AArch32 access

bit 24 - 1 if non-secure access, 0 if secure access

bits 23:20 - CRm value

bits 19:16 - CRn value

bits 15:12 - op2 value

bits 11:8 - op1 value

bits 7:4 - op0 value (AArch64) or coprocessor number (AArch32)

bits 3:0 - zero

As an example, to view non-secure writes to writes to CNTFRQ_EL0 in AArch64 state, install a write monitor on address range 0x020e0330:0x020e0333.

1.8.8 System Register Implementation

If parameter “enableSystemBus” is True, an artifact 32-bit bus “System” is enabled for each PE. Slave callbacks installed on this bus can be used to implement modified system register behavior (use opBusSlaveNew or icmMapExternalMemory, depending on the client API). The format of the address on the bus is the same as for the system monitor bus, described above.

Chapter 2

Configuration

2.1 Location

This model's VLVN is arm.ovpworld.org/processor/arm/1.0.

The model source is usually at:

`$IMPERAS_HOME/ImperasLib/source/arm.ovpworld.org/processor/arm/1.0`

The model binary is usually at:

`$IMPERAS_HOME/lib/$IMPERAS_ARCH/ImperasLib/arm.ovpworld.org/processor/arm/1.0`

2.2 GDB Path

The default GDB for this model is: `$IMPERAS_HOME/lib/$IMPERAS_ARCH/gdb/aarch64-none-elf-gdb`.

2.3 Semi-Host Library

The default semi-host library file is `arm.ovpworld.org/semihosting/armAngel/1.0`

2.4 Processor Endian-ness

This model can be set to either endian-ness (normally by a pin, or the ELF code).

2.5 QuantumLeap Support

This processor is qualified to run in a QuantumLeap enabled simulator.

2.6 Processor ELF code

ELF codes supported by this model are: 0xb7 and 0x28.

Chapter 3

All Variants in this model

This model has these variants

| Variant | Description |
|----------------|-------------|
| ARMv4T | |
| ARMv4xM | |
| ARMv4 | |
| ARMv4TxM | |
| ARMv5xM | |
| ARMv5 | |
| ARMv5TxM | |
| ARMv5T | |
| ARMv5TExP | |
| ARMv5TE | |
| ARMv5TEJ | |
| ARMv6 | |
| ARMv6K | |
| ARMv6T2 | |
| ARMv6KZ | |
| ARMv7 | |
| ARM7TDMI | |
| ARM7EJ-S | |
| ARM720T | |
| ARM920T | |
| ARM922T | |
| ARM926EJ-S | |
| ARM940T | |
| ARM946E | |
| ARM966E | |
| ARM968E-S | |
| ARM1020E | |
| ARM1022E | |
| ARM1026EJ-S | |
| ARM1136J-S | |
| ARM1156T2-S | |

| | |
|----------------|--|
| ARM1176JZ-S | |
| Cortex-R4 | |
| Cortex-R4F | |
| Cortex-A5UP | |
| Cortex-A5MPx1 | |
| Cortex-A5MPx2 | |
| Cortex-A5MPx3 | |
| Cortex-A5MPx4 | |
| Cortex-A8 | |
| Cortex-A9UP | |
| Cortex-A9MPx1 | |
| Cortex-A9MPx2 | |
| Cortex-A9MPx3 | |
| Cortex-A9MPx4 | |
| Cortex-A7UP | |
| Cortex-A7MPx1 | |
| Cortex-A7MPx2 | |
| Cortex-A7MPx3 | |
| Cortex-A7MPx4 | |
| Cortex-A15UP | |
| Cortex-A15MPx1 | |
| Cortex-A15MPx2 | |
| Cortex-A15MPx3 | |
| Cortex-A15MPx4 | |
| Cortex-A17MPx1 | |
| Cortex-A17MPx2 | |
| Cortex-A17MPx3 | |
| Cortex-A17MPx4 | |
| AArch32 | |
| AArch64 | |
| Cortex-A32MPx1 | |
| Cortex-A32MPx2 | |
| Cortex-A32MPx3 | |
| Cortex-A32MPx4 | |
| Cortex-A35MPx1 | |
| Cortex-A35MPx2 | |
| Cortex-A35MPx3 | |
| Cortex-A35MPx4 | |
| Cortex-A53MPx1 | |
| Cortex-A53MPx2 | |
| Cortex-A53MPx3 | |
| Cortex-A53MPx4 | |
| Cortex-A55MPx1 | |
| Cortex-A55MPx2 | |
| Cortex-A55MPx3 | |

| | |
|----------------|------------------------------|
| Cortex-A55MPx4 | |
| Cortex-A57MPx1 | |
| Cortex-A57MPx2 | |
| Cortex-A57MPx3 | |
| Cortex-A57MPx4 | |
| Cortex-A72MPx1 | |
| Cortex-A72MPx2 | |
| Cortex-A72MPx3 | (described in this document) |
| Cortex-A72MPx4 | |
| Cortex-A73MPx1 | |
| Cortex-A73MPx2 | |
| Cortex-A73MPx3 | |
| Cortex-A73MPx4 | |
| Cortex-A75MPx1 | |
| Cortex-A75MPx2 | |
| Cortex-A75MPx3 | |
| Cortex-A75MPx4 | |
| MultiCluster | |

Table 3.1: All Variants in this model

Chapter 4

Bus Master Ports

This model has these bus master ports.

| Name | min | max | Connect? | Description |
|---------------|-----|-----|-----------|-----------------------------------|
| INSTRUCTION | 32 | 53 | mandatory | |
| DATA | 32 | 53 | optional | |
| GICRegisters | 32 | 32 | optional | GIC memory-mapped register block |
| GICDRegisters | 32 | 32 | optional | GICD memory-mapped register block |

Table 4.1: Bus Master Ports

Chapter 5

Bus Slave Ports

This model has no bus slave ports.

Chapter 6

Net Ports

This model has these net ports.

| Name | Type | Connect? | Description |
|-------|-------|----------|-----------------------------|
| SPI32 | input | optional | Shared peripheral interrupt |
| SPI33 | input | optional | Shared peripheral interrupt |
| SPI34 | input | optional | Shared peripheral interrupt |
| SPI35 | input | optional | Shared peripheral interrupt |
| SPI36 | input | optional | Shared peripheral interrupt |
| SPI37 | input | optional | Shared peripheral interrupt |
| SPI38 | input | optional | Shared peripheral interrupt |
| SPI39 | input | optional | Shared peripheral interrupt |
| SPI40 | input | optional | Shared peripheral interrupt |
| SPI41 | input | optional | Shared peripheral interrupt |
| SPI42 | input | optional | Shared peripheral interrupt |
| SPI43 | input | optional | Shared peripheral interrupt |
| SPI44 | input | optional | Shared peripheral interrupt |
| SPI45 | input | optional | Shared peripheral interrupt |
| SPI46 | input | optional | Shared peripheral interrupt |
| SPI47 | input | optional | Shared peripheral interrupt |
| SPI48 | input | optional | Shared peripheral interrupt |
| SPI49 | input | optional | Shared peripheral interrupt |
| SPI50 | input | optional | Shared peripheral interrupt |
| SPI51 | input | optional | Shared peripheral interrupt |
| SPI52 | input | optional | Shared peripheral interrupt |
| SPI53 | input | optional | Shared peripheral interrupt |
| SPI54 | input | optional | Shared peripheral interrupt |
| SPI55 | input | optional | Shared peripheral interrupt |
| SPI56 | input | optional | Shared peripheral interrupt |
| SPI57 | input | optional | Shared peripheral interrupt |
| SPI58 | input | optional | Shared peripheral interrupt |
| SPI59 | input | optional | Shared peripheral interrupt |
| SPI60 | input | optional | Shared peripheral interrupt |
| SPI61 | input | optional | Shared peripheral interrupt |
| SPI62 | input | optional | Shared peripheral interrupt |

| | | | |
|-------------|--------|----------|--------------------------------------------------------------------------------------|
| SPI63 | input | optional | Shared peripheral interrupt |
| SPI64 | input | optional | Shared peripheral interrupt |
| SPI65 | input | optional | Shared peripheral interrupt |
| SPI66 | input | optional | Shared peripheral interrupt |
| SPI67 | input | optional | Shared peripheral interrupt |
| SPI68 | input | optional | Shared peripheral interrupt |
| SPI69 | input | optional | Shared peripheral interrupt |
| SPI70 | input | optional | Shared peripheral interrupt |
| SPI71 | input | optional | Shared peripheral interrupt |
| SPI72 | input | optional | Shared peripheral interrupt |
| SPI73 | input | optional | Shared peripheral interrupt |
| SPI74 | input | optional | Shared peripheral interrupt |
| SPI75 | input | optional | Shared peripheral interrupt |
| SPI76 | input | optional | Shared peripheral interrupt |
| SPI77 | input | optional | Shared peripheral interrupt |
| SPI78 | input | optional | Shared peripheral interrupt |
| SPI79 | input | optional | Shared peripheral interrupt |
| SPI80 | input | optional | Shared peripheral interrupt |
| SPI81 | input | optional | Shared peripheral interrupt |
| SPI82 | input | optional | Shared peripheral interrupt |
| SPI83 | input | optional | Shared peripheral interrupt |
| SPI84 | input | optional | Shared peripheral interrupt |
| SPI85 | input | optional | Shared peripheral interrupt |
| SPI86 | input | optional | Shared peripheral interrupt |
| SPI87 | input | optional | Shared peripheral interrupt |
| SPI88 | input | optional | Shared peripheral interrupt |
| SPI89 | input | optional | Shared peripheral interrupt |
| SPI90 | input | optional | Shared peripheral interrupt |
| SPI91 | input | optional | Shared peripheral interrupt |
| SPI92 | input | optional | Shared peripheral interrupt |
| SPI93 | input | optional | Shared peripheral interrupt |
| SPI94 | input | optional | Shared peripheral interrupt |
| SPI95 | input | optional | Shared peripheral interrupt |
| SPIVector | input | optional | Shared peripheral interrupt vectorized input |
| periphReset | input | optional | Peripheral reset (active high) |
| GICCDISABLE | input | optional | GIC CPU interface logic disable (active high, sampled on rising edge of periphReset) |
| EVENTI | input | optional | Event input signal, active on rising edge |
| EVENTO | output | optional | Event output signal, active on rising edge |
| PPI16_CPU0 | input | optional | Private peripheral interrupt |
| PPI17_CPU0 | input | optional | Private peripheral interrupt |
| PPI18_CPU0 | input | optional | Private peripheral interrupt |
| PPI19_CPU0 | input | optional | Private peripheral interrupt |

| | | | |
|-------------------|--------|----------|--------------------------------------------------------|
| PPI20_CPU0 | input | optional | Private peripheral interrupt |
| PPI21_CPU0 | input | optional | Private peripheral interrupt |
| PPI22_CPU0 | input | optional | Private peripheral interrupt |
| PPI23_CPU0 | input | optional | Private peripheral interrupt |
| PPI24_CPU0 | input | optional | Private peripheral interrupt |
| PPI25_CPU0 | input | optional | Private peripheral interrupt |
| PPI26_CPU0 | input | optional | Private peripheral interrupt |
| PPI27_CPU0 | input | optional | Private peripheral interrupt |
| PPI28_CPU0 | input | optional | Private peripheral interrupt |
| PPI29_CPU0 | input | optional | Private peripheral interrupt |
| PPI30_CPU0 | input | optional | Private peripheral interrupt |
| PPI31_CPU0 | input | optional | Private peripheral interrupt |
| CNTVIRQ_CPU0 | output | optional | Virtual timer event (active high) |
| CNTPSIRQ_CPU0 | output | optional | Secure physical timer event (active high) |
| CNTPNSIRQ_CPU0 | output | optional | Non-secure physical timer event (active high) |
| CNTPHIRQ_CPU0 | output | optional | Hypervisor physical timer event (active high) |
| IRQOUT_CPU0 | output | optional | IRQ wakeup |
| FIQOUT_CPU0 | output | optional | FIQ wakeup |
| CLUSTERIDAFF1 | input | optional | Configure MPIDR.Aff1 |
| CLUSTERIDAFF2 | input | optional | Configure MPIDR.Aff2 |
| VINITL_CPU0 | input | optional | Configure HIVECS mode (SCTLR.V) |
| CFGEND_CPU0 | input | optional | Configure exception endianness (SCTLR.EE) |
| CFGTE_CPU0 | input | optional | Configure exception state at reset (SCTLR.TE) |
| reset_CPU0 | input | optional | Processor reset, active high |
| fiq_CPU0 | input | optional | FIQ interrupt, active high (negation of nFIQ) |
| irq_CPU0 | input | optional | IRQ interrupt, active high (negation of nIRQ) |
| sei_CPU0 | input | optional | System error interrupt, active high |
| vfiq_CPU0 | input | optional | Virtual FIQ interrupt, active high (negation of nVFIQ) |
| virq_CPU0 | input | optional | Virtual IRQ interrupt, active high (negation of nVIRQ) |
| vsei_CPU0 | input | optional | Virtual system error interrupt, active high |
| AXLSLVERR_CPU0 | input | optional | AXI external abort type (DECERR=0, SLVERR=1) |
| CP15SDISABLE_CPU0 | input | optional | CP15SDISABLE (active high) |
| PMUIRQ_CPU0 | output | optional | Performance monitor event (active high) |
| SMPEN_CPU0 | output | optional | CPUECTLR.SMPEN current value |
| PPI16_CPU1 | input | optional | Private peripheral interrupt |
| PPI17_CPU1 | input | optional | Private peripheral interrupt |

| | | | |
|-------------------|--------|----------|--------------------------------------------------------|
| PPI18_CPU1 | input | optional | Private peripheral interrupt |
| PPI19_CPU1 | input | optional | Private peripheral interrupt |
| PPI20_CPU1 | input | optional | Private peripheral interrupt |
| PPI21_CPU1 | input | optional | Private peripheral interrupt |
| PPI22_CPU1 | input | optional | Private peripheral interrupt |
| PPI23_CPU1 | input | optional | Private peripheral interrupt |
| PPI24_CPU1 | input | optional | Private peripheral interrupt |
| PPI25_CPU1 | input | optional | Private peripheral interrupt |
| PPI26_CPU1 | input | optional | Private peripheral interrupt |
| PPI27_CPU1 | input | optional | Private peripheral interrupt |
| PPI28_CPU1 | input | optional | Private peripheral interrupt |
| PPI29_CPU1 | input | optional | Private peripheral interrupt |
| PPI30_CPU1 | input | optional | Private peripheral interrupt |
| PPI31_CPU1 | input | optional | Private peripheral interrupt |
| CNTVIRQ_CPU1 | output | optional | Virtual timer event (active high) |
| CNTPSIRQ_CPU1 | output | optional | Secure physical timer event (active high) |
| CNTPNSIRQ_CPU1 | output | optional | Non-secure physical timer event (active high) |
| CNTPHIRQ_CPU1 | output | optional | Hypervisor physical timer event (active high) |
| IRQOUT_CPU1 | output | optional | IRQ wakeup |
| FIQOUT_CPU1 | output | optional | FIQ wakeup |
| VINITHL_CPU1 | input | optional | Configure HIVECS mode (SCTLR.V) |
| CFGEND_CPU1 | input | optional | Configure exception endianness (SCTLR.EE) |
| CFGTE_CPU1 | input | optional | Configure exception state at reset (SCTLR.TE) |
| reset_CPU1 | input | optional | Processor reset, active high |
| fiq_CPU1 | input | optional | FIQ interrupt, active high (negation of nFIQ) |
| irq_CPU1 | input | optional | IRQ interrupt, active high (negation of nIRQ) |
| sei_CPU1 | input | optional | System error interrupt, active high |
| vfiq_CPU1 | input | optional | Virtual FIQ interrupt, active high (negation of nVFIQ) |
| virq_CPU1 | input | optional | Virtual IRQ interrupt, active high (negation of nVIRQ) |
| vsei_CPU1 | input | optional | Virtual system error interrupt, active high |
| AXI_SLVERR_CPU1 | input | optional | AXI external abort type (DECERR=0, SLVERR=1) |
| CP15SDISABLE_CPU1 | input | optional | CP15SDISABLE (active high) |
| PMUIRQ_CPU1 | output | optional | Performance monitor event (active high) |
| SMPEN_CPU1 | output | optional | CPUECTLR.SMPEN current value |
| PPI16_CPU2 | input | optional | Private peripheral interrupt |
| PPI17_CPU2 | input | optional | Private peripheral interrupt |

| | | | |
|-------------------|--------|----------|--------------------------------------------------------|
| PPI18_CPU2 | input | optional | Private peripheral interrupt |
| PPI19_CPU2 | input | optional | Private peripheral interrupt |
| PPI20_CPU2 | input | optional | Private peripheral interrupt |
| PPI21_CPU2 | input | optional | Private peripheral interrupt |
| PPI22_CPU2 | input | optional | Private peripheral interrupt |
| PPI23_CPU2 | input | optional | Private peripheral interrupt |
| PPI24_CPU2 | input | optional | Private peripheral interrupt |
| PPI25_CPU2 | input | optional | Private peripheral interrupt |
| PPI26_CPU2 | input | optional | Private peripheral interrupt |
| PPI27_CPU2 | input | optional | Private peripheral interrupt |
| PPI28_CPU2 | input | optional | Private peripheral interrupt |
| PPI29_CPU2 | input | optional | Private peripheral interrupt |
| PPI30_CPU2 | input | optional | Private peripheral interrupt |
| PPI31_CPU2 | input | optional | Private peripheral interrupt |
| CNTVIRQ_CPU2 | output | optional | Virtual timer event (active high) |
| CNTPSIRQ_CPU2 | output | optional | Secure physical timer event (active high) |
| CNTPNSIRQ_CPU2 | output | optional | Non-secure physical timer event (active high) |
| CNTPHIRQ_CPU2 | output | optional | Hypervisor physical timer event (active high) |
| IRQOUT_CPU2 | output | optional | IRQ wakeup |
| FIQOUT_CPU2 | output | optional | FIQ wakeup |
| VINITHL_CPU2 | input | optional | Configure HIVECS mode (SCTLR.V) |
| CFGEND_CPU2 | input | optional | Configure exception endianness (SCTLR.EE) |
| CFGTE_CPU2 | input | optional | Configure exception state at reset (SCTLR.TE) |
| reset_CPU2 | input | optional | Processor reset, active high |
| fiq_CPU2 | input | optional | FIQ interrupt, active high (negation of nFIQ) |
| irq_CPU2 | input | optional | IRQ interrupt, active high (negation of nIRQ) |
| sei_CPU2 | input | optional | System error interrupt, active high |
| vfiq_CPU2 | input | optional | Virtual FIQ interrupt, active high (negation of nVFIQ) |
| virq_CPU2 | input | optional | Virtual IRQ interrupt, active high (negation of nVIRQ) |
| vsei_CPU2 | input | optional | Virtual system error interrupt, active high |
| AXLSLVERR_CPU2 | input | optional | AXI external abort type (DECERR=0, SLVERR=1) |
| CP15SDISABLE_CPU2 | input | optional | CP15SDISABLE (active high) |
| PMUIRQ_CPU2 | output | optional | Performance monitor event (active high) |
| SMPEN_CPU2 | output | optional | CPUECTLR.SMPEN current value |

Table 6.1: Net Ports

Chapter 7

FIFO Ports

This model has no FIFO ports.

Chapter 8

Formal Parameters

| Name | Type | Description |
|------------------------|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| variant | Enumeration | Selects variant (either a generic ISA or a specific model) |
| verbose | Boolean | Specify verbosity of output |
| showHiddenRegs | Boolean | Show hidden registers during register tracing |
| UAL | Boolean | Disassemble using UAL syntax |
| disableGICModel | Boolean | Disable the internal GIC model entirely |
| enableGICv3 | Boolean | Enable/disable GICv3 support |
| supportSTATUSR | Boolean | Enable/disable support for GICv3 GIC[CDV]_STATUSR registers |
| enableVFPAAtReset | Boolean | Enable vector floating point (SIMD and VFP) instructions at reset. (Enables cp10/11 in CPACR and sets FPEXC.EN) |
| SVEImplementedSizes | Uns32 | For processors with ARMv8.2 SVE extension, mask of configurable vector sizes (vector length N is configurable if mask contains $1 < ((N/128)-1)$) |
| enableSystemBus | Boolean | Add 32-bit artifact System bus port, allowing system registers to be externally implemented |
| enableSystemMonitorBus | Boolean | Add 32-bit artifact SystemMonitor bus port, allowing system register accesses to be externally monitored |
| distinctMTCores | Boolean | For multi-threaded (MT) processors, simulate threads as separate cores (otherwise, simulate MT threads as a single entity) |
| compatibility | Enumeration | Specify compatibility mode (ISA, gdb or nopSVC) |
| unpredictable | Enumeration | Specify unpredictable instruction behavior (undefined, nop, raz_wi, execute or assert) |
| maxSIMDUnroll | Uns32 | If SIMD operations are supported, specify the maximum number of parallel SIMD operations to unroll (unrolled operations can be faster, but produce more verbose JIT code) |
| override_debugMask | Uns32 | Specifies debug mask, enabling debug output for model components |
| endian | Endian | Model endian |
| override_numCPUs | Uns32 | Specify the number of cores in a multiprocessor (maximum of 8 for GICv1/GICv2) |
| override_affinityMask | Uns32 | Specify bitmask of implemented affinity bits in format Aff3:Aff2:Aff1:Aff0 (each a byte) |
| override_MPIDR_MT | Boolean | Specifies that processor is multithreaded |
| override_MPIDR_Aff0 | Uns32 | Override Aff0 field in MPIDR/MPIDR_EL1 register |
| override_MPIDR_Aff1 | Uns32 | Override Aff1 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF1 configuration net) |

| | | |
|--------------------------------|---------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| override_MPIDR_Aff2 | Uns32 | Override Aff2 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF2 configuration net) |
| override_fcsePresent | Boolean | Specifies that FCSE is present (if true) |
| override_fpexcDexPresent | Boolean | Specifies that the FPEXC.DEX register field is implemented (if true) |
| override_advSIMDPresent | Boolean | Specifies that Advanced SIMD extensions are present (if true) |
| override_vfpPresent | Boolean | Specifies that VFP extensions are present (if true) |
| override_physicalBits | Uns32 | Specifies the implemented physical bus bits (defaults to connected physical bus width) |
| override_timerScaleFactor | Uns32 | Specifies the fraction of MIPS rate to use for MPCore timers (generic timers or global/local/watchdogs depending on implementation). Defaults to 20 for generic timers, 2 for others |
| override_GICD_NSACRPresent | Boolean | Specifies that optional GICD_NSACR distributor registers are present (GICv2 only) |
| override_GICD_PPISRPresent | Boolean | Specifies that implementation-specific GICD_PPISR distributor register is present (GICv1 ICDPPIS/ICPPISR, GICv1 and GICv2 only) |
| override_GICD_SPISRPresent | Boolean | Specifies that implementation-specific GICD_SPISR distributor registers are present (GICv1 ICDSPIS/ICSPISR) |
| override_GICv3_DistributorBase | Uns64 | Specify distributor register block base address (GICv3 only) |
| override_GICv3_E1NWFPresent | Boolean | Specifies that GICR_CTLR.E1NWF is implemented (GICv3 only) |
| override_GIC_PPIMask | Uns32 | Specify bitmask of implemented PPIs in the GIC (e.g. ID16 is 0x0001, ID31 is 0x8000) |
| override_GICCDISABLE | Boolean | Specify initial value of GICCDISABLE |
| override_SCTLR_V | Boolean | Override SCTLR.V with the passed value (enables high vectors) |
| override_SCTLR_CP15BEN_Present | Boolean | Enable ARMv7 SCTLR.CP15BEN bit (CP15 barrier enable) |
| override_MIDR | Uns32 | Override MIDR/MIDR_EL1 register |
| override_CTR | Uns32 | Override CTR/CTR_EL0 register |
| override_TLBTR | Uns32 | Override TLBTR register |
| override_CLIDR | Uns32 | Override CLIDR/CLIDR_EL1 register |
| override_AIDR | Uns32 | Override AIDR/AIDR_EL1 register |
| override_CBAR | Uns32 | Override Configuration Base Address Register (Corresponds to value on PERIPHBASE input pins) |
| override_PFR0 | Uns32 | Override ID_PFR0/ID_PFR0_EL1 register |
| override_PFR1 | Uns32 | Override ID_PFR1/ID_PFR1_EL1 register |
| override_DFR0 | Uns32 | Override ID_DFR0/ID_DFR0_EL1 register |
| override_AFR0 | Uns32 | Override ID_AFR0/ID_AFR0_EL1 register |
| override_MMFR0 | Uns32 | Override ID_MMFR0/ID_MMFR0_EL1 register |
| override_MMFR1 | Uns32 | Override ID_MMFR1/ID_MMFR1_EL1 register |
| override_MMFR2 | Uns32 | Override ID_MMFR2/ID_MMFR2_EL1 register |
| override_MMFR3 | Uns32 | Override ID_MMFR3/ID_MMFR3_EL1 register |
| override_MMFR4 | Uns32 | Override ID_MMFR4/ID_MMFR4_EL1 register |
| override_ISAR0 | Uns32 | Override ID_ISAR0/ID_ISAR0_EL1 register |
| override_ISAR1 | Uns32 | Override ID_ISAR1/ID_ISAR1_EL1 register |
| override_ISAR2 | Uns32 | Override ID_ISAR2/ID_ISAR2_EL1 register |
| override_ISAR3 | Uns32 | Override ID_ISAR3/ID_ISAR3_EL1 register |
| override_ISAR4 | Uns32 | Override ID_ISAR4/ID_ISAR4_EL1 register |
| override_ISAR5 | Uns32 | Override ID_ISAR5/ID_ISAR5_EL1 register |
| override_ISAR6 | Uns32 | Override ID_ISAR6/ID_ISAR6_EL1 register |

| | | |
|-----------------------------|-------|-----------------------------------------------------------------------------------|
| override_PMCR | Uns32 | Override PMCR/PMCR_EL0 register (not functionally significant in the model) |
| override_PMCEID0 | Uns64 | Override PMCEID0/PMCEID0_EL0 register (not functionally significant in the model) |
| override_PMCEID1 | Uns64 | Override PMCEID1/PMCEID1_EL0 register (not functionally significant in the model) |
| override_DBGDIDR | Uns32 | Override DBGDIDR register (not functionally significant in the model) |
| override_DBGDEVID | Uns32 | Override DBGDEVID register (not functionally significant in the model) |
| override_DBGDEVID1 | Uns32 | Override DBGDEVID1 register (not functionally significant in the model) |
| override_DBGDEVID2 | Uns32 | Override DBGDEVID2 register (not functionally significant in the model) |
| override_FPSID | Uns32 | Override SIMD/VFP FPSID register |
| override_MVFR0 | Uns32 | Override SIMD/VFP MVFR0/MVFR0_EL1 register |
| override_MVFR1 | Uns32 | Override SIMD/VFP MVFR1/MVFR1_EL1 register |
| override_MVFR2 | Uns32 | Override SIMD/VFP MVFR2/MVFR2_EL1 register |
| override_FPEXC | Uns32 | Override SIMD/VFP FPEXC/FPEXC32_EL2 register |
| override_GICC_IIDR | Uns32 | Override GICC_IIDR register (GICv1 ICCIIDR) |
| override_GICD_TYPER | Uns32 | Override GICD_TYPER register (GICv1 ICDICTR) |
| override_GICD_TYPER_ITLines | Uns32 | Override ITLinesNumber field of GICD_TYPER register (GICv1 ICDICTR) |
| override_GICD_ICFGRN | Uns32 | Override reset value of GICD_ICFGR2...GICD_ICFGRn (GICv1 ICDICFR2...ICDICFRn) |
| override_GICD_IIDR | Uns32 | Override GICD_IIDR register (GICv1 ICDIIDR) |
| override_GICH_VTR | Uns32 | Override GICH_VTR register |
| override_GICR_IIDR | Uns32 | Override GICR_IIDR register (GICv3 and later) |
| override_GITS_IIDR | Uns32 | Override GITS_IIDR register (GICv3 and later) |
| override_GITS_TYPER | Uns64 | Override GITS_TYPER register (GICv3 and later) |
| override_ICCPMRBits | Uns32 | Specify the number of writable bits in GICC_PMR (GICv1 ICCPMR) |
| override_minICCBPR | Uns32 | Specify the minimum possible value for GICC_BPR (GICv1 ICCBPR) |
| override_ERG | Uns32 | Specifies exclusive reservation granule |
| override_CCSIDR_1I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 1 instruction) |
| override_CCSIDR_1D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 1 data) |
| override_CCSIDR_2I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 2 instruction) |
| override_CCSIDR_2D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 2 data) |
| override_CCSIDR_3I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 3 instruction) |
| override_CCSIDR_3D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 3 data) |
| override_CCSIDR_4I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 4 instruction) |
| override_CCSIDR_4D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 4 data) |
| override_CCSIDR_5I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 5 instruction) |
| override_CCSIDR_5D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 5 data) |
| override_CCSIDR_6I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 6 instruction) |
| override_CCSIDR_6D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 6 data) |
| override_CCSIDR_7I | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 7 instruction) |
| override_CCSIDR_7D | Uns32 | Override CCSIDR/CCSIDR_EL1 (level 7 data) |
| override_RMR | Uns32 | Override RMR register alias at highest-implemented exception level |
| override_RVBAR | Uns64 | Override RVBAR register alias at highest-implemented exception level |
| override_AA64PFR0_EL1 | Uns64 | Override ID_AA64PFR0_EL1 register |
| override_AA64PFR1_EL1 | Uns64 | Override ID_AA64PFR1_EL1 register |
| override_AA64DFR0_EL1 | Uns64 | Override ID_AA64DFR0_EL1 register |

| | | |
|---------------------------------|---------|------------------------------------------------------------------------------------------------------------------------------------------|
| override_AA64DFR1_EL1 | Uns64 | Override ID_AA64DFR1_EL1 register |
| override_AA64AFR0_EL1 | Uns64 | Override ID_AA64AFR0_EL1 register |
| override_AA64AFR1_EL1 | Uns64 | Override ID_AA64AFR1_EL1 register |
| override_AA64ISAR0_EL1 | Uns64 | Override ID_AA64ISAR0_EL1 register |
| override_AA64ISAR1_EL1 | Uns64 | Override ID_AA64ISAR1_EL1 register |
| override_AA64MMFR0_EL1 | Uns64 | Override ID_AA64MMFR0_EL1 register |
| override_AA64MMFR1_EL1 | Uns64 | Override ID_AA64MMFR1_EL1 register |
| override_AA64MMFR2_EL1 | Uns64 | Override ID_AA64MMFR2_EL1 register |
| override_DCZID_EL0 | Uns32 | Override DCZID_EL0 register |
| override_LORID_EL1 | Uns32 | Override LORID_EL1 register (ARMv8.1 only) |
| override_STRoffsetPC12 | Boolean | Specifies that STR/STR of PC should do so with 12:byte offset from the current instruction (if true), otherwise an 8:byte offset is used |
| override_fcseRequiresMMU | Boolean | Specifies that FCSE is active only when MMU is enabled (if true) |
| override_ignoreBadCp15 | Boolean | Specifies whether invalid coprocessor 15 access should be ignored (if true) or cause Invalid Instruction exceptions (if false) |
| override_SGIDisable | Boolean | Override whether GIC SGIs may be disabled (if true) or are permanently enabled (if false) |
| override_condUndefined | Boolean | Force undefined instructions to take Undefined Instruction exception even if they are conditional |
| override_deviceStrongAligned | Boolean | Force accesses to Device and Strongly Ordered regions to be aligned |
| override_stage1SZMinFault | Boolean | Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ <minimum (by default, clamp to minimum) |
| override_stage1SZMaxFault | Boolean | Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ >maximum (by default, clamp to maximum) |
| override_stage2SZMinFault | Boolean | Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ <minimum (by default, clamp to minimum) |
| override_stage2SZMaxFault | Boolean | Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ >maximum (by default, clamp to maximum) |
| override_mask_ACTLR_EL1 | Uns64 | Override mask of writable bits in AArch64 ACTLR_EL1 register, or AArch32 non-secure ACTLR/ACTLR2 pair, if implemented |
| override_mask_ACTLR_EL2 | Uns64 | Override mask of writable bits in AArch64 ACTLR_EL2 register, or AArch32 HACTLR/HACTLR2 pair, if implemented |
| override_mask_ACTLR_EL3 | Uns64 | Override mask of writable bits in AArch64 ACTLR_EL3 register, or AArch32 secure ACTLR/ACTLR2 pair, if implemented |
| override_Control_V | Boolean | Override SCTLR.V with the passed value (deprecated, use override_SCTLR_V) |
| override_MainId | Uns32 | Override MIDR register (deprecated, use override_MIDR) |
| override_CacheType | Uns32 | Override CTR register (deprecated, use override_CTR) |
| override_TLBType | Uns32 | Override TLBTR register (deprecated, use override_TLBTR) |
| override_InstructionAttributes0 | Uns32 | Override ID_ISAR0 register (deprecated, use override_ISAR0) |
| override_InstructionAttributes1 | Uns32 | Override ID_ISAR1 register (deprecated, use override_ISAR1) |
| override_InstructionAttributes2 | Uns32 | Override ID_ISAR2 register (deprecated, use override_ISAR2) |

| | | |
|---------------------------------|-------|-------------------------------------------------------------|
| override.InstructionAttributes3 | Uns32 | Override ID_ISAR3 register (deprecated, use override_ISAR3) |
| override.InstructionAttributes4 | Uns32 | Override ID_ISAR4 register (deprecated, use override_ISAR4) |
| override.InstructionAttributes5 | Uns32 | Override ID_ISAR5 register (deprecated, use override_ISAR5) |

Table 8.1: Parameters that can be set in: MPCORE

Chapter 9

Execution Modes

| Mode | Code |
|------------|------|
| EL0t | 0 |
| EL1t | 4 |
| EL1h | 5 |
| EL2t | 8 |
| EL2h | 9 |
| EL3t | 12 |
| EL3h | 13 |
| User | 16 |
| FIQ | 17 |
| IRQ | 18 |
| Supervisor | 19 |
| Monitor | 22 |
| Abort | 23 |
| Hypervisor | 26 |
| Undefined | 27 |
| System | 31 |

Table 9.1: Modes implemented in: CPU

Chapter 10

Exceptions

| Exception | Code |
|-------------------|------|
| Reset | 0 |
| Undefined | 1 |
| SupervisorCall | 2 |
| SecureMonitorCall | 3 |
| HypervisorCall | 4 |
| PrefetchAbort | 5 |
| DataAbort | 6 |
| HypervisorTrap | 7 |
| IRQ | 8 |
| FIQ | 9 |
| IllegalState | 10 |
| MisalignedPC | 11 |
| MisalignedSP | 12 |
| SError | 13 |

Table 10.1: Exceptions implemented in: CPU

Chapter 11

Hierarchy of the model

A CPU core may be configured to instance many processors of a Symmetrical Multi Processor (SMP). A CPU core may also have sub elements within a processor, for example hardware threading blocks.

OVP processor models can be written to include SMP blocks and to have many levels of hierarchy. Some OVP CPU models may have a fixed hierarchy, and some may be configured by settings in a configuration register. Please see the register definitions of this model.

This model documentation shows the settings and hierarchy of the default settings for this model variant.

11.1 Level 1: MPCORE

This level in the model hierarchy has 2 commands.

This level in the model hierarchy has no register groups.

This level in the model hierarchy has 3 children:

CPU0, CPU1 and CPU2.

11.2 Level 2: CPU

This level in the model hierarchy has 5 commands.

This level in the model hierarchy has 31 register groups:

| Group name | Registers |
|---------------|-----------|
| Core | 15 |
| Core_AAarch64 | 33 |
| Control | 3 |
| User | 7 |
| FIQ | 8 |
| IRQ | 3 |
| Supervisor | 3 |
| Monitor | 3 |
| Hypervisor | 3 |
| Undefined | 3 |
| Abort | 3 |

| | |
|------------------------------------|-----|
| SIMD_VFP | 32 |
| SIMD_VFP_SYS | 6 |
| SIMD_FP_AArch64 | 32 |
| AArch32_32_bit_system | 277 |
| AArch32_32_bit_secure_system | 32 |
| AArch32_32_bit_non_secure_system | 32 |
| AArch32_64_bit_system | 21 |
| AArch32_64_bit_secure_system | 4 |
| AArch32_64_bit_non_secure_system | 4 |
| AArch64_system | 257 |
| AArch64_secure_system | 5 |
| AArch64_non_secure_system | 5 |
| AArch64_SYS_instruction_registers | 55 |
| Integration_support | 31 |
| MPCore_distributor | 179 |
| MPCore_physical_redistributor | 43 |
| MPCore_processor_interface | 16 |
| MPCore_virtual_interface_control | 11 |
| MPCore_virtual_processor_interface | 31 |
| MPCore_ITS | 14 |

Table 11.1: Register groups

This level in the model hierarchy has no children.

Chapter 12

Model Commands

A Processor model can implement one or more **Model Commands** available to be invoked from the simulator command line, from the OP API or from the Imperas Multiprocessor Debugger.

12.1 Level 1: MPCORE

12.1.1 isync

specify instruction address range for synchronous execution

| Argument | Type | Description |
|------------|-------|----------------------------------------------|
| -addresshi | Uns64 | end address of synchronous execution range |
| -addresslo | Uns64 | start address of synchronous execution range |

Table 12.1: isync command arguments

12.1.2 itrace

enable or disable instruction tracing

| Argument | Type | Description |
|-------------------|---------|----------------------------------------------|
| -after | Uns64 | apply after this many instructions |
| -enable | Boolean | enable instruction tracing |
| -instructioncount | Boolean | include the instruction number in each trace |
| -off | Boolean | disable instruction tracing |
| -on | Boolean | enable instruction tracing |
| -registerchange | Boolean | show registers changed by this instruction |
| -registers | Boolean | show registers after each trace |

Table 12.2: itrace command arguments

12.2 Level 2: CPU

12.2.1 debugflags

show or modify the processor debug flags

| Argument | Type | Description |
|----------|---------|-------------------------------------------------------------|
| -get | Boolean | print current processor flags value |
| -mask | Boolean | print current processor flags value |
| -set | Int32 | new processor flags (only flags 0x000003e4 can be modified) |

Table 12.3: debugflags command arguments

12.2.2 dumpTLB

report TLB contents

| Argument | Type | Description |
|----------|---------|---------------------------------------------------------------------|
| -all | Boolean | show the contents of all TLBs (if False, show just the current TLB) |

Table 12.4: dumpTLB command arguments

12.2.3 isync

specify instruction address range for synchronous execution

| Argument | Type | Description |
|------------|-------|----------------------------------------------|
| -addresshi | Uns64 | end address of synchronous execution range |
| -addresslo | Uns64 | start address of synchronous execution range |

Table 12.5: isync command arguments

12.2.4 itrace

enable or disable instruction tracing

| Argument | Type | Description |
|-------------------|---------|----------------------------------------------|
| -after | Uns64 | apply after this many instructions |
| -enable | Boolean | enable instruction tracing |
| -instructioncount | Boolean | include the instruction number in each trace |
| -off | Boolean | disable instruction tracing |
| -on | Boolean | enable instruction tracing |
| -registerchange | Boolean | show registers changed by this instruction |
| -registers | Boolean | show registers after each trace |

Table 12.6: itrace command arguments

12.2.5 validateTLB

check TLB contents against page tables in memory and report incoherent entries

| Argument | Type | Description |
|----------|------|-------------|
|----------|------|-------------|

| | | |
|----------|---------|---------------------------------------------------------------|
| -all | Boolean | check all TLBs (if False, validate just the current TLB) |
| -verbose | Boolean | show all TLB entries (if False, show only incoherent entries) |

Table 12.7: validateTLB command arguments

Chapter 13

Registers

13.1 Level 1: MPCORE

No registers.

13.2 Level 2: CPU

13.2.1 Core

Registers at level:2, type:CPU group:Core

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|---------------|
| r0 | 32 | 0 | rw | |
| r1 | 32 | 0 | rw | |
| r2 | 32 | 0 | rw | |
| r3 | 32 | 0 | rw | |
| r4 | 32 | 0 | rw | |
| r5 | 32 | 0 | rw | |
| r6 | 32 | 0 | rw | |
| r7 | 32 | 0 | rw | |
| r8 | 32 | 0 | rw | |
| r9 | 32 | 0 | rw | |
| r10 | 32 | 0 | rw | |
| r11 | 32 | 0 | rw | frame pointer |
| r12 | 32 | 0 | rw | |
| sp | 32 | 0 | rw | stack pointer |
| lr | 32 | 0 | rw | |

Table 13.1: Registers at level 2, type:CPU group:Core

13.2.2 Core_AAarch64

Registers at level:2, type:CPU group:Core_AAarch64

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| x0 | 64 | 0 | rw | |
| x1 | 64 | 0 | rw | |
| x2 | 64 | 0 | rw | |
| x3 | 64 | 0 | rw | |
| x4 | 64 | 0 | rw | |

| | | | | |
|-----|----|---|----|-----------------|
| x5 | 64 | 0 | rw | |
| x6 | 64 | 0 | rw | |
| x7 | 64 | 0 | rw | |
| x8 | 64 | 0 | rw | |
| x9 | 64 | 0 | rw | |
| x10 | 64 | 0 | rw | |
| x11 | 64 | 0 | rw | |
| x12 | 64 | 0 | rw | |
| x13 | 64 | 0 | rw | |
| x14 | 64 | 0 | rw | |
| x15 | 64 | 0 | rw | |
| x16 | 64 | 0 | rw | |
| x17 | 64 | 0 | rw | |
| x18 | 64 | 0 | rw | |
| x19 | 64 | 0 | rw | |
| x20 | 64 | 0 | rw | |
| x21 | 64 | 0 | rw | |
| x22 | 64 | 0 | rw | |
| x23 | 64 | 0 | rw | |
| x24 | 64 | 0 | rw | |
| x25 | 64 | 0 | rw | |
| x26 | 64 | 0 | rw | |
| x27 | 64 | 0 | rw | |
| x28 | 64 | 0 | rw | |
| x29 | 64 | 0 | rw | frame pointer |
| x30 | 64 | 0 | rw | |
| sp | 64 | 0 | rw | stack pointer |
| pc | 64 | 0 | rw | program counter |

Table 13.2: Registers at level 2, type:CPU group:Core_AAarch64

13.2.3 Control

Registers at level:2, type:CPU group:Control

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|------------------------------|
| fps | 32 | 0 | rw | archaic FPSCR view (for gdb) |
| cpsr | 32 | 3cd | rw | |
| spsr | 32 | 0 | rw | |

Table 13.3: Registers at level 2, type:CPU group:Control

13.2.4 User

Registers at level:2, type:CPU group:User

| Name | Bits | Initial-Hex | RW | Description |
|---------|------|-------------|----|-------------|
| r8_usr | 32 | 0 | rw | |
| r9_usr | 32 | 0 | rw | |
| r10_usr | 32 | 0 | rw | |
| r11_usr | 32 | 0 | rw | |
| r12_usr | 32 | 0 | rw | |
| sp_usr | 32 | 0 | rw | |
| lr_usr | 32 | 0 | rw | |

Table 13.4: Registers at level 2, type:CPU group:User

13.2.5 FIQ

Registers at level:2, type:CPU group:FIQ

| Name | Bits | Initial-Hex | RW | Description |
|----------|------|-------------|----|-------------|
| r8_fiq | 32 | 0 | rw | |
| r9_fiq | 32 | 0 | rw | |
| r10_fiq | 32 | 0 | rw | |
| r11_fiq | 32 | 0 | rw | |
| r12_fiq | 32 | 0 | rw | |
| sp_fiq | 32 | 0 | rw | |
| lr_fiq | 32 | 0 | rw | |
| spsr_fiq | 32 | 0 | rw | |

Table 13.5: Registers at level 2, type:CPU group:FIQ

13.2.6 IRQ

Registers at level:2, type:CPU group:IRQ

| Name | Bits | Initial-Hex | RW | Description |
|----------|------|-------------|----|-------------|
| sp_irq | 32 | 0 | rw | |
| lr_irq | 32 | 0 | rw | |
| spsr_irq | 32 | 0 | rw | |

Table 13.6: Registers at level 2, type:CPU group:IRQ

13.2.7 Supervisor

Registers at level:2, type:CPU group:Supervisor

| Name | Bits | Initial-Hex | RW | Description |
|----------|------|-------------|----|-------------|
| sp_svc | 32 | 0 | rw | |
| lr_svc | 32 | 0 | rw | |
| spsr_svc | 32 | 0 | rw | |

Table 13.7: Registers at level 2, type:CPU group:Supervisor

13.2.8 Monitor

Registers at level:2, type:CPU group:Monitor

| Name | Bits | Initial-Hex | RW | Description |
|----------|------|-------------|----|-------------|
| sp_mon | 32 | 0 | rw | |
| lr_mon | 32 | 0 | rw | |
| spsr_mon | 32 | 0 | rw | |

Table 13.8: Registers at level 2, type:CPU group:Monitor

13.2.9 Hypervisor

Registers at level:2, type:CPU group:Hypervisor

| Name | Bits | Initial-Hex | RW | Description |
|---------|------|-------------|----|-------------|
| sp_hyp | 32 | 0 | rw | |
| elr_hyp | 32 | 0 | rw | |

| | | | | |
|----------|----|---|----|--|
| spsr_hyp | 32 | 0 | rw | |
|----------|----|---|----|--|

Table 13.9: Registers at level 2, type:CPU group:Hypervisor

13.2.10 Undefined

Registers at level:2, type:CPU group:Undefined

| Name | Bits | Initial-Hex | RW | Description |
|------------|------|-------------|----|-------------|
| sp_undef | 32 | 0 | rw | |
| lr_undef | 32 | 0 | rw | |
| spsr_undef | 32 | 0 | rw | |

Table 13.10: Registers at level 2, type:CPU group:Undefined

13.2.11 Abort

Registers at level:2, type:CPU group:Abort

| Name | Bits | Initial-Hex | RW | Description |
|----------|------|-------------|----|-------------|
| sp_abt | 32 | 0 | rw | |
| lr_abt | 32 | 0 | rw | |
| spsr_abt | 32 | 0 | rw | |

Table 13.11: Registers at level 2, type:CPU group:Abort

13.2.12 SIMD_VFP

Registers at level:2, type:CPU group:SIMD_VFP

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| d0 | 64 | 0 | rw | |
| d1 | 64 | 0 | rw | |
| d2 | 64 | 0 | rw | |
| d3 | 64 | 0 | rw | |
| d4 | 64 | 0 | rw | |
| d5 | 64 | 0 | rw | |
| d6 | 64 | 0 | rw | |
| d7 | 64 | 0 | rw | |
| d8 | 64 | 0 | rw | |
| d9 | 64 | 0 | rw | |
| d10 | 64 | 0 | rw | |
| d11 | 64 | 0 | rw | |
| d12 | 64 | 0 | rw | |
| d13 | 64 | 0 | rw | |
| d14 | 64 | 0 | rw | |
| d15 | 64 | 0 | rw | |
| d16 | 64 | 0 | rw | |
| d17 | 64 | 0 | rw | |
| d18 | 64 | 0 | rw | |
| d19 | 64 | 0 | rw | |
| d20 | 64 | 0 | rw | |
| d21 | 64 | 0 | rw | |
| d22 | 64 | 0 | rw | |
| d23 | 64 | 0 | rw | |

| | | | | |
|-----|----|---|----|--|
| d24 | 64 | 0 | rw | |
| d25 | 64 | 0 | rw | |
| d26 | 64 | 0 | rw | |
| d27 | 64 | 0 | rw | |
| d28 | 64 | 0 | rw | |
| d29 | 64 | 0 | rw | |
| d30 | 64 | 0 | rw | |
| d31 | 64 | 0 | rw | |

Table 13.12: Registers at level 2, type:CPU group:SIMD_VFP

13.2.13 SIMD_VFP_SYS

Registers at level:2, type:CPU group:SIMD_VFP_SYS

| Name | Bits | Initial-Hex | RW | Description |
|-------|------|-------------|----|-------------------------------|
| FPSID | 32 | 41034080 | r- | floating-point system ID |
| FPSCR | 32 | 0 | rw | floating-point status/control |
| FPEXC | 32 | 700 | rw | floating-point exception |
| MVFR0 | 32 | 10110222 | r- | Media/VFP feature 0 |
| MVFR1 | 32 | 12111111 | r- | Media/VFP feature 1 |
| MVFR2 | 32 | 43 | r- | Media/VFP feature 2 |

Table 13.13: Registers at level 2, type:CPU group:SIMD_VFP_SYS

13.2.14 SIMD_FP_AArch64

Registers at level:2, type:CPU group:SIMD_FP_AArch64

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| v0 | 128 | - | rw | |
| v1 | 128 | - | rw | |
| v2 | 128 | - | rw | |
| v3 | 128 | - | rw | |
| v4 | 128 | - | rw | |
| v5 | 128 | - | rw | |
| v6 | 128 | - | rw | |
| v7 | 128 | - | rw | |
| v8 | 128 | - | rw | |
| v9 | 128 | - | rw | |
| v10 | 128 | - | rw | |
| v11 | 128 | - | rw | |
| v12 | 128 | - | rw | |
| v13 | 128 | - | rw | |
| v14 | 128 | - | rw | |
| v15 | 128 | - | rw | |
| v16 | 128 | - | rw | |
| v17 | 128 | - | rw | |
| v18 | 128 | - | rw | |
| v19 | 128 | - | rw | |
| v20 | 128 | - | rw | |
| v21 | 128 | - | rw | |
| v22 | 128 | - | rw | |
| v23 | 128 | - | rw | |
| v24 | 128 | - | rw | |

| | | | | |
|-----|-----|---|----|--|
| v25 | 128 | - | rw | |
| v26 | 128 | - | rw | |
| v27 | 128 | - | rw | |
| v28 | 128 | - | rw | |
| v29 | 128 | - | rw | |
| v30 | 128 | - | rw | |
| v31 | 128 | - | rw | |

Table 13.14: Registers at level 2, type:CPU group:SIMD_FP_AAArch64

13.2.15 AAarch32_32_bit_system

Registers at level:2, type:CPU group:AArch32_32_bit_system

| Name | Bits | Initial-Hex | RW | Description |
|------------|------|-------------|----|---------------------------------------------------------------------|
| ACTLR | 32 | 0 | rw | Auxiliary Control |
| ADFSR | 32 | 0 | rw | Auxiliary Data Fault Status |
| AIDR | 32 | 0 | r- | Auxiliary ID |
| AIFSR | 32 | 0 | rw | Auxiliary Instruction Fault Status |
| AMAIR0 | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 0 |
| AMAIR1 | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 1 |
| ATS1CPR | 32 | - | -w | Address Translate Stage 1 Current State EL1 Read |
| ATS1CPW | 32 | - | -w | Address Translate Stage 1 Current State EL1 Write |
| ATS1CUR | 32 | - | -w | Address Translate Stage 1 Current State Unprivileged Read |
| ATS1CUW | 32 | - | -w | Address Translate Stage 1 Current State Unprivileged Write |
| ATS1HR | 32 | - | -w | Address Translate Stage 1 Hyp Mode Read |
| ATS1HW | 32 | - | -w | Address Translate Stage 1 Hyp Mode Write |
| ATS12NSOPR | 32 | - | -w | Address Translate Stages 1 and 2 Non-Secure Only EL1 Read |
| ATS12NSOPW | 32 | - | -w | Address Translate Stages 1 and 2 Non-Secure Only EL1 Write |
| ATS12NSOUR | 32 | - | -w | Address Translate Stages 1 and 2 Non-Secure Only Unprivileged Read |
| ATS12NSOUW | 32 | - | -w | Address Translate Stages 1 and 2 Non-Secure Only Unprivileged Write |
| BPIALL | 32 | - | -w | Branch Predictor Invalidate All |
| BPIALLIS | 32 | - | -w | Branch Predictor Invalidate All (IS) |
| BPIMVA | 32 | - | -w | Branch Predictor Invalidate by VA |
| CBAR | 32 | 13080000 | r- | Configuration Base Address |
| CCSIDR | 32 | 701fe00a | r- | Cache Size ID |
| CLIDR | 32 | a200023 | r- | Cache Level ID |
| CNTFRQ | 32 | 4c4b40 | rw | Counter Frequency |
| CNTHCTL | 32 | 3 | rw | Timer EL2 Control |
| CNTHP_CTL | 32 | 0 | rw | Counter-Timer Hyp Physical Timer Control |
| CNTHP_TVAL | 32 | 0 | rw | Counter-Timer Hyp Physical Timer TimerValue |
| CNTKCTL | 32 | 0 | rw | Timer EL1 Control |
| CNTP_CTL | 32 | 0 | rw | Counter-Timer Physical Timer Control |
| CNTP_TVAL | 32 | 0 | rw | Counter-Timer Physical Timer TimerValue |
| CNTV_CTL | 32 | 0 | rw | Counter-Timer Virtual Timer Control |
| CNTV_TVAL | 32 | 0 | rw | Counter-Timer Virtual Timer TimerValue |
| CONTEXTIDR | 32 | 0 | rw | Context ID |
| CP15DMB | 32 | - | -w | CP15 Data Memory Barrier |
| CP15DSB | 32 | - | -w | CP15 Data Synchronization Barrier |
| CP15ISB | 32 | - | -w | CP15 Instruction Synchronization Barrier |
| CPACR | 32 | 0 | rw | Coprocessor Access Control |
| CSSELR | 32 | 0 | rw | Cache Size Selection |
| CTR | 32 | 8444c004 | r- | Cache Type |
| DACR | 32 | 0 | rw | Domain Access Control |

| | | | | |
|---------------|----|----------|----|---------------------------------------------------|
| DEGAUTHSTATUS | 32 | aa | r- | Debug Authentication Status |
| DBGBCR0 | 32 | 0 | rw | Debug Breakpoint Control 0 |
| DBGBCR1 | 32 | 0 | rw | Debug Breakpoint Control 1 |
| DBGBCR2 | 32 | 0 | rw | Debug Breakpoint Control 2 |
| DBGBCR3 | 32 | 0 | rw | Debug Breakpoint Control 3 |
| DBGBCR4 | 32 | 0 | rw | Debug Breakpoint Control 4 |
| DBGBCR5 | 32 | 0 | rw | Debug Breakpoint Control 5 |
| DBGBVR0 | 32 | 0 | rw | Debug Breakpoint Value 0 |
| DBGBVR1 | 32 | 0 | rw | Debug Breakpoint Value 1 |
| DBGBVR2 | 32 | 0 | rw | Debug Breakpoint Value 2 |
| DBGBVR3 | 32 | 0 | rw | Debug Breakpoint Value 3 |
| DBGBVR4 | 32 | 0 | rw | Debug Breakpoint Value 4 |
| DBGBVR5 | 32 | 0 | rw | Debug Breakpoint Value 5 |
| DBGBXVR0 | 32 | 0 | rw | Debug Breakpoint Extended Value 0 |
| DBGBXVR1 | 32 | 0 | rw | Debug Breakpoint Extended Value 1 |
| DBGBXVR2 | 32 | 0 | rw | Debug Breakpoint Extended Value 2 |
| DBGBXVR3 | 32 | 0 | rw | Debug Breakpoint Extended Value 3 |
| DBGBXVR4 | 32 | 0 | rw | Debug Breakpoint Extended Value 4 |
| DBGBXVR5 | 32 | 0 | rw | Debug Breakpoint Extended Value 5 |
| DBGCLAIMCLR | 32 | 0 | rw | Debug Claim Tag Clear |
| DBGCLAIMSET | 32 | 0 | rw | Debug Claim Tag Set |
| DBGDCCINT | 32 | 0 | rw | DCC Interrupt Enable |
| DBGDEVID | 32 | 1110f13 | r- | Debug Device ID |
| DBGDEVID1 | 32 | 2 | r- | Debug Device ID 1 |
| DBGDEVID2 | 32 | 0 | r- | Debug Device ID 2 |
| DBGDIDR | 32 | 3516d000 | r- | Debug ID |
| DBGDRAR | 32 | 0 | r- | Debug ROM Address (32-bit) |
| DBGDSAR | 32 | 0 | r- | Debug Self Address (32-bit) |
| DBGDSCRExt | 32 | 0 | rw | Debug Status and Control |
| DBGDSCRint | 32 | 0 | r- | Debug Status and Control, Internal View |
| DBGDTRRXext | 32 | 0 | rw | Debug Data Transfer, Receive, External View |
| DBGDTRTRXint | 32 | 0 | rw | Debug Data Transfer, Transmit/Receive |
| DBGDTRTXext | 32 | 0 | rw | Debug Data Transfer, Transmit, External View |
| DBGOSDLR | 32 | 0 | rw | Debug OS Double Lock |
| DBGOSECCR | 32 | 0 | rw | Debug OS Lock Exception Catch Control |
| DBGOSLAR | 32 | - | -w | Debug OS Lock Access |
| DBGOSLSR | 32 | a | r- | Debug OS Lock Status |
| DBGPRCR | 32 | 0 | rw | Debug Power Control |
| DBGVCR | 32 | 0 | rw | Debug Vector Catch |
| DBGWCR0 | 32 | 0 | rw | Debug Watchpoint Control 0 |
| DBGWCR1 | 32 | 0 | rw | Debug Watchpoint Control 1 |
| DBGWCR2 | 32 | 0 | rw | Debug Watchpoint Control 2 |
| DBGWCR3 | 32 | 0 | rw | Debug Watchpoint Control 3 |
| DBGWFAR | 32 | 0 | rw | Debug Watchpoint Fault Address |
| DBGWVR0 | 32 | 0 | rw | Debug Watchpoint Value 0 |
| DBGWVR1 | 32 | 0 | rw | Debug Watchpoint Value 1 |
| DBGWVR2 | 32 | 0 | rw | Debug Watchpoint Value 2 |
| DBGWVR3 | 32 | 0 | rw | Debug Watchpoint Value 3 |
| DCCIMVAC | 32 | - | -w | Data Cache Line Clean and Invalidate by VA to PoC |
| DCCISW | 32 | - | -w | Data Cache Line Clean and Invalidate by Set/Way |
| DCCMVAC | 32 | - | -w | Data Cache Line Clean by VA to PoC |
| DCCMVAU | 32 | - | -w | Data Cache Line Clean by VA to PoU |
| DCCSW | 32 | - | -w | Data Cache Line Clean by Set/Way |
| DCIMVAC | 32 | - | -w | Data Cache Line Invalidate by VA to PoC |
| DCISW | 32 | - | -w | Data Cache Line Invalidate by Set/Way |
| DFAR | 32 | 0 | rw | Data Fault Address |

| | | | | |
|-------------|----|----------|----|-------------------------------------------------------------|
| DFSR | 32 | 0 | rw | Data Fault Status |
| DL1DATA0 | 32 | 0 | rw | Data L1 Data 0 |
| DL1DATA1 | 32 | 0 | rw | Data L1 Data 1 |
| DL1DATA2 | 32 | 0 | rw | Data L1 Data 2 |
| DL1DATA3 | 32 | 0 | rw | Data L1 Data 3 |
| DL1DATA4 | 32 | 0 | rw | Data L1 Data 4 |
| DLR | 32 | 0 | rw | Debug Link |
| DSPSR | 32 | 0 | rw | Debug Saved Program Status |
| DTLBIALL | 32 | - | -w | Invalidate Entire Data TLB |
| DTLBIASID | 32 | - | -w | Invalidate Data TLB by ASID |
| DTLBMVA | 32 | - | -w | Invalidate Data TLB by VA |
| HACR | 32 | 0 | rw | Hyp Auxiliary Configuration |
| HACTLR | 32 | 0 | rw | Hyp Auxiliary Control |
| HADFSR | 32 | 0 | rw | Hyp Auxiliary Data Fault Status |
| HAIFSR | 32 | 0 | rw | Hyp Auxiliary Instruction Fault Status |
| HAMAIRO | 32 | 0 | rw | Hyp Auxiliary Memory Attribute Indirection 0 |
| HMAIR1 | 32 | 0 | rw | Hyp Auxiliary Memory Attribute Indirection 1 |
| HCPTR | 32 | 33ff | rw | Hyp Coprocessor Trap |
| HCR | 32 | 0 | rw | Hyp Configuration |
| HCR2 | 32 | 0 | rw | Hyp Configuration 2 |
| HDCR | 32 | 6 | rw | Hyp Debug Configuration |
| HDFAR | 32 | 0 | rw | Hyp Data Fault Address |
| HIFAR | 32 | 0 | rw | Hyp Instruction Fault Address |
| HMAIRO | 32 | 0 | rw | Hyp Memory Attribute Indirection 0 |
| HMAIR1 | 32 | 0 | rw | Hyp Memory Attribute Indirection 1 |
| HPFAR | 32 | 0 | rw | Hyp IPA Fault Address |
| HSCTLR | 32 | 30c50838 | rw | Hyp System Control |
| HSR | 32 | 0 | rw | Hyp Syndrome |
| HSTR | 32 | 0 | rw | Hyp System Trap |
| HTCR | 32 | 80800000 | rw | Hyp Translation Control |
| HTPIDR | 32 | 0 | rw | Hyp Thread and Process ID |
| HVBAR | 32 | 0 | rw | Hyp Vector Base Address |
| ICC_AP0R0 | 32 | 0 | rw | Interrupt Controller Active Priorities Group 0, 0 |
| ICC_AP1R0 | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_BPR0 | 32 | 2 | rw | Interrupt Controller Binary Point 0 |
| ICC_BPR1 | 32 | 3 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR | 32 | 400 | rw | Interrupt Controller Control |
| ICC_DIR | 32 | - | -w | Interrupt Controller Deactivate Interrupt |
| ICC_EOIR0 | 32 | - | -w | Interrupt Controller End of Interrupt 0 |
| ICC_EOIR1 | 32 | - | -w | Interrupt Controller End of Interrupt 1 |
| ICC_HPPIR0 | 32 | 3ff | r- | Interrupt Controller Highest Priority Pending Interrupt 0 |
| ICC_HPPIR1 | 32 | 3ff | r- | Interrupt Controller Highest Priority Pending Interrupt 1 |
| ICC_HSRE | 32 | 0 | rw | Interrupt Controller Hyp System Register Enable |
| ICC_IAR0 | 32 | 3ff | r- | Interrupt Controller Interrupt Acknowledge 0 |
| ICC_IAR1 | 32 | 3ff | r- | Interrupt Controller Interrupt Acknowledge 1 |
| ICC_IGRPEN0 | 32 | 0 | rw | Interrupt Controller Interrupt Group 0 Enable |
| ICC_IGRPEN1 | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_MCTLR | 32 | 400 | rw | Interrupt Controller Monitor Control |
| ICC_MGRPEN1 | 32 | 0 | rw | Interrupt Controller Monitor Interrupt Group 1 Enable |
| ICC_MSRE | 32 | 0 | rw | Interrupt Controller Monitor System Register Enable |
| ICC_PMR | 32 | 0 | rw | Interrupt Controller Priority Mask |
| ICC_RPR | 32 | ff | r- | Interrupt Controller Running Priority |
| ICC_SRE | 32 | 0 | rw | Interrupt Controller System Register Enable |
| ICH_AP0R0 | 32 | 0 | rw | Interrupt Controller Hyp Active Priorities Group 0 (Word 0) |
| ICH_AP1R0 | 32 | 0 | rw | Interrupt Controller Hyp Active Priorities Group 1 (Word 0) |
| ICH_EISR | 32 | 0 | r- | Interrupt Controller End of Interrupt Status |

| | | | | |
|-----------|----|----------|----|--------------------------------------------------|
| ICH_ELRSR | 32 | f | r- | Interrupt Controller Empty List Register Status |
| ICH_HCR | 32 | 0 | rw | Interrupt Controller Hypervisor Control |
| ICH_LR0 | 32 | 0 | rw | Interrupt Controller List 0 (Bits 31:0) |
| ICH_LR1 | 32 | 0 | rw | Interrupt Controller List 1 (Bits 31:0) |
| ICH_LR2 | 32 | 0 | rw | Interrupt Controller List 2 (Bits 31:0) |
| ICH_LR3 | 32 | 0 | rw | Interrupt Controller List 3 (Bits 31:0) |
| ICH_LRC0 | 32 | 0 | rw | Interrupt Controller List 0 (Bits 63:32) |
| ICH_LRC1 | 32 | 0 | rw | Interrupt Controller List 1 (Bits 63:32) |
| ICH_LRC2 | 32 | 0 | rw | Interrupt Controller List 2 (Bits 63:32) |
| ICH_LRC3 | 32 | 0 | rw | Interrupt Controller List 3 (Bits 63:32) |
| ICH_MISR | 32 | 0 | r- | Interrupt Controller Maintenance Interrupt State |
| ICH_VMCR | 32 | 4c0000 | rw | Interrupt Controller Virtual Machine Control |
| ICH_VTR | 32 | 90100003 | r- | Interrupt Controller VGIC Type |
| ICIALLU | 32 | - | -w | Instruction Cache Invalidate All |
| ICIALLUIS | 32 | - | -w | Instruction Cache Invalidate All (IS) |
| ICIMVAU | 32 | - | -w | Instruction Cache Invalidate by VA |
| ID_AFR0 | 32 | 0 | r- | Auxiliary Feature 0 |
| ID_DFR0 | 32 | 3010066 | r- | Debug Feature 0 |
| ID_ISAR0 | 32 | 2101110 | r- | Instruction Set Attribute 0 |
| ID_ISAR1 | 32 | 13112111 | r- | Instruction Set Attribute 1 |
| ID_ISAR2 | 32 | 21232042 | r- | Instruction Set Attribute 2 |
| ID_ISAR3 | 32 | 1112131 | r- | Instruction Set Attribute 3 |
| ID_ISAR4 | 32 | 11142 | r- | Instruction Set Attribute 4 |
| ID_ISAR5 | 32 | 1 | r- | Instruction Set Attribute 5 |
| ID_MMFR0 | 32 | 10201105 | r- | Memory Model Feature 0 |
| ID_MMFR1 | 32 | 40000000 | r- | Memory Model Feature 1 |
| ID_MMFR2 | 32 | 1260000 | r- | Memory Model Feature 2 |
| ID_MMFR3 | 32 | 2102211 | r- | Memory Model Feature 3 |
| ID_PFR0 | 32 | 131 | r- | Processor Feature 0 |
| ID_PFR1 | 32 | 10011011 | r- | Processor Feature 1 |
| IFAR | 32 | 0 | rw | Instruction Fault Address |
| IFSR | 32 | 0 | rw | Instruction Fault Status |
| IL1DATA0 | 32 | 0 | rw | Instruction L1 Data 0 |
| IL1DATA1 | 32 | 0 | rw | Instruction L1 Data 1 |
| IL1DATA2 | 32 | 0 | rw | Instruction L1 Data 2 |
| IL1DATA3 | 32 | 0 | rw | Instruction L1 Data 3 |
| ISR | 32 | 0 | r- | Interrupt Status |
| ITLBIALL | 32 | - | -w | Invalidate Entire Instruction TLB |
| ITLBIASID | 32 | - | -w | Invalidate Instruction TLB by ASID |
| ITLBIMVA | 32 | - | -w | Invalidate Instruction TLB by VA |
| JIDR | 32 | 0 | rw | Jazelle ID |
| JMCR | 32 | 0 | rw | Jazelle Main Configuration |
| JOSCR | 32 | 0 | rw | Jazelle OS Control |
| L2ACTLR | 32 | 0 | rw | L2 Auxiliary Control |
| L2CTLR | 32 | 2000000 | rw | L2 Control |
| L2ECTLR | 32 | 0 | rw | L2 Extended Control |
| MAIR0 | 32 | 98aa4 | rw | Memory Attribute Indirection 0 |
| MAIR1 | 32 | 44e048e0 | rw | Memory Attribute Indirection 1 |
| MIDR | 32 | 410fd081 | r- | Main ID |
| MPIDR | 32 | 80000000 | r- | Multiprocessor Affinity |
| MVBAR | 32 | 0 | rw | Monitor Vector Base Address |
| NMRR | 32 | 44e048e0 | rw | Normal Memory Remap |
| NSACR | 32 | c00 | rw | Non-Secure Access Control |
| PAR | 32 | 0 | rw | Physical Address |
| PMCCFILTR | 32 | 0 | rw | Performance Monitors Cycle Count Filter |
| PMCCNTR | 32 | 0 | rw | Performance Monitors Cycle Count |

| | | | | |
|---------------|----|----------|----|---------------------------------------------------------|
| PMCEID0 | 32 | 7fff0f3f | r- | Performance Monitors Common Event ID 0 |
| PMCEID1 | 32 | 0 | r- | Performance Monitors Common Event ID 1 |
| PMCNTENCLR | 32 | 0 | rw | Performance Monitors Count Enable Clear |
| PMCNTENSET | 32 | 0 | rw | Performance Monitors Count Enable Set |
| PMCR | 32 | 41023000 | rw | Performance Monitors Control |
| PMEVCNTR0 | 32 | 0 | rw | Performance Monitors Event Count 0 |
| PMEVCNTR1 | 32 | 0 | rw | Performance Monitors Event Count 1 |
| PMEVCNTR2 | 32 | 0 | rw | Performance Monitors Event Count 2 |
| PMEVCNTR3 | 32 | 0 | rw | Performance Monitors Event Count 3 |
| PMEVCNTR4 | 32 | 0 | rw | Performance Monitors Event Count 4 |
| PMEVCNTR5 | 32 | 0 | rw | Performance Monitors Event Count 5 |
| PMEVTYPEPER0 | 32 | 0 | rw | Performance Monitors Event Type 0 |
| PMEVTYPEPER1 | 32 | 0 | rw | Performance Monitors Event Type 1 |
| PMEVTYPEPER2 | 32 | 0 | rw | Performance Monitors Event Type 2 |
| PMEVTYPEPER3 | 32 | 0 | rw | Performance Monitors Event Type 3 |
| PMEVTYPEPER4 | 32 | 0 | rw | Performance Monitors Event Type 4 |
| PMEVTYPEPER5 | 32 | 0 | rw | Performance Monitors Event Type 5 |
| PMINTENCLR | 32 | 0 | rw | Performance Monitors Interrupt Enable Clear |
| PMINTENSET | 32 | 0 | rw | Performance Monitors Interrupt Enable Set |
| PMOVS | 32 | 0 | rw | Performance Monitors Overflow Flag Status |
| PMOVSSET | 32 | 0 | rw | Performance Monitors Overflow Flag Status Set |
| PMSEL | 32 | 0 | rw | Performance Monitors Event Counter Selection |
| PMSWINC | 32 | - | -w | Performance Monitors Software Increment |
| PMUSERENR | 32 | 0 | rw | Performance Monitors User Enable |
| PMXEVNTR | 32 | 0 | rw | Performance Monitors Selected Event Count |
| PMXEVTYPEPER | 32 | 0 | rw | Performance Monitors Selected Event Type |
| PRRR | 32 | 98aa4 | rw | Primary Region Remap |
| RAMINDEX | 32 | - | -w | RAM Index |
| REVIDR | 32 | 0 | r- | Revision ID |
| RMR | 32 | 1 | rw | Reset Management |
| SCR | 32 | 0 | rw | Secure Configuration |
| SCTLR | 32 | c50838 | rw | System Control |
| SDCR | 32 | 0 | rw | Secure Debug Configuration |
| SDER | 32 | 0 | rw | Secure Debug Enable |
| TCMTR | 32 | 0 | r- | TCM Type |
| TLBIALL | 32 | - | -w | Invalidate Entire Unified TLB |
| TLBIALLH | 32 | - | -w | Invalidate Entire Hyp Unified TLB |
| TLBIALLHIS | 32 | - | -w | Invalidate Entire Hyp TLB (IS) |
| TLBIALLIS | 32 | - | -w | Invalidate Entire Unified TLB (IS) |
| TLBIALLNSNH | 32 | - | -w | Invalidate Entire Non-Secure Non-Hyp Unified TLB |
| TLBIALLNSNHIS | 32 | - | -w | Invalidate Entire Non-Secure Non-Hyp Unified TLB (IS) |
| TLBIASID | 32 | - | -w | Invalidate Unified TLB by ASID |
| TLBIASIDIS | 32 | - | -w | Invalidate Unified TLB by ASID (IS) |
| TLBIIPAS2 | 32 | - | -w | Invalidate by IPA, Stage 2 |
| TLBIIPAS2IS | 32 | - | -w | Invalidate by IPA, Stage 2 (IS) |
| TLBIIPAS2L | 32 | - | -w | Invalidate by IPA, Stage 2, Last level |
| TLBIIPAS2LIS | 32 | - | -w | Invalidate by IPA, Stage 2, Last level (IS) |
| TLBIMVA | 32 | - | -w | Invalidate Unified TLB by VA |
| TLBIMVAA | 32 | - | -w | Invalidate Unified TLB by VA, all ASID |
| TLBIMVAAIS | 32 | - | -w | Invalidate Unified TLB by VA, all ASID (IS) |
| TLBIMVAAL | 32 | - | -w | Invalidate Unified TLB by VA, all ASID, Last level |
| TLBIMVAALIS | 32 | - | -w | Invalidate Unified TLB by VA, all ASID, Last level (IS) |
| TLBIMVAH | 32 | - | -w | Invalidate Hyp Unified TLB by VA |
| TLBIMVAHIS | 32 | - | -w | Invalidate Hyp Unified TLB by VA (IS) |
| TLBIMVAIS | 32 | - | -w | Invalidate Unified TLB by VA (IS) |
| TLBIMVAL | 32 | - | -w | Invalidate Unified TLB by VA, Last level |

| | | | | |
|-------------|----|----------|----|---------------------------------------------------|
| TLBIMVALH | 32 | - | -w | Invalidate Hyp Unified TLB by VA, Last level |
| TLBIMVALHIS | 32 | - | -w | Invalidate Hyp Unified TLB by VA, Last level (IS) |
| TLBIMVALIS | 32 | - | -w | Invalidate Unified TLB by VA, Last level (IS) |
| TLBTR | 32 | 0 | r- | TLB Type |
| TPIDRPRW | 32 | 0 | rw | PL0 Read/Write Software Thread ID |
| TPIDRURO | 32 | 0 | rw | PL0 Read-Only Software Thread ID |
| TPIDRURW | 32 | 0 | rw | PL1 Software Thread ID |
| TTBCR | 32 | 0 | rw | Translation Table Base Control |
| TTBR0 | 32 | 0 | rw | Translation Table Base 0 |
| TTBR1 | 32 | 0 | rw | Translation Table Base 1 |
| VBAR | 32 | 0 | rw | Vector Base Address |
| VMPIDR | 32 | 80000000 | rw | Virtualization Multiprocessor ID |
| VPIDR | 32 | 410fd081 | rw | Virtualization Processor ID |
| VTCR | 32 | 80000000 | rw | Virtualization Translation Control |

Table 13.15: Registers at level 2, type:CPU group:AArch32_32_bit_system

13.2.16 AArch32_32_bit_secure_system

Registers at level:2, type:CPU group:AArch32_32_bit_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|---------------|------|-------------|----|---------------------------------------------------|
| ACTLR_S | 32 | 0 | rw | Auxiliary Control |
| ADFSR_S | 32 | 0 | rw | Auxiliary Data Fault Status |
| AIFSR_S | 32 | 0 | rw | Auxiliary Instruction Fault Status |
| AMAIRO_S | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 0 |
| AMAIR1_S | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 1 |
| CNTP_CTL_S | 32 | 0 | rw | Counter-Timer Physical Timer Control |
| CNTP_TVAL_S | 32 | 0 | rw | Counter-Timer Physical Timer TimerValue |
| CONTEXTIDR_S | 32 | 0 | rw | Context ID |
| CSSELR_S | 32 | 0 | rw | Cache Size Selection |
| DACR_S | 32 | 0 | rw | Domain Access Control |
| DFAR_S | 32 | 0 | rw | Data Fault Address |
| DFSR_S | 32 | 0 | rw | Data Fault Status |
| ICC_APIRO_S | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_BPR1_S | 32 | 2 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR_S | 32 | 400 | rw | Interrupt Controller Control |
| ICC_IGRPEN1_S | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_SRE_S | 32 | 0 | rw | Interrupt Controller System Register Enable |
| IFAR_S | 32 | 0 | rw | Instruction Fault Address |
| IFSR_S | 32 | 0 | rw | Instruction Fault Status |
| MAIRO_S | 32 | 98aa4 | rw | Memory Attribute Indirection 0 |
| MAIR1_S | 32 | 44e048e0 | rw | Memory Attribute Indirection 1 |
| NMRR_S | 32 | 44e048e0 | rw | Normal Memory Remap |
| PAR_S | 32 | 0 | rw | Physical Address |
| PRRR_S | 32 | 98aa4 | rw | Primary Region Remap |
| SCTLR_S | 32 | c50838 | rw | System Control |
| TPIDRPRW_S | 32 | 0 | rw | PL0 Read/Write Software Thread ID |
| TPIDRURO_S | 32 | 0 | rw | PL0 Read-Only Software Thread ID |
| TPIDRURW_S | 32 | 0 | rw | PL1 Software Thread ID |
| TTBCR_S | 32 | 0 | rw | Translation Table Base Control |
| TTBR0_S | 32 | 0 | rw | Translation Table Base 0 |
| TTBR1_S | 32 | 0 | rw | Translation Table Base 1 |
| VBAR_S | 32 | 0 | rw | Vector Base Address |

Table 13.16: Registers at level 2, type:CPU group:AArch32_32_bit_secure_system

13.2.17 AArch32_32_bit_non_secure_system

Registers at level:2, type:CPU group:AArch32_32_bit_non_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|----------------|------|-------------|----|---------------------------------------------------|
| ACTLR_NS | 32 | 0 | rw | Auxiliary Control |
| ADFSR_NS | 32 | 0 | rw | Auxiliary Data Fault Status |
| AIFSR_NS | 32 | 0 | rw | Auxiliary Instruction Fault Status |
| AMAIR0_NS | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 0 |
| AMAIR1_NS | 32 | 0 | rw | Auxiliary Memory Attribute Indirection 1 |
| CNTP_CTL_NS | 32 | 0 | rw | Counter-Timer Physical Timer Control |
| CNTP_TVAL_NS | 32 | 0 | rw | Counter-Timer Physical Timer TimerValue |
| CONTEXTIDR_NS | 32 | 0 | rw | Context ID |
| CSSELR_NS | 32 | 0 | rw | Cache Size Selection |
| DACR_NS | 32 | 0 | rw | Domain Access Control |
| DFAR_NS | 32 | 0 | rw | Data Fault Address |
| DFSR_NS | 32 | 0 | rw | Data Fault Status |
| ICC_APIR0_NS | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_BPR1_NS | 32 | 3 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR_NS | 32 | 400 | rw | Interrupt Controller Control |
| ICC_IGRPEN1_NS | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_SRE_NS | 32 | 0 | rw | Interrupt Controller System Register Enable |
| IFAR_NS | 32 | 0 | rw | Instruction Fault Address |
| IFSR_NS | 32 | 0 | rw | Instruction Fault Status |
| MAIR0_NS | 32 | 98aa4 | rw | Memory Attribute Indirection 0 |
| MAIR1_NS | 32 | 44e048e0 | rw | Memory Attribute Indirection 1 |
| NMRR_NS | 32 | 44e048e0 | rw | Normal Memory Remap |
| PAR_NS | 32 | 0 | rw | Physical Address |
| PRRR_NS | 32 | 98aa4 | rw | Primary Region Remap |
| SCTLR_NS | 32 | c50838 | rw | System Control |
| TPIDRPRW_NS | 32 | 0 | rw | PL0 Read/Write Software Thread ID |
| TPIDRURO_NS | 32 | 0 | rw | PL0 Read-Only Software Thread ID |
| TPIDRURW_NS | 32 | 0 | rw | PL1 Software Thread ID |
| TTBCR_NS | 32 | 0 | rw | Translation Table Base Control |
| TTBR0_NS | 32 | 0 | rw | Translation Table Base 0 |
| TTBR1_NS | 32 | 0 | rw | Translation Table Base 1 |
| VBAR_NS | 32 | 0 | rw | Vector Base Address |

Table 13.17: Registers at level 2, type:CPU group:AArch32_32_bit_non_secure_system

13.2.18 AArch32_64_bit_system

Registers at level:2, type:CPU group:AArch32_64_bit_system

| Name | Bits | Initial-Hex | RW | Description |
|------------|------|-------------|----|-----------------------------------------------|
| CNTHP_CVAL | 64 | 0 | rw | Counter-Timer Hyp Physical Timer CompareValue |
| CNTPCT | 64 | 0 | r- | Counter-Timer Physical Count |
| CNTP_CVAL | 64 | 0 | rw | Counter-Timer Physical Timer CompareValue |
| CNTVCT | 64 | 0 | r- | Counter-Timer Virtual Count |
| CNTVOFF | 64 | 0 | rw | Virtual Offset |
| CNTV_CVAL | 64 | 0 | rw | Counter-Timer Virtual Timer CompareValue |
| CPUACTLR | 64 | 0 | rw | CPU Auxiliary Control |
| CPUECTLR | 64 | 1b 00000000 | rw | CPU Extended Control |
| CPUMERRSR | 64 | 0 | rw | CPU Memory Error Syndrome |
| DBGDRAR64 | 64 | 0 | r- | Debug ROM Address (64-bit) |
| DBGDSAR64 | 64 | 0 | r- | Debug Self Address (64-bit) |
| HTTBR | 64 | 0 | rw | Hyp Translation Table Base |

| | | | | |
|------------|----|---|----|-------------------------------------------|
| ICC.ASGI1R | 64 | - | -w | Interrupt Controller Alias SGI Group 1 |
| ICC.SGI0R | 64 | - | -w | Interrupt Controller SGI Group 0 |
| ICC.SGI1R | 64 | - | -w | Interrupt Controller SGI Group 1 |
| L2MERRSR | 64 | 0 | rw | L2 Memory Error Syndrome |
| PARLPA | 64 | 0 | rw | Physical Address |
| PMCCNTR64 | 64 | 0 | rw | Performance Monitors Cycle Count (64-bit) |
| TTBR0LPA | 64 | 0 | rw | Translation Table Base 0 |
| TTBR1LPA | 64 | 0 | rw | Translation Table Base 1 |
| VTBR | 64 | 0 | rw | Virtualization Translation Table Base |

Table 13.18: Registers at level 2, type:CPU group:AArch32_64_bit_system

13.2.19 AArch32_64_bit_secure_system

Registers at level:2, type:CPU group:AArch32_64_bit_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|------------|------|-------------|----|-------------------------------------------|
| CNTP_CVALS | 64 | 0 | rw | Counter-Timer Physical Timer CompareValue |
| PARLPA_S | 64 | 0 | rw | Physical Address |
| TTBR0LPA_S | 64 | 0 | rw | Translation Table Base 0 |
| TTBR1LPA_S | 64 | 0 | rw | Translation Table Base 1 |

Table 13.19: Registers at level 2, type:CPU group:AArch32_64_bit_secure_system

13.2.20 AArch32_64_bit_non_secure_system

Registers at level:2, type:CPU group:AArch32_64_bit_non_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|--------------|------|-------------|----|-------------------------------------------|
| CNTP_CVAL_NS | 64 | 0 | rw | Counter-Timer Physical Timer CompareValue |
| PARLPA_NS | 64 | 0 | rw | Physical Address |
| TTBR0LPA_NS | 64 | 0 | rw | Translation Table Base 0 |
| TTBR1LPA_NS | 64 | 0 | rw | Translation Table Base 1 |

Table 13.20: Registers at level 2, type:CPU group:AArch32_64_bit_non_secure_system

13.2.21 AArch64_system

Registers at level:2, type:CPU group:AArch64_system

| Name | Bits | Initial-Hex | RW | Description |
|-----------|------|-------------|----|----------------------------------------------|
| ACTLR_EL1 | 64 | 0 | rw | Auxiliary Control (EL1) |
| ACTLR_EL2 | 64 | 0 | rw | Auxiliary Control (EL2) |
| ACTLR_EL3 | 64 | 0 | rw | Auxiliary Control (EL3) |
| AFSR0_EL1 | 32 | 0 | rw | Auxiliary Fault Status 0 (EL1) |
| AFSR0_EL2 | 32 | 0 | rw | Auxiliary Fault Status 0 (EL2) |
| AFSR0_EL3 | 32 | 0 | rw | Auxiliary Fault Status 0 (EL3) |
| AFSR1_EL1 | 32 | 0 | rw | Auxiliary Fault Status 1 (EL1) |
| AFSR1_EL2 | 32 | 0 | rw | Auxiliary Fault Status 1 (EL2) |
| AFSR1_EL3 | 32 | 0 | rw | Auxiliary Fault Status 1 (EL3) |
| AIDR_EL1 | 32 | 0 | r- | Auxiliary ID |
| AMAIR_EL1 | 64 | 0 | rw | Auxiliary Memory Attribute Indirection (EL1) |
| AMAIR_EL2 | 64 | 0 | rw | Auxiliary Memory Attribute Indirection (EL2) |
| AMAIR_EL3 | 64 | 0 | rw | Auxiliary Memory Attribute Indirection (EL3) |
| CBAR_EL1 | 64 | 13080000 | r- | Configuration Base Address |

| | | | | |
|-------------------|----|-------------|----|------------------------------------------------------|
| CCSIDR_EL1 | 32 | 701fe00a | r- | Current Cache Size ID |
| CLIDR_EL1 | 32 | a200023 | r- | Cache Level ID |
| CNTFRQ_EL0 | 32 | 4c4b40 | rw | Counter-Timer Frequency |
| CNTHCTL_EL2 | 32 | 3 | rw | Counter-Timer Hypervisor Control |
| CNTHP_CTL_EL2 | 32 | 0 | rw | Counter-Timer Hypervisor Physical Timer Control |
| CNTHP_CVAL_EL2 | 64 | 0 | rw | Counter-Timer Hypervisor Physical Timer CompareValue |
| CNTHP_TVAL_EL2 | 32 | 0 | rw | Counter-Timer Hypervisor Physical Timer TimerValue |
| CNTKCTL_EL1 | 32 | 0 | rw | Counter-Timer Kernel Control |
| CNTPCT_EL0 | 64 | 0 | r- | Counter-Timer Physical Count |
| CNTPS_CTL_EL1 | 32 | 0 | rw | Counter-Timer Physical Secure Timer Control |
| CNTPS_CVAL_EL1 | 64 | 0 | rw | Counter-Timer Physical Secure Timer CompareValue |
| CNTPS_TVAL_EL1 | 32 | 0 | rw | Counter-Timer Physical Secure Timer TimerValue |
| CNTP_CTL_EL0 | 32 | 0 | rw | Counter-Timer Physical Timer Control |
| CNTP_CVAL_EL0 | 64 | 0 | rw | Counter-Timer Physical Timer CompareValue |
| CNTP_TVAL_EL0 | 32 | 0 | rw | Counter-Timer Physical Timer TimerValue |
| CNTVCT_EL0 | 64 | 0 | r- | Counter-Timer Virtual Count |
| CNTVOFF_EL2 | 64 | 0 | rw | Counter-Timer Virtual Offset |
| CNTV_CTL_EL0 | 32 | 0 | rw | Counter-Timer Virtual Timer Control |
| CNTV_CVAL_EL0 | 64 | 0 | rw | Counter-Timer Virtual Timer CompareValue |
| CNTV_TVAL_EL0 | 32 | 0 | rw | Counter-Timer Virtual Timer TimerValue |
| CONTEXTIDR_EL1 | 32 | 0 | rw | Context ID (EL1) |
| CPACR_EL1 | 32 | 0 | rw | Architectural Feature Access Control |
| CPTR_EL2 | 32 | 33ff | rw | Architectural Feature Trap (EL2) |
| CPTR_EL3 | 32 | 0 | rw | Architectural Feature Trap (EL3) |
| CPUACTLR_EL1 | 64 | 0 | rw | CPU Auxiliary Control |
| CPUECTLR_EL1 | 64 | 1b 00000000 | rw | CPU Extended Control |
| CPUMERRSR_EL1 | 64 | 0 | rw | CPU Memory Error Syndrome |
| CSSELR_EL1 | 32 | 0 | rw | Current Size Selection |
| CTR_EL0 | 32 | 8444c004 | r- | Cache Type |
| CurrentEL | 32 | c | r- | Current Exception Level |
| DACR32_EL2 | 32 | 0 | rw | Domain Access Control |
| DAIF | 32 | 3c0 | rw | Interrupt Mask Bits |
| DBGAUTHSTATUS_EL1 | 32 | aa | r- | Debug Authentication Status |
| DBGBCR0_EL1 | 32 | 0 | rw | Debug Breakpoint Control 0 |
| DBGBCR1_EL1 | 32 | 0 | rw | Debug Breakpoint Control 1 |
| DBGBCR2_EL1 | 32 | 0 | rw | Debug Breakpoint Control 2 |
| DBGBCR3_EL1 | 32 | 0 | rw | Debug Breakpoint Control 3 |
| DBGBCR4_EL1 | 32 | 0 | rw | Debug Breakpoint Control 4 |
| DBGBCR5_EL1 | 32 | 0 | rw | Debug Breakpoint Control 5 |
| DBGBVR0_EL1 | 64 | 0 | rw | Debug Breakpoint Value 0 |
| DBGBVR1_EL1 | 64 | 0 | rw | Debug Breakpoint Value 1 |
| DBGBVR2_EL1 | 64 | 0 | rw | Debug Breakpoint Value 2 |
| DBGBVR3_EL1 | 64 | 0 | rw | Debug Breakpoint Value 3 |
| DBGBVR4_EL1 | 64 | 0 | rw | Debug Breakpoint Value 4 |
| DBGBVR5_EL1 | 64 | 0 | rw | Debug Breakpoint Value 5 |
| DBGCLAIMCLR_EL1 | 32 | 0 | rw | Debug Claim Tag Clear |
| DBGCLAIMSET_EL1 | 32 | 0 | rw | Debug Claim Tag Set |
| DBGDTRTRX_EL0 | 32 | 0 | rw | Debug Data Transfer, Transmit/Receive |
| DBGDTR_EL0 | 64 | 0 | rw | Debug Data Transfer |
| DBGPRCR_EL1 | 32 | 0 | rw | Debug Power Control |
| DBGVCR32_EL2 | 32 | 0 | rw | Debug Vector Catch |
| DBGWCR0_EL1 | 32 | 0 | rw | Debug Watchpoint Control 0 |
| DBGWCR1_EL1 | 32 | 0 | rw | Debug Watchpoint Control 1 |
| DBGWCR2_EL1 | 32 | 0 | rw | Debug Watchpoint Control 2 |
| DBGWCR3_EL1 | 32 | 0 | rw | Debug Watchpoint Control 3 |

| | | | | |
|-----------------|----|-----|----|-------------------------------------------------------------|
| DBGWVR0_EL1 | 64 | 0 | rw | Debug Watchpoint Value 0 |
| DBGWVR1_EL1 | 64 | 0 | rw | Debug Watchpoint Value 1 |
| DBGWVR2_EL1 | 64 | 0 | rw | Debug Watchpoint Value 2 |
| DBGWVR3_EL1 | 64 | 0 | rw | Debug Watchpoint Value 3 |
| DCZID_EL0 | 32 | 4 | r- | Data Cache Zero ID |
| DL1DATA0_EL1 | 32 | 0 | rw | Data L1 Data 0 |
| DL1DATA1_EL1 | 32 | 0 | rw | Data L1 Data 1 |
| DL1DATA2_EL1 | 32 | 0 | rw | Data L1 Data 2 |
| DL1DATA3_EL1 | 32 | 0 | rw | Data L1 Data 3 |
| DL1DATA4_EL1 | 32 | 0 | rw | Data L1 Data 4 |
| DLR_EL0 | 64 | 0 | rw | Debug Link |
| DSPSR_EL0 | 32 | 0 | rw | Debug Saved Program Status |
| ELR_EL1 | 64 | 0 | rw | Exception Link (EL1) |
| ELR_EL2 | 64 | 0 | rw | Exception Link (EL2) |
| ELR_EL3 | 64 | 0 | rw | Exception Link (EL3) |
| ESR_EL1 | 32 | 0 | rw | Exception Syndrome (EL1) |
| ESR_EL2 | 32 | 0 | rw | Exception Syndrome (EL2) |
| ESR_EL3 | 32 | 0 | rw | Exception Syndrome (EL3) |
| FAR_EL1 | 64 | 0 | rw | Fault Address (EL1) |
| FAR_EL2 | 64 | 0 | rw | Fault Address (EL2) |
| FAR_EL3 | 64 | 0 | rw | Fault Address (EL3) |
| FPCR | 32 | 0 | rw | Floating Point Control |
| FPEXC32_EL2 | 32 | 700 | rw | Floating Point Exception Control |
| FPSR | 32 | 0 | rw | Floating Point Status |
| HACR_EL2 | 32 | 0 | rw | Hypervisor Auxiliary Control |
| HCR_EL2 | 64 | 0 | rw | Hypervisor Configuration |
| HPFAR_EL2 | 64 | 0 | rw | Hypervisor IPA Fault Address |
| HSTR_EL2 | 32 | 0 | rw | Hypervisor System Trap |
| ICC_AP0R0_EL1 | 32 | 0 | rw | Interrupt Controller Active Priorities Group 0, 0 |
| ICC_AP1R0_EL1 | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_ASGI1R_EL1 | 64 | - | -w | Interrupt Controller Alias SGI Group 1 |
| ICC_BPR0_EL1 | 32 | 2 | rw | Interrupt Controller Binary Point 0 |
| ICC_BPR1_EL1 | 32 | 2 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR_EL1 | 32 | 400 | rw | Interrupt Controller Control (EL1) |
| ICC_CTLR_EL3 | 32 | 400 | rw | Interrupt Controller Control (EL3) |
| ICC_DIR_EL1 | 32 | - | -w | Interrupt Controller Deactivate Interrupt |
| ICC_EOIR0_EL1 | 32 | - | -w | Interrupt Controller End of Interrupt 0 |
| ICC_EOIR1_EL1 | 32 | - | -w | Interrupt Controller End of Interrupt 1 |
| ICC_HPPIR0_EL1 | 32 | 3ff | r- | Interrupt Controller Highest Priority Pending Interrupt 0 |
| ICC_HPPIR1_EL1 | 32 | 3ff | r- | Interrupt Controller Highest Priority Pending Interrupt 1 |
| ICC_IAR0_EL1 | 32 | 3ff | r- | Interrupt Controller Interrupt Acknowledge 0 |
| ICC_IAR1_EL1 | 32 | 3ff | r- | Interrupt Controller Interrupt Acknowledge 1 |
| ICC_IGRPEN0_EL1 | 32 | 0 | rw | Interrupt Controller Interrupt Group 0 Enable |
| ICC_IGRPEN1_EL1 | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_IGRPEN1_EL3 | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable (EL3) |
| ICC_PMR_EL1 | 32 | 0 | rw | Interrupt Controller Priority Mask |
| ICC_RPR_EL1 | 32 | ff | r- | Interrupt Controller Running Priority |
| ICC_SGI0R_EL1 | 64 | - | -w | Interrupt Controller SGI Group 0 |
| ICC_SGI1R_EL1 | 64 | - | -w | Interrupt Controller SGI Group 1 |
| ICC_SRE_EL1 | 32 | 0 | rw | Interrupt Controller System Register Enable (EL1) |
| ICC_SRE_EL2 | 32 | 0 | rw | Interrupt Controller System Register Enable (EL2) |
| ICC_SRE_EL3 | 32 | 0 | rw | Interrupt Controller System Register Enable (EL3) |
| ICH_AP0R0_EL2 | 32 | 0 | rw | Interrupt Controller Hyp Active Priorities Group 0 (Word 0) |

| | | | | |
|------------------|----|----------------------|----|-------------------------------------------------------------|
| ICH_AP1R0_EL2 | 32 | 0 | rw | Interrupt Controller Hyp Active Priorities Group 1 (Word 0) |
| ICH_EISR_EL2 | 32 | 0 | r- | Interrupt Controller End of Interrupt Status |
| ICH_ELRSR_EL2 | 32 | f | r- | Interrupt Controller Empty List Register Status |
| ICH_HCR_EL2 | 32 | 0 | rw | Interrupt Controller Hypervisor Control |
| ICH_LR0_EL2 | 64 | 0 | rw | Interrupt Controller List 0 |
| ICH_LR1_EL2 | 64 | 0 | rw | Interrupt Controller List 1 |
| ICH_LR2_EL2 | 64 | 0 | rw | Interrupt Controller List 2 |
| ICH_LR3_EL2 | 64 | 0 | rw | Interrupt Controller List 3 |
| ICH_MISR_EL2 | 32 | 0 | r- | Interrupt Controller Maintenance Interrupt State |
| ICH_VMCR_EL2 | 32 | 4c0000 | rw | Interrupt Controller Virtual Machine Control |
| ICH_VTR_EL2 | 32 | 90100003 | r- | Interrupt Controller VGIC Type |
| ID_AA64AFR0_EL1 | 64 | 0 | r- | AArch64 Auxiliary Feature 0 |
| ID_AA64AFR1_EL1 | 64 | 0 | r- | AArch64 Auxiliary Feature 1 |
| ID_AA64DFR0_EL1 | 64 | 10305106 | r- | AArch64 Debug Feature 0 |
| ID_AA64DFR1_EL1 | 64 | 0 | r- | AArch64 Debug Feature 1 |
| ID_AA64ISAR0_EL1 | 64 | 0 | r- | AArch64 Instruction Set Attribute 0 |
| ID_AA64ISAR1_EL1 | 64 | 0 | r- | AArch64 Instruction Set Attribute 1 |
| ID_AA64MMFR0_EL1 | 64 | 1124 | r- | AArch64 Memory Model Feature 0 |
| ID_AA64MMFR1_EL1 | 64 | 0 | r- | AArch64 Memory Model Feature 1 |
| ID_AA64PFR0_EL1 | 64 | 1002222 | r- | AArch64 Processor Feature 0 |
| ID_AA64PFR1_EL1 | 64 | 0 | r- | AArch64 Processor Feature 1 |
| ID_AFR0_EL1 | 32 | 0 | r- | Auxiliary Feature 0 |
| ID_DFR0_EL1 | 32 | 3010066 | r- | Debug Feature 0 |
| ID_ISAR0_EL1 | 32 | 2101110 | r- | Instruction Set Attribute 0 |
| ID_ISAR1_EL1 | 32 | 13112111 | r- | Instruction Set Attribute 1 |
| ID_ISAR2_EL1 | 32 | 21232042 | r- | Instruction Set Attribute 2 |
| ID_ISAR3_EL1 | 32 | 1112131 | r- | Instruction Set Attribute 3 |
| ID_ISAR4_EL1 | 32 | 11142 | r- | Instruction Set Attribute 4 |
| ID_ISAR5_EL1 | 32 | 1 | r- | Instruction Set Attribute 5 |
| ID_MMFR0_EL1 | 32 | 10201105 | r- | Memory Model Feature 0 |
| ID_MMFR1_EL1 | 32 | 40000000 | r- | Memory Model Feature 1 |
| ID_MMFR2_EL1 | 32 | 1260000 | r- | Memory Model Feature 2 |
| ID_MMFR3_EL1 | 32 | 2102211 | r- | Memory Model Feature 3 |
| ID_PFR0_EL1 | 32 | 131 | r- | Processor Feature 0 |
| ID_PFR1_EL1 | 32 | 10011011 | r- | Processor Feature 1 |
| IFSR32_EL2 | 32 | 0 | rw | Instruction Fault Status (EL2) |
| IL1DATA0_EL1 | 32 | 0 | rw | Instruction L1 Data 0 |
| IL1DATA1_EL1 | 32 | 0 | rw | Instruction L1 Data 1 |
| IL1DATA2_EL1 | 32 | 0 | rw | Instruction L1 Data 2 |
| IL1DATA3_EL1 | 32 | 0 | rw | Instruction L1 Data 3 |
| ISR_EL1 | 32 | 0 | r- | Interrupt Status |
| L2ACTLR_EL1 | 32 | 0 | rw | L2 Auxiliary Control |
| L2CTLR_EL1 | 32 | 2000000 | rw | L2 Control |
| L2ECTLR_EL1 | 32 | 0 | rw | L2 Extended Control |
| L2MERRSR_EL1 | 64 | 0 | rw | L2 Memory Error Syndrome |
| MAIR_EL1 | 64 | 44e048e0 00098aa4 | rw | Memory Attribute Indirection (EL1) |
| MAIR_EL2 | 64 | 0 | rw | Memory Attribute Indirection (EL2) |
| MAIR_EL3 | 64 | 44e048e0 00098aa4 | rw | Memory Attribute Indirection (EL3) |
| MDCCINT_EL1 | 32 | 0 | rw | Monitor DCC Interrupt Enable |
| MDCCSR_EL0 | 32 | 0 | r- | Monitor DCC Status |
| MDCR_EL2 | 32 | 6 | rw | Monitor Debug Configuration (EL2) |
| MDCR_EL3 | 32 | 0 | rw | Monitor Debug Configuration (EL3) |
| MDRAR_EL1 | 64 | 0 | r- | Monitor Debug ROM Address |

| | | | | |
|----------------|----|----------|----|-------------------------------------------------|
| MDSCR_EL1 | 32 | 0 | rw | Monitor Debug System Control |
| MIDR_EL1 | 32 | 410fd081 | r- | Main ID |
| MPIDR_EL1 | 64 | 80000000 | r- | Multiprocessor Affinity |
| MVFR0_EL1 | 32 | 10110222 | r- | Media and VFP Feature 0 |
| MVFR1_EL1 | 32 | 12111111 | r- | Media and VFP Feature 1 |
| MVFR2_EL1 | 32 | 43 | r- | Media and VFP Feature 2 |
| NZCV | 32 | 0 | rw | Condition Flags |
| OSDLR_EL1 | 32 | 0 | rw | OS Double Lock |
| OSDTRRX_EL1 | 32 | 0 | rw | OS Lock Data Transfer, Receive |
| OSDTRTX_EL1 | 32 | 0 | rw | OS Lock Data Transfer, Transmit |
| OSECCR_EL1 | 32 | 0 | rw | OS Lock Exception Catch Control |
| OSLAR_EL1 | 32 | - | -w | OS Lock Access |
| OSLSR_EL1 | 32 | a | r- | OS Lock Status |
| PAR_EL1 | 64 | 0 | rw | Physical Address |
| PMCCFILTR_EL0 | 32 | 0 | rw | Performance Monitors Cycle Count Filter |
| PMCCNTR_EL0 | 64 | 0 | rw | Performance Monitors Cycle Count |
| PMCEID0_EL0 | 32 | 7ff0f3f | r- | Performance Monitors Common Event ID 0 |
| PMCEID1_EL0 | 32 | 0 | r- | Performance Monitors Common Event ID 1 |
| PMCNTENCLR_EL0 | 32 | 0 | rw | Performance Monitors Count Enable Clear |
| PMCNTENSET_EL0 | 32 | 0 | rw | Performance Monitors Count Enable Set |
| PMCR_EL0 | 32 | 41023000 | rw | Performance Monitors Control |
| PMEVCNTR0_EL0 | 32 | 0 | rw | Performance Monitors Event Count 0 |
| PMEVCNTR1_EL0 | 32 | 0 | rw | Performance Monitors Event Count 1 |
| PMEVCNTR2_EL0 | 32 | 0 | rw | Performance Monitors Event Count 2 |
| PMEVCNTR3_EL0 | 32 | 0 | rw | Performance Monitors Event Count 3 |
| PMEVCNTR4_EL0 | 32 | 0 | rw | Performance Monitors Event Count 4 |
| PMEVCNTR5_EL0 | 32 | 0 | rw | Performance Monitors Event Count 5 |
| PMEVTYPER0_EL0 | 32 | 0 | rw | Performance Monitors Event Type 0 |
| PMEVTYPER1_EL0 | 32 | 0 | rw | Performance Monitors Event Type 1 |
| PMEVTYPER2_EL0 | 32 | 0 | rw | Performance Monitors Event Type 2 |
| PMEVTYPER3_EL0 | 32 | 0 | rw | Performance Monitors Event Type 3 |
| PMEVTYPER4_EL0 | 32 | 0 | rw | Performance Monitors Event Type 4 |
| PMEVTYPER5_EL0 | 32 | 0 | rw | Performance Monitors Event Type 5 |
| PMINTENCLR_EL1 | 32 | 0 | rw | Performance Monitors Interrupt Enable Clear |
| PMINTENSET_EL1 | 32 | 0 | rw | Performance Monitors Interrupt Enable Set |
| PMOVSCLR_EL0 | 32 | 0 | rw | Performance Monitors Overflow Flag Status Clear |
| PMOVSSET_EL0 | 32 | 0 | rw | Performance Monitors Overflow Flag Status Set |
| PMSELR_EL0 | 32 | 0 | rw | Performance Monitors Event Counter Selection |
| PMSWINC_EL0 | 32 | - | -w | Performance Monitors Software Increment |
| PMUSERENR_EL0 | 32 | 0 | rw | Performance Monitors User Enable |
| PMXVCNTR_EL0 | 32 | 0 | rw | Performance Monitors Selected Event Count |
| PMXVTYPER_EL0 | 32 | 0 | rw | Performance Monitors Selected Event Type |
| RAMINDEX_EL1 | 32 | - | -w | RAM Index |
| REVIDR_EL1 | 32 | 0 | r- | Revision ID |
| RMR_EL3 | 32 | 1 | rw | Reset Management (EL3) |
| RVBAR_EL3 | 64 | 0 | r- | Reset Vector Base Address (EL3) |
| SCR_EL3 | 32 | 0 | rw | Secure Configuration |
| SCTLR_EL1 | 32 | c50838 | rw | System Control Register (EL1) |
| SCTLR_EL2 | 32 | 30c50838 | rw | System Control Register (EL2) |
| SCTLR_EL3 | 32 | c50838 | rw | System Control (EL3) |
| SDER32_EL3 | 32 | 0 | rw | AArch32 Secure Debug Enable |
| SPSR_EL1 | 32 | 0 | rw | Saved Program Status (EL1) |
| SPSR_EL2 | 32 | 0 | rw | Saved Program Status (EL2) |
| SPSR_EL3 | 32 | 0 | rw | Saved Program Status (EL3) |
| SPSR_abt | 32 | 0 | rw | Saved Program Status (Abort Mode) |
| SPSR_fiq | 32 | 0 | rw | Saved Program Status (FIQ Mode) |

| | | | | |
|-------------|----|----------|----|---------------------------------------|
| SPSR_irq | 32 | 0 | rw | Saved Program Status (IRQ Mode) |
| SPSR_und | 32 | 0 | rw | Saved Program Status (Undefined Mode) |
| SPSel | 32 | 1 | rw | Stack Pointer Select |
| SP_EL0 | 64 | 0 | rw | Stack Pointer (EL0) |
| SP_EL1 | 64 | 0 | rw | Stack Pointer (EL1) |
| SP_EL2 | 64 | 0 | rw | Stack Pointer (EL2) |
| SP_EL3 | 64 | 0 | rw | Stack Pointer (EL3) |
| TCR_EL1 | 64 | 0 | rw | Translation Control (EL1) |
| TCR_EL2 | 32 | 80800000 | rw | Translation Control (EL2) |
| TCR_EL3 | 32 | 0 | rw | Translation Control (EL3) |
| TPIDRRO_EL0 | 64 | 0 | rw | Thread Pointer/ID, Read-Only (EL0) |
| TPIDR_EL0 | 64 | 0 | rw | Thread Pointer/ID (EL0) |
| TPIDR_EL1 | 64 | 0 | rw | Thread Pointer/ID (EL1) |
| TPIDR_EL2 | 64 | 0 | rw | Thread Pointer/ID (EL2) |
| TPIDR_EL3 | 64 | 0 | rw | Thread Pointer/ID (EL3) |
| TTBR0_EL1 | 64 | 0 | rw | Translation Table Base 0 (EL1) |
| TTBR0_EL2 | 64 | 0 | rw | Translation Table Base 0 (EL2) |
| TTBR0_EL3 | 64 | 0 | rw | Translation Table Base 0 (EL3) |
| TTBR1_EL1 | 64 | 0 | rw | Translation Table Base 1 (EL1) |
| VBAR_EL1 | 64 | 0 | rw | Vector Base Address (EL1) |
| VBAR_EL2 | 64 | 0 | rw | Vector Base Address (EL2) |
| VBAR_EL3 | 64 | 0 | rw | Vector Base Address (EL3) |
| VMPIDR_EL2 | 64 | 80000000 | rw | Virtualization Multiprocessor ID |
| VPIDR_EL2 | 32 | 410fd081 | rw | Virtualization Processor ID |
| VTCR_EL2 | 32 | 80000000 | rw | Virtualization Translation Control |
| VTTBR_EL2 | 64 | 0 | rw | Virtualization Translation Table Base |

Table 13.21: Registers at level 2, type:CPU group:AArch64_system

13.2.22 AArch64_secure_system

Registers at level:2, type:CPU group:AArch64_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|-------------------|------|-------------|----|---------------------------------------------------|
| ICC_APIR0_EL1.S | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_BPR1_EL1.S | 32 | 2 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR_EL1.S | 32 | 400 | rw | Interrupt Controller Control (EL1) |
| ICC_IGRPEN1_EL1.S | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_SRE_EL1.S | 32 | 0 | rw | Interrupt Controller System Register Enable (EL1) |

Table 13.22: Registers at level 2, type:CPU group:AArch64_secure_system

13.2.23 AArch64_non_secure_system

Registers at level:2, type:CPU group:AArch64_non_secure_system

| Name | Bits | Initial-Hex | RW | Description |
|--------------------|------|-------------|----|---------------------------------------------------|
| ICC_APIR0_EL1.NS | 32 | 0 | rw | Interrupt Controller Active Priorities Group 1, 0 |
| ICC_BPR1_EL1.NS | 32 | 3 | rw | Interrupt Controller Binary Point 1 |
| ICC_CTLR_EL1.NS | 32 | 400 | rw | Interrupt Controller Control (EL1) |
| ICC_IGRPEN1_EL1.NS | 32 | 0 | rw | Interrupt Controller Interrupt Group 1 Enable |
| ICC_SRE_EL1.NS | 32 | 0 | rw | Interrupt Controller System Register Enable (EL1) |

Table 13.23: Registers at level 2, type:CPU group:AArch64_non_secure_system

13.2.24 AArch64_SYS_instruction_registers

Registers at level:2, type:CPU group:AArch64_SYS_instruction_registers

| Name | Bits | Initial-Hex | RW | Description |
|------------|------|-------------|----|-------------|
| ALLE1 | 64 | - | -w | |
| ALLE1IS | 64 | - | -w | |
| ALLE2 | 64 | - | -w | |
| ALLE2IS | 64 | - | -w | |
| ALLE3 | 64 | - | -w | |
| ALLE3IS | 64 | - | -w | |
| ASIDE1 | 64 | - | -w | |
| ASIDE1IS | 64 | - | -w | |
| CISW | 32 | - | -w | |
| CIVAC | 64 | - | -w | |
| CSW | 32 | - | -w | |
| CVAC | 64 | - | -w | |
| CVAU | 64 | - | -w | |
| IALLU | 32 | - | -w | |
| IALLUIS | 32 | - | -w | |
| IPAS2E1 | 64 | - | -w | |
| IPAS2E1IS | 64 | - | -w | |
| IPAS2LE1 | 64 | - | -w | |
| IPAS2LE1IS | 64 | - | -w | |
| ISW | 32 | - | -w | |
| IVAC | 64 | - | -w | |
| IVAU | 64 | - | -w | |
| S1E0R | 64 | - | -w | |
| S1E0W | 64 | - | -w | |
| S1E1R | 64 | - | -w | |
| S1E1W | 64 | - | -w | |
| S1E2R | 64 | - | -w | |
| S1E2W | 64 | - | -w | |
| S1E3R | 64 | - | -w | |
| S1E3W | 64 | - | -w | |
| S12E0R | 64 | - | -w | |
| S12E0W | 64 | - | -w | |
| S12E1R | 64 | - | -w | |
| S12E1W | 64 | - | -w | |
| VAAE1 | 64 | - | -w | |
| VAAE1IS | 64 | - | -w | |
| VAALE1 | 64 | - | -w | |
| VAALE1IS | 64 | - | -w | |
| VAE1 | 64 | - | -w | |
| VAE1IS | 64 | - | -w | |
| VAE2 | 64 | - | -w | |
| VAE2IS | 64 | - | -w | |
| VAE3 | 64 | - | -w | |
| VAE3IS | 64 | - | -w | |
| VALE1 | 64 | - | -w | |
| VALE1IS | 64 | - | -w | |
| VALE2 | 64 | - | -w | |
| VALE2IS | 64 | - | -w | |
| VALE3 | 64 | - | -w | |
| VALE3IS | 64 | - | -w | |
| VMALLE1 | 64 | - | -w | |
| VMALLE1IS | 64 | - | -w | |

| | | | | |
|--------------|----|---|----|--|
| VMALLS12E1 | 64 | - | -w | |
| VMALLS12E1IS | 64 | - | -w | |
| ZVA | 32 | - | -w | |

Table 13.24: Registers at level 2, type:CPU group:AArch64_SYS_instruction_registers

13.2.25 Integration_support

Registers at level:2, type:CPU group:Integration_support

| Name | Bits | Initial-Hex | RW | Description |
|-----------------|------|-------------|----|---------------------------------------------------------------------------------------------------------------------------------------------------|
| transactPL | 32 | 3 | r- | privilege level of current memory transaction |
| transactAT | 32 | 0 | r- | current memory transaction type: PA=1, VA=0 |
| artifactPAR | 64 | 0 | r- | result of address translation for artifact write to ATS1CPR etc |
| PTWBankSelect | 8 | 0 | rw | select PTW bank (0 is stage 1, 1 is stage 2, 2-5 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively) |
| PTWBankValid | 8 | 0 | r- | bitmask of valid banks (0x01 is stage 1, 0x02 is stage 2, 0x04-0x20 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively) |
| PTWAddressValid | 8 | 0 | r- | bitmask of valid bits for each of PTWAddressL0...PTWAddressL3, PTWBase, PTWInput and PTWOutput in current bank |
| PTWValueValid | 8 | 0 | r- | bitmask of valid bits for each of PTWValueL0...PTWValueL3 in current bank |
| PTWAddressL0 | 64 | 0 | r- | current bank PTW address, level 0 |
| PTWAddressL1 | 64 | 0 | r- | current bank PTW address, level 1 |
| PTWAddressL2 | 64 | 0 | r- | current bank PTW address, level 2 |
| PTWAddressL3 | 64 | 0 | r- | current bank PTW address, level 3 |
| PTWValueL0 | 64 | 0 | r- | current bank PTW value, level 0 |
| PTWValueL1 | 64 | 0 | r- | current bank PTW value, level 1 |
| PTWValueL2 | 64 | 0 | r- | current bank PTW value, level 2 |
| PTWValueL3 | 64 | 0 | r- | current bank PTW value, level 3 |
| PTWBase | 64 | 0 | r- | current bank PTW table base address |
| PTWInput | 64 | 0 | r- | current bank PTW input address |
| PTWOutput | 64 | 0 | r- | current bank PTW output address |
| PTWLEL1S | 64 | - | -w | perform EL1(S) stage 1 page table walk for fetch, filling PTW query registers |
| PTWD_EL1S | 64 | - | -w | perform EL1(S) stage 1 page table walk for load/store, filling PTW query registers |
| PTWLEL1NS | 64 | - | -w | perform EL1(NS) stage 1 page table walk for fetch, filling PTW query registers |
| PTWD_EL1NS | 64 | - | -w | perform EL1(NS) stage 1 page table walk for load/store, filling PTW query registers |
| PTWLEL2 | 64 | - | -w | perform EL2 page table walk for fetch, filling PTW query registers |
| PTWD_EL2 | 64 | - | -w | perform EL2 page table walk for load/store, filling PTW query registers |
| PTWLS2 | 64 | - | -w | perform stage 2 page table walk for fetch, filling PTW query registers |
| PTWD_S2 | 64 | - | -w | perform stage 2 page table walk for load/store, filling PTW query registers |
| PTWLEL3 | 64 | - | -w | perform EL3 page table walk for fetch, filling PTW query registers |
| PTWD_EL3 | 64 | - | -w | perform EL3 page table walk for load/store, filling PTW query registers |

| | | | | |
|--------------|----|---|----|----------------------------------------------------------------------------------|
| PTWI_current | 64 | - | -w | perform current mode page table walk for fetch, filling PTW query registers |
| PTWD_current | 64 | - | -w | perform current mode page table walk for load/store, filling PTW query registers |
| HaltReason | 8 | 0 | r- | bit field indicating halt reason |

Table 13.25: Registers at level 2, type:CPU group:Integration_support

13.2.26 MPCore_distributor

Registers at level:2, type:CPU group:MPCore_distributor

| Name | Bits | Initial-Hex | RW | Description |
|------------------|------|-------------|----|----------------------------|
| GICD_CIDR0 | 32 | d | r- | Component ID 0 |
| GICD_CIDR1 | 32 | f0 | r- | Component ID 1 |
| GICD_CIDR2 | 32 | 5 | r- | Component ID 2 |
| GICD_CIDR3 | 32 | b1 | r- | Component ID 3 |
| GICD_CLRSPLNSR | 32 | 0 | -w | Clear SPI |
| GICD_CLRSPLSR | 32 | 0 | -w | Clear SPI, Secure |
| GICD_CPENDSGIR0 | 32 | 0 | rw | SGI Clear-Pending 0 |
| GICD_CPENDSGIR1 | 32 | 0 | rw | SGI Clear-Pending 1 |
| GICD_CPENDSGIR2 | 32 | 0 | rw | SGI Clear-Pending 2 |
| GICD_CPENDSGIR3 | 32 | 0 | rw | SGI Clear-Pending 3 |
| GICD_CTLR | 32 | 0 | rw | Distributor Control |
| GICD_ICACTIVER0 | 32 | 0 | rw | Interrupt Clear-Active 0 |
| GICD_ICACTIVER1 | 32 | 0 | rw | Interrupt Clear-Active 1 |
| GICD_ICACTIVER2 | 32 | 0 | rw | Interrupt Clear-Active 2 |
| GICD_ICENABLER0 | 32 | ffff | rw | Interrupt Clear-Enable 0 |
| GICD_ICENABLER1 | 32 | 0 | rw | Interrupt Clear-Enable 1 |
| GICD_ICENABLER2 | 32 | 0 | rw | Interrupt Clear-Enable 2 |
| GICD_ICFGR0 | 32 | aaaaaaaa | rw | Interrupt Configuration 0 |
| GICD_ICFGR1 | 32 | 55540000 | rw | Interrupt Configuration 1 |
| GICD_ICFGR2 | 32 | 0 | rw | Interrupt Configuration 2 |
| GICD_ICFGR3 | 32 | 0 | rw | Interrupt Configuration 3 |
| GICD_ICFGR4 | 32 | 0 | rw | Interrupt Configuration 4 |
| GICD_ICFGR5 | 32 | 0 | rw | Interrupt Configuration 5 |
| GICD_ICPENDR0 | 32 | 0 | rw | Interrupt Clear-Pending 0 |
| GICD_ICPENDR1 | 32 | 0 | rw | Interrupt Clear-Pending 1 |
| GICD_ICPENDR2 | 32 | 0 | rw | Interrupt Clear-Pending 2 |
| GICD_IGROUPR0 | 32 | 0 | rw | Interrupt Group 0 |
| GICD_IGROUPR1 | 32 | 0 | rw | Interrupt Group 1 |
| GICD_IGROUPR2 | 32 | 0 | rw | Interrupt Group 2 |
| GICD_IGRPMODR0 | 32 | 0 | rw | Interrupt Group Modifier 0 |
| GICD_IGRPMODR1 | 32 | 0 | rw | Interrupt Group Modifier 1 |
| GICD_IGRPMODR2 | 32 | 0 | rw | Interrupt Group Modifier 2 |
| GICD_IIDR | 32 | 102043b | r- | Distributor Implementor ID |
| GICD_IPRIORITYR0 | 32 | 0 | rw | Interrupt Priority 0 |
| GICD_IPRIORITYR1 | 32 | 0 | rw | Interrupt Priority 1 |
| GICD_IPRIORITYR2 | 32 | 0 | rw | Interrupt Priority 2 |
| GICD_IPRIORITYR3 | 32 | 0 | rw | Interrupt Priority 3 |
| GICD_IPRIORITYR4 | 32 | 0 | rw | Interrupt Priority 4 |
| GICD_IPRIORITYR5 | 32 | 0 | rw | Interrupt Priority 5 |
| GICD_IPRIORITYR6 | 32 | 0 | rw | Interrupt Priority 6 |
| GICD_IPRIORITYR7 | 32 | 0 | rw | Interrupt Priority 7 |
| GICD_IPRIORITYR8 | 32 | 0 | rw | Interrupt Priority 8 |
| GICD_IPRIORITYR9 | 32 | 0 | rw | Interrupt Priority 9 |

| | | | | |
|-------------------|----|---|----|-----------------------|
| GICD_IPRIORITYR10 | 32 | 0 | rw | Interrupt Priority 10 |
| GICD_IPRIORITYR11 | 32 | 0 | rw | Interrupt Priority 11 |
| GICD_IPRIORITYR12 | 32 | 0 | rw | Interrupt Priority 12 |
| GICD_IPRIORITYR13 | 32 | 0 | rw | Interrupt Priority 13 |
| GICD_IPRIORITYR14 | 32 | 0 | rw | Interrupt Priority 14 |
| GICD_IPRIORITYR15 | 32 | 0 | rw | Interrupt Priority 15 |
| GICD_IPRIORITYR16 | 32 | 0 | rw | Interrupt Priority 16 |
| GICD_IPRIORITYR17 | 32 | 0 | rw | Interrupt Priority 17 |
| GICD_IPRIORITYR18 | 32 | 0 | rw | Interrupt Priority 18 |
| GICD_IPRIORITYR19 | 32 | 0 | rw | Interrupt Priority 19 |
| GICD_IPRIORITYR20 | 32 | 0 | rw | Interrupt Priority 20 |
| GICD_IPRIORITYR21 | 32 | 0 | rw | Interrupt Priority 21 |
| GICD_IPRIORITYR22 | 32 | 0 | rw | Interrupt Priority 22 |
| GICD_IPRIORITYR23 | 32 | 0 | rw | Interrupt Priority 23 |
| GICD_IROUTER32 | 64 | 0 | rw | Interrupt Routing 32 |
| GICD_IROUTER33 | 64 | 0 | rw | Interrupt Routing 33 |
| GICD_IROUTER34 | 64 | 0 | rw | Interrupt Routing 34 |
| GICD_IROUTER35 | 64 | 0 | rw | Interrupt Routing 35 |
| GICD_IROUTER36 | 64 | 0 | rw | Interrupt Routing 36 |
| GICD_IROUTER37 | 64 | 0 | rw | Interrupt Routing 37 |
| GICD_IROUTER38 | 64 | 0 | rw | Interrupt Routing 38 |
| GICD_IROUTER39 | 64 | 0 | rw | Interrupt Routing 39 |
| GICD_IROUTER40 | 64 | 0 | rw | Interrupt Routing 40 |
| GICD_IROUTER41 | 64 | 0 | rw | Interrupt Routing 41 |
| GICD_IROUTER42 | 64 | 0 | rw | Interrupt Routing 42 |
| GICD_IROUTER43 | 64 | 0 | rw | Interrupt Routing 43 |
| GICD_IROUTER44 | 64 | 0 | rw | Interrupt Routing 44 |
| GICD_IROUTER45 | 64 | 0 | rw | Interrupt Routing 45 |
| GICD_IROUTER46 | 64 | 0 | rw | Interrupt Routing 46 |
| GICD_IROUTER47 | 64 | 0 | rw | Interrupt Routing 47 |
| GICD_IROUTER48 | 64 | 0 | rw | Interrupt Routing 48 |
| GICD_IROUTER49 | 64 | 0 | rw | Interrupt Routing 49 |
| GICD_IROUTER50 | 64 | 0 | rw | Interrupt Routing 50 |
| GICD_IROUTER51 | 64 | 0 | rw | Interrupt Routing 51 |
| GICD_IROUTER52 | 64 | 0 | rw | Interrupt Routing 52 |
| GICD_IROUTER53 | 64 | 0 | rw | Interrupt Routing 53 |
| GICD_IROUTER54 | 64 | 0 | rw | Interrupt Routing 54 |
| GICD_IROUTER55 | 64 | 0 | rw | Interrupt Routing 55 |
| GICD_IROUTER56 | 64 | 0 | rw | Interrupt Routing 56 |
| GICD_IROUTER57 | 64 | 0 | rw | Interrupt Routing 57 |
| GICD_IROUTER58 | 64 | 0 | rw | Interrupt Routing 58 |
| GICD_IROUTER59 | 64 | 0 | rw | Interrupt Routing 59 |
| GICD_IROUTER60 | 64 | 0 | rw | Interrupt Routing 60 |
| GICD_IROUTER61 | 64 | 0 | rw | Interrupt Routing 61 |
| GICD_IROUTER62 | 64 | 0 | rw | Interrupt Routing 62 |
| GICD_IROUTER63 | 64 | 0 | rw | Interrupt Routing 63 |
| GICD_IROUTER64 | 64 | 0 | rw | Interrupt Routing 64 |
| GICD_IROUTER65 | 64 | 0 | rw | Interrupt Routing 65 |
| GICD_IROUTER66 | 64 | 0 | rw | Interrupt Routing 66 |
| GICD_IROUTER67 | 64 | 0 | rw | Interrupt Routing 67 |
| GICD_IROUTER68 | 64 | 0 | rw | Interrupt Routing 68 |
| GICD_IROUTER69 | 64 | 0 | rw | Interrupt Routing 69 |
| GICD_IROUTER70 | 64 | 0 | rw | Interrupt Routing 70 |
| GICD_IROUTER71 | 64 | 0 | rw | Interrupt Routing 71 |
| GICD_IROUTER72 | 64 | 0 | rw | Interrupt Routing 72 |
| GICD_IROUTER73 | 64 | 0 | rw | Interrupt Routing 73 |

| | | | | |
|------------------|----|---------|----|---------------------------------------|
| GICD_IROUTER74 | 64 | 0 | rw | Interrupt Routing 74 |
| GICD_IROUTER75 | 64 | 0 | rw | Interrupt Routing 75 |
| GICD_IROUTER76 | 64 | 0 | rw | Interrupt Routing 76 |
| GICD_IROUTER77 | 64 | 0 | rw | Interrupt Routing 77 |
| GICD_IROUTER78 | 64 | 0 | rw | Interrupt Routing 78 |
| GICD_IROUTER79 | 64 | 0 | rw | Interrupt Routing 79 |
| GICD_IROUTER80 | 64 | 0 | rw | Interrupt Routing 80 |
| GICD_IROUTER81 | 64 | 0 | rw | Interrupt Routing 81 |
| GICD_IROUTER82 | 64 | 0 | rw | Interrupt Routing 82 |
| GICD_IROUTER83 | 64 | 0 | rw | Interrupt Routing 83 |
| GICD_IROUTER84 | 64 | 0 | rw | Interrupt Routing 84 |
| GICD_IROUTER85 | 64 | 0 | rw | Interrupt Routing 85 |
| GICD_IROUTER86 | 64 | 0 | rw | Interrupt Routing 86 |
| GICD_IROUTER87 | 64 | 0 | rw | Interrupt Routing 87 |
| GICD_IROUTER88 | 64 | 0 | rw | Interrupt Routing 88 |
| GICD_IROUTER89 | 64 | 0 | rw | Interrupt Routing 89 |
| GICD_IROUTER90 | 64 | 0 | rw | Interrupt Routing 90 |
| GICD_IROUTER91 | 64 | 0 | rw | Interrupt Routing 91 |
| GICD_IROUTER92 | 64 | 0 | rw | Interrupt Routing 92 |
| GICD_IROUTER93 | 64 | 0 | rw | Interrupt Routing 93 |
| GICD_IROUTER94 | 64 | 0 | rw | Interrupt Routing 94 |
| GICD_IROUTER95 | 64 | 0 | rw | Interrupt Routing 95 |
| GICD_ISACTIVER0 | 32 | 0 | rw | Interrupt Set-Active 0 |
| GICD_ISACTIVER1 | 32 | 0 | rw | Interrupt Set-Active 1 |
| GICD_ISACTIVER2 | 32 | 0 | rw | Interrupt Set-Active 2 |
| GICD_ISENBALER0 | 32 | fff | rw | Interrupt Set-Enable 0 |
| GICD_ISENBALER1 | 32 | 0 | rw | Interrupt Set-Enable 1 |
| GICD_ISENBALER2 | 32 | 0 | rw | Interrupt Set-Enable 2 |
| GICD_ISPENDR0 | 32 | 0 | rw | Interrupt Set-Pending 0 |
| GICD_ISPENDR1 | 32 | 0 | rw | Interrupt Set-Pending 1 |
| GICD_ISPENDR2 | 32 | 0 | rw | Interrupt Set-Pending 2 |
| GICD_ITARGETSR0 | 32 | 1010101 | rw | Interrupt Processor Targets 0 |
| GICD_ITARGETSR1 | 32 | 1010101 | rw | Interrupt Processor Targets 1 |
| GICD_ITARGETSR2 | 32 | 1010101 | rw | Interrupt Processor Targets 2 |
| GICD_ITARGETSR3 | 32 | 1010101 | rw | Interrupt Processor Targets 3 |
| GICD_ITARGETSR4 | 32 | 0 | rw | Interrupt Processor Targets 4 |
| GICD_ITARGETSR5 | 32 | 0 | rw | Interrupt Processor Targets 5 |
| GICD_ITARGETSR6 | 32 | 1010100 | rw | Interrupt Processor Targets 6 |
| GICD_ITARGETSR7 | 32 | 1010101 | rw | Interrupt Processor Targets 7 |
| GICD_ITARGETSR8 | 32 | 0 | rw | Interrupt Processor Targets 8 |
| GICD_ITARGETSR9 | 32 | 0 | rw | Interrupt Processor Targets 9 |
| GICD_ITARGETSR10 | 32 | 0 | rw | Interrupt Processor Targets 10 |
| GICD_ITARGETSR11 | 32 | 0 | rw | Interrupt Processor Targets 11 |
| GICD_ITARGETSR12 | 32 | 0 | rw | Interrupt Processor Targets 12 |
| GICD_ITARGETSR13 | 32 | 0 | rw | Interrupt Processor Targets 13 |
| GICD_ITARGETSR14 | 32 | 0 | rw | Interrupt Processor Targets 14 |
| GICD_ITARGETSR15 | 32 | 0 | rw | Interrupt Processor Targets 15 |
| GICD_ITARGETSR16 | 32 | 0 | rw | Interrupt Processor Targets 16 |
| GICD_ITARGETSR17 | 32 | 0 | rw | Interrupt Processor Targets 17 |
| GICD_ITARGETSR18 | 32 | 0 | rw | Interrupt Processor Targets 18 |
| GICD_ITARGETSR19 | 32 | 0 | rw | Interrupt Processor Targets 19 |
| GICD_ITARGETSR20 | 32 | 0 | rw | Interrupt Processor Targets 20 |
| GICD_ITARGETSR21 | 32 | 0 | rw | Interrupt Processor Targets 21 |
| GICD_ITARGETSR22 | 32 | 0 | rw | Interrupt Processor Targets 22 |
| GICD_ITARGETSR23 | 32 | 0 | rw | Interrupt Processor Targets 23 |
| GICD_NSACR0 | 32 | 0 | rw | Interrupt Non-secure Access Control 0 |

| | | | | |
|-----------------|----|--------|----|---------------------------------------|
| GICD_NSACR1 | 32 | 0 | rw | Interrupt Non-secure Access Control 1 |
| GICD_NSACR2 | 32 | 0 | rw | Interrupt Non-secure Access Control 2 |
| GICD_NSACR3 | 32 | 0 | rw | Interrupt Non-secure Access Control 3 |
| GICD_NSACR4 | 32 | 0 | rw | Interrupt Non-secure Access Control 4 |
| GICD_NSACR5 | 32 | 0 | rw | Interrupt Non-secure Access Control 5 |
| GICD_PIDR0 | 32 | 92 | r- | Peripheral ID 0 |
| GICD_PIDR1 | 32 | b4 | r- | Peripheral ID 1 |
| GICD_PIDR2 | 32 | 3b | r- | Peripheral ID 2 |
| GICD_PIDR3 | 32 | 0 | r- | Peripheral ID 3 |
| GICD_PIDR4 | 32 | 44 | r- | Peripheral ID 4 |
| GICD_PIDR5 | 32 | 0 | r- | Peripheral ID 5 |
| GICD_PIDR6 | 32 | 0 | r- | Peripheral ID 6 |
| GICD_PIDR7 | 32 | 0 | r- | Peripheral ID 7 |
| GICD_SETSPINSR | 32 | 0 | -w | Set SPI |
| GICD_SETSPISR | 32 | 0 | -w | Set SPI, Secure |
| GICD_SGIR | 32 | 0 | -w | Software-Generated Interrupt |
| GICD_SPENDSGIR0 | 32 | 0 | rw | SIGI Set-Pending 0 |
| GICD_SPENDSGIR1 | 32 | 0 | rw | SIGI Set-Pending 1 |
| GICD_SPENDSGIR2 | 32 | 0 | rw | SIGI Set-Pending 2 |
| GICD_SPENDSGIR3 | 32 | 0 | rw | SIGI Set-Pending 3 |
| GICD_SPISR0 | 32 | 0 | r- | SPI Status 0 |
| GICD_SPISR1 | 32 | 0 | r- | SPI Status 1 |
| GICD_STATUSR | 32 | 0 | rw | Distributor Status |
| GICD_TYPER | 32 | 7b0442 | r- | Interrupt Controller Type |

Table 13.26: Registers at level 2, type:CPU group:MPCore_distributor

13.2.27 MPCore_physical_redistributor

Registers at level:2, type:CPU group:MPCore_physical_redistributor

| Name | Bits | Initial-Hex | RW | Description |
|------------------|------|-------------|----|------------------------------------------|
| GICR_CIDR0 | 32 | d | r- | Redistributor Component ID 0 |
| GICR_CIDR1 | 32 | f0 | r- | Redistributor Component ID 1 |
| GICR_CIDR2 | 32 | 5 | r- | Redistributor Component ID 2 |
| GICR_CIDR3 | 32 | b1 | r- | Redistributor Component ID 3 |
| GICR_CLRLPIR | 64 | 0 | -w | Clear LPI Pending |
| GICR_CTLR | 32 | 0 | rw | Redistributor Control |
| GICR_ICACTIVER0 | 32 | 0 | rw | Interrupt Clear-Active 0 |
| GICR_ICENABLER0 | 32 | fff | rw | Interrupt Clear-Enable 0 |
| GICR_ICFGR0 | 32 | aaaaaaaa | rw | Interrupt Configuration 0 |
| GICR_ICFGR1 | 32 | 55540000 | rw | Interrupt Configuration 1 |
| GICR_ICPENDR0 | 32 | 0 | rw | Interrupt Clear-Pending 0 |
| GICR_IGROUPR0 | 32 | 0 | rw | Interrupt Group 0 |
| GICR_IGRPMODR0 | 32 | 0 | rw | Interrupt Group Modifier 0 |
| GICR_IIDR | 32 | 43b | r- | Redistributor Implementer Identification |
| GICR_INVALLR | 64 | 0 | -w | Redistributor Invalidate All |
| GICR_INVLPIR | 64 | 0 | -w | Redistributor Invalidate LPI |
| GICR_IPRIORITYR0 | 32 | 0 | rw | Interrupt Priority 0 |
| GICR_IPRIORITYR1 | 32 | 0 | rw | Interrupt Priority 1 |
| GICR_IPRIORITYR2 | 32 | 0 | rw | Interrupt Priority 2 |
| GICR_IPRIORITYR3 | 32 | 0 | rw | Interrupt Priority 3 |
| GICR_IPRIORITYR4 | 32 | 0 | rw | Interrupt Priority 4 |
| GICR_IPRIORITYR5 | 32 | 0 | rw | Interrupt Priority 5 |
| GICR_IPRIORITYR6 | 32 | 0 | rw | Interrupt Priority 6 |
| GICR_IPRIORITYR7 | 32 | 0 | rw | Interrupt Priority 7 |

| | | | | |
|-----------------|----|------|----|----------------------------------------------|
| GICR.ISACTIVER0 | 32 | 0 | rw | Interrupt Set-Active 0 |
| GICR.ISENBALER0 | 32 | ffff | rw | Interrupt Set-Enable 0 |
| GICR.ISPENDR0 | 32 | 0 | rw | Interrupt Set-Pending 0 |
| GICR.NSACR | 32 | 0 | rw | Interrupt Non-secure Access Control |
| GICR.PENDBASER | 64 | 0 | rw | Redistributor LPI Pending Table Base Address |
| GICR.PIDR0 | 32 | 93 | r- | Redistributor Peripheral ID 0 |
| GICR.PIDR1 | 32 | b4 | r- | Redistributor Peripheral ID 1 |
| GICR.PIDR2 | 32 | 3b | r- | Redistributor Peripheral ID 2 |
| GICR.PIDR3 | 32 | 0 | r- | Redistributor Peripheral ID 3 |
| GICR.PIDR4 | 32 | 44 | r- | Redistributor Peripheral ID 4 |
| GICR.PIDR5 | 32 | 0 | r- | Redistributor Peripheral ID 5 |
| GICR.PIDR6 | 32 | 0 | r- | Redistributor Peripheral ID 6 |
| GICR.PIDR7 | 32 | 0 | r- | Redistributor Peripheral ID 7 |
| GICR.PROPBASER | 64 | 0 | rw | Redistributor Properties Base Address |
| GICR.SETLPIR | 64 | 0 | -w | Set LPI Pending |
| GICR.STATUSR | 32 | 0 | rw | Redistributor Status |
| GICR.SYNCR | 32 | 0 | r- | Redistributor Synchronize |
| GICR.TYPER | 64 | 9 | r- | Redistributor Type |
| GICR.WAKER | 32 | 6 | rw | Redistributor Wake |

Table 13.27: Registers at level 2, type:CPU group:MPCore.physical.redistributor

13.2.28 MPCore_processor_interface

Registers at level:2, type:CPU group:MPCore_processor_interface

| Name | Bits | Initial-Hex | RW | Description |
|--------------|------|-------------|----|--------------------------------------------|
| GICC_ABPR | 32 | 3 | rw | Aliased Binary Point |
| GICC_AEOIR | 32 | 0 | -w | Aliased End of Interrupt |
| GICC_AHPPIR | 32 | 3ff | r- | Aliased Highest Priority Pending Interrupt |
| GICC_AIAR | 32 | 3ff | r- | Aliased Interrupt Acknowledge |
| GICC_APR0 | 32 | 0 | rw | Active Priorities 0 |
| GICC_BPR | 32 | 2 | rw | Binary Point |
| GICC_CTLR | 32 | 0 | rw | CPU Interface Control |
| GICC_DIR | 32 | 0 | -w | Deactivate Interrupt |
| GICC_EOIR | 32 | 0 | -w | End of Interrupt |
| GICC_HPPIR | 32 | 3ff | r- | Highest Priority Pending Interrupt |
| GICC_IAR | 32 | 3ff | r- | Interrupt Acknowledge |
| GICC_IIDR | 32 | 4043b | r- | CPU Interface ID |
| GICC_NSAPR0 | 32 | 0 | rw | Non-secure Active Priorities 0 |
| GICC_PMR | 32 | 0 | rw | Interrupt Priority Mask |
| GICC_RPR | 32 | ff | r- | Running Priority |
| GICC_STATUSR | 32 | 0 | rw | CPU Interface Status |

Table 13.28: Registers at level 2, type:CPU group:MPCore_processor_interface

13.2.29 MPCore_virtual_interface_control

Registers at level:2, type:CPU group:MPCore_virtual_interface_control

| Name | Bits | Initial-Hex | RW | Description |
|-------------|------|-------------|----|------------------------------|
| GICH_APR0 | 32 | 0 | rw | Active Priorities 0 |
| GICH_EISR0 | 32 | 0 | r- | End of Interrupt Status 0 |
| GICH_ELRSR0 | 32 | f | r- | Empty List Register Status 0 |
| GICH_HCR | 32 | 0 | rw | Hypervisor Control |

| | | | | |
|-----------|----|----------|----|------------------------------|
| GICH_LR0 | 32 | 0 | rw | List 0 |
| GICH_LR1 | 32 | 0 | rw | List 1 |
| GICH_LR2 | 32 | 0 | rw | List 2 |
| GICH_LR3 | 32 | 0 | rw | List 3 |
| GICH_MISR | 32 | 0 | r- | Maintenance Interrupt Status |
| GICH_VMCR | 32 | 4c0000 | rw | Virtual Machine Control |
| GICH_VTR | 32 | 90000003 | r- | VGIC Type |

Table 13.29: Registers at level 2, type:CPU group:MPCore_virtual_interface_control

13.2.30 MPCore_virtual_processor_interface

Registers at level:2, type:CPU group:MPCore_virtual_processor_interface

| Name | Bits | Initial-Hex | RW | Description |
|-----------------|------|-------------|----|-----------------------------------------------|
| GICV_ABPR | 32 | 3 | rw | VM Aliased Binary Point |
| GICV_AEOIR | 32 | 0 | -w | VM Aliased End of Interrupt |
| GICV_AHPPIR | 32 | 3ff | r- | VM Aliased Highest Priority Pending Interrupt |
| GICV_AIAR | 32 | 3ff | r- | VM Aliased Interrupt Acknowledge |
| GICV_APR0 | 32 | 0 | rw | VM Active Priorities 0 |
| GICV_BPR | 32 | 2 | rw | VM Binary Point |
| GICV_CTLR | 32 | 0 | rw | Virtual Machine Control |
| GICV_DIR | 32 | 0 | -w | VM Deactivate Interrupt |
| GICV_EOIR | 32 | 0 | -w | VM End of Interrupt |
| GICV_HPPIR | 32 | 3ff | r- | VM Highest Priority Pending Interrupt |
| GICV_IAR | 32 | 3ff | r- | VM Interrupt Acknowledge |
| GICV_IIDR | 32 | 4043b | r- | VM CPU Interface ID |
| GICV_PMR | 32 | 0 | rw | VM Priority Mask |
| GICV_RPR | 32 | ff | r- | VM Running Priority |
| GICV_STATUSR | 32 | 0 | rw | VM CPU Interface Status |
| ICV_APR0_EL1 | 32 | 0 | rw | VM Group 0 Active Priorities 0 |
| ICV_APIR0_EL1 | 32 | 0 | rw | VM Group 1 Active Priorities 0 |
| ICV_BPR0_EL1 | 32 | 2 | rw | VM Group 0 Binary Point |
| ICV_BPR1_EL1 | 32 | 3 | rw | VM Group 1 Binary Point |
| ICV_CTLR_EL1 | 32 | 400 | rw | Virtual Machine Control |
| ICV_DIR_EL1 | 32 | 0 | -w | VM Deactivate Interrupt |
| ICV_EOIR0_EL1 | 32 | 0 | -w | VM Group 0 End of Interrupt |
| ICV_EOIR1_EL1 | 32 | 0 | -w | VM Group 1 End of Interrupt |
| ICV_HPPIR0_EL1 | 32 | 3ff | r- | VM Group 0 Highest Priority Pending Interrupt |
| ICV_HPPIR1_EL1 | 32 | 3ff | r- | VM Group 1 Highest Priority Pending Interrupt |
| ICV_IAR0_EL1 | 32 | 3ff | r- | VM Group 0 Interrupt Acknowledge |
| ICV_IAR1_EL1 | 32 | 3ff | r- | VM Group 1 Interrupt Acknowledge |
| ICV_IGRPEN0_EL1 | 32 | 0 | rw | VM Group 0 Interrupt Enable |
| ICV_IGRPEN1_EL1 | 32 | 0 | rw | VM Group 1 Interrupt Enable |
| ICV_PMR_EL1 | 32 | 0 | rw | VM Priority Mask |
| ICV_RPR_EL1 | 32 | ff | r- | VM Running Priority |

Table 13.30: Registers at level 2, type:CPU group:MPCore_virtual_processor_interface

13.2.31 MPCore_ITS

Registers at level:2, type:CPU group:MPCore_ITS

| Name | Bits | Initial-Hex | RW | Description |
|-------------|------|-------------|----|------------------------------------|
| GITS_BASER0 | 64 | 0 | rw | ITS Translation Table Descriptor 0 |

| | | | | |
|--------------|----|----------|----|------------------------------------|
| GITS.BASER1 | 64 | 0 | rw | ITS Translation Table Descriptor 1 |
| GITS.BASER2 | 64 | 0 | rw | ITS Translation Table Descriptor 2 |
| GITS.BASER3 | 64 | 0 | rw | ITS Translation Table Descriptor 3 |
| GITS.BASER4 | 64 | 0 | rw | ITS Translation Table Descriptor 4 |
| GITS.BASER5 | 64 | 0 | rw | ITS Translation Table Descriptor 5 |
| GITS.BASER6 | 64 | 0 | rw | ITS Translation Table Descriptor 6 |
| GITS.BASER7 | 64 | 0 | rw | ITS Translation Table Descriptor 7 |
| GITS.CBASER | 64 | 0 | rw | ITS Command Queue Descriptor |
| GITS.CREADR | 64 | 0 | rw | ITS Read |
| GITS.CTLR | 32 | 80000000 | rw | ITS Control |
| GITS.CWRITER | 64 | 0 | rw | ITS Write |
| GITS.IIDR | 32 | 43b | r- | ITS Identification |
| GITS.TYPER | 64 | 9ef79 | r- | ITS Type |

Table 13.31: Registers at level 2, type:CPU group:MPCore.ITS