



## OVP Guide to Using Processor Models

### Model specific information for MIPS\_P6600

Imperas Software Limited  
Imperas Buildings, North Weston  
Thame, Oxfordshire, OX9 2HA, U.K.  
docs@imperas.com



Author	Imperas Software Limited
Version	20211118.0
Filename	OVP_Model_Specific_Information_mips64_P6600.pdf
Created	18 November 2021
Status	OVP Standard Release

## Copyright Notice

Copyright (c) 2021 Imperas Software Limited. All rights reserved. This software and documentation contain information that is the property of Imperas Software Limited. The software and documentation are furnished under a license agreement and may be used or copied only in accordance with the terms of the license agreement. No part of the software and documentation may be reproduced, transmitted, or translated, in any form or by any means, electronic, mechanical, manual, optical, or otherwise, without prior written permission of Imperas Software Limited, or as expressly provided by the license agreement.

## Right to Copy Documentation

The license agreement with Imperas permits licensee to make copies of the documentation for its internal use only. Each copy shall include all copyrights, trademarks, service marks, and proprietary rights notices, if any.

## Destination Control Statement

All technical data contained in this publication is subject to the export control laws of the United States of America. Disclosure to nationals of other countries contrary to United States law is prohibited. It is the readers responsibility to determine the applicable regulations and to comply with them.

## Disclaimer

IMPERAS SOFTWARE LIMITED, AND ITS LICENSORS MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

## Model Release Status

This model is released as part of OVP releases and is included in OVPworld packages. Please visit [OVPworld.org](http://OVPworld.org).

# Contents

<b>1 Overview</b>	<b>1</b>
1.1 Description . . . . .	1
1.2 Licensing . . . . .	1
1.3 Limitations . . . . .	2
1.4 Verification . . . . .	2
1.5 Features . . . . .	2
<b>2 Configuration</b>	<b>3</b>
2.1 Location . . . . .	3
2.2 GDB Path . . . . .	3
2.3 Semi-Host Library . . . . .	3
2.4 Processor Endian-ness . . . . .	3
2.5 QuantumLeap Support . . . . .	3
2.6 Processor ELF code . . . . .	3
<b>3 All Variants in this model</b>	<b>4</b>
<b>4 Bus Master Ports</b>	<b>5</b>
<b>5 Bus Slave Ports</b>	<b>6</b>
<b>6 Net Ports</b>	<b>7</b>
<b>7 FIFO Ports</b>	<b>12</b>
<b>8 Formal Parameters</b>	<b>13</b>
8.1 Parameter values . . . . .	23
8.2 Parameter values . . . . .	43
<b>9 Execution Modes</b>	<b>54</b>
<b>10 Exceptions</b>	<b>55</b>
<b>11 Hierarchy of the model</b>	<b>57</b>
11.1 Level 1: CMP . . . . .	57
11.2 Level 2: CPU . . . . .	57
<b>12 Model Commands</b>	<b>59</b>
12.1 Level 1: CMP . . . . .	59

12.1.1	isync	59
12.1.2	itrace	59
12.2	Level 2: CPU	60
12.2.1	isync	60
12.2.2	itrace	60
12.2.3	mipsCOP0	60
12.2.4	mipsCacheDisable	60
12.2.4.1	Argument description	60
12.2.5	mipsCacheEnable	60
12.2.6	mipsCacheRatio	61
12.2.7	mipsCacheReport	61
12.2.7.1	Argument description	61
12.2.8	mipsCacheReset	61
12.2.8.1	Argument description	61
12.2.9	mipsCacheTrace	61
12.2.10	mipsDebugFlags	61
12.2.11	mipsReadRegister	62
12.2.12	mipsReadTLBEntry	62
12.2.13	mipsTLBDump	62
12.2.13.1	Argument description	62
12.2.14	mipsTLBDumpGuest	62
12.2.14.1	Argument description	62
12.2.15	mipsTLBDumpRoot	62
12.2.15.1	Argument description	62
12.2.16	mipsTLBGetPhys	62
12.2.17	mipsTraceGuest	63
12.2.18	mipsTraceRoot	63
12.2.19	mipsWriteRegister	63
12.2.20	mipsWriteTLBEntry	63
<b>13</b>	<b>Registers</b>	<b>64</b>
13.1	Level 1: CMP	64
13.2	Level 2: CPU	64
13.2.1	Core	64
13.2.2	FPU	65
13.2.3	DSP	66
13.2.4	Shadow	66
13.2.5	COP0	68
13.2.6	SPRAM	71
13.2.7	MSA	71
13.2.8	CMP_GCR	72
13.2.9	CMP_CPC	73
13.2.10	CMP_GIC	73
13.2.11	Integration_support	86

# Chapter 1

## Overview

This document provides the details of an OVP Fast Processor Model variant.

OVP Fast Processor Models are written in C and provide a C API for use in C based platforms. The models also provide a native interface for use in SystemC TLM2 platforms.

The models are written using the OVP VMI API that provides a Virtual Machine Interface that defines the behavior of the processor. The VMI API makes a clear line between model and simulator allowing very good optimization and world class high speed performance. Most models are provided as a binary shared object and also as source. This allows the download and use of the model binary or the use of the source to explore and modify the model.

The models are run through an extensive QA and regression testing process and most model families are validated using technology provided by the processor IP owners. There is a companion document (OVP Guide to Using Processor Models) which explains the general concepts of OVP Fast Processor Models and their use. It is downloadable from the OVPworld website documentation pages.

### 1.1 Description

MIPS64 Configurable Processor Model

If you need other variants, these models can be obtained from [www.OVPworld.org/MIPUser](http://www.OVPworld.org/MIPUser).

### 1.2 Licensing

Usage of binary model under license governing simulator usage. Source of model available under Imperas Software License Agreement.

## 1.3 Limitations

If this model is not part of your installation, then it is available for download from [www.OVPworld.org/MIPUser](http://www.OVPworld.org/MIPUser).

Cache model does not implement coherency

## 1.4 Verification

Models have been validated correct as part of the MIPS Verified program and run through the MIPS AVP test programs

## 1.5 Features

Only MIPS64 Instruction set implemented

MMU Type: Standard TLB

FPU implemented

L1 I and D cache model in either full or tag-only mode implemented (disabled by default)

Segmentation control implemented

Enhanced virtual address (EVA) supported

Vectored interrupts implemented

# Chapter 2

## Configuration

### 2.1 Location

This model's VLVN is `mips.ovpworld.org/processor/mips64/1.0`.

The model source is usually at:

`$IMPERAS_HOME/ImperasLib/source/mips.ovpworld.org/processor/mips64/1.0`

The model binary is usually at:

`$IMPERAS_HOME/lib/$IMPERAS_ARCH/ImperasLib/mips.ovpworld.org/processor/mips64/1.0`

### 2.2 GDB Path

The default GDB for this model is: `$IMPERAS_HOME/lib/$IMPERAS_ARCH/gdb/mips-sde-elf-gdb`.

### 2.3 Semi-Host Library

The default semi-host library file is `mips.ovpworld.org/semihosting/mips64Newlib/1.0`

### 2.4 Processor Endian-ness

This model can be set to either endian-ness (normally by a pin, or the ELF code).

### 2.5 QuantumLeap Support

This processor is qualified to run in a QuantumLeap enabled simulator.

### 2.6 Processor ELF code

The ELF code supported by this model is: `0x8`.

## Chapter 3

# All Variants in this model

This model has these variants

<b>Variant</b>	Description
P6600	(described in this document)
I6400	
MIPS64R6	
I6500	

Table 3.1: All Variants in this model



## Chapter 4

# Bus Master Ports

This model has these bus master ports.

<b>Name</b>	min	max	Connect?	Description
INSTRUCTION	12	59	mandatory	
DATA	12	59	optional	
USPRAM	32	32	optional	unified scratchpad RAM

Table 4.1: Bus Master Ports

## Chapter 5

# Bus Slave Ports

This model has no bus slave ports.

## Chapter 6

# Net Ports

This model has these net ports.

Name	Type	Connect?	Description
reset	input	optional	CMP reset
dint	input	optional	Debug external interrupt
int0	input	optional	GIC external interrupt
int1	input	optional	GIC external interrupt
int2	input	optional	GIC external interrupt
int3	input	optional	GIC external interrupt
int4	input	optional	GIC external interrupt
int5	input	optional	GIC external interrupt
int6	input	optional	GIC external interrupt
int7	input	optional	GIC external interrupt
int8	input	optional	GIC external interrupt
int9	input	optional	GIC external interrupt
int10	input	optional	GIC external interrupt
int11	input	optional	GIC external interrupt
int12	input	optional	GIC external interrupt
int13	input	optional	GIC external interrupt
int14	input	optional	GIC external interrupt
int15	input	optional	GIC external interrupt
int16	input	optional	GIC external interrupt
int17	input	optional	GIC external interrupt
int18	input	optional	GIC external interrupt
int19	input	optional	GIC external interrupt
int20	input	optional	GIC external interrupt
int21	input	optional	GIC external interrupt
int22	input	optional	GIC external interrupt
int23	input	optional	GIC external interrupt
int24	input	optional	GIC external interrupt
int25	input	optional	GIC external interrupt
int26	input	optional	GIC external interrupt
int27	input	optional	GIC external interrupt
int28	input	optional	GIC external interrupt

int29	input	optional	GIC external interrupt
int30	input	optional	GIC external interrupt
int31	input	optional	GIC external interrupt
int32	input	optional	GIC external interrupt
int33	input	optional	GIC external interrupt
int34	input	optional	GIC external interrupt
int35	input	optional	GIC external interrupt
int36	input	optional	GIC external interrupt
int37	input	optional	GIC external interrupt
int38	input	optional	GIC external interrupt
int39	input	optional	GIC external interrupt
ej_disable_probe_debug	input	optional	GIC ej_disable_probe_debug
ejtagbrk_override	input	optional	GIC ejtagbrk_override
ej_dint_in	input	optional	GIC ej_dint_in
GCR_CUSTOM_BASE	output	optional	Provides the least significant 32-bits of the value written to the GCR_CUSTOM_BASE register. Second half of GCR_CUSTOM_BASE_HI and GCR_CUSTOM_BASE output.
GCR_CUSTOM_BASE_UPPER	output	optional	Provides the most significant 32-bits of value written to the the GCR_CUSTOM_BASE register. First half of GCR_CUSTOM_BASE_HI and GCR_CUSTOM_BASE output.
reset_CPU0	input	optional	Core reset
hwint0_CPU0	input	optional	External interrupt
hwint1_CPU0	input	optional	External interrupt
hwint2_CPU0	input	optional	External interrupt
hwint3_CPU0	input	optional	External interrupt
hwint4_CPU0	input	optional	External interrupt
hwint5_CPU0	input	optional	External interrupt
nmi_CPU0	input	optional	Non-maskable external interrupt
EICPresent_CPU0	input	optional	Input signal SLEICPresent per VPE
EIC_RIPL_CPU0	input	optional	External interrupt controller RIPL (alias of hwint0 - 5 or 7)
EIC_EICSS_CPU0	input	optional	External interrupt controller EICSS
EIC_VectorNum_CPU0	input	optional	External interrupt controller vector number
EIC_VectorOffset_CPU0	input	optional	External interrupt controller vector offset
EIC_GID_CPU0	input	optional	External interrupt controller guest ID
intISS_CPU0	output	optional	True when interrupt request is serviced
causeTI_CPU0	output	optional	True when timer interrupt expires
causeIP0_CPU0	output	optional	Raised for software interrupt request IP0
causeIP1_CPU0	output	optional	Raised for software interrupt request IP1
si_sleep_CPU0	output	optional	True when the VPE is in WAIT state

hwint0	input	optional	External interrupt for compatibility
vc_run_CPU0	input	optional	Set to force stop of execution on processor VPE (simulation control only)
Guest.EIC_RIPL_CPU0	input	optional	Guest External interrupt controller RIPL
Guest.EIC_EICSS_CPU0	input	optional	Guest External interrupt controller EICSS
Guest.EIC_VectorNum_CPU0	input	optional	Guest External interrupt controller vector number
Guest.EIC_VectorOffset_CPU0	input	optional	Guest External interrupt controller vector offset
Guest.EIC_GID_CPU0	input	optional	Guest External interrupt controller guest ID
Guest.intISS_CPU0	output	optional	True when Guest interrupt request is serviced
Guest.causeTI_CPU0	output	optional	True when Guest timer interrupt expires
Guest.causeIP0_CPU0	output	optional	Raised for Guest software interrupt request IP0
Guest.causeIP1_CPU0	output	optional	Raised for Guest software interrupt request IP1
reset_CPU1	input	optional	Core reset
hwint0_CPU1	input	optional	External interrupt
hwint1_CPU1	input	optional	External interrupt
hwint2_CPU1	input	optional	External interrupt
hwint3_CPU1	input	optional	External interrupt
hwint4_CPU1	input	optional	External interrupt
hwint5_CPU1	input	optional	External interrupt
nmi_CPU1	input	optional	Non-maskable external interrupt
EICPresent_CPU1	input	optional	Input signal SI_EICPresent per VPE
EIC_RIPL_CPU1	input	optional	External interrupt controller RIPL (alias of hwint0 - 5 or 7)
EIC_EICSS_CPU1	input	optional	External interrupt controller EICSS
EIC_VectorNum_CPU1	input	optional	External interrupt controller vector number
EIC_VectorOffset_CPU1	input	optional	External interrupt controller vector offset
EIC_GID_CPU1	input	optional	External interrupt controller guest ID
intISS_CPU1	output	optional	True when interrupt request is serviced
causeTI_CPU1	output	optional	True when timer interrupt expires
causeIP0_CPU1	output	optional	Raised for software interrupt request IP0
causeIP1_CPU1	output	optional	Raised for software interrupt request IP1
si_sleep_CPU1	output	optional	True when the VPE is in WAIT state
vc_run_CPU1	input	optional	Set to force stop of execution on processor VPE (simulation control only)
Guest.EIC_RIPL_CPU1	input	optional	Guest External interrupt controller RIPL
Guest.EIC_EICSS_CPU1	input	optional	Guest External interrupt controller EICSS
Guest.EIC_VectorNum_CPU1	input	optional	Guest External interrupt controller vector number

Guest.EIC_VectorOffset_CPU1	input	optional	Guest External interrupt controller vector offset
Guest.EIC_GID_CPU1	input	optional	Guest External interrupt controller guest ID
Guest.intISS_CPU1	output	optional	True when Guest interrupt request is serviced
Guest.causeTI_CPU1	output	optional	True when Guest timer interrupt expires
Guest.causeIP0_CPU1	output	optional	Raised for Guest software interrupt request IP0
Guest.causeIP1_CPU1	output	optional	Raised for Guest software interrupt request IP1
reset_CPU2	input	optional	Core reset
hwint0_CPU2	input	optional	External interrupt
hwint1_CPU2	input	optional	External interrupt
hwint2_CPU2	input	optional	External interrupt
hwint3_CPU2	input	optional	External interrupt
hwint4_CPU2	input	optional	External interrupt
hwint5_CPU2	input	optional	External interrupt
nmi_CPU2	input	optional	Non-maskable external interrupt
EICPresent_CPU2	input	optional	Input signal SI_EICPresent per VPE
EIC_RIPL_CPU2	input	optional	External interrupt controller RIPL (alias of hwint0 - 5 or 7)
EIC_EICSS_CPU2	input	optional	External interrupt controller EICSS
EIC_VectorNum_CPU2	input	optional	External interrupt controller vector number
EIC_VectorOffset_CPU2	input	optional	External interrupt controller vector offset
EIC_GID_CPU2	input	optional	External interrupt controller guest ID
intISS_CPU2	output	optional	True when interrupt request is serviced
causeTI_CPU2	output	optional	True when timer interrupt expires
causeIP0_CPU2	output	optional	Raised for software interrupt request IP0
causeIP1_CPU2	output	optional	Raised for software interrupt request IP1
si_sleep_CPU2	output	optional	True when the VPE is in WAIT state
vc_run_CPU2	input	optional	Set to force stop of execution on processor VPE (simulation control only)
Guest.EIC_RIPL_CPU2	input	optional	Guest External interrupt controller RIPL
Guest.EIC_EICSS_CPU2	input	optional	Guest External interrupt controller EICSS
Guest.EIC_VectorNum_CPU2	input	optional	Guest External interrupt controller vector number
Guest.EIC_VectorOffset_CPU2	input	optional	Guest External interrupt controller vector offset
Guest.EIC_GID_CPU2	input	optional	Guest External interrupt controller guest ID
Guest.intISS_CPU2	output	optional	True when Guest interrupt request is serviced
Guest.causeTI_CPU2	output	optional	True when Guest timer interrupt expires

Guest.causeIP0_CPU2	output	optional	Raised for Guest software interrupt request IP0
Guest.causeIP1_CPU2	output	optional	Raised for Guest software interrupt request IP1
reset_CPU3	input	optional	Core reset
hwint0_CPU3	input	optional	External interrupt
hwint1_CPU3	input	optional	External interrupt
hwint2_CPU3	input	optional	External interrupt
hwint3_CPU3	input	optional	External interrupt
hwint4_CPU3	input	optional	External interrupt
hwint5_CPU3	input	optional	External interrupt
nmi_CPU3	input	optional	Non-maskable external interrupt
EICPresent_CPU3	input	optional	Input signal SI_EICPresent per VPE
EIC_RIPL_CPU3	input	optional	External interrupt controller RIPL (alias of hwint0 - 5 or 7)
EIC_EICSS_CPU3	input	optional	External interrupt controller EICSS
EIC_VectorNum_CPU3	input	optional	External interrupt controller vector number
EIC_VectorOffset_CPU3	input	optional	External interrupt controller vector offset
EIC_GID_CPU3	input	optional	External interrupt controller guest ID
intISS_CPU3	output	optional	True when interrupt request is serviced
causeTI_CPU3	output	optional	True when timer interrupt expires
causeIP0_CPU3	output	optional	Raised for software interrupt request IP0
causeIP1_CPU3	output	optional	Raised for software interrupt request IP1
si_sleep_CPU3	output	optional	True when the VPE is in WAIT state
vc_run_CPU3	input	optional	Set to force stop of execution on processor VPE (simulation control only)
Guest.EIC_RIPL_CPU3	input	optional	Guest External interrupt controller RIPL
Guest.EIC_EICSS_CPU3	input	optional	Guest External interrupt controller EICSS
Guest.EIC_VectorNum_CPU3	input	optional	Guest External interrupt controller vector number
Guest.EIC_VectorOffset_CPU3	input	optional	Guest External interrupt controller vector offset
Guest.EIC_GID_CPU3	input	optional	Guest External interrupt controller guest ID
Guest.intISS_CPU3	output	optional	True when Guest interrupt request is serviced
Guest.causeTI_CPU3	output	optional	True when Guest timer interrupt expires
Guest.causeIP0_CPU3	output	optional	Raised for Guest software interrupt request IP0
Guest.causeIP1_CPU3	output	optional	Raised for Guest software interrupt request IP1

Table 6.1: Net Ports

## Chapter 7

# FIFO Ports

This model has no FIFO ports.



# Chapter 8

## Formal Parameters

Name	Type	Description
variant	Enumeration	Processor variant
endian	Endian	Model endian
cacheenable	Enumeration	Select cache model mode (default, tag or full)
cachedebug	Uns32	Cache debug flags
cacheextbiuinfo	Pointer	Pointer to platform-provided BIU cache info structure
mipsHexFile	String	Load a MIPS hex file (test-mode)
IMPERAS_MIPS_AVP_OPCODES	Boolean	Enable MIPS-specific magic Pass/Fail opcodes (specific for AVP test termination)
cacheIndexBypassTLB	Boolean	When set, cache index ops do not generate TLB exceptions
MIPS_TRACE	Boolean	Enable MIPS-format trace output
gprNames	Boolean	Disassemble the register names from the default ABI instead of register numbers for MIPS-format trace output
supervisorMode	Boolean	Override whether processor implements supervisor mode
busErrors	Boolean	Override bus error exception behavior. When true, accesses of memory not defined by platform will cause bus error exceptions
fixedMMU	Boolean	Override the MMU type to fixed mapping when true (sets Config.MT=3, Config.KU/K23=2 and Config1.MMUSizeM1=0)
fixedDbgRegSize	Boolean	Enable applications to debug on P5600 with GDB version 2015.06-05 and prior
removeDSP	Boolean	Override the DSP-present configuration when true (sets Config3.DSPP/DSP2P=0)
removeCMP	Boolean	Override the CMP-Present configuration when true (sets Config3.CMGCR and GCR_BASE to 0)
removeFP	Boolean	Override the FP-Present configuration when true (sets Config1.FP to 0)
removeFTLB	Boolean	Override the FTLBEn configuration when true (disable FTLB)
isISA	Boolean	Enable to specify ISA model (reset address from ELF, all coprocessors enabled)
hiddenTLBentries	Boolean	Deprecated - Instead set config1MMUSizeM1 to maximum value to improve performance
perfCounters	Uns32	Performance Counters
MTFPU	Uns32	Enable multi-threaded FPU (1:old mttc1 behavior, 2:new mttc1 behavior)

supportDenormals	Boolean	Enable to specify that the FPU supports denormal operands and results
VPE0MaxTC	Uns32	Specifies the maximum TCs initially on VPE0. Ignored if less than two VPEs configured.
VPE1MaxTC	Uns32	Specifies the maximum TCs initially on VPE1. Ignored if less than three VPEs configured.
segBits	Uns32	Override the number of address bits implemented for 64 bit segments (MIPS64 Only)
mpuRegions	Uns32	Number of regions for memory protection unit
mpuType	Uns32	Type of MPU implementation
mpuEnable	Boolean	Enable MPU2 segment control at reset
mpuSegment0	Uns32	Attributes for segment 0 in MPU2 SegmentControl_0 register
mpuSegment1	Uns32	Attributes for segment 1 in MPU2 SegmentControl_0 register
mpuSegment2	Uns32	Attributes for segment 2 in MPU2 SegmentControl_0 register
mpuSegment3	Uns32	Attributes for segment 3 in MPU2 SegmentControl_0 register
mpuSegment4	Uns32	Attributes for segment 4 in MPU2 SegmentControl_1 register
mpuSegment5	Uns32	Attributes for segment 5 in MPU2 SegmentControl_1 register
mpuSegment6	Uns32	Attributes for segment 6 in MPU2 SegmentControl_1 register
mpuSegment7	Uns32	Attributes for segment 7 in MPU2 SegmentControl_1 register
mpuSegment8	Uns32	Attributes for segment 8 in MPU2 SegmentControl_2 register
mpuSegment9	Uns32	Attributes for segment 9 in MPU2 SegmentControl_2 register
mpuSegment10	Uns32	Attributes for segment 10 in MPU2 SegmentControl_2 register
mpuSegment11	Uns32	Attributes for segment 11 in MPU2 SegmentControl_2 register
mpuSegment12	Uns32	Attributes for segment 12 in MPU2 SegmentControl_3 register
mpuSegment13	Uns32	Attributes for segment 13 in MPU2 SegmentControl_3 register
mpuSegment14	Uns32	Attributes for segment 14 in MPU2 SegmentControl_3 register
mpuSegment15	Uns32	Attributes for segment 15 in MPU2 SegmentControl_3 register
mvpconf0vpe	Uns32	Override MVPConf0.PVPE
tcDisable	Uns32	Number of disabled TCs
vpeDisable	Uns32	Number of disabled VPEs
mvpconf0tc	Uns32	Override MVPConf0.PTC
mvpconf0pcp	Boolean	Override MVPConf0.PCP
mvpconf0tcp	Boolean	Override MVPConf0.TCP
mvpconflc1f	Boolean	Override MVPConf.C1F
mvpcontrolPolicyMode	Boolean	Override MVPControl.POLICY_MODE
hasFDC	Uns32	Specify the size of Fast Debug Channel register block
licenseWarningDays	Uns32	Specify the number of days before a license expires to start issuing a warning. 0 disables warnings.
MIPS_UHI	Boolean	Enable MIPS-Unified Hosting interface

mipsUhiArgs	String	Specifies UHI arguments string separated by spaces
mipsUhiJail	String	Specifies UHI jailroot
MIPS_DV_MODE	Boolean	Enable Design Verification mode
MIPS_MAGIC_OPCODES	Boolean	Enable MIPS-specific magic Pass/Fail opcodes
enableTrickbox	Boolean	Enable trickbox addresses (specific for AVP)
fpuxcdisable	Boolean	Disable FPU exceptions
TRU_PRESENT	Boolean	Disable or Enable based on TRU presence to control certain fields (e.x.perfCtl.PCTD
ucLLwordsLocked	Uns32	Numbers of words (4 byte) an uncached LL is locking. Maximum: 4K
FUSA	Boolean	Enable Functional Safety
CPC_FAULT_SUPPORTED	Uns32	Specify the value for Functional Safety Supported register
CPC_FAULT_ENABLE	Uns32	Specify the value for Functional Safety Enable register
cop2Bits	Uns32	Specifies width in bits of COP2 registers (32 or 64)
cop2FileName	String	Specifies COP2 dynamically-loaded object (.so/.dll) defining COP2 instructions
udiConfig	Int32	Specifies UDI configuration attribute
udiFileName	String	Specifies UDI dynamically-loaded object (.so/.dll) defining UDI instructions
vectoredinterrupt	Boolean	Enables vectored interrupts (sets Config3 VInt)
externalinterrupt	Boolean	Enables the use of an external interrupt controller (sets Config3 VEIC)
rootFixedMMU	Boolean	Override the root MMU type to fixed mapping when true (sets Config.MT=3 and Config.KU/K23=2)
rootMMUSizeM1	Uns32	Override the root MMUSizeM1 field in Config1 register (number of MMU entries-1)
srscctlHSS	Uns32	Override the HSS field in SRSCtl register (number of shadow register sets)
firPS	Uns32	Override the PS field in FIR register
firHas2008	Uns32	Override the Has2008 field in FIR register
usePreciseFpu	Uns32	Use the precise Floating Point emulation
simulateLite	Enumeration	Run Simulation with optimization. There are several optimizations which could be combined (NONE, FS, MA or FSMA)
pridCompanyOptions	Uns32	Override the Company Options field in PRId register
pridRevision	Uns32	Override the Revision field in PRId register
globalClusterNum	Uns32	Override the ClusterNum field in GlobalNumber register
intctlIPTI	Uns32	Override the IPTI field in IntCtl register
intctlIPFDC	Uns32	Override the IPFDC field in IntCtl register
intctlIPPCI	Uns32	Override the IPPCI field in IntCtl register
numWatch	Uns32	Specify number of WatchLo/WatchHi register pairs
xconfigSpecified	Boolean	True if the configuration comes from a valid xconfig file
segcfg0PA	Uns32	Set CFG0.PA field of SegCtl0 register
segcfg1PA	Uns32	Set CFG1.PA field of SegCtl0 register
segcfg2PA	Uns32	Set CFG2.PA field of SegCtl1 register
segcfg3PA	Uns32	Set CFG3.PA field of SegCtl1 register
segcfg4PA	Uns32	Set CFG4.PA field of SegCtl2 register
segcfg5PA	Uns32	Set CFG5.PA field of SegCtl2 register
segcfg0AM	Uns32	Set CFG0.AM field of SegCtl0 register
segcfg1AM	Uns32	Set CFG1.AM field of SegCtl0 register

segcfg2AM	Uns32	Set CFG2.AM field of SegCtl1 register
segcfg3AM	Uns32	Set CFG3.AM field of SegCtl1 register
segcfg4AM	Uns32	Set CFG4.AM field of SegCtl2 register
segcfg5AM	Uns32	Set CFG5.AM field of SegCtl2 register
segcfg0EU	Uns32	Set CFG0.EU field of SegCtl0 register
segcfg1EU	Uns32	Set CFG1.EU field of SegCtl0 register
segcfg2EU	Uns32	Set CFG2.EU field of SegCtl1 register
segcfg3EU	Uns32	Set CFG3.EU field of SegCtl1 register
segcfg4EU	Uns32	Set CFG4.EU field of SegCtl2 register
segcfg5EU	Uns32	Set CFG5.EU field of SegCtl2 register
segcfg0C	Uns32	Set CFG0.C field of SegCtl0 register
segcfg1C	Uns32	Set CFG1.C field of SegCtl0 register
segcfg2C	Uns32	Set CFG2.C field of SegCtl1 register
segcfg3C	Uns32	Set CFG3.C field of SegCtl1 register
segcfg4C	Uns32	Set CFG4.C field of SegCtl2 register
segcfg5C	Uns32	Set CFG5.C field of SegCtl2 register
cdmmSize	Uns32	Override the cdmmSize reset value
configAR	Uns32	Enables R6 support
configBM	Uns32	Override the BM field in Config register (burst mode)
configDSP	Boolean	Override Config.DSP (data scratchpad RAM present)
configISP	Boolean	Override Config.ISP (instruction scratchpad RAM present)
configK0	Uns32	Override power on value of Config.K0 (set Kseg0 cacheability)
configKU	Uns32	Override power on value of Config.KU (set Useg cacheability)
configK23	Uns32	Override power on value of Config.K23 (set Kseg23 cacheability)
configMDU	Boolean	Override Config.MDU (iterative multiply/divide unit)
configMM	Boolean	Override Config.MM (merging mode for write)
configMT	Uns32	Override Config.MT
configSB	Boolean	Override Config.SB (simple bus transfers only)
configBCP	Boolean	Override Config.BCP (Buffer Cache Present)
MIPS16eASE	Boolean	Override Config1.CA (enables the MIPS16e ASE)
config1DA	Uns32	Override Config1.DA (Dcache associativity)
config1DL	Uns32	Override Config1.DL (Dcache line size)
config1DS	Uns32	Override Config1.DS (Dcache sets per way)
config1EP	Boolean	Override Config1.EP (EJTag present)
config1IA	Uns32	Override Config1.IA (Icache associativity)
config1IL	Uns32	Override Config1.IL (Icache line size)
config1IS	Uns32	Override Config1.IS (Icache sets per way)
config1MMUSizeM1	Uns32	Override Config1.MMUSizeM1 (number of MMU entries-1)
config1MMUSizeM1_VPE1	Uns32	Override Config1.MMUSizeM1 for VPE1
config1MMUSizeM1_VPE2	Uns32	Override Config1.MMUSizeM1 for VPE2
config1MMUSizeM1_VPE3	Uns32	Override Config1.MMUSizeM1 for VPE3
config1WR	Boolean	Override Config1.WR (watchpoint registers present)
config1PC	Boolean	Override Config1.PC (Performance Counters present)
config1C2	Boolean	Override Config1.C2 (Coprocessor 2 present)
config2SU	Uns32	Override the SU field in Config2 register
config2SS	Uns32	Override the SS field in Config2 register

config2SL	Uns32	Override the SL field in Config2 register
config2SA	Uns32	Override the SA field in Config2 register
config3BI	Boolean	Override Config3.BI
config3BP	Boolean	Override Config3.BP
config3CDMM	Boolean	Override Config3.CDMM
config3CTXTC	Boolean	Override Config3.CTXTC
config3DSPP	Boolean	Override Config3.DSPP
config3DSP2P	Boolean	Override Config3.DSP2P
config3IPLW	Uns32	Override Config3.IPLW
config3ISA	Uns32	Override Config3.ISA
config3ISAOnExc	Boolean	Override Config3.ISAOnExc
config3ITL	Boolean	Override Config3.ITL
config3LPA	Boolean	Override Config3.LPA
config3MCU	Boolean	Override Config3.MCU
config3MMAR	Uns32	Override Config3.MMAR
config3RXI	Boolean	Override Config3.RXI
config3SC	Boolean	Override Config3.SC
config3ULRI	Boolean	Override Config3.ULRI
config3VZ	Boolean	Override Config3.VZ
config3MSAP	Boolean	Override Config3.MSAP
config3CMGCR	Boolean	Override the CMGCR field in Config3 register
config3SP	Boolean	Override the SP field in Config3 register
config3TL	Uns32	Override the TL field in Config3 register
config3PW	Boolean	Override the PW field in Config3 register
config4AE	Boolean	Override Config4.AE
config4IE	Uns32	Override Config4.IE
config4MMUConfig	Uns32	Override Config4.MMUConfig field (interpretation depends on MMUExtDef value)
config4MMUExtDef	Uns32	Override Config4.MMUExtDef
config4VTLBSizeExt	Uns32	Override Config4.VTLBSizeExt
config4KScrExist	Uns32	Override Config4.KScrExist
config5EVA	Boolean	Override Config5.EVA
config5LLB	Boolean	Override Config5.LLB (LLAddr supports LLbit)
config5MRP	Boolean	Override Config5.MRP (MaaR Present)
config5NFExists	Boolean	Override Config5.NFExists
mips32Macro	Boolean	Enables the MIPS32 SAVE and RESTORE macro instructions. Ignored if Config5.CA2 is not set)
config5MSAEn	Boolean	Override Config5.MSAEn
config5MVH	Boolean	Override Config5.MVH (enable MTHC0 and MFHC0 instructions)
config5DEC	Boolean	Override Config5.DEC (to test Dual Endian Capability)
config5GI	Uns32	Override Config5.GI (enable GINV)
config5CRCP	Boolean	Override Config5.CRCP (CRCP Present)
config5VP	Boolean	Override Config5.VP
config6FTLBEEn	Boolean	Override power on value of Config6.FTLBEEn
config7AR	Boolean	Override Config7.AR (Alias removed Data cache)
config7DCIDX_MODE	Uns32	Override Config7.DCIDX_MODE
config7HCI	Boolean	Override Config7.HCI (Hardware Cache Initialization)
config7IAR	Boolean	Override Config7.IAR (Alias removed Instruction cache)
config7WII	Boolean	Override Config7.WII (wait IE/IXMT ignore)
config7ES	Uns32	Override the ES field in Config7 register (Externalize sync)

config7WR	Boolean	Override Config7[31] bit (Alternative implementation of Watch registers)
config7FPR	Boolean	Override Config7.FPR (one-half FPU clock ratio)
config7USP	Uns32	Override Config7.USP (USPRAM enable)
config7BTLM	Boolean	Override Config7.BTLM bit
config7BusSlp	Boolean	Override Config7.BusSlp bit
config7IVAD	Boolean	Override Config7.IVAD bit
config7RPS	Boolean	Override Config7.RPS bit
config7IAR_CPU0_VPE0	Boolean	Override Config7.IAR bit for CPU0/VPE0
config7IAR_CPU0_VPE1	Boolean	Override Config7.IAR bit for CPU0/VPE1
config7IAR_CPU0_VPE2	Boolean	Override Config7.IAR bit for CPU0/VPE2
config7IAR_CPU0_VPE3	Boolean	Override Config7.IAR bit for CPU0/VPE3
config7IAR_CPU1_VPE0	Boolean	Override Config7.IAR bit for CPU1/VPE0
config7IAR_CPU1_VPE1	Boolean	Override Config7.IAR bit for CPU1/VPE1
config7IAR_CPU1_VPE2	Boolean	Override Config7.IAR bit for CPU1/VPE2
config7IAR_CPU1_VPE3	Boolean	Override Config7.IAR bit for CPU1/VPE3
config7IAR_CPU2_VPE0	Boolean	Override Config7.IAR bit for CPU2/VPE0
config7IAR_CPU2_VPE1	Boolean	Override Config7.IAR bit for CPU2/VPE1
config7IAR_CPU2_VPE2	Boolean	Override Config7.IAR bit for CPU2/VPE2
config7IAR_CPU2_VPE3	Boolean	Override Config7.IAR bit for CPU2/VPE3
config7IAR_CPU3_VPE0	Boolean	Override Config7.IAR bit for CPU3/VPE0
config7IAR_CPU3_VPE1	Boolean	Override Config7.IAR bit for CPU3/VPE1
config7IAR_CPU3_VPE2	Boolean	Override Config7.IAR bit for CPU3/VPE2
config7IAR_CPU3_VPE3	Boolean	Override Config7.IAR bit for CPU3/VPE3
config7IAR_CPU4_VPE0	Boolean	Override Config7.IAR bit for CPU4/VPE0
config7IAR_CPU4_VPE1	Boolean	Override Config7.IAR bit for CPU4/VPE1
config7IAR_CPU4_VPE2	Boolean	Override Config7.IAR bit for CPU4/VPE2
config7IAR_CPU4_VPE3	Boolean	Override Config7.IAR bit for CPU4/VPE3
config7IAR_CPU5_VPE0	Boolean	Override Config7.IAR bit for CPU5/VPE0
config7IAR_CPU5_VPE1	Boolean	Override Config7.IAR bit for CPU5/VPE1
config7IAR_CPU5_VPE2	Boolean	Override Config7.IAR bit for CPU5/VPE2
config7IAR_CPU5_VPE3	Boolean	Override Config7.IAR bit for CPU5/VPE3
config7IAR_CPU6_VPE0	Boolean	Override Config7.IAR bit for CPU6/VPE0
config7IAR_CPU6_VPE1	Boolean	Override Config7.IAR bit for CPU6/VPE1
config7IAR_CPU6_VPE2	Boolean	Override Config7.IAR bit for CPU6/VPE2
config7IAR_CPU6_VPE3	Boolean	Override Config7.IAR bit for CPU6/VPE3
config7IAR_CPU7_VPE0	Boolean	Override Config7.IAR bit for CPU7/VPE0
config7IAR_CPU7_VPE1	Boolean	Override Config7.IAR bit for CPU7/VPE1
config7IAR_CPU7_VPE2	Boolean	Override Config7.IAR bit for CPU7/VPE2
config7IAR_CPU7_VPE3	Boolean	Override Config7.IAR bit for CPU7/VPE3
config7IVAD_CPU0_VPE0	Boolean	Override Config7.IVAD bit for CPU0/VPE0
config7IVAD_CPU0_VPE1	Boolean	Override Config7.IVAD bit for CPU0/VPE1
config7IVAD_CPU0_VPE2	Boolean	Override Config7.IVAD bit for CPU0/VPE2
config7IVAD_CPU0_VPE3	Boolean	Override Config7.IVAD bit for CPU0/VPE3
config7IVAD_CPU1_VPE0	Boolean	Override Config7.IVAD bit for CPU1/VPE0
config7IVAD_CPU1_VPE1	Boolean	Override Config7.IVAD bit for CPU1/VPE1
config7IVAD_CPU1_VPE2	Boolean	Override Config7.IVAD bit for CPU1/VPE2
config7IVAD_CPU1_VPE3	Boolean	Override Config7.IVAD bit for CPU1/VPE3
config7IVAD_CPU2_VPE0	Boolean	Override Config7.IVAD bit for CPU2/VPE0
config7IVAD_CPU2_VPE1	Boolean	Override Config7.IVAD bit for CPU2/VPE1
config7IVAD_CPU2_VPE2	Boolean	Override Config7.IVAD bit for CPU2/VPE2
config7IVAD_CPU2_VPE3	Boolean	Override Config7.IVAD bit for CPU2/VPE3
config7IVAD_CPU3_VPE0	Boolean	Override Config7.IVAD bit for CPU3/VPE0
config7IVAD_CPU3_VPE1	Boolean	Override Config7.IVAD bit for CPU3/VPE1
config7IVAD_CPU3_VPE2	Boolean	Override Config7.IVAD bit for CPU3/VPE2
config7IVAD_CPU3_VPE3	Boolean	Override Config7.IVAD bit for CPU3/VPE3



config7IVAD_CPU4_VPE0	Boolean	Override Config7.IVAD bit for CPU4/VPE0
config7IVAD_CPU4_VPE1	Boolean	Override Config7.IVAD bit for CPU4/VPE1
config7IVAD_CPU4_VPE2	Boolean	Override Config7.IVAD bit for CPU4/VPE2
config7IVAD_CPU4_VPE3	Boolean	Override Config7.IVAD bit for CPU4/VPE3
config7IVAD_CPU5_VPE0	Boolean	Override Config7.IVAD bit for CPU5/VPE0
config7IVAD_CPU5_VPE1	Boolean	Override Config7.IVAD bit for CPU5/VPE1
config7IVAD_CPU5_VPE2	Boolean	Override Config7.IVAD bit for CPU5/VPE2
config7IVAD_CPU5_VPE3	Boolean	Override Config7.IVAD bit for CPU5/VPE3
config7IVAD_CPU6_VPE0	Boolean	Override Config7.IVAD bit for CPU6/VPE0
config7IVAD_CPU6_VPE1	Boolean	Override Config7.IVAD bit for CPU6/VPE1
config7IVAD_CPU6_VPE2	Boolean	Override Config7.IVAD bit for CPU6/VPE2
config7IVAD_CPU6_VPE3	Boolean	Override Config7.IVAD bit for CPU6/VPE3
config7IVAD_CPU7_VPE0	Boolean	Override Config7.IVAD bit for CPU7/VPE0
config7IVAD_CPU7_VPE1	Boolean	Override Config7.IVAD bit for CPU7/VPE1
config7IVAD_CPU7_VPE2	Boolean	Override Config7.IVAD bit for CPU7/VPE2
config7IVAD_CPU7_VPE3	Boolean	Override Config7.IVAD bit for CPU7/VPE3
config7RPS_CPU0_VPE0	Boolean	Override Config7.RPS bit for CPU0/VPE0
config7RPS_CPU0_VPE1	Boolean	Override Config7.RPS bit for CPU0/VPE1
config7RPS_CPU0_VPE2	Boolean	Override Config7.RPS bit for CPU0/VPE2
config7RPS_CPU0_VPE3	Boolean	Override Config7.RPS bit for CPU0/VPE3
config7RPS_CPU1_VPE0	Boolean	Override Config7.RPS bit for CPU1/VPE0
config7RPS_CPU1_VPE1	Boolean	Override Config7.RPS bit for CPU1/VPE1
config7RPS_CPU1_VPE2	Boolean	Override Config7.RPS bit for CPU1/VPE2
config7RPS_CPU1_VPE3	Boolean	Override Config7.RPS bit for CPU1/VPE3
config7RPS_CPU2_VPE0	Boolean	Override Config7.RPS bit for CPU2/VPE0
config7RPS_CPU2_VPE1	Boolean	Override Config7.RPS bit for CPU2/VPE1
config7RPS_CPU2_VPE2	Boolean	Override Config7.RPS bit for CPU2/VPE2
config7RPS_CPU2_VPE3	Boolean	Override Config7.RPS bit for CPU2/VPE3
config7RPS_CPU3_VPE0	Boolean	Override Config7.RPS bit for CPU3/VPE0
config7RPS_CPU3_VPE1	Boolean	Override Config7.RPS bit for CPU3/VPE1
config7RPS_CPU3_VPE2	Boolean	Override Config7.RPS bit for CPU3/VPE2
config7RPS_CPU3_VPE3	Boolean	Override Config7.RPS bit for CPU3/VPE3
config7RPS_CPU4_VPE0	Boolean	Override Config7.RPS bit for CPU4/VPE0
config7RPS_CPU4_VPE1	Boolean	Override Config7.RPS bit for CPU4/VPE1
config7RPS_CPU4_VPE2	Boolean	Override Config7.RPS bit for CPU4/VPE2
config7RPS_CPU4_VPE3	Boolean	Override Config7.RPS bit for CPU4/VPE3
config7RPS_CPU5_VPE0	Boolean	Override Config7.RPS bit for CPU5/VPE0
config7RPS_CPU5_VPE1	Boolean	Override Config7.RPS bit for CPU5/VPE1
config7RPS_CPU5_VPE2	Boolean	Override Config7.RPS bit for CPU5/VPE2
config7RPS_CPU5_VPE3	Boolean	Override Config7.RPS bit for CPU5/VPE3
config7RPS_CPU6_VPE0	Boolean	Override Config7.RPS bit for CPU6/VPE0
config7RPS_CPU6_VPE1	Boolean	Override Config7.RPS bit for CPU6/VPE1
config7RPS_CPU6_VPE2	Boolean	Override Config7.RPS bit for CPU6/VPE2
config7RPS_CPU6_VPE3	Boolean	Override Config7.RPS bit for CPU6/VPE3
config7RPS_CPU7_VPE0	Boolean	Override Config7.RPS bit for CPU7/VPE0
config7RPS_CPU7_VPE1	Boolean	Override Config7.RPS bit for CPU7/VPE1
config7RPS_CPU7_VPE2	Boolean	Override Config7.RPS bit for CPU7/VPE2
config7RPS_CPU7_VPE3	Boolean	Override Config7.RPS bit for CPU7/VPE3
statusFR	Boolean	Override power on value in Status.FR (Floating point register mode)
fcsrABS2008	Boolean	Override FCSR.ABS2008 (ABS/NEG compliant with IEEE 754-2008)
fcsrNaN2008	Boolean	Override FCSR.NAN2008 (QNaN/SNaN encodings match IEEE 754-2008 recommendation)
numMaarRegs	Uns32	Override number of MAAR registers (must be even)
srsconf0SRS1	Uns32	Override the SRS1 field in SRSCnf0 register

srsconf0SRS2	Uns32	Override the SRS2 field in SRSCnf0 register
srsconf0SRS3	Uns32	Override the SRS3 field in SRSCnf0 register
wiredLimit	Uns32	Override Limit field of the Wired register
wiredLimitBits	Uns32	Override width of Limit field of the Wired register
wiredWiredBits	Uns32	Override width of Wired field of the Wired register
cdmmBaseCI	Boolean	Override CDMMBase.CI
parityEnable	Uns32	Specify error detection support: 0 - none; 1 - parity; 2 - ECC
useMpTb	Boolean	Override Use of multi-processor test bench
ExceptionBase	Uns32	Specify the BEV Exception Base address. (use GCR_Cx_RESET_BASE on CMP processors)
UseExceptionBase	Boolean	Set to one to use ExceptionBase[29:12] as the corresponding BEV address bits
l1BufferCache	Boolean	L1 Buffer Cache
GCU_EX	Boolean	CMP system only: GCR custom block present
GIC_EX	Boolean	CMP system only: GIC unit present
CPC_EX	Boolean	CMP system only: CPC unit present
TIMER_ROUTABLE	Boolean	CMP system only: cpu timer interrupt routable within cluster
SWINT_ROUTABLE	Boolean	CMP system only: software interrupt routable within cluster
PERFCNT_ROUTABLE	Boolean	CMP system only: performance counter interrupt routable within cluster
FDC_ROUTABLE	Boolean	CMP system only: fast debug channel interrupt routable within cluster
GCR_PCORES	Uns32	CMP system only: override GCR_CONFIG.PCORES (number of cores-1)
GCR_ADDR_REGIONS	Uns32	CMP system only: override GCR_CONFIG.ADDR_REGIONS (number of MMIO address regions)
GCR_NUMAUX	Uns32	CMP system only: override GCR_CONFIG.NUMAUX (number of auxiliary memory ports)
GCR_BASE	Uns64	CMP system only: override GCR_BASE.GCR_BASE (default GCR register address)
GCR_MINOR_REV	Uns32	CMP system only: override GCR_REV.MINOR_REV
GCR_MAJOR_REV	Uns32	CMP system only: override GCR_REV.MAJOR_REV
GCR_CACHE_MINOR_REV	Uns32	CMP system only: override GCR_CACHE_REV.MINOR_REV
GCR_CACHE_MAJOR_REV	Uns32	CMP system only: override GCR_CACHE_REV.MAJOR_REV
GCR_L2_ASSOC	Uns32	CMP system only: override GCR_L2_CONFIG.ASSOC
GCR_L2_SET_SIZE	Uns32	CMP system only: override GCR_L2_CONFIG.SET_SIZE
GCR_SYS_CONFIG2_MAX_VP_WIDTH	Uns32	CMP system only: override GCR_SYS_CONFIG2.MAX_VP_WIDTH
GCR_IOCUI1_MINOR_REV	Uns32	CMP system only: override GCR_IOCUI1_REV.MINOR_REV
GCR_IOCUI1_MAJOR_REV	Uns32	CMP system only: override GCR_IOCUI1_REV.MAJOR_REV
GCR_BEV_BASE	Uns32	CMP system only: override GCR_BEV_BASE



GCR_KX_BASE_MODE	Boolean	CMP system only: override BEV_BASE_MODE & RESET_BASE_MODE
GCR_MMIO_REQ_LIMIT	Uns32	CMP system only: override GCR_MMIO_REQ_LIMIT.MMIO_REQ_LIMIT value
GCR_MMIO0_BOTTOM	Uns64	CMP system only: override GCR_MMIO0_BOTTOM register value
GCR_MMIO0_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO0_TOP.TOP_ADDR value
GCR_MMIO1_BOTTOM	Uns64	CMP system only: override GCR_MMIO1_BOTTOM register value
GCR_MMIO1_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO1_TOP.TOP_ADDR value
GCR_MMIO2_BOTTOM	Uns64	CMP system only: override GCR_MMIO2_BOTTOM register value
GCR_MMIO2_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO2_TOP.TOP_ADDR value
GCR_MMIO3_BOTTOM	Uns64	CMP system only: override GCR_MMIO3_BOTTOM register value
GCR_MMIO3_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO3_TOP.TOP_ADDR value
GIC_NUMINTERRUPTS	Uns32	CMP system only: override GIC_SH_CONFIG.NUMINTERRUPTS
GIC_COUNTBITS	Uns32	CMP system only: override GIC_SH_CONFIG.COUNTBITS
GIC_MINOR_REV	Uns32	CMP system only: override GIC_SH_REVISION.MINOR_REV
GIC_MAJOR_REV	Uns32	CMP system only: override GIC_SH_REVISION.MAJOR_REV
GIC_NUM_TEAMS	Uns32	CMP system only: override GIC_SH_DBG_CONFIG.NUM_TEAMS
GIC_TRIG_RESET	Uns32	CMP system only: Zero value of GIC_SH_TRIG_[31_0, 63_32]
GIC_PVPES	Uns32	CMP system only: override GIC_SH_CONFIG.PVPE
CPC_MICROSTEP	Uns32	CMP system only: override CPC_SEQDEL.MICROSTEP
CPC_RAILDELAY	Uns32	CMP system only: override CPC_RAIL.RAILDELAY
CPC_RESETLEN	Uns32	CMP system only: override CPC_RESETLEN.RESETLEN
CPC_MINOR_REV	Uns32	CMP system only: override CPC_REVISION.MINOR_REV
CPC_MAJOR_REV	Uns32	CMP system only: override CPC_REVISION.MAJOR_REV
GIC_SH_GID_CONFIG31_0	Uns32	CMP system only: override GIC_SH_GID_CONFIG[31_0]
GIC_SH_GID_CONFIG63_32	Uns32	CMP system only: override GIC_SH_GID_CONFIG[63_32]
GIC_SH_GID_CONFIG95_64	Uns32	CMP system only: override GIC_SH_GID_CONFIG[95_64]
GIC_SH_GID_CONFIG127_96	Uns32	CMP system only: override GIC_SH_GID_CONFIG[127_96]
GIC_SH_GID_CONFIG159_128	Uns32	CMP system only: override GIC_SH_GID_CONFIG[159_128]
GIC_SH_GID_CONFIG191_160	Uns32	CMP system only: override GIC_SH_GID_CONFIG[191_160]

GIC.SH.GID.CONFIG223_192	Uns32	CMP system only: override GIC.SH.GID.CONFIG[223_192]
GIC.SH.GID.CONFIG255_224	Uns32	CMP system only: override GIC.SH.GID.CONFIG[255_224]
GCR.C0.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 0
GCR.C1.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 1
GCR.C2.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 2
GCR.C3.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 3
GCR.C4.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 4
GCR.C5.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 5
GCR.C6.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 6
GCR.C7.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 7
GCR.C8.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 8
GCR.C9.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 9
GCR.C0.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 0
GCR.C1.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 1
GCR.C2.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 2
GCR.C3.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 3
GCR.C4.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 4
GCR.C5.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 5
GCR.C6.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 6
GCR.C7.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 7
GCR.C8.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 8
GCR.C9.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 9
CPC.C0.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 0
CPC.C1.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 1
CPC.C2.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 2
CPC.C3.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 3
CPC.C4.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 4
CPC.C5.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 5
CPC.C6.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 6
CPC.C7.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 7
CPC.C8.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 8
CPC.C9.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 9
EIC.OPTION	Uns32	Override the external interrupt controller EIC.OPTION

guestCtl0RI	Uns32	Override the RI field in GuestCtl0 register
guestCtl0MC	Uns32	Override the MC field in GuestCtl0 register
guestCtl0CP0	Uns32	Override the CP0 field in GuestCtl0 register
guestCtl0AT	Uns32	Override the AT field in GuestCtl0 register
guestCtl0GT	Uns32	Override the GT field in GuestCtl0 register
guestCtl0CG	Uns32	Override the CG field in GuestCtl0 register
guestCtl0CF	Uns32	Override the CF field in GuestCtl0 register
guestCtl0G1	Uns32	Override the G1 field in GuestCtl0 register
guestCtl0RAD	Uns32	Override the RAD field in GuestCtl0 register
guestCtl0DRG	Uns32	Override the DRG field in GuestCtl0 register
hasImpl17	Boolean	Enable read/write of Impl17 bit in Status register
hasImpl16	Boolean	Enable read/write of Impl16 bit in Status register
guestIntctlIPTI	Uns32	Override the Guest IPTI field in IntCtl register
guestIntctlIPFDC	Uns32	Override the Guest IPFDC field in IntCtl register
guestIntctlIPPCI	Uns32	Override the Guest IPPCI field in IntCtl register
ISPRAM_SIZE	Uns32	Encoded size of the ISPRAM region ( $\log_2(\langle \text{ISPRAM size in bytes} \rangle) - 11$ )
ISPRAM_BASE	Uns64	Starting physical address of the ISPRAM region
ISPRAM_ENABLE	Boolean	Set the enable bit of the ISPRAM region's tag (used to enable the ISPRAM region prior to reset)
ISPRAM_FILE	String	Load a MIPS hex file into the ISPRAM region prior to reset
DSPRAM_SIZE	Uns32	Encoded size of the DSPRAM region ( $\log_2(\langle \text{DSPRAM size in bytes} \rangle) - 11$ )
DSPRAM_BASE	Uns64	Starting physical address of the DSPRAM region
DSPRAM_ENABLE	Boolean	Set the enable bit of the DSPRAM region's tag (used to enable the DSPRAM region prior to reset)
DSPRAM_PRESENT	Boolean	DSPRAM is present with SAAR
USPRAM_SIZE	Uns32	Encoded size of the USPRAM region ( $\log_2(\langle \text{USPRAM size in bytes} \rangle) - 11$ )
USPRAM_BASE	Uns64	Starting physical address of the USPRAM region
USPRAM_ENABLE	Boolean	Set the enable bit of the USPRAM region's tag (used to enable the USPRAM region prior to reset)
USPRAM_FILE	String	Load a MIPS hex file into the USPRAM region prior to reset
misalignedDataException	Enumeration	Select misaligned data access exception signaling: never, checkCCA or always (never, checkCCA or always)
commitTlbwErr	Boolean	Commit TLBWI/TLBRI on ECC; in MIPS_DV_MODE only

Table 8.1: Parameters that can be set in: CMP

## 8.1 Parameter values

These are the current parameter values.

Name	Value
<b>(Others)</b>	
variant	P6600
endian	none
cacheenable	default

cachedebug	0
cacheextbiuinfo	0x0
mipsHexFile	
IMPERAS_MIPS_AVP_OPCODES	F
cacheIndexBypassTLB	F
MIPS_TRACE	F
gprNames	F
supervisorMode	F
busErrors	T
fixedMMU	F
fixedDbgRegSize	F
removeDSP	F
removeCMP	F
removeFP	F
removeFTLB	F
isISA	F
hiddenTLBentries	F
perfCounters	0
MTFPU	0
supportDenormals	F
VPE0MaxTC	0
VPE1MaxTC	0
segBits	0
mpuRegions	0
mpuType	0
mpuEnable	F
mpuSegment0	0
mpuSegment1	0
mpuSegment2	0
mpuSegment3	0
mpuSegment4	0
mpuSegment5	0
mpuSegment6	0
mpuSegment7	0
mpuSegment8	0
mpuSegment9	0
mpuSegment10	0
mpuSegment11	0
mpuSegment12	0
mpuSegment13	0
mpuSegment14	0
mpuSegment15	0
mvpcnf0vpe	0
tcDisable	0
vpeDisable	0

mvpconf0tc	0
mvpconf0pcp	F
mvpconf0tcp	F
mvpconf1c1f	F
mvpcontrolPolicyMode	F
hasFDC	0
licenseWarningDays	15
MIPS_UHI	F
mipsUhiArgs	
mipsUhiJail	
MIPS_DV_MODE	F
MIPS_MAGIC_OPCODES	F
enableTrickbox	F
fpuexcdisable	F
TRU_PRESENT	F
ucLLwordsLocked	0
FUSA	F
CPC_FAULT_SUPPORTED	0
CPC_FAULT_ENABLE	0
cop2Bits	32
cop2FileName	
udiConfig	0
udiFileName	
vectoredinterrupt	F
externalinterrupt	F
rootFixedMMU	F
rootMMUSizeM1	0
srscctlHSS	0
firPS	0
firHas2008	0
usePreciseFpu	0
simulateLite	NONE
pridCompanyOptions	0
pridRevision	0
globalClusterNum	0
intctlIPTI	0
intctlIPFDC	0
intctlIPPCI	0
numWatch	0
xconfigSpecified	F
segcfg0PA	0
segcfg1PA	0
segcfg2PA	0
segcfg3PA	0
segcfg4PA	0

segcfg5PA	0
segcfg0AM	0
segcfg1AM	0
segcfg2AM	0
segcfg3AM	0
segcfg4AM	0
segcfg5AM	0
segcfg0EU	0
segcfg1EU	0
segcfg2EU	0
segcfg3EU	0
segcfg4EU	0
segcfg5EU	0
segcfg0C	0
segcfg1C	0
segcfg2C	0
segcfg3C	0
segcfg4C	0
segcfg5C	0
cdmmSize	0
configAR	0
configBM	0
configDSP	F
configISP	F
configK0	0
configKU	0
configK23	0
configMDU	F
configMM	F
configMT	0
configSB	F
configBCP	F
MIPS16eASE	F
config1DA	0
config1DL	0
config1DS	0
config1EP	F
config1IA	0
config1IL	0
config1IS	0
config1MMUSizeM1	0
config1MMUSizeM1_VPE1	0
config1MMUSizeM1_VPE2	0
config1MMUSizeM1_VPE3	0
config1WR	F

config1PC	F
config1C2	F
config2SU	0
config2SS	0
config2SL	0
config2SA	0
config3BI	F
config3BP	F
config3CDMM	F
config3CTXTC	F
config3DSPP	F
config3DSP2P	F
config3IPLW	0
config3ISA	0
config3ISAOnExc	F
config3ITL	F
config3LPA	F
config3MCU	F
config3MMAR	0
config3RXI	F
config3SC	F
config3ULRI	F
config3VZ	F
config3MSAP	F
config3CMGCR	F
config3SP	F
config3TL	0
config3PW	F
config4AE	F
config4IE	0
config4MMUConfig	0
config4MMUExtDef	0
config4VTLBSizeExt	0
config4KScrExist	0
config5EVA	F
config5LLB	F
config5MRP	F
config5NFExists	F
mips32Macro	F
config5MSAEn	F
config5MVH	F
config5DEC	F
config5GI	0
config5CRCP	F
config5VP	F

config6FTLBEEn	F
config7AR	F
config7DCIDX_MODE	0
config7HCI	F
config7IAR	F
config7WII	F
config7ES	0
config7WR	F
config7FPR	F
config7USP	0
config7BTLM	F
config7BusSlp	F
config7IVAD	F
config7RPS	F
config7IAR_CPU0_VPE0	F
config7IAR_CPU0_VPE1	F
config7IAR_CPU0_VPE2	F
config7IAR_CPU0_VPE3	F
config7IAR_CPU1_VPE0	F
config7IAR_CPU1_VPE1	F
config7IAR_CPU1_VPE2	F
config7IAR_CPU1_VPE3	F
config7IAR_CPU2_VPE0	F
config7IAR_CPU2_VPE1	F
config7IAR_CPU2_VPE2	F
config7IAR_CPU2_VPE3	F
config7IAR_CPU3_VPE0	F
config7IAR_CPU3_VPE1	F
config7IAR_CPU3_VPE2	F
config7IAR_CPU3_VPE3	F
config7IAR_CPU4_VPE0	F
config7IAR_CPU4_VPE1	F
config7IAR_CPU4_VPE2	F
config7IAR_CPU4_VPE3	F
config7IAR_CPU5_VPE0	F
config7IAR_CPU5_VPE1	F
config7IAR_CPU5_VPE2	F
config7IAR_CPU5_VPE3	F
config7IAR_CPU6_VPE0	F
config7IAR_CPU6_VPE1	F
config7IAR_CPU6_VPE2	F
config7IAR_CPU6_VPE3	F
config7IAR_CPU7_VPE0	F
config7IAR_CPU7_VPE1	F
config7IAR_CPU7_VPE2	F



config7IAR_CPU7_VPE3	F
config7IVAD_CPU0_VPE0	F
config7IVAD_CPU0_VPE1	F
config7IVAD_CPU0_VPE2	F
config7IVAD_CPU0_VPE3	F
config7IVAD_CPU1_VPE0	F
config7IVAD_CPU1_VPE1	F
config7IVAD_CPU1_VPE2	F
config7IVAD_CPU1_VPE3	F
config7IVAD_CPU2_VPE0	F
config7IVAD_CPU2_VPE1	F
config7IVAD_CPU2_VPE2	F
config7IVAD_CPU2_VPE3	F
config7IVAD_CPU3_VPE0	F
config7IVAD_CPU3_VPE1	F
config7IVAD_CPU3_VPE2	F
config7IVAD_CPU3_VPE3	F
config7IVAD_CPU4_VPE0	F
config7IVAD_CPU4_VPE1	F
config7IVAD_CPU4_VPE2	F
config7IVAD_CPU4_VPE3	F
config7IVAD_CPU5_VPE0	F
config7IVAD_CPU5_VPE1	F
config7IVAD_CPU5_VPE2	F
config7IVAD_CPU5_VPE3	F
config7IVAD_CPU6_VPE0	F
config7IVAD_CPU6_VPE1	F
config7IVAD_CPU6_VPE2	F
config7IVAD_CPU6_VPE3	F
config7IVAD_CPU7_VPE0	F
config7IVAD_CPU7_VPE1	F
config7IVAD_CPU7_VPE2	F
config7IVAD_CPU7_VPE3	F
config7RPS_CPU0_VPE0	F
config7RPS_CPU0_VPE1	F
config7RPS_CPU0_VPE2	F
config7RPS_CPU0_VPE3	F
config7RPS_CPU1_VPE0	F
config7RPS_CPU1_VPE1	F
config7RPS_CPU1_VPE2	F
config7RPS_CPU1_VPE3	F
config7RPS_CPU2_VPE0	F
config7RPS_CPU2_VPE1	F
config7RPS_CPU2_VPE2	F
config7RPS_CPU2_VPE3	F

config7RPS_CPU3_VPE0	F
config7RPS_CPU3_VPE1	F
config7RPS_CPU3_VPE2	F
config7RPS_CPU3_VPE3	F
config7RPS_CPU4_VPE0	F
config7RPS_CPU4_VPE1	F
config7RPS_CPU4_VPE2	F
config7RPS_CPU4_VPE3	F
config7RPS_CPU5_VPE0	F
config7RPS_CPU5_VPE1	F
config7RPS_CPU5_VPE2	F
config7RPS_CPU5_VPE3	F
config7RPS_CPU6_VPE0	F
config7RPS_CPU6_VPE1	F
config7RPS_CPU6_VPE2	F
config7RPS_CPU6_VPE3	F
config7RPS_CPU7_VPE0	F
config7RPS_CPU7_VPE1	F
config7RPS_CPU7_VPE2	F
config7RPS_CPU7_VPE3	F
statusFR	F
fcsrABS2008	F
fcsrNAN2008	F
numMaarRegs	6
srsconf0SRS1	0
srsconf0SRS2	0
srsconf0SRS3	0
wiredLimit	0
wiredLimitBits	0
wiredWiredBits	0
cdmmBaseCI	F
parityEnable	1
useMpTb	T
ExceptionBase	0
UseExceptionBase	F
l1BufferCache	F
GCU_EX	F
GIC_EX	F
CPC_EX	F
TIMER_ROUTABLE	F
SWINT_ROUTABLE	F
PERFCNT_ROUTABLE	F
FDC_ROUTABLE	F
GCR_PCORES	0
GCR_ADDR_REGIONS	0

GCR_NUMAUX	0
GCR_BASE	0
GCR_MINOR_REV	0
GCR_MAJOR_REV	0
GCR_CACHE_MINOR_REV	0
GCR_CACHE_MAJOR_REV	0
GCR_L2_ASSOC	0
GCR_L2_SET_SIZE	0
GCR_SYS_CONFIG2_MAX_VP_WIDTH	0
GCR_IOCU1_MINOR_REV	0
GCR_IOCU1_MAJOR_REV	0
GCR_BEV_BASE	0
GCR_KX_BASE_MODE	F
GCR_MMIO_REQ_LIMIT	0
GCR_MMIO0_BOTTOM	0
GCR_MMIO0_TOP_ADDR	0
GCR_MMIO1_BOTTOM	0
GCR_MMIO1_TOP_ADDR	0
GCR_MMIO2_BOTTOM	0
GCR_MMIO2_TOP_ADDR	0
GCR_MMIO3_BOTTOM	0
GCR_MMIO3_TOP_ADDR	0
GIC_NUMINTERRUPTS	0
GIC_COUNTBITS	0
GIC_MINOR_REV	0
GIC_MAJOR_REV	0
GIC_NUM_TEAMS	7
GIC_TRIG_RESET	0
GIC_PVPES	0
CPC_MICROSTEP	0
CPC_RAILDELAY	0
CPC_RESETLEN	0
CPC_MINOR_REV	0
CPC_MAJOR_REV	0
GIC_SH_GID_CONFIG31_0	0
GIC_SH_GID_CONFIG63_32	0
GIC_SH_GID_CONFIG95_64	0
GIC_SH_GID_CONFIG127_96	0
GIC_SH_GID_CONFIG159_128	0
GIC_SH_GID_CONFIG191_160	0
GIC_SH_GID_CONFIG223_192	0
GIC_SH_GID_CONFIG255_224	0
GCR_C0_RESET_BASE	0
GCR_C1_RESET_BASE	0
GCR_C2_RESET_BASE	0

GCR_C3_RESET_BASE	0
GCR_C4_RESET_BASE	0
GCR_C5_RESET_BASE	0
GCR_C6_RESET_BASE	0
GCR_C7_RESET_BASE	0
GCR_C8_RESET_BASE	0
GCR_C9_RESET_BASE	0
GCR_C0_RESET_EXT_BASE	0
GCR_C1_RESET_EXT_BASE	0
GCR_C2_RESET_EXT_BASE	0
GCR_C3_RESET_EXT_BASE	0
GCR_C4_RESET_EXT_BASE	0
GCR_C5_RESET_EXT_BASE	0
GCR_C6_RESET_EXT_BASE	0
GCR_C7_RESET_EXT_BASE	0
GCR_C8_RESET_EXT_BASE	0
GCR_C9_RESET_EXT_BASE	0
CPC_C0_VP_EN	0
CPC_C1_VP_EN	0
CPC_C2_VP_EN	0
CPC_C3_VP_EN	0
CPC_C4_VP_EN	0
CPC_C5_VP_EN	0
CPC_C6_VP_EN	0
CPC_C7_VP_EN	0
CPC_C8_VP_EN	0
CPC_C9_VP_EN	0
EIC_OPTION	2
guestCtl0RI	0
guestCtl0MC	0
guestCtl0CP0	0
guestCtl0AT	0
guestCtl0GT	0
guestCtl0CG	0
guestCtl0CF	0
guestCtl0G1	0
guestCtl0RAD	0
guestCtl0DRG	0
hasImpl17	F
hasImpl16	F
guestintctlIPTI	0
guestintctlIPFDC	0
guestintctlIPPCI	0
ISPRAM_SIZE	0
ISPRAM_BASE	0

ISPRAM_ENABLE	F
ISPRAM_FILE	
DSPRAM_SIZE	0
DSPRAM_BASE	0
DSPRAM_ENABLE	F
DSPRAM_PRESENT	F
USPRAM_SIZE	0
USPRAM_BASE	0
USPRAM_ENABLE	F
USPRAM_FILE	
misalignedDataException	never
commitTlbwErr	F

Table 8.2: Parameter values

Name	Type	Description
endian	Endian	Model endian
cacheenable	Enumeration	Select cache model mode (default, tag or full)
cachedebug	Uns32	Cache debug flags
cacheextbiuinfo	Pointer	Pointer to platform-provided BIU cache info structure
mipsHexFile	String	Load a MIPS hex file (test-mode)
IMPERAS_MIPS_AVP_OPCODES	Boolean	Enable MIPS-specific magic Pass/Fail opcodes (specific for AVP test termination)
cacheIndexBypassTLB	Boolean	When set, cache index ops do not generate TLB exceptions
MIPS_TRACE	Boolean	Enable MIPS-format trace output
gprNames	Boolean	Disassemble the register names from the default ABI instead of register numbers for MIPS-format trace output
supervisorMode	Boolean	Override whether processor implements supervisor mode
busErrors	Boolean	Override bus error exception behavior. When true, accesses of memory not defined by platform will cause bus error exceptions
fixedMMU	Boolean	Override the MMU type to fixed mapping when true (sets Config.MT=3, Config.KU/K23=2 and Config1.MMUSizeM1=0)
fixedDbgRegSize	Boolean	Enable applications to debug on P5600 with GDB version 2015.06-05 and prior
removeDSP	Boolean	Override the DSP-present configuration when true (sets Config3.DSPP/DSP2P=0)
removeCMP	Boolean	Override the CMP-Present configuration when true (sets Config3.CMGCR and GCR_BASE to 0)
removeFP	Boolean	Override the FP-Present configuration when true (sets Config1.FP to 0)
removeFTLB	Boolean	Override the FTLBEn configuration when true (disable FTLB)
isISA	Boolean	Enable to specify ISA model (reset address from ELF, all coprocessors enabled)
hiddenTLBentries	Boolean	Deprecated - Instead set config1MMUSizeM1 to maximum value to improve performance
perfCounters	Uns32	Performance Counters

MTFPU	Uns32	Enable multi-threaded FPU (1:old mttc1 behavior, 2:new mttc1 behavior)
supportDenormals	Boolean	Enable to specify that the FPU supports denormal operands and results
VPE0MaxTC	Uns32	Specifies the maximum TCs initially on VPE0. Ignored if less than two VPEs configured.
VPE1MaxTC	Uns32	Specifies the maximum TCs initially on VPE1. Ignored if less than three VPEs configured.
segBits	Uns32	Override the number of address bits implemented for 64 bit segments (MIPS64 Only)
mpuRegions	Uns32	Number of regions for memory protection unit
mpuType	Uns32	Type of MPU implementation
mpuEnable	Boolean	Enable MPU2 segment control at reset
mpuSegment0	Uns32	Attributes for segment 0 in MPU2 SegmentControl_0 register
mpuSegment1	Uns32	Attributes for segment 1 in MPU2 SegmentControl_0 register
mpuSegment2	Uns32	Attributes for segment 2 in MPU2 SegmentControl_0 register
mpuSegment3	Uns32	Attributes for segment 3 in MPU2 SegmentControl_0 register
mpuSegment4	Uns32	Attributes for segment 4 in MPU2 SegmentControl_1 register
mpuSegment5	Uns32	Attributes for segment 5 in MPU2 SegmentControl_1 register
mpuSegment6	Uns32	Attributes for segment 6 in MPU2 SegmentControl_1 register
mpuSegment7	Uns32	Attributes for segment 7 in MPU2 SegmentControl_1 register
mpuSegment8	Uns32	Attributes for segment 8 in MPU2 SegmentControl_2 register
mpuSegment9	Uns32	Attributes for segment 9 in MPU2 SegmentControl_2 register
mpuSegment10	Uns32	Attributes for segment 10 in MPU2 SegmentControl_2 register
mpuSegment11	Uns32	Attributes for segment 11 in MPU2 SegmentControl_2 register
mpuSegment12	Uns32	Attributes for segment 12 in MPU2 SegmentControl_3 register
mpuSegment13	Uns32	Attributes for segment 13 in MPU2 SegmentControl_3 register
mpuSegment14	Uns32	Attributes for segment 14 in MPU2 SegmentControl_3 register
mpuSegment15	Uns32	Attributes for segment 15 in MPU2 SegmentControl_3 register
mvpconf0vpe	Uns32	Override MVPConf0.PVPE
tcDisable	Uns32	Number of disabled TCs
vpeDisable	Uns32	Number of disabled VPEs
mvpconf0tc	Uns32	Override MVPConf0.PTC
mvpconf0pcp	Boolean	Override MVPConf0.PCP
mvpconf0tcp	Boolean	Override MVPConf0.TCP
mvpconf1c1f	Boolean	Override MVPConf.C1F
mvpcontrolPolicyMode	Boolean	Override MVPControl.POLICY_MODE
hasFDC	Uns32	Specify the size of Fast Debug Channel register block

licenseWarningDays	Uns32	Specify the number of days before a license expires to start issuing a warning. 0 disables warnings.
MIPS_UHI	Boolean	Enable MIPS-Unified Hosting interface
mipsUhiArgs	String	Specifies UHI arguments string separated by spaces
mipsUhiJail	String	Specifies UHI jailroot
MIPS_DV_MODE	Boolean	Enable Design Verification mode
MIPS_MAGIC_OPCODES	Boolean	Enable MIPS-specific magic Pass/Fail opcodes
enableTrickbox	Boolean	Enable trickbox addresses (specific for AVP)
fpuexcdisable	Boolean	Disable FPU exceptions
TRU_PRESENT	Boolean	Disable or Enable based on TRU presence to control certain fields (e.x.perfCtl.PCTD
ucLLwordsLocked	Uns32	Numbers of words (4 byte) an uncached LL is locking. Maximum: 4K
FUSA	Boolean	Enable Functional Safety
CPC_FAULT_SUPPORTED	Uns32	Specify the value for Functional Safety Supported register
CPC_FAULT_ENABLE	Uns32	Specify the value for Functional Safety Enable register
cop2Bits	Uns32	Specifies width in bits of COP2 registers (32 or 64)
cop2FileName	String	Specifies COP2 dynamically-loaded object (.so/.dll) defining COP2 instructions
udiConfig	Int32	Specifies UDI configuration attribute
udiFileName	String	Specifies UDI dynamically-loaded object (.so/.dll) defining UDI instructions
vectoredinterrupt	Boolean	Enables vectored interrupts (sets Config3 VInt)
externalinterrupt	Boolean	Enables the use of an external interrupt controller (sets Config3 VEIC)
rootFixedMMU	Boolean	Override the root MMU type to fixed mapping when true (sets Config.MT=3 and Config.KU/K23=2)
rootMMUSizeM1	Uns32	Override the root MMUSizeM1 field in Config1 register (number of MMU entries-1)
srsctlHSS	Uns32	Override the HSS field in SRSCtl register (number of shadow register sets)
firPS	Uns32	Override the PS field in FIR register
firHas2008	Uns32	Override the Has2008 field in FIR register
usePreciseFpu	Uns32	Use the precise Floating Point emulation
simulateLite	Enumeration	Run Simulation with optimization. There are several optimizations which could be combined (NONE, FS, MA or FSMA)
pridCompanyOptions	Uns32	Override the Company Options field in PRId register
pridRevision	Uns32	Override the Revision field in PRId register
globalClusterNum	Uns32	Override the ClusterNum field in GlobalNumber register
intctlIPTI	Uns32	Override the IPTI field in IntCtl register
intctlIPFDC	Uns32	Override the IPFDC field in IntCtl register
intctlIPPCI	Uns32	Override the IPPCI field in IntCtl register
numWatch	Uns32	Specify number of WatchLo/WatchHi register pairs
xconfigSpecified	Boolean	True if the configuration comes from a valid xconfig file
segcfg0PA	Uns32	Set CFG0.PA field of SegCtl0 register
segcfg1PA	Uns32	Set CFG1.PA field of SegCtl0 register
segcfg2PA	Uns32	Set CFG2.PA field of SegCtl1 register
segcfg3PA	Uns32	Set CFG3.PA field of SegCtl1 register
segcfg4PA	Uns32	Set CFG4.PA field of SegCtl2 register

segcfg5PA	Uns32	Set CFG5.PA field of SegCtl2 register
segcfg0AM	Uns32	Set CFG0.AM field of SegCtl0 register
segcfg1AM	Uns32	Set CFG1.AM field of SegCtl0 register
segcfg2AM	Uns32	Set CFG2.AM field of SegCtl1 register
segcfg3AM	Uns32	Set CFG3.AM field of SegCtl1 register
segcfg4AM	Uns32	Set CFG4.AM field of SegCtl2 register
segcfg5AM	Uns32	Set CFG5.AM field of SegCtl2 register
segcfg0EU	Uns32	Set CFG0.EU field of SegCtl0 register
segcfg1EU	Uns32	Set CFG1.EU field of SegCtl0 register
segcfg2EU	Uns32	Set CFG2.EU field of SegCtl1 register
segcfg3EU	Uns32	Set CFG3.EU field of SegCtl1 register
segcfg4EU	Uns32	Set CFG4.EU field of SegCtl2 register
segcfg5EU	Uns32	Set CFG5.EU field of SegCtl2 register
segcfg0C	Uns32	Set CFG0.C field of SegCtl0 register
segcfg1C	Uns32	Set CFG1.C field of SegCtl0 register
segcfg2C	Uns32	Set CFG2.C field of SegCtl1 register
segcfg3C	Uns32	Set CFG3.C field of SegCtl1 register
segcfg4C	Uns32	Set CFG4.C field of SegCtl2 register
segcfg5C	Uns32	Set CFG5.C field of SegCtl2 register
cdmmSize	Uns32	Override the cdmmSize reset value
configAR	Uns32	Enables R6 support
configBM	Uns32	Override the BM field in Config register (burst mode)
configDSP	Boolean	Override Config.DSP (data scratchpad RAM present)
configISP	Boolean	Override Config.ISP (instruction scratchpad RAM present)
configK0	Uns32	Override power on value of Config.K0 (set Kseg0 cacheability)
configKU	Uns32	Override power on value of Config.KU (set Useg cacheability)
configK23	Uns32	Override power on value of Config.K23 (set Kseg23 cacheability)
configMDU	Boolean	Override Config.MDU (iterative multiply/divide unit)
configMM	Boolean	Override Config.MM (merging mode for write)
configMT	Uns32	Override Config.MT
configSB	Boolean	Override Config.SB (simple bus transfers only)
configBCP	Boolean	Override Config.BCP (Buffer Cache Present)
MIPS16eASE	Boolean	Override Config1.CA (enables the MIPS16e ASE)
config1DA	Uns32	Override Config1.DA (Dcache associativity)
config1DL	Uns32	Override Config1.DL (Dcache line size)
config1DS	Uns32	Override Config1.DS (Dcache sets per way)
config1EP	Boolean	Override Config1.EP (EJTag present)
config1IA	Uns32	Override Config1.IA (Icache associativity)
config1IL	Uns32	Override Config1.IL (Icache line size)
config1IS	Uns32	Override Config1.IS (Icache sets per way)
config1MMUSizeM1	Uns32	Override Config1.MMUSizeM1 (number of MMU entries-1)
config1MMUSizeM1_VPE1	Uns32	Override Config1.MMUSizeM1 for VPE1
config1MMUSizeM1_VPE2	Uns32	Override Config1.MMUSizeM1 for VPE2
config1MMUSizeM1_VPE3	Uns32	Override Config1.MMUSizeM1 for VPE3
config1WR	Boolean	Override Config1.WR (watchpoint registers present)
config1PC	Boolean	Override Config1.PC (Performance Counters present)



config1C2	Boolean	Override Config1.C2 (Coprocessor 2 present)
config2SU	Uns32	Override the SU field in Config2 register
config2SS	Uns32	Override the SS field in Config2 register
config2SL	Uns32	Override the SL field in Config2 register
config2SA	Uns32	Override the SA field in Config2 register
config3BI	Boolean	Override Config3.BI
config3BP	Boolean	Override Config3.BP
config3CDMM	Boolean	Override Config3.CDMM
config3CTXTC	Boolean	Override Config3.CTXTC
config3DSPP	Boolean	Override Config3.DSPP
config3DSP2P	Boolean	Override Config3.DSP2P
config3IPLW	Uns32	Override Config3.IPLW
config3ISA	Uns32	Override Config3.ISA
config3ISAOnExc	Boolean	Override Config3.ISAOnExc
config3ITL	Boolean	Override Config3.ITL
config3LPA	Boolean	Override Config3.LPA
config3MCU	Boolean	Override Config3.MCU
config3MMAR	Uns32	Override Config3.MMAR
config3RXI	Boolean	Override Config3.RXI
config3SC	Boolean	Override Config3.SC
config3ULRI	Boolean	Override Config3.ULRI
config3VZ	Boolean	Override Config3.VZ
config3MSAP	Boolean	Override Config3.MSAP
config3CMGCR	Boolean	Override the CMGCR field in Config3 register
config3SP	Boolean	Override the SP field in Config3 register
config3TL	Uns32	Override the TL field in Config3 register
config3PW	Boolean	Override the PW field in Config3 register
config4AE	Boolean	Override Config4.AE
config4IE	Uns32	Override Config4.IE
config4MMUConfig	Uns32	Override Config4.MMUConfig field (interpretation depends on MMUExtDef value)
config4MMUExtDef	Uns32	Override Config4.MMUExtDef
config4VTLBSizeExt	Uns32	Override Config4.VTLBSizeExt
config4KScrExist	Uns32	Override Config4.KScrExist
config5EVA	Boolean	Override Config5.EVA
config5LLB	Boolean	Override Config5.LLB (LLAddr supports LLbit)
config5MRP	Boolean	Override Config5.MRP (Maar Present)
config5NFExists	Boolean	Override Config5.NFExists
mips32Macro	Boolean	Enables the MIPS32 SAVE and RESTORE macro instructions. Ignored if Config5.CA2 is not set)
config5MSAEn	Boolean	Override Config5.MSAEn
config5MVH	Boolean	Override Config5.MVH (enable MTHC0 and MFHC0 instructions)
config5DEC	Boolean	Override Config5.DEC (to test Dual Endian Capability)
config5GI	Uns32	Override Config5.GI (enable GINV)
config5CRCP	Boolean	Override Config5.CRCP (CRCP Present)
config5VP	Boolean	Override Config5.VP
config6FTLBEEn	Boolean	Override power on value of Config6.FTLBEEn
config7AR	Boolean	Override Config7.AR (Alias removed Data cache)
config7DCIDX_MODE	Uns32	Override Config7.DCIDX_MODE
config7HCI	Boolean	Override Config7.HCI (Hardware Cache Initialization)
config7IAR	Boolean	Override Config7.IAR (Alias removed Instruction cache)
config7WII	Boolean	Override Config7.WII (wait IE/IXMT ignore)

config7ES	Uns32	Override the ES field in Config7 register (Externalize sync)
config7WR	Boolean	Override Config7[31] bit (Alternative implementation of Watch registers)
config7FPR	Boolean	Override Config7.FPR (one-half FPU clock ratio)
config7USP	Uns32	Override Config7.USP (USPRAM enable)
config7BTLM	Boolean	Override Config7.BTLM bit
config7BusSlp	Boolean	Override Config7.BusSlp bit
config7IVAD	Boolean	Override Config7.IVAD bit
config7RPS	Boolean	Override Config7.RPS bit
config7IAR_CPU0_VPE0	Boolean	Override Config7.IAR bit for CPU0/VPE0
config7IAR_CPU0_VPE1	Boolean	Override Config7.IAR bit for CPU0/VPE1
config7IAR_CPU0_VPE2	Boolean	Override Config7.IAR bit for CPU0/VPE2
config7IAR_CPU0_VPE3	Boolean	Override Config7.IAR bit for CPU0/VPE3
config7IAR_CPU1_VPE0	Boolean	Override Config7.IAR bit for CPU1/VPE0
config7IAR_CPU1_VPE1	Boolean	Override Config7.IAR bit for CPU1/VPE1
config7IAR_CPU1_VPE2	Boolean	Override Config7.IAR bit for CPU1/VPE2
config7IAR_CPU1_VPE3	Boolean	Override Config7.IAR bit for CPU1/VPE3
config7IAR_CPU2_VPE0	Boolean	Override Config7.IAR bit for CPU2/VPE0
config7IAR_CPU2_VPE1	Boolean	Override Config7.IAR bit for CPU2/VPE1
config7IAR_CPU2_VPE2	Boolean	Override Config7.IAR bit for CPU2/VPE2
config7IAR_CPU2_VPE3	Boolean	Override Config7.IAR bit for CPU2/VPE3
config7IAR_CPU3_VPE0	Boolean	Override Config7.IAR bit for CPU3/VPE0
config7IAR_CPU3_VPE1	Boolean	Override Config7.IAR bit for CPU3/VPE1
config7IAR_CPU3_VPE2	Boolean	Override Config7.IAR bit for CPU3/VPE2
config7IAR_CPU3_VPE3	Boolean	Override Config7.IAR bit for CPU3/VPE3
config7IAR_CPU4_VPE0	Boolean	Override Config7.IAR bit for CPU4/VPE0
config7IAR_CPU4_VPE1	Boolean	Override Config7.IAR bit for CPU4/VPE1
config7IAR_CPU4_VPE2	Boolean	Override Config7.IAR bit for CPU4/VPE2
config7IAR_CPU4_VPE3	Boolean	Override Config7.IAR bit for CPU4/VPE3
config7IAR_CPU5_VPE0	Boolean	Override Config7.IAR bit for CPU5/VPE0
config7IAR_CPU5_VPE1	Boolean	Override Config7.IAR bit for CPU5/VPE1
config7IAR_CPU5_VPE2	Boolean	Override Config7.IAR bit for CPU5/VPE2
config7IAR_CPU5_VPE3	Boolean	Override Config7.IAR bit for CPU5/VPE3
config7IAR_CPU6_VPE0	Boolean	Override Config7.IAR bit for CPU6/VPE0
config7IAR_CPU6_VPE1	Boolean	Override Config7.IAR bit for CPU6/VPE1
config7IAR_CPU6_VPE2	Boolean	Override Config7.IAR bit for CPU6/VPE2
config7IAR_CPU6_VPE3	Boolean	Override Config7.IAR bit for CPU6/VPE3
config7IAR_CPU7_VPE0	Boolean	Override Config7.IAR bit for CPU7/VPE0
config7IAR_CPU7_VPE1	Boolean	Override Config7.IAR bit for CPU7/VPE1
config7IAR_CPU7_VPE2	Boolean	Override Config7.IAR bit for CPU7/VPE2
config7IAR_CPU7_VPE3	Boolean	Override Config7.IAR bit for CPU7/VPE3
config7IVAD_CPU0_VPE0	Boolean	Override Config7.IVAD bit for CPU0/VPE0
config7IVAD_CPU0_VPE1	Boolean	Override Config7.IVAD bit for CPU0/VPE1
config7IVAD_CPU0_VPE2	Boolean	Override Config7.IVAD bit for CPU0/VPE2
config7IVAD_CPU0_VPE3	Boolean	Override Config7.IVAD bit for CPU0/VPE3
config7IVAD_CPU1_VPE0	Boolean	Override Config7.IVAD bit for CPU1/VPE0
config7IVAD_CPU1_VPE1	Boolean	Override Config7.IVAD bit for CPU1/VPE1
config7IVAD_CPU1_VPE2	Boolean	Override Config7.IVAD bit for CPU1/VPE2
config7IVAD_CPU1_VPE3	Boolean	Override Config7.IVAD bit for CPU1/VPE3
config7IVAD_CPU2_VPE0	Boolean	Override Config7.IVAD bit for CPU2/VPE0
config7IVAD_CPU2_VPE1	Boolean	Override Config7.IVAD bit for CPU2/VPE1
config7IVAD_CPU2_VPE2	Boolean	Override Config7.IVAD bit for CPU2/VPE2
config7IVAD_CPU2_VPE3	Boolean	Override Config7.IVAD bit for CPU2/VPE3
config7IVAD_CPU3_VPE0	Boolean	Override Config7.IVAD bit for CPU3/VPE0
config7IVAD_CPU3_VPE1	Boolean	Override Config7.IVAD bit for CPU3/VPE1

config7IVAD_CPU3_VPE2	Boolean	Override Config7.IVAD bit for CPU3/VPE2
config7IVAD_CPU3_VPE3	Boolean	Override Config7.IVAD bit for CPU3/VPE3
config7IVAD_CPU4_VPE0	Boolean	Override Config7.IVAD bit for CPU4/VPE0
config7IVAD_CPU4_VPE1	Boolean	Override Config7.IVAD bit for CPU4/VPE1
config7IVAD_CPU4_VPE2	Boolean	Override Config7.IVAD bit for CPU4/VPE2
config7IVAD_CPU4_VPE3	Boolean	Override Config7.IVAD bit for CPU4/VPE3
config7IVAD_CPU5_VPE0	Boolean	Override Config7.IVAD bit for CPU5/VPE0
config7IVAD_CPU5_VPE1	Boolean	Override Config7.IVAD bit for CPU5/VPE1
config7IVAD_CPU5_VPE2	Boolean	Override Config7.IVAD bit for CPU5/VPE2
config7IVAD_CPU5_VPE3	Boolean	Override Config7.IVAD bit for CPU5/VPE3
config7IVAD_CPU6_VPE0	Boolean	Override Config7.IVAD bit for CPU6/VPE0
config7IVAD_CPU6_VPE1	Boolean	Override Config7.IVAD bit for CPU6/VPE1
config7IVAD_CPU6_VPE2	Boolean	Override Config7.IVAD bit for CPU6/VPE2
config7IVAD_CPU6_VPE3	Boolean	Override Config7.IVAD bit for CPU6/VPE3
config7IVAD_CPU7_VPE0	Boolean	Override Config7.IVAD bit for CPU7/VPE0
config7IVAD_CPU7_VPE1	Boolean	Override Config7.IVAD bit for CPU7/VPE1
config7IVAD_CPU7_VPE2	Boolean	Override Config7.IVAD bit for CPU7/VPE2
config7IVAD_CPU7_VPE3	Boolean	Override Config7.IVAD bit for CPU7/VPE3
config7RPS_CPU0_VPE0	Boolean	Override Config7.RPS bit for CPU0/VPE0
config7RPS_CPU0_VPE1	Boolean	Override Config7.RPS bit for CPU0/VPE1
config7RPS_CPU0_VPE2	Boolean	Override Config7.RPS bit for CPU0/VPE2
config7RPS_CPU0_VPE3	Boolean	Override Config7.RPS bit for CPU0/VPE3
config7RPS_CPU1_VPE0	Boolean	Override Config7.RPS bit for CPU1/VPE0
config7RPS_CPU1_VPE1	Boolean	Override Config7.RPS bit for CPU1/VPE1
config7RPS_CPU1_VPE2	Boolean	Override Config7.RPS bit for CPU1/VPE2
config7RPS_CPU1_VPE3	Boolean	Override Config7.RPS bit for CPU1/VPE3
config7RPS_CPU2_VPE0	Boolean	Override Config7.RPS bit for CPU2/VPE0
config7RPS_CPU2_VPE1	Boolean	Override Config7.RPS bit for CPU2/VPE1
config7RPS_CPU2_VPE2	Boolean	Override Config7.RPS bit for CPU2/VPE2
config7RPS_CPU2_VPE3	Boolean	Override Config7.RPS bit for CPU2/VPE3
config7RPS_CPU3_VPE0	Boolean	Override Config7.RPS bit for CPU3/VPE0
config7RPS_CPU3_VPE1	Boolean	Override Config7.RPS bit for CPU3/VPE1
config7RPS_CPU3_VPE2	Boolean	Override Config7.RPS bit for CPU3/VPE2
config7RPS_CPU3_VPE3	Boolean	Override Config7.RPS bit for CPU3/VPE3
config7RPS_CPU4_VPE0	Boolean	Override Config7.RPS bit for CPU4/VPE0
config7RPS_CPU4_VPE1	Boolean	Override Config7.RPS bit for CPU4/VPE1
config7RPS_CPU4_VPE2	Boolean	Override Config7.RPS bit for CPU4/VPE2
config7RPS_CPU4_VPE3	Boolean	Override Config7.RPS bit for CPU4/VPE3
config7RPS_CPU5_VPE0	Boolean	Override Config7.RPS bit for CPU5/VPE0
config7RPS_CPU5_VPE1	Boolean	Override Config7.RPS bit for CPU5/VPE1
config7RPS_CPU5_VPE2	Boolean	Override Config7.RPS bit for CPU5/VPE2
config7RPS_CPU5_VPE3	Boolean	Override Config7.RPS bit for CPU5/VPE3
config7RPS_CPU6_VPE0	Boolean	Override Config7.RPS bit for CPU6/VPE0
config7RPS_CPU6_VPE1	Boolean	Override Config7.RPS bit for CPU6/VPE1
config7RPS_CPU6_VPE2	Boolean	Override Config7.RPS bit for CPU6/VPE2
config7RPS_CPU6_VPE3	Boolean	Override Config7.RPS bit for CPU6/VPE3
config7RPS_CPU7_VPE0	Boolean	Override Config7.RPS bit for CPU7/VPE0
config7RPS_CPU7_VPE1	Boolean	Override Config7.RPS bit for CPU7/VPE1
config7RPS_CPU7_VPE2	Boolean	Override Config7.RPS bit for CPU7/VPE2
config7RPS_CPU7_VPE3	Boolean	Override Config7.RPS bit for CPU7/VPE3
statusFR	Boolean	Override power on value in Status.FR (Floating point register mode)
fcsrABS2008	Boolean	Override FCSR.ABS2008 (ABS/NEG compliant with IEEE 754-2008)
fcsrNaN2008	Boolean	Override FCSR.NAN2008 (QNaN/SNaN encodings match IEEE 754-2008 recommendation)

numMaarRegs	Uns32	Override number of MAAR registers (must be even)
srsconf0SRS1	Uns32	Override the SRS1 field in SRSCnf0 register
srsconf0SRS2	Uns32	Override the SRS2 field in SRSCnf0 register
srsconf0SRS3	Uns32	Override the SRS3 field in SRSCnf0 register
wiredLimit	Uns32	Override Limit field of the Wired register
wiredLimitBits	Uns32	Override width of Limit field of the Wired register
wiredWiredBits	Uns32	Override width of Wired field of the Wired register
cdmmBaseCI	Boolean	Override CDMMBase.CI
parityEnable	Uns32	Specify error detection support: 0 - none; 1 - parity; 2 - ECC
useMpTb	Boolean	Override Use of multi-processor test bench
ExceptionBase	Uns32	Specify the BEV Exception Base address. (use GCR.Cx.RESET_BASE on CMP processors)
UseExceptionBase	Boolean	Set to one to use ExceptionBase[29:12] as the corresponding BEV address bits
l1BufferCache	Boolean	L1 Buffer Cache
GCU_EX	Boolean	CMP system only: GCR custom block present
GIC_EX	Boolean	CMP system only: GIC unit present
CPC_EX	Boolean	CMP system only: CPC unit present
TIMER_ROUTABLE	Boolean	CMP system only: cpu timer interrupt routable within cluster
SWINT_ROUTABLE	Boolean	CMP system only: software interrupt routable within cluster
PERFCNT_ROUTABLE	Boolean	CMP system only: performance counter interrupt routable within cluster
FDC_ROUTABLE	Boolean	CMP system only: fast debug channel interrupt routable within cluster
GCR_PCORES	Uns32	CMP system only: override GCR.CONFIG.PCORES (number of cores-1)
GCR_ADDR_REGIONS	Uns32	CMP system only: override GCR.CONFIG.ADDR_REGIONS (number of MMIO address regions)
GCR_NUMAUX	Uns32	CMP system only: override GCR.CONFIG.NUMAUX (number of auxiliary memory ports)
GCR_BASE	Uns64	CMP system only: override GCR.BASE.GCR_BASE (default GCR register address)
GCR_MINOR_REV	Uns32	CMP system only: override GCR.REV.MINOR_REV
GCR_MAJOR_REV	Uns32	CMP system only: override GCR.REV.MAJOR_REV
GCR_CACHE_MINOR_REV	Uns32	CMP system only: override GCR.CACHE.REV.MINOR_REV
GCR_CACHE_MAJOR_REV	Uns32	CMP system only: override GCR.CACHE.REV.MAJOR_REV
GCR_L2_ASSOC	Uns32	CMP system only: override GCR.L2.CONFIG.ASSOC
GCR_L2_SET_SIZE	Uns32	CMP system only: override GCR.L2.CONFIG.SET_SIZE
GCR_SYS_CONFIG2_MAX_VP_WIDTH	Uns32	CMP system only: override GCR.SYS_CONFIG2.MAX_VP_WIDTH
GCR_IOCUI1_MINOR_REV	Uns32	CMP system only: override GCR.IOCUI1.REV.MINOR_REV
GCR_IOCUI1_MAJOR_REV	Uns32	CMP system only: override GCR.IOCUI1.REV.MAJOR_REV

GCR_BEV_BASE	Uns32	CMP system only: override GCR_BEV_BASE
GCR_KX_BASE_MODE	Boolean	CMP system only: override BEV_BASE_MODE & RESET_BASE_MODE
GCR_MMIO_REQ_LIMIT	Uns32	CMP system only: override GCR_MMIO_REQ_LIMIT.MMIO_REQ_LIMIT value
GCR_MMIO0_BOTTOM	Uns64	CMP system only: override GCR_MMIO0_BOTTOM register value
GCR_MMIO0_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO0_TOP.TOP_ADDR value
GCR_MMIO1_BOTTOM	Uns64	CMP system only: override GCR_MMIO1_BOTTOM register value
GCR_MMIO1_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO1_TOP.TOP_ADDR value
GCR_MMIO2_BOTTOM	Uns64	CMP system only: override GCR_MMIO2_BOTTOM register value
GCR_MMIO2_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO2_TOP.TOP_ADDR value
GCR_MMIO3_BOTTOM	Uns64	CMP system only: override GCR_MMIO3_BOTTOM register value
GCR_MMIO3_TOP_ADDR	Uns32	CMP system only: override GCR_MMIO3_TOP.TOP_ADDR value
GIC_NUMINTERRUPTS	Uns32	CMP system only: override GIC_SH_CONFIG.NUMINTERRUPTS
GIC_COUNTBITS	Uns32	CMP system only: override GIC_SH_CONFIG.COUNTBITS
GIC_MINOR_REV	Uns32	CMP system only: override GIC_SH_REVISION.MINOR_REV
GIC_MAJOR_REV	Uns32	CMP system only: override GIC_SH_REVISION.MAJOR_REV
GIC_NUM_TEAMS	Uns32	CMP system only: override GIC_SH_DBG_CONFIG.NUM_TEAMS
GIC_TRIG_RESET	Uns32	CMP system only: Zero value of GIC_SH_TRIG_[31.0, 63.32]
GIC_PVPES	Uns32	CMP system only: override GIC_SH_CONFIG.PVPE
CPC_MICROSTEP	Uns32	CMP system only: override CPC_SEQDEL.MICROSTEP
CPC_RAILDELAY	Uns32	CMP system only: override CPC_RAIL.RAILDELAY
CPC_RESETLEN	Uns32	CMP system only: override CPC_RESETLEN.RESETLEN
CPC_MINOR_REV	Uns32	CMP system only: override CPC_REVISION.MINOR_REV
CPC_MAJOR_REV	Uns32	CMP system only: override CPC_REVISION.MAJOR_REV
GIC_SH_GID_CONFIG31.0	Uns32	CMP system only: override GIC_SH_GID_CONFIG[31.0]
GIC_SH_GID_CONFIG63.32	Uns32	CMP system only: override GIC_SH_GID_CONFIG[63.32]
GIC_SH_GID_CONFIG95.64	Uns32	CMP system only: override GIC_SH_GID_CONFIG[95.64]
GIC_SH_GID_CONFIG127.96	Uns32	CMP system only: override GIC_SH_GID_CONFIG[127.96]
GIC_SH_GID_CONFIG159.128	Uns32	CMP system only: override GIC_SH_GID_CONFIG[159.128]

GIC.SH.GID.CONFIG191_160	Uns32	CMP system only: override GIC.SH.GID.CONFIG[191_160]
GIC.SH.GID.CONFIG223_192	Uns32	CMP system only: override GIC.SH.GID.CONFIG[223_192]
GIC.SH.GID.CONFIG255_224	Uns32	CMP system only: override GIC.SH.GID.CONFIG[255_224]
GCR.C0.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 0
GCR.C1.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 1
GCR.C2.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 2
GCR.C3.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 3
GCR.C4.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 4
GCR.C5.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 5
GCR.C6.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 6
GCR.C7.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 7
GCR.C8.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 8
GCR.C9.RESET_BASE	Uns32	CMP system only: GCR.CL.RESET.BASE for core 9
GCR.C0.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 0
GCR.C1.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 1
GCR.C2.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 2
GCR.C3.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 3
GCR.C4.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 4
GCR.C5.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 5
GCR.C6.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 6
GCR.C7.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 7
GCR.C8.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 8
GCR.C9.RESET_EXT_BASE	Uns32	CMP system only: GCR.CL.RESET_EXT.BASE for core 9
CPC.C0.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 0
CPC.C1.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 1
CPC.C2.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 2
CPC.C3.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 3
CPC.C4.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 4
CPC.C5.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 5
CPC.C6.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 6
CPC.C7.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 7
CPC.C8.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 8
CPC.C9.VP_EN	Uns32	CMP system only: CPC.VP_EN for core 9



EIC_OPTION	Uns32	Override the external interrupt controller EIC_OPTION
guestCtl0RI	Uns32	Override the RI field in GuestCtl0 register
guestCtl0MC	Uns32	Override the MC field in GuestCtl0 register
guestCtl0CP0	Uns32	Override the CP0 field in GuestCtl0 register
guestCtl0AT	Uns32	Override the AT field in GuestCtl0 register
guestCtl0GT	Uns32	Override the GT field in GuestCtl0 register
guestCtl0CG	Uns32	Override the CG field in GuestCtl0 register
guestCtl0CF	Uns32	Override the CF field in GuestCtl0 register
guestCtl0G1	Uns32	Override the G1 field in GuestCtl0 register
guestCtl0RAD	Uns32	Override the RAD field in GuestCtl0 register
guestCtl0DRG	Uns32	Override the DRG field in GuestCtl0 register
hasImpl17	Boolean	Enable read/write of Impl17 bit in Status register
hasImpl16	Boolean	Enable read/write of Impl16 bit in Status register
guestIntctlIPTI	Uns32	Override the Guest IPTI field in IntCtl register
guestIntctlIPFDC	Uns32	Override the Guest IPFDC field in IntCtl register
guestIntctlIPPCI	Uns32	Override the Guest IPPCI field in IntCtl register
ISPRAM_SIZE	Uns32	Encoded size of the ISPRAM region ( $\log_2(\text{<ISPRAM size in bytes>}) - 11$ )
ISPRAM_BASE	Uns64	Starting physical address of the ISPRAM region
ISPRAM_ENABLE	Boolean	Set the enable bit of the ISPRAM region's tag (used to enable the ISPRAM region prior to reset)
ISPRAM_FILE	String	Load a MIPS hex file into the ISPRAM region prior to reset
DSPRAM_SIZE	Uns32	Encoded size of the DSPRAM region ( $\log_2(\text{<DSPRAM size in bytes>}) - 11$ )
DSPRAM_BASE	Uns64	Starting physical address of the DSPRAM region
DSPRAM_ENABLE	Boolean	Set the enable bit of the DSPRAM region's tag (used to enable the DSPRAM region prior to reset)
DSPRAM_PRESENT	Boolean	DSPRAM is present with SAAR
USPRAM_SIZE	Uns32	Encoded size of the USPRAM region ( $\log_2(\text{<USPRAM size in bytes>}) - 11$ )
USPRAM_BASE	Uns64	Starting physical address of the USPRAM region
USPRAM_ENABLE	Boolean	Set the enable bit of the USPRAM region's tag (used to enable the USPRAM region prior to reset)
USPRAM_FILE	String	Load a MIPS hex file into the USPRAM region prior to reset
misalignedDataException	Enumeration	Select misaligned data access exception signaling: never, checkCCA or always (never, checkCCA or always)
commitTlbwErr	Boolean	Commit TLBWI/TLBRI on ECC; in MIPS_DV_MODE only

Table 8.3: Parameters that can be set in: CPU

## 8.2 Parameter values

These are the current parameter values.

Name	Value
<b>(Others)</b>	
endian	none

cacheenable	default
cachedebug	0
cacheextbiuinfo	0x0
mipsHexFile	
IMPERAS_MIPS_AVP_OPCODES	F
cacheIndexBypassTLB	F
MIPS_TRACE	F
gprNames	F
supervisorMode	F
busErrors	T
fixedMMU	F
fixedDbgRegSize	F
removeDSP	F
removeCMP	F
removeFP	F
removeFTLB	F
isISA	F
hiddenTLBentries	F
perfCounters	0
MTFPU	0
supportDenormals	F
VPE0MaxTC	0
VPE1MaxTC	0
segBits	0
mpuRegions	0
mpuType	0
mpuEnable	F
mpuSegment0	0
mpuSegment1	0
mpuSegment2	0
mpuSegment3	0
mpuSegment4	0
mpuSegment5	0
mpuSegment6	0
mpuSegment7	0
mpuSegment8	0
mpuSegment9	0
mpuSegment10	0
mpuSegment11	0
mpuSegment12	0
mpuSegment13	0
mpuSegment14	0
mpuSegment15	0
mvpcnf0vpe	0
tcDisable	0



vpeDisable	0
mvpconf0tc	0
mvpconf0pcp	F
mvpconf0tcp	F
mvpconf1c1f	F
mvpcontrolPolicyMode	F
hasFDC	0
licenseWarningDays	15
MIPS_UHI	F
mipsUhiArgs	
mipsUhiJail	
MIPS_DV_MODE	F
MIPS_MAGIC_OPCODES	F
enableTrickbox	F
fpuexcdisable	F
TRU_PRESENT	F
ucLLwordsLocked	0
FUSA	F
CPC_FAULT_SUPPORTED	0
CPC_FAULT_ENABLE	0
cop2Bits	32
cop2FileName	
udiConfig	0
udiFileName	
vectoredinterrupt	F
externalinterrupt	F
rootFixedMMU	F
rootMMUSizeM1	0
srsc1HSS	0
firPS	0
firHas2008	0
usePreciseFpu	0
simulateLite	NONE
pridCompanyOptions	0
pridRevision	0
globalClusterNum	0
intctlIPTI	0
intctlIPFDC	0
intctlIPPCI	0
numWatch	0
xconfigSpecified	F
segcfg0PA	0
segcfg1PA	0
segcfg2PA	0
segcfg3PA	0

segcfg4PA	0
segcfg5PA	0
segcfg0AM	0
segcfg1AM	0
segcfg2AM	0
segcfg3AM	0
segcfg4AM	0
segcfg5AM	0
segcfg0EU	0
segcfg1EU	0
segcfg2EU	0
segcfg3EU	0
segcfg4EU	0
segcfg5EU	0
segcfg0C	0
segcfg1C	0
segcfg2C	0
segcfg3C	0
segcfg4C	0
segcfg5C	0
cdmmSize	0
configAR	0
configBM	0
configDSP	F
configISP	F
configK0	0
configKU	0
configK23	0
configMDU	F
configMM	F
configMT	0
configSB	F
configBCP	F
MIPS16eASE	F
config1DA	0
config1DL	0
config1DS	0
config1EP	F
config1IA	0
config1IL	0
config1IS	0
config1MMUSizeM1	0
config1MMUSizeM1_VPE1	0
config1MMUSizeM1_VPE2	0
config1MMUSizeM1_VPE3	0

config1WR	F
config1PC	F
config1C2	F
config2SU	0
config2SS	0
config2SL	0
config2SA	0
config3BI	F
config3BP	F
config3CDMM	F
config3CTXTC	F
config3DSPP	F
config3DSP2P	F
config3IPLW	0
config3ISA	0
config3ISAOnExc	F
config3ITL	F
config3LPA	F
config3MCU	F
config3MMAR	0
config3RXI	F
config3SC	F
config3ULRI	F
config3VZ	F
config3MSAP	F
config3CMGCR	F
config3SP	F
config3TL	0
config3PW	F
config4AE	F
config4IE	0
config4MMUConfig	0
config4MMUExtDef	0
config4VTLBSizeExt	0
config4KScrExist	0
config5EVA	F
config5LLB	F
config5MRP	F
config5NFExists	F
mips32Macro	F
config5MSAEn	F
config5MVH	F
config5DEC	F
config5GI	0
config5CRCP	F

config5VP	F
config6FTLBEEn	F
config7AR	F
config7DCIDX_MODE	0
config7HCI	F
config7IAR	F
config7WII	F
config7ES	0
config7WR	F
config7FPR	F
config7USP	0
config7BTLM	F
config7BusSlp	F
config7IVAD	F
config7RPS	F
config7IAR_CPU0_VPE0	F
config7IAR_CPU0_VPE1	F
config7IAR_CPU0_VPE2	F
config7IAR_CPU0_VPE3	F
config7IAR_CPU1_VPE0	F
config7IAR_CPU1_VPE1	F
config7IAR_CPU1_VPE2	F
config7IAR_CPU1_VPE3	F
config7IAR_CPU2_VPE0	F
config7IAR_CPU2_VPE1	F
config7IAR_CPU2_VPE2	F
config7IAR_CPU2_VPE3	F
config7IAR_CPU3_VPE0	F
config7IAR_CPU3_VPE1	F
config7IAR_CPU3_VPE2	F
config7IAR_CPU3_VPE3	F
config7IAR_CPU4_VPE0	F
config7IAR_CPU4_VPE1	F
config7IAR_CPU4_VPE2	F
config7IAR_CPU4_VPE3	F
config7IAR_CPU5_VPE0	F
config7IAR_CPU5_VPE1	F
config7IAR_CPU5_VPE2	F
config7IAR_CPU5_VPE3	F
config7IAR_CPU6_VPE0	F
config7IAR_CPU6_VPE1	F
config7IAR_CPU6_VPE2	F
config7IAR_CPU6_VPE3	F
config7IAR_CPU7_VPE0	F
config7IAR_CPU7_VPE1	F

config7IAR_CPU7_VPE2	F
config7IAR_CPU7_VPE3	F
config7IVAD_CPU0_VPE0	F
config7IVAD_CPU0_VPE1	F
config7IVAD_CPU0_VPE2	F
config7IVAD_CPU0_VPE3	F
config7IVAD_CPU1_VPE0	F
config7IVAD_CPU1_VPE1	F
config7IVAD_CPU1_VPE2	F
config7IVAD_CPU1_VPE3	F
config7IVAD_CPU2_VPE0	F
config7IVAD_CPU2_VPE1	F
config7IVAD_CPU2_VPE2	F
config7IVAD_CPU2_VPE3	F
config7IVAD_CPU3_VPE0	F
config7IVAD_CPU3_VPE1	F
config7IVAD_CPU3_VPE2	F
config7IVAD_CPU3_VPE3	F
config7IVAD_CPU4_VPE0	F
config7IVAD_CPU4_VPE1	F
config7IVAD_CPU4_VPE2	F
config7IVAD_CPU4_VPE3	F
config7IVAD_CPU5_VPE0	F
config7IVAD_CPU5_VPE1	F
config7IVAD_CPU5_VPE2	F
config7IVAD_CPU5_VPE3	F
config7IVAD_CPU6_VPE0	F
config7IVAD_CPU6_VPE1	F
config7IVAD_CPU6_VPE2	F
config7IVAD_CPU6_VPE3	F
config7IVAD_CPU7_VPE0	F
config7IVAD_CPU7_VPE1	F
config7IVAD_CPU7_VPE2	F
config7IVAD_CPU7_VPE3	F
config7RPS_CPU0_VPE0	F
config7RPS_CPU0_VPE1	F
config7RPS_CPU0_VPE2	F
config7RPS_CPU0_VPE3	F
config7RPS_CPU1_VPE0	F
config7RPS_CPU1_VPE1	F
config7RPS_CPU1_VPE2	F
config7RPS_CPU1_VPE3	F
config7RPS_CPU2_VPE0	F
config7RPS_CPU2_VPE1	F
config7RPS_CPU2_VPE2	F

config7RPS_CPU2_VPE3	F
config7RPS_CPU3_VPE0	F
config7RPS_CPU3_VPE1	F
config7RPS_CPU3_VPE2	F
config7RPS_CPU3_VPE3	F
config7RPS_CPU4_VPE0	F
config7RPS_CPU4_VPE1	F
config7RPS_CPU4_VPE2	F
config7RPS_CPU4_VPE3	F
config7RPS_CPU5_VPE0	F
config7RPS_CPU5_VPE1	F
config7RPS_CPU5_VPE2	F
config7RPS_CPU5_VPE3	F
config7RPS_CPU6_VPE0	F
config7RPS_CPU6_VPE1	F
config7RPS_CPU6_VPE2	F
config7RPS_CPU6_VPE3	F
config7RPS_CPU7_VPE0	F
config7RPS_CPU7_VPE1	F
config7RPS_CPU7_VPE2	F
config7RPS_CPU7_VPE3	F
statusFR	F
fcsrABS2008	F
fcsrNAN2008	F
numMaarRegs	6
srscnf0SRS1	0
srscnf0SRS2	0
srscnf0SRS3	0
wiredLimit	0
wiredLimitBits	0
wiredWiredBits	0
cdmmBaseCI	F
parityEnable	1
useMpTb	T
ExceptionBase	0
UseExceptionBase	F
l1BufferCache	F
GCU_EX	F
GIC_EX	F
CPC_EX	F
TIMER_ROUTABLE	F
SWINT_ROUTABLE	F
PERFCNT_ROUTABLE	F
FDC_ROUTABLE	F
GCR_PCORES	0

GCR_ADDR_REGIONS	0
GCR_NUMAUX	0
GCR_BASE	0
GCR_MINOR_REV	0
GCR_MAJOR_REV	0
GCR_CACHE_MINOR_REV	0
GCR_CACHE_MAJOR_REV	0
GCR_L2_ASSOC	0
GCR_L2_SET_SIZE	0
GCR_SYS_CONFIG2_MAX_VP_WIDTH	0
GCR_IOCUI_MINOR_REV	0
GCR_IOCUI_MAJOR_REV	0
GCR_BEV_BASE	0
GCR_KX_BASE_MODE	F
GCR_MMIO_REQ_LIMIT	0
GCR_MMIO0_BOTTOM	0
GCR_MMIO0_TOP_ADDR	0
GCR_MMIO1_BOTTOM	0
GCR_MMIO1_TOP_ADDR	0
GCR_MMIO2_BOTTOM	0
GCR_MMIO2_TOP_ADDR	0
GCR_MMIO3_BOTTOM	0
GCR_MMIO3_TOP_ADDR	0
GIC_NUMINTERRUPTS	0
GIC_COUNTBITS	0
GIC_MINOR_REV	0
GIC_MAJOR_REV	0
GIC_NUM_TEAMS	7
GIC_TRIG_RESET	0
GIC_PVPES	0
CPC_MICROSTEP	0
CPC_RAILDELAY	0
CPC_RESETLEN	0
CPC_MINOR_REV	0
CPC_MAJOR_REV	0
GIC_SH_GID_CONFIG31_0	0
GIC_SH_GID_CONFIG63_32	0
GIC_SH_GID_CONFIG95_64	0
GIC_SH_GID_CONFIG127_96	0
GIC_SH_GID_CONFIG159_128	0
GIC_SH_GID_CONFIG191_160	0
GIC_SH_GID_CONFIG223_192	0
GIC_SH_GID_CONFIG255_224	0
GCR_C0_RESET_BASE	0
GCR_C1_RESET_BASE	0

GCR_C2_RESET_BASE	0
GCR_C3_RESET_BASE	0
GCR_C4_RESET_BASE	0
GCR_C5_RESET_BASE	0
GCR_C6_RESET_BASE	0
GCR_C7_RESET_BASE	0
GCR_C8_RESET_BASE	0
GCR_C9_RESET_BASE	0
GCR_C0_RESET_EXT_BASE	0
GCR_C1_RESET_EXT_BASE	0
GCR_C2_RESET_EXT_BASE	0
GCR_C3_RESET_EXT_BASE	0
GCR_C4_RESET_EXT_BASE	0
GCR_C5_RESET_EXT_BASE	0
GCR_C6_RESET_EXT_BASE	0
GCR_C7_RESET_EXT_BASE	0
GCR_C8_RESET_EXT_BASE	0
GCR_C9_RESET_EXT_BASE	0
CPC_C0_VP_EN	0
CPC_C1_VP_EN	0
CPC_C2_VP_EN	0
CPC_C3_VP_EN	0
CPC_C4_VP_EN	0
CPC_C5_VP_EN	0
CPC_C6_VP_EN	0
CPC_C7_VP_EN	0
CPC_C8_VP_EN	0
CPC_C9_VP_EN	0
EIC_OPTION	2
guestCtl0RI	0
guestCtl0MC	0
guestCtl0CP0	0
guestCtl0AT	0
guestCtl0GT	0
guestCtl0CG	0
guestCtl0CF	0
guestCtl0G1	0
guestCtl0RAD	0
guestCtl0DRG	0
hasImpl17	F
hasImpl16	F
guestintctlIPTI	0
guestintctlIPFDC	0
guestintctlIPPCI	0
ISPRAM_SIZE	0



ISPRAM_BASE	0
ISPRAM_ENABLE	F
ISPRAM_FILE	
DSPRAM_SIZE	0
DSPRAM_BASE	0
DSPRAM_ENABLE	F
DSPRAM_PRESENT	F
USPRAM_SIZE	0
USPRAM_BASE	0
USPRAM_ENABLE	F
USPRAM_FILE	
misalignedDataException	never
commitTlbwErr	F

Table 8.4: Parameter values

## Chapter 9

# Execution Modes

Mode	Code
KERNEL	0
DEBUG	1
SUPERVISOR	2
USER	3

Table 9.1: Modes implemented in: CMP

Mode	Code
KERNEL	0
DEBUG	1
SUPERVISOR	2
USER	3
GUEST_KERNEL	4
GUEST_SUPERVISOR	5
GUEST_USER	6

Table 9.2: Modes implemented in: CPU

## Chapter 10

# Exceptions

Exception	Code
Int	0
Mod	1
TLBL	2
TLBS	3
AdEL	4
AdES	5
IBE	6
DBE	7
Sys	8
Bp	9
RI	10
CpU	11
Ov	12
Tr	13
MSAFPE	14
FPE	15
Impl1	16
Impl2	17
C2E	18
TLBRI	19
TLBXI	20
MSADis	21
MDMX	22
WATCH	23
MCheck	24
Thread	25
DSPDis	26
GE	27
Prot	29
CacheErr	30

Table 10.1: Exceptions implemented in: CMP

<b>Exception</b>	<b>Code</b>
Int	0
Mod	1
TLBL	2
TLBS	3
AdEL	4
AdES	5
IBE	6
DBE	7
Sys	8
Bp	9
RI	10
CpU	11
Ov	12
Tr	13
MSAFPE	14
FPE	15
Impl1	16
Impl2	17
C2E	18
TLBRI	19
TLBXI	20
MSADis	21
MDMX	22
WATCH	23
MCheck	24
Thread	25
DSPDis	26
GE	27
Prot	29
CacheErr	30

Table 10.2: Exceptions implemented in: CPU

# Chapter 11

## Hierarchy of the model

A CPU core may be configured to instance many processors of a Symmetrical Multi Processor (SMP). A CPU core may also have sub elements within a processor, for example hardware threading blocks.

OVP processor models can be written to include SMP blocks and to have many levels of hierarchy. Some OVP CPU models may have a fixed hierarchy, and some may be configured by settings in a configuration register. Please see the register definitions of this model.

This model documentation shows the settings and hierarchy of the default settings for this model variant.

### 11.1 Level 1: CMP

This level in the model hierarchy has 2 commands.

This level in the model hierarchy has no register groups.

This level in the model hierarchy has 4 children:

CPU0, CPU1, CPU2 and CPU3.

### 11.2 Level 2: CPU

This level in the model hierarchy has 20 commands.

This level in the model hierarchy has 11 register groups:

Group name	Registers
Core	65
FPU	34
DSP	9
Shadow	64
COPO	158
SPRAM	5
MSA	40
CMP_GCR	49
CMP_CPC	17
CMP_GIC	726
Integration_support	1

---

Table 11.1: Register groups

This level in the model hierarchy has no children.

# Chapter 12

## Model Commands

A Processor model can implement one or more **Model Commands** available to be invoked from the simulator command line, from the OP API or from the Imperas Multiprocessor Debugger.

### 12.1 Level 1: CMP

#### 12.1.1 isync

specify instruction address range for synchronous execution

Argument	Type	Description
-addresshi	Uns64	end address of synchronous execution range
-addresslo	Uns64	start address of synchronous execution range

Table 12.1: isync command arguments

#### 12.1.2 itrace

enable or disable instruction tracing

Argument	Type	Description
-after	Uns64	apply after this many instructions
-enable	Boolean	enable instruction tracing
-instructioncount	Boolean	include the instruction number in each trace
-memory	String	show memory accesses by this instruction. Argument can be any combination of X (execute), L (load or store access) and S (system)
-off	Boolean	disable instruction tracing
-on	Boolean	enable instruction tracing
-processorname	Boolean	Include processor name in all trace lines
-registerchange	Boolean	show registers changed by this instruction
-registers	Boolean	show registers after each trace

Table 12.2: itrace command arguments

## 12.2 Level 2: CPU

### 12.2.1 isync

specify instruction address range for synchronous execution

Argument	Type	Description
-addresshi	Uns64	end address of synchronous execution range
-addresslo	Uns64	start address of synchronous execution range

Table 12.3: isync command arguments

### 12.2.2 itrace

enable or disable instruction tracing

Argument	Type	Description
-after	Uns64	apply after this many instructions
-enable	Boolean	enable instruction tracing
-instructioncount	Boolean	include the instruction number in each trace
-memory	String	show memory accesses by this instruction. Argument can be any combination of X (execute), L (load or store access) and S (system)
-off	Boolean	disable instruction tracing
-on	Boolean	enable instruction tracing
-processorname	Boolean	Include processor name in all trace lines
-registerchange	Boolean	show registers changed by this instruction
-registers	Boolean	show registers after each trace

Table 12.4: itrace command arguments

### 12.2.3 mipsCOP0

query a COP0 register value using <register><select>

Argument	Type	Description
-register	Uns32	specify the COP0 register resource
-select	Uns32	specify the COP0 register select

Table 12.5: mipsCOP0 command arguments

### 12.2.4 mipsCacheDisable

#### 12.2.4.1 Argument description

Disables tag or full cache model

### 12.2.5 mipsCacheEnable

enable tag or full cache model



Argument	Type	Description
-debug	Int32	set cache model debug flags
-full	Boolean	enable full cache model
-tag	Boolean	enable cache tag line only model

Table 12.6: mipsCacheEnable command arguments

## 12.2.6 mipsCacheRatio

Report current hit ratio for selected cache

Argument	Type	Description
-dcache	Boolean	report hit ratio for dcache
-icache	Boolean	report hit ratio for icache

Table 12.7: mipsCacheRatio command arguments

## 12.2.7 mipsCacheReport

### 12.2.7.1 Argument description

Report current cache statistics

## 12.2.8 mipsCacheReset

### 12.2.8.1 Argument description

reset the cache model

## 12.2.9 mipsCacheTrace

Control the tracing of cache accesses

Argument	Type	Description
-noartifact	Boolean	
-nocached	Boolean	
-nodcache	Boolean	
-noicache	Boolean	
-notrue	Boolean	
-nouncached	Boolean	
-off	Boolean	turn off the cache tracing
-on	Boolean	turn on the cache tracing

Table 12.8: mipsCacheTrace command arguments

## 12.2.10 mipsDebugFlags

Set the mips model debug value

Argument	Type	Description
----------	------	-------------

-value	Uns32	specify mips model debug flags
--------	-------	--------------------------------

Table 12.9: mipsDebugFlags command arguments

### 12.2.11 mipsReadRegister

Read processor register using <resource><offset>

Argument	Type	Description
-offset	Uns32	the register offset
-resource	Uns32	the register resource

Table 12.10: mipsReadRegister command arguments

### 12.2.12 mipsReadTLBEntry

read a TLB entry specified by the index

Argument	Type	Description
-index	Uns64	select the TLB entry

Table 12.11: mipsReadTLBEntry command arguments

### 12.2.13 mipsTLBDump

#### 12.2.13.1 Argument description

Dumps the current contents of the TLB

### 12.2.14 mipsTLBDumpGuest

#### 12.2.14.1 Argument description

Dumps the current contents of the Guest TLB

### 12.2.15 mipsTLBDumpRoot

#### 12.2.15.1 Argument description

Dumps the current contents of the Root TLB

### 12.2.16 mipsTLBGetPhys

Reports the entry(s) in the TLB that match the given virtual address and ASID

Argument	Type	Description
-asid	Uns64	ASID
-va	Uns64	virtual address

Table 12.12: mipsTLBGetPhys command arguments

### 12.2.17 mipsTraceGuest

control tracing of guest

Argument	Type	Description
-off	Boolean	stop tracing
-on	Boolean	start tracing

Table 12.13: mipsTraceGuest command arguments

### 12.2.18 mipsTraceRoot

control tracing on root processor

Argument	Type	Description
-off	Boolean	stop tracing
-on	Boolean	start tracing

Table 12.14: mipsTraceRoot command arguments

### 12.2.19 mipsWriteRegister

Write processor register using <resource><offset><value>

Argument	Type	Description
-offset	Uns32	the register offset
-resource	Uns32	the register resource
-value	Uns64	the value to write to register

Table 12.15: mipsWriteRegister command arguments

### 12.2.20 mipsWriteTLBEntry

Writes values to a TLB entry using the index, lo0, lo1, hi0 and mask fields

Argument	Type	Description
-hi0	Uns64	the TLB entry high address
-index	Uns64	the TLB entry index
-lo0	Uns64	the TLB entry low address 0
-lo1	Uns64	the TLB entry low address 1
-mask	Uns64	the TLB entry mask

Table 12.16: mipsWriteTLBEntry command arguments

# Chapter 13

## Registers

### 13.1 Level 1: CMP

No registers.

### 13.2 Level 2: CPU

#### 13.2.1 Core

Registers at level:2, type:CPU group:Core

Name	Bits	Initial-Hex	RW	Description
zero	64	0	r-	constant zero
at	64	0	rw	
v0	64	0	rw	
v1	64	0	rw	
a0	64	0	rw	
a1	64	0	rw	
a2	64	0	rw	
a3	64	0	rw	
t0	64	0	rw	
t1	64	0	rw	
t2	64	0	rw	
t3	64	0	rw	
t4	64	0	rw	
t5	64	0	rw	
t6	64	0	rw	
t7	64	0	rw	
s0	64	0	rw	
s1	64	0	rw	
s2	64	0	rw	
s3	64	0	rw	
s4	64	0	rw	
s5	64	0	rw	
s6	64	0	rw	
s7	64	0	rw	
t8	64	0	rw	
t9	64	0	rw	
k0	64	0	rw	
k1	64	0	rw	

gp	64	0	rw	
sp	64	0	rw	stack pointer
s8	64	0	rw	frame pointer
ra	64	0	rw	
pc	64	ffffff bfc00000	rw	program counter
r0	64	0	r-	constant zero
r1	64	0	rw	
r2	64	0	rw	
r3	64	0	rw	
r4	64	0	rw	
r5	64	0	rw	
r6	64	0	rw	
r7	64	0	rw	
r8	64	0	rw	
r9	64	0	rw	
r10	64	0	rw	
r11	64	0	rw	
r12	64	0	rw	
r13	64	0	rw	
r14	64	0	rw	
r15	64	0	rw	
r16	64	0	rw	
r17	64	0	rw	
r18	64	0	rw	
r19	64	0	rw	
r20	64	0	rw	
r21	64	0	rw	
r22	64	0	rw	
r23	64	0	rw	
r24	64	0	rw	
r25	64	0	rw	
r26	64	0	rw	
r27	64	0	rw	
r28	64	0	rw	
r29	64	0	rw	stack pointer
r30	64	0	rw	frame pointer
r31	64	0	rw	

Table 13.1: Registers at level 2, type:CPU group:Core

### 13.2.2 FPU

Registers at level:2, type:CPU group:FPU

Name	Bits	Initial-Hex	RW	Description
f0	64	0	rw	
f1	64	0	rw	
f2	64	0	rw	
f3	64	0	rw	
f4	64	0	rw	
f5	64	0	rw	
f6	64	0	rw	
f7	64	0	rw	
f8	64	0	rw	
f9	64	0	rw	

f10	64	0	rw	
f11	64	0	rw	
f12	64	0	rw	
f13	64	0	rw	
f14	64	0	rw	
f15	64	0	rw	
f16	64	0	rw	
f17	64	0	rw	
f18	64	0	rw	
f19	64	0	rw	
f20	64	0	rw	
f21	64	0	rw	
f22	64	0	rw	
f23	64	0	rw	
f24	64	0	rw	
f25	64	0	rw	
f26	64	0	rw	
f27	64	0	rw	
f28	64	0	rw	
f29	64	0	rw	
f30	64	0	rw	
f31	64	0	rw	
fsr	64	c0000	rw	floating point status
fir	64	20f30320	r-	floating point information

Table 13.2: Registers at level 2, type:CPU group:FPU

### 13.2.3 DSP

Registers at level:2, type:CPU group:DSP

Name	Bits	Initial-Hex	RW	Description
lo	64	0	rw	
hi	64	0	rw	
lo1	64	0	rw	
hi1	64	0	rw	
lo2	64	0	rw	
hi2	64	0	rw	
lo3	64	0	rw	
hi3	64	0	rw	
dspctl	64	0	rw	DSP control

Table 13.3: Registers at level 2, type:CPU group:DSP

### 13.2.4 Shadow

Registers at level:2, type:CPU group:Shadow

Name	Bits	Initial-Hex	RW	Description
zero[0]	64	0	r-	constant zero
at[0]	64	0	rw	
v0[0]	64	0	rw	
v1[0]	64	0	rw	
a0[0]	64	0	rw	
a1[0]	64	0	rw	

a2[0]	64	0	rw	
a3[0]	64	0	rw	
t0[0]	64	0	rw	
t1[0]	64	0	rw	
t2[0]	64	0	rw	
t3[0]	64	0	rw	
t4[0]	64	0	rw	
t5[0]	64	0	rw	
t6[0]	64	0	rw	
t7[0]	64	0	rw	
s0[0]	64	0	rw	
s1[0]	64	0	rw	
s2[0]	64	0	rw	
s3[0]	64	0	rw	
s4[0]	64	0	rw	
s5[0]	64	0	rw	
s6[0]	64	0	rw	
s7[0]	64	0	rw	
t8[0]	64	0	rw	
t9[0]	64	0	rw	
k0[0]	64	0	rw	
k1[0]	64	0	rw	
gp[0]	64	0	rw	
sp[0]	64	0	rw	stack pointer
s8[0]	64	0	rw	frame pointer
ra[0]	64	0	rw	
r0[0]	64	0	r-	constant zero
r1[0]	64	0	rw	
r2[0]	64	0	rw	
r3[0]	64	0	rw	
r4[0]	64	0	rw	
r5[0]	64	0	rw	
r6[0]	64	0	rw	
r7[0]	64	0	rw	
r8[0]	64	0	rw	
r9[0]	64	0	rw	
r10[0]	64	0	rw	
r11[0]	64	0	rw	
r12[0]	64	0	rw	
r13[0]	64	0	rw	
r14[0]	64	0	rw	
r15[0]	64	0	rw	
r16[0]	64	0	rw	
r17[0]	64	0	rw	
r18[0]	64	0	rw	
r19[0]	64	0	rw	
r20[0]	64	0	rw	
r21[0]	64	0	rw	
r22[0]	64	0	rw	
r23[0]	64	0	rw	
r24[0]	64	0	rw	
r25[0]	64	0	rw	
r26[0]	64	0	rw	
r27[0]	64	0	rw	
r28[0]	64	0	rw	
r29[0]	64	0	rw	stack pointer

r30[0]	64	0	rw	frame pointer
r31[0]	64	0	rw	

Table 13.4: Registers at level 2, type:CPU group:Shadow

### 13.2.5 COP0

Registers at level:2, type:CPU group:COP0

Name	Bits	Initial-Hex	RW	Description
sr	64	4400004	rw	CP0 register 12/0 (status)
bad	64	0	rw	CP0 register 8/0 (badvaddr)
cause	64	0	rw	CP0 register 13/0 (cause)
index	64	0	rw	CP0 register 0/0
entrylo0	64	0	rw	CP0 register 2/0
entrylo1	64	0	rw	CP0 register 3/0
context	64	0	rw	CP0 register 4/0
contextconfig	64	7ffff0	rw	CP0 register 4/1
userlocal	64	0	rw	CP0 register 4/2
xcontextconfig	64	7f fffff0	rw	CP0 register 4/3
pagemask	64	0	rw	CP0 register 5/0
pagegrain	64	c8000000	rw	CP0 register 5/1
segctl0	64	200010	rw	CP0 register 5/2
segctl1	64	30002	rw	CP0 register 5/3
segctl2	64	380438	rw	CP0 register 5/4
pwbase	64	0	rw	CP0 register 5/5
pwfield	64	c30c302	rw	CP0 register 5/6
pwsiz	64	40	rw	CP0 register 5/7
wired	64	0	rw	CP0 register 6/0
pwctl	64	0	rw	CP0 register 6/6
hwrena	64	0	rw	CP0 register 7/0
badvaddr	64	0	rw	CP0 register 8/0
badinstr	64	0	rw	CP0 register 8/1
badinstrp	64	0	rw	CP0 register 8/2
count	64	0	rw	CP0 register 9/0
entryhi	64	0	rw	CP0 register 10/0
guestctl1	64	0	rw	CP0 register 10/4
guestctl2	64	0	rw	CP0 register 10/5
guestctl3	64	0	rw	CP0 register 10/6
compare	64	0	rw	CP0 register 11/0
guestctl0ext	64	80	rw	CP0 register 11/4
status	64	4400004	rw	CP0 register 12/0
intctl	64	ff800000	rw	CP0 register 12/1
srctl	64	0	rw	CP0 register 12/2
srsmap	64	0	rw	CP0 register 12/3
guestctl0	64	c4c00fc	rw	CP0 register 12/6
gtoffset	64	0	rw	CP0 register 12/7
epc	64	0	rw	CP0 register 14/0
prid	64	1a400	rw	CP0 register 15/0
ebase	64	ffffff 80000000	rw	CP0 register 15/1
cdmmbase	64	1fc1000	rw	CP0 register 15/2
cmgcrbase	64	1fbf800	rw	CP0 register 15/3
bevva	64	bfc00000	rw	CP0 register 15/4
config	64	8004c882	rw	CP0 register 16/0
config1	64	fea35193	rw	CP0 register 16/1



config2	64	80000000	rw	CP0 register 16/2
config3	64	ff8032a8	rw	CP0 register 16/3
config4	64	c0fc0000	rw	CP0 register 16/4
config5	64	10002818	rw	CP0 register 16/5
config6	64	0	rw	CP0 register 16/6
config7	64	80054c20	rw	CP0 register 16/7
lladdr	64	0	rw	CP0 register 17/0
maar	64	0	rw	CP0 register 17/1
maari	64	0	rw	CP0 register 17/2
xcontext	64	0	rw	CP0 register 20/0
debug	64	2030000	rw	CP0 register 23/0
depc	64	0	rw	CP0 register 24/0
perfctl0	64	80000000	rw	CP0 register 25/0
perfent0	64	0	rw	CP0 register 25/1
perfctl1	64	80000000	rw	CP0 register 25/2
perfent1	64	0	rw	CP0 register 25/3
perfctl2	64	80000000	rw	CP0 register 25/4
perfent2	64	0	rw	CP0 register 25/5
perfctl3	64	0	rw	CP0 register 25/6
perfent3	64	0	rw	CP0 register 25/7
errctl	64	0	rw	CP0 register 26/0
itaglo	64	0	rw	CP0 register 28/0
idatalo	64	0	rw	CP0 register 28/1
dtaglo	64	0	rw	CP0 register 28/2
ddatalo	64	0	rw	CP0 register 28/3
itaghi	64	0	rw	CP0 register 29/0
idatahi	64	0	rw	CP0 register 29/1
errorepc	64	0	rw	CP0 register 30/0
desave	64	0	rw	CP0 register 31/0
kscratch1	64	0	rw	CP0 register 31/2
kscratch2	64	0	rw	CP0 register 31/3
kscratch3	64	0	rw	CP0 register 31/4
kscratch4	64	0	rw	CP0 register 31/5
kscratch5	64	0	rw	CP0 register 31/6
kscratch6	64	0	rw	CP0 register 31/7
guestindex	64	0	rw	CP0 guest register 0/0
guestentrylo0	64	0	rw	CP0 guest register 2/0
guestentrylo1	64	0	rw	CP0 guest register 3/0
guestcontext	64	0	rw	CP0 guest register 4/0
guestcontextconfig	64	7fff0	rw	CP0 guest register 4/1
guestuserlocal	64	0	rw	CP0 guest register 4/2
guestxcontextconfig	64	7f fffff0	rw	CP0 guest register 4/3
guestpagemask	64	0	rw	CP0 guest register 5/0
guestpagegrain	64	c8000000	rw	CP0 guest register 5/1
guestsegctl0	64	200010	rw	CP0 guest register 5/2
guestsegctl1	64	30002	rw	CP0 guest register 5/3
guestsegctl2	64	380438	rw	CP0 guest register 5/4
guestpwbase	64	0	rw	CP0 guest register 5/5
guestpwfield	64	c30c302	rw	CP0 guest register 5/6
guestpwsiz	64	40	rw	CP0 guest register 5/7
guestwired	64	0	rw	CP0 guest register 6/0
guestpwctl	64	0	rw	CP0 guest register 6/6
guesthwrena	64	0	rw	CP0 guest register 7/0
guestbadvaddr	64	0	rw	CP0 guest register 8/0
guestbadinstr	64	0	rw	CP0 guest register 8/1
guestbadinstrp	64	0	rw	CP0 guest register 8/2

guestcount	64	0	rw	CP0 guest register 9/0
guestentryhi	64	0	rw	CP0 guest register 10/0
guestguestctl1	64	0	rw	CP0 guest register 10/4
guestguestctl2	64	0	rw	CP0 guest register 10/5
guestguestctl3	64	0	rw	CP0 guest register 10/6
guestcompare	64	0	rw	CP0 guest register 11/0
guestguestctl0ext	64	0	rw	CP0 guest register 11/4
gueststatus	64	4400004	rw	CP0 guest register 12/0
guestintctl	64	ff800000	rw	CP0 guest register 12/1
guestsrsctl	64	0	rw	CP0 guest register 12/2
guestsrsmap	64	0	rw	CP0 guest register 12/3
guestguestctl0	64	0	rw	CP0 guest register 12/6
guestgtoffset	64	0	rw	CP0 guest register 12/7
guestcause	64	0	rw	CP0 guest register 13/0
guestepc	64	0	rw	CP0 guest register 14/0
guestprid	64	0	rw	CP0 guest register 15/0
guestbase	64	ffffff 80000000	rw	CP0 guest register 15/1
guestcdmibase	64	0	rw	CP0 guest register 15/2
guestcmgrbase	64	0	rw	CP0 guest register 15/3
guestbevva	64	0	rw	CP0 guest register 15/4
guestconfig	64	8004c882	rw	CP0 guest register 16/0
guestconfig1	64	fea35193	rw	CP0 guest register 16/1
guestconfig2	64	80007000	rw	CP0 guest register 16/2
guestconfig3	64	df003220	rw	CP0 guest register 16/3
guestconfig4	64	c0fc0000	rw	CP0 guest register 16/4
guestconfig5	64	10002818	rw	CP0 guest register 16/5
guestconfig6	64	0	rw	CP0 guest register 16/6
guestconfig7	64	0	rw	CP0 guest register 16/7
guestlladdr	64	0	rw	CP0 guest register 17/0
guestmaar	64	0	rw	CP0 guest register 17/1
guestmaari	64	0	rw	CP0 guest register 17/2
guestxcontext	64	0	rw	CP0 guest register 20/0
guestdebug	64	0	rw	CP0 guest register 23/0
guestdepc	64	0	rw	CP0 guest register 24/0
guestperfcctl0	64	80000000	rw	CP0 guest register 25/0
guestperfcctl1	64	0	rw	CP0 guest register 25/1
guestperfcctl2	64	80000000	rw	CP0 guest register 25/2
guestperfcctl3	64	0	rw	CP0 guest register 25/3
guestperfcctl4	64	80000000	rw	CP0 guest register 25/4
guestperfcctl5	64	0	rw	CP0 guest register 25/5
guestperfcctl6	64	0	rw	CP0 guest register 25/6
guestperfcctl7	64	0	rw	CP0 guest register 25/7
guesterrctl	64	0	rw	CP0 guest register 26/0
guestitaglo	64	0	rw	CP0 guest register 28/0
guestidatalo	64	0	rw	CP0 guest register 28/1
guestdtaglo	64	0	rw	CP0 guest register 28/2
guestddatalo	64	0	rw	CP0 guest register 28/3
guestitaghi	64	0	rw	CP0 guest register 29/0
guestidatahi	64	0	rw	CP0 guest register 29/1
guesterrorepc	64	0	rw	CP0 guest register 30/0
guestdesave	64	0	rw	CP0 guest register 31/0
guestkscratch1	64	0	rw	CP0 guest register 31/2
guestkscratch2	64	0	rw	CP0 guest register 31/3
guestkscratch3	64	0	rw	CP0 guest register 31/4
guestkscratch4	64	0	rw	CP0 guest register 31/5

guestkscratch5	64	0	rw	CP0 guest register 31/6
guestkscratch6	64	0	rw	CP0 guest register 31/7

Table 13.5: Registers at level 2, type:CPU group:COP0

### 13.2.6 SPRAM

Registers at level:2, type:CPU group:SPRAM

Name	Bits	Initial-Hex	RW	Description
USPRAM_ENABLE	8	0	rw	
USPRAM_SIZE	8	0	rw	
USPRAM_BASE	64	0	rw	
USPRAM_FILE	64	-	-w	
USPRAM_WRITE	32	-	-w	

Table 13.6: Registers at level 2, type:CPU group:SPRAM

### 13.2.7 MSA

Registers at level:2, type:CPU group:MSA

Name	Bits	Initial-Hex	RW	Description
w0	128	-	rw	
w1	128	-	rw	
w2	128	-	rw	
w3	128	-	rw	
w4	128	-	rw	
w5	128	-	rw	
w6	128	-	rw	
w7	128	-	rw	
w8	128	-	rw	
w9	128	-	rw	
w10	128	-	rw	
w11	128	-	rw	
w12	128	-	rw	
w13	128	-	rw	
w14	128	-	rw	
w15	128	-	rw	
w16	128	-	rw	
w17	128	-	rw	
w18	128	-	rw	
w19	128	-	rw	
w20	128	-	rw	
w21	128	-	rw	
w22	128	-	rw	
w23	128	-	rw	
w24	128	-	rw	
w25	128	-	rw	
w26	128	-	rw	
w27	128	-	rw	
w28	128	-	rw	
w29	128	-	rw	
w30	128	-	rw	
w31	128	-	rw	

msair	64	320	r-	MSA implementation
msacsr	64	0	rw	MSA control and status
msaaccess	64	-	r-	MSA access
msasave	64	-	r-	MSA save
msamodify	64	-	r-	MSA modify
msarequest	64	-	r-	MSA request
msamap	64	-	r-	MSA map
msaunmap	64	-	r-	MSA unmap

Table 13.7: Registers at level 2, type:CPU group:MSA

### 13.2.8 CMP\_GCR

Registers at level:2, type:CPU group:CMP\_GCR

Name	Bits	Initial-Hex	RW	Description
GCR_CONFIG	64	3	r-	
GCR_BASE	64	1fbf8000	r-	
GCR_BASE_UPPER	64	0	rw	
GCR_CONTROL	64	40200000	rw	
GCR_ACCESS	64	ff	rw	
GCR_REV	64	0	r-	
GCR_ERROR_CONTROL	64	13	rw	
GCR_ERROR_MASK	64	0	rw	
GCR_ERROR_CAUSE	64	0	r-	
GCR_ERROR_ADDR	64	0	r-	
GCR_ERROR_ADDR_UPPER	64	0	-	
GCR_ERROR_MULT	64	0	r-	
GCR_CUSTOM_BASE	64	0	rw	
GCR_CUSTOM_STATUS	64	0	r-	
GCR_GIC_BASE	64	0	rw	
GCR_GIC_BASE_UPPER	64	0	rw	
GCR_CPC_BASE	64	0	rw	
GCR_CPC_BASE_UPPER	64	0	rw	
GCR_GIC_STATUS	64	1	r-	
GCR_CACHE_REV	64	0	r-	
GCR_CPC_STATUS	64	1	r-	
GCR_ACCESS	64	ff	rw	
GCR_L2_CONFIG	64	0	rw	
GCR_SYS_CONFIG2	64	0	r-	
GCR_IOCUI_REV	64	0	r-	
GCR_L2_RAM_CONFIG	64	0	r-	
GCR_L2_TAG_ADDR	64	0	rw	
GCR_L2_TAG_STATE	64	0	rw	
GCR_L2_TAG_STATE_UPPER	64	0	rw	
GCR_L2_DATA	64	0	rw	
GCR_L2_DATA_UPPER	64	0	rw	
GCR_L2_ECC	64	0	rw	
GCR_L2_ECC_UPPER	64	0	rw	
GCR_BEV_BASE	64	0	rw	
GCR_MMIO_REQ_LIMIT	64	0	rw	
GCR_CL_RESET_RELEASE	64	0	-w	
GCR_CL_COHERENCE	64	0	rw	
GCR_CL_CONFIG	64	0	r-	
GCR_CL_OTHER	64	0	rw	
GCR_CL_RESET_BASE	64	bfc00000	rw	

GCR_CL_ID	64	0	r-	
GCR_CL_RESET_EXT_BASE	64	40000001	rw	
GCR_CO_RESET_RELEASE	64	0	-w	
GCR_CO_COHERENCE	64	0	rw	
GCR_CO_CONFIG	64	0	r-	
GCR_CO_OTHER	64	0	rw	
GCR_CO_RESET_BASE	64	bfc00000	rw	
GCR_CO_ID	64	0	r-	
GCR_CO_RESET_EXT_BASE	64	40000001	rw	

Table 13.8: Registers at level 2, type:CPU group:CMP\_GCR

### 13.2.9 CMP\_CPC

Registers at level:2, type:CPU group:CMP\_CPC

Name	Bits	Initial-Hex	RW	Description
CPC_ACCESS	64	ff	rw	
CPC_SEQDEL	64	0	rw	
CPC_RAIL	64	0	rw	
CPC_RESETLEN	64	0	rw	
CPC_REVISION	64	0	r-	
CPC_CMD	64	3	rw	
CPC_STAT_CONF	64	300200	rw	
CPC_OTHER	64	0	rw	
CPC_CL_VP_STOP	64	0	rw	
CPC_CL_VP_RUN	64	0	rw	
CPC_CL_VP_RUNNING	64	0	r-	
CPC_CMD	64	3	rw	
CPC_STAT_CONF	64	300200	rw	
CPC_OTHER	64	0	rw	
CPC_CO_VP_STOP	64	0	rw	
CPC_CO_VP_RUN	64	0	rw	
CPC_CO_VP_RUNNING	64	0	r-	

Table 13.9: Registers at level 2, type:CPU group:CMP\_CPC

### 13.2.10 CMP\_GIC

Registers at level:2, type:CPU group:CMP\_GIC

Name	Bits	Initial-Hex	RW	Description
GIC_SH_CONFIG	64	8040003	rw	
GIC_Counter	64	0	rw	
GIC_SH_REVISION	64	0	r-	
GIC_SH_POL63_0	64	0	rw	
GIC_SH_POL127_64	64	0	rw	
GIC_SH_POL191_128	64	0	rw	
GIC_SH_POL255_192	64	0	rw	
GIC_SH_TRIG63_0	64	0	rw	
GIC_SH_TRIG127_64	64	0	rw	
GIC_SH_TRIG191_128	64	0	rw	
GIC_SH_TRIG255_192	64	0	rw	
GIC_SH_DUAL63_0	64	0	rw	
GIC_SH_DUAL127_64	64	0	rw	

GIC_SH_DUAL191_128	64	0	rw	
GIC_SH_DUAL255_192	64	0	rw	
GIC_SH_WEDGE	64	0	-w	
GIC_SH_RMASK63_0	64	0	-w	
GIC_SH_RMASK127_64	64	0	-w	
GIC_SH_RMASK191_128	64	0	-w	
GIC_SH_RMASK255_192	64	0	-w	
GIC_SH_SMASK63_0	64	0	-w	
GIC_SH_SMASK127_64	64	0	-w	
GIC_SH_SMASK191_128	64	0	-w	
GIC_SH_SMASK255_192	64	0	-w	
GIC_SH_MASK63_0	64	0	r-	
GIC_SH_MASK127_64	64	0	r-	
GIC_SH_MASK191_128	64	0	r-	
GIC_SH_MASK255_192	64	0	r-	
GIC_SH_PEND63_0	64	0	r-	
GIC_SH_PEND127_64	64	0	r-	
GIC_SH_PEND191_128	64	0	r-	
GIC_SH_PEND255_192	64	0	r-	
GIC_SH_MAP000_PIN	64	80000000	rw	
GIC_SH_MAP001_PIN	64	80000000	rw	
GIC_SH_MAP002_PIN	64	80000000	rw	
GIC_SH_MAP003_PIN	64	80000000	rw	
GIC_SH_MAP004_PIN	64	80000000	rw	
GIC_SH_MAP005_PIN	64	80000000	rw	
GIC_SH_MAP006_PIN	64	80000000	rw	
GIC_SH_MAP007_PIN	64	80000000	rw	
GIC_SH_MAP008_PIN	64	80000000	rw	
GIC_SH_MAP009_PIN	64	80000000	rw	
GIC_SH_MAP010_PIN	64	80000000	rw	
GIC_SH_MAP011_PIN	64	80000000	rw	
GIC_SH_MAP012_PIN	64	80000000	rw	
GIC_SH_MAP013_PIN	64	80000000	rw	
GIC_SH_MAP014_PIN	64	80000000	rw	
GIC_SH_MAP015_PIN	64	80000000	rw	
GIC_SH_MAP016_PIN	64	80000000	rw	
GIC_SH_MAP017_PIN	64	80000000	rw	
GIC_SH_MAP018_PIN	64	80000000	rw	
GIC_SH_MAP019_PIN	64	80000000	rw	
GIC_SH_MAP020_PIN	64	80000000	rw	
GIC_SH_MAP021_PIN	64	80000000	rw	
GIC_SH_MAP022_PIN	64	80000000	rw	
GIC_SH_MAP023_PIN	64	80000000	rw	
GIC_SH_MAP024_PIN	64	80000000	rw	
GIC_SH_MAP025_PIN	64	80000000	rw	
GIC_SH_MAP026_PIN	64	80000000	rw	
GIC_SH_MAP027_PIN	64	80000000	rw	
GIC_SH_MAP028_PIN	64	80000000	rw	
GIC_SH_MAP029_PIN	64	80000000	rw	
GIC_SH_MAP030_PIN	64	80000000	rw	
GIC_SH_MAP031_PIN	64	80000000	rw	
GIC_SH_MAP032_PIN	64	80000000	rw	
GIC_SH_MAP033_PIN	64	80000000	rw	
GIC_SH_MAP034_PIN	64	80000000	rw	
GIC_SH_MAP035_PIN	64	80000000	rw	
GIC_SH_MAP036_PIN	64	80000000	rw	

GIC.SH_MAP037_PIN	64	80000000	rw	
GIC.SH_MAP038_PIN	64	80000000	rw	
GIC.SH_MAP039_PIN	64	80000000	rw	
GIC.SH_MAP040_PIN	64	0	rw	
GIC.SH_MAP041_PIN	64	0	rw	
GIC.SH_MAP042_PIN	64	0	rw	
GIC.SH_MAP043_PIN	64	0	rw	
GIC.SH_MAP044_PIN	64	0	rw	
GIC.SH_MAP045_PIN	64	0	rw	
GIC.SH_MAP046_PIN	64	0	rw	
GIC.SH_MAP047_PIN	64	0	rw	
GIC.SH_MAP048_PIN	64	0	rw	
GIC.SH_MAP049_PIN	64	0	rw	
GIC.SH_MAP050_PIN	64	0	rw	
GIC.SH_MAP051_PIN	64	0	rw	
GIC.SH_MAP052_PIN	64	0	rw	
GIC.SH_MAP053_PIN	64	0	rw	
GIC.SH_MAP054_PIN	64	0	rw	
GIC.SH_MAP055_PIN	64	0	rw	
GIC.SH_MAP056_PIN	64	0	rw	
GIC.SH_MAP057_PIN	64	0	rw	
GIC.SH_MAP058_PIN	64	0	rw	
GIC.SH_MAP059_PIN	64	0	rw	
GIC.SH_MAP060_PIN	64	0	rw	
GIC.SH_MAP061_PIN	64	0	rw	
GIC.SH_MAP062_PIN	64	0	rw	
GIC.SH_MAP063_PIN	64	0	rw	
GIC.SH_MAP064_PIN	64	0	rw	
GIC.SH_MAP065_PIN	64	0	rw	
GIC.SH_MAP066_PIN	64	0	rw	
GIC.SH_MAP067_PIN	64	0	rw	
GIC.SH_MAP068_PIN	64	0	rw	
GIC.SH_MAP069_PIN	64	0	rw	
GIC.SH_MAP070_PIN	64	0	rw	
GIC.SH_MAP071_PIN	64	0	rw	
GIC.SH_MAP072_PIN	64	0	rw	
GIC.SH_MAP073_PIN	64	0	rw	
GIC.SH_MAP074_PIN	64	0	rw	
GIC.SH_MAP075_PIN	64	0	rw	
GIC.SH_MAP076_PIN	64	0	rw	
GIC.SH_MAP077_PIN	64	0	rw	
GIC.SH_MAP078_PIN	64	0	rw	
GIC.SH_MAP079_PIN	64	0	rw	
GIC.SH_MAP080_PIN	64	0	rw	
GIC.SH_MAP081_PIN	64	0	rw	
GIC.SH_MAP082_PIN	64	0	rw	
GIC.SH_MAP083_PIN	64	0	rw	
GIC.SH_MAP084_PIN	64	0	rw	
GIC.SH_MAP085_PIN	64	0	rw	
GIC.SH_MAP086_PIN	64	0	rw	
GIC.SH_MAP087_PIN	64	0	rw	
GIC.SH_MAP088_PIN	64	0	rw	
GIC.SH_MAP089_PIN	64	0	rw	
GIC.SH_MAP090_PIN	64	0	rw	
GIC.SH_MAP091_PIN	64	0	rw	
GIC.SH_MAP092_PIN	64	0	rw	

GIC_SH_MAP093_PIN	64	0	rw	
GIC_SH_MAP094_PIN	64	0	rw	
GIC_SH_MAP095_PIN	64	0	rw	
GIC_SH_MAP096_PIN	64	0	rw	
GIC_SH_MAP097_PIN	64	0	rw	
GIC_SH_MAP098_PIN	64	0	rw	
GIC_SH_MAP099_PIN	64	0	rw	
GIC_SH_MAP100_PIN	64	0	rw	
GIC_SH_MAP101_PIN	64	0	rw	
GIC_SH_MAP102_PIN	64	0	rw	
GIC_SH_MAP103_PIN	64	0	rw	
GIC_SH_MAP104_PIN	64	0	rw	
GIC_SH_MAP105_PIN	64	0	rw	
GIC_SH_MAP106_PIN	64	0	rw	
GIC_SH_MAP107_PIN	64	0	rw	
GIC_SH_MAP108_PIN	64	0	rw	
GIC_SH_MAP109_PIN	64	0	rw	
GIC_SH_MAP110_PIN	64	0	rw	
GIC_SH_MAP111_PIN	64	0	rw	
GIC_SH_MAP112_PIN	64	0	rw	
GIC_SH_MAP113_PIN	64	0	rw	
GIC_SH_MAP114_PIN	64	0	rw	
GIC_SH_MAP115_PIN	64	0	rw	
GIC_SH_MAP116_PIN	64	0	rw	
GIC_SH_MAP117_PIN	64	0	rw	
GIC_SH_MAP118_PIN	64	0	rw	
GIC_SH_MAP119_PIN	64	0	rw	
GIC_SH_MAP120_PIN	64	0	rw	
GIC_SH_MAP121_PIN	64	0	rw	
GIC_SH_MAP122_PIN	64	0	rw	
GIC_SH_MAP123_PIN	64	0	rw	
GIC_SH_MAP124_PIN	64	0	rw	
GIC_SH_MAP125_PIN	64	0	rw	
GIC_SH_MAP126_PIN	64	0	rw	
GIC_SH_MAP127_PIN	64	0	rw	
GIC_SH_MAP128_PIN	64	0	rw	
GIC_SH_MAP129_PIN	64	0	rw	
GIC_SH_MAP130_PIN	64	0	rw	
GIC_SH_MAP131_PIN	64	0	rw	
GIC_SH_MAP132_PIN	64	0	rw	
GIC_SH_MAP133_PIN	64	0	rw	
GIC_SH_MAP134_PIN	64	0	rw	
GIC_SH_MAP135_PIN	64	0	rw	
GIC_SH_MAP136_PIN	64	0	rw	
GIC_SH_MAP137_PIN	64	0	rw	
GIC_SH_MAP138_PIN	64	0	rw	
GIC_SH_MAP139_PIN	64	0	rw	
GIC_SH_MAP140_PIN	64	0	rw	
GIC_SH_MAP141_PIN	64	0	rw	
GIC_SH_MAP142_PIN	64	0	rw	
GIC_SH_MAP143_PIN	64	0	rw	
GIC_SH_MAP144_PIN	64	0	rw	
GIC_SH_MAP145_PIN	64	0	rw	
GIC_SH_MAP146_PIN	64	0	rw	
GIC_SH_MAP147_PIN	64	0	rw	
GIC_SH_MAP148_PIN	64	0	rw	



GIC.SH_MAP149_PIN	64	0	rw	
GIC.SH_MAP150_PIN	64	0	rw	
GIC.SH_MAP151_PIN	64	0	rw	
GIC.SH_MAP152_PIN	64	0	rw	
GIC.SH_MAP153_PIN	64	0	rw	
GIC.SH_MAP154_PIN	64	0	rw	
GIC.SH_MAP155_PIN	64	0	rw	
GIC.SH_MAP156_PIN	64	0	rw	
GIC.SH_MAP157_PIN	64	0	rw	
GIC.SH_MAP158_PIN	64	0	rw	
GIC.SH_MAP159_PIN	64	0	rw	
GIC.SH_MAP160_PIN	64	0	rw	
GIC.SH_MAP161_PIN	64	0	rw	
GIC.SH_MAP162_PIN	64	0	rw	
GIC.SH_MAP163_PIN	64	0	rw	
GIC.SH_MAP164_PIN	64	0	rw	
GIC.SH_MAP165_PIN	64	0	rw	
GIC.SH_MAP166_PIN	64	0	rw	
GIC.SH_MAP167_PIN	64	0	rw	
GIC.SH_MAP168_PIN	64	0	rw	
GIC.SH_MAP169_PIN	64	0	rw	
GIC.SH_MAP170_PIN	64	0	rw	
GIC.SH_MAP171_PIN	64	0	rw	
GIC.SH_MAP172_PIN	64	0	rw	
GIC.SH_MAP173_PIN	64	0	rw	
GIC.SH_MAP174_PIN	64	0	rw	
GIC.SH_MAP175_PIN	64	0	rw	
GIC.SH_MAP176_PIN	64	0	rw	
GIC.SH_MAP177_PIN	64	0	rw	
GIC.SH_MAP178_PIN	64	0	rw	
GIC.SH_MAP179_PIN	64	0	rw	
GIC.SH_MAP180_PIN	64	0	rw	
GIC.SH_MAP181_PIN	64	0	rw	
GIC.SH_MAP182_PIN	64	0	rw	
GIC.SH_MAP183_PIN	64	0	rw	
GIC.SH_MAP184_PIN	64	0	rw	
GIC.SH_MAP185_PIN	64	0	rw	
GIC.SH_MAP186_PIN	64	0	rw	
GIC.SH_MAP187_PIN	64	0	rw	
GIC.SH_MAP188_PIN	64	0	rw	
GIC.SH_MAP189_PIN	64	0	rw	
GIC.SH_MAP190_PIN	64	0	rw	
GIC.SH_MAP191_PIN	64	0	rw	
GIC.SH_MAP192_PIN	64	0	rw	
GIC.SH_MAP193_PIN	64	0	rw	
GIC.SH_MAP194_PIN	64	0	rw	
GIC.SH_MAP195_PIN	64	0	rw	
GIC.SH_MAP196_PIN	64	0	rw	
GIC.SH_MAP197_PIN	64	0	rw	
GIC.SH_MAP198_PIN	64	0	rw	
GIC.SH_MAP199_PIN	64	0	rw	
GIC.SH_MAP200_PIN	64	0	rw	
GIC.SH_MAP201_PIN	64	0	rw	
GIC.SH_MAP202_PIN	64	0	rw	
GIC.SH_MAP203_PIN	64	0	rw	
GIC.SH_MAP204_PIN	64	0	rw	

GIC.SH_MAP205_PIN	64	0	rw	
GIC.SH_MAP206_PIN	64	0	rw	
GIC.SH_MAP207_PIN	64	0	rw	
GIC.SH_MAP208_PIN	64	0	rw	
GIC.SH_MAP209_PIN	64	0	rw	
GIC.SH_MAP210_PIN	64	0	rw	
GIC.SH_MAP211_PIN	64	0	rw	
GIC.SH_MAP212_PIN	64	0	rw	
GIC.SH_MAP213_PIN	64	0	rw	
GIC.SH_MAP214_PIN	64	0	rw	
GIC.SH_MAP215_PIN	64	0	rw	
GIC.SH_MAP216_PIN	64	0	rw	
GIC.SH_MAP217_PIN	64	0	rw	
GIC.SH_MAP218_PIN	64	0	rw	
GIC.SH_MAP219_PIN	64	0	rw	
GIC.SH_MAP220_PIN	64	0	rw	
GIC.SH_MAP221_PIN	64	0	rw	
GIC.SH_MAP222_PIN	64	0	rw	
GIC.SH_MAP223_PIN	64	0	rw	
GIC.SH_MAP224_PIN	64	0	rw	
GIC.SH_MAP225_PIN	64	0	rw	
GIC.SH_MAP226_PIN	64	0	rw	
GIC.SH_MAP227_PIN	64	0	rw	
GIC.SH_MAP228_PIN	64	0	rw	
GIC.SH_MAP229_PIN	64	0	rw	
GIC.SH_MAP230_PIN	64	0	rw	
GIC.SH_MAP231_PIN	64	0	rw	
GIC.SH_MAP232_PIN	64	0	rw	
GIC.SH_MAP233_PIN	64	0	rw	
GIC.SH_MAP234_PIN	64	0	rw	
GIC.SH_MAP235_PIN	64	0	rw	
GIC.SH_MAP236_PIN	64	0	rw	
GIC.SH_MAP237_PIN	64	0	rw	
GIC.SH_MAP238_PIN	64	0	rw	
GIC.SH_MAP239_PIN	64	0	rw	
GIC.SH_MAP240_PIN	64	0	rw	
GIC.SH_MAP241_PIN	64	0	rw	
GIC.SH_MAP242_PIN	64	0	rw	
GIC.SH_MAP243_PIN	64	0	rw	
GIC.SH_MAP244_PIN	64	0	rw	
GIC.SH_MAP245_PIN	64	0	rw	
GIC.SH_MAP246_PIN	64	0	rw	
GIC.SH_MAP247_PIN	64	0	rw	
GIC.SH_MAP248_PIN	64	0	rw	
GIC.SH_MAP249_PIN	64	0	rw	
GIC.SH_MAP250_PIN	64	0	rw	
GIC.SH_MAP251_PIN	64	0	rw	
GIC.SH_MAP252_PIN	64	0	rw	
GIC.SH_MAP253_PIN	64	0	rw	
GIC.SH_MAP254_PIN	64	0	rw	
GIC.SH_MAP255_PIN	64	0	rw	
GIC.SH_MAP000_VPE31_0	64	0	rw	
GIC.SH_MAP001_VPE31_0	64	0	rw	
GIC.SH_MAP002_VPE31_0	64	0	rw	
GIC.SH_MAP003_VPE31_0	64	0	rw	
GIC.SH_MAP004_VPE31_0	64	0	rw	

GIC_SH_MAP005_VPE31_0	64	0	rw	
GIC_SH_MAP006_VPE31_0	64	0	rw	
GIC_SH_MAP007_VPE31_0	64	0	rw	
GIC_SH_MAP008_VPE31_0	64	0	rw	
GIC_SH_MAP009_VPE31_0	64	0	rw	
GIC_SH_MAP010_VPE31_0	64	0	rw	
GIC_SH_MAP011_VPE31_0	64	0	rw	
GIC_SH_MAP012_VPE31_0	64	0	rw	
GIC_SH_MAP013_VPE31_0	64	0	rw	
GIC_SH_MAP014_VPE31_0	64	0	rw	
GIC_SH_MAP015_VPE31_0	64	0	rw	
GIC_SH_MAP016_VPE31_0	64	0	rw	
GIC_SH_MAP017_VPE31_0	64	0	rw	
GIC_SH_MAP018_VPE31_0	64	0	rw	
GIC_SH_MAP019_VPE31_0	64	0	rw	
GIC_SH_MAP020_VPE31_0	64	0	rw	
GIC_SH_MAP021_VPE31_0	64	0	rw	
GIC_SH_MAP022_VPE31_0	64	0	rw	
GIC_SH_MAP023_VPE31_0	64	0	rw	
GIC_SH_MAP024_VPE31_0	64	0	rw	
GIC_SH_MAP025_VPE31_0	64	0	rw	
GIC_SH_MAP026_VPE31_0	64	0	rw	
GIC_SH_MAP027_VPE31_0	64	0	rw	
GIC_SH_MAP028_VPE31_0	64	0	rw	
GIC_SH_MAP029_VPE31_0	64	0	rw	
GIC_SH_MAP030_VPE31_0	64	0	rw	
GIC_SH_MAP031_VPE31_0	64	0	rw	
GIC_SH_MAP032_VPE31_0	64	0	rw	
GIC_SH_MAP033_VPE31_0	64	0	rw	
GIC_SH_MAP034_VPE31_0	64	0	rw	
GIC_SH_MAP035_VPE31_0	64	0	rw	
GIC_SH_MAP036_VPE31_0	64	0	rw	
GIC_SH_MAP037_VPE31_0	64	0	rw	
GIC_SH_MAP038_VPE31_0	64	0	rw	
GIC_SH_MAP039_VPE31_0	64	0	rw	
GIC_SH_MAP040_VPE31_0	64	0	rw	
GIC_SH_MAP041_VPE31_0	64	0	rw	
GIC_SH_MAP042_VPE31_0	64	0	rw	
GIC_SH_MAP043_VPE31_0	64	0	rw	
GIC_SH_MAP044_VPE31_0	64	0	rw	
GIC_SH_MAP045_VPE31_0	64	0	rw	
GIC_SH_MAP046_VPE31_0	64	0	rw	
GIC_SH_MAP047_VPE31_0	64	0	rw	
GIC_SH_MAP048_VPE31_0	64	0	rw	
GIC_SH_MAP049_VPE31_0	64	0	rw	
GIC_SH_MAP050_VPE31_0	64	0	rw	
GIC_SH_MAP051_VPE31_0	64	0	rw	
GIC_SH_MAP052_VPE31_0	64	0	rw	
GIC_SH_MAP053_VPE31_0	64	0	rw	
GIC_SH_MAP054_VPE31_0	64	0	rw	
GIC_SH_MAP055_VPE31_0	64	0	rw	
GIC_SH_MAP056_VPE31_0	64	0	rw	
GIC_SH_MAP057_VPE31_0	64	0	rw	
GIC_SH_MAP058_VPE31_0	64	0	rw	
GIC_SH_MAP059_VPE31_0	64	0	rw	
GIC_SH_MAP060_VPE31_0	64	0	rw	

GIC_SH_MAP061_VPE31_0	64	0	rw	
GIC_SH_MAP062_VPE31_0	64	0	rw	
GIC_SH_MAP063_VPE31_0	64	0	rw	
GIC_SH_MAP064_VPE31_0	64	0	rw	
GIC_SH_MAP065_VPE31_0	64	0	rw	
GIC_SH_MAP066_VPE31_0	64	0	rw	
GIC_SH_MAP067_VPE31_0	64	0	rw	
GIC_SH_MAP068_VPE31_0	64	0	rw	
GIC_SH_MAP069_VPE31_0	64	0	rw	
GIC_SH_MAP070_VPE31_0	64	0	rw	
GIC_SH_MAP071_VPE31_0	64	0	rw	
GIC_SH_MAP072_VPE31_0	64	0	rw	
GIC_SH_MAP073_VPE31_0	64	0	rw	
GIC_SH_MAP074_VPE31_0	64	0	rw	
GIC_SH_MAP075_VPE31_0	64	0	rw	
GIC_SH_MAP076_VPE31_0	64	0	rw	
GIC_SH_MAP077_VPE31_0	64	0	rw	
GIC_SH_MAP078_VPE31_0	64	0	rw	
GIC_SH_MAP079_VPE31_0	64	0	rw	
GIC_SH_MAP080_VPE31_0	64	0	rw	
GIC_SH_MAP081_VPE31_0	64	0	rw	
GIC_SH_MAP082_VPE31_0	64	0	rw	
GIC_SH_MAP083_VPE31_0	64	0	rw	
GIC_SH_MAP084_VPE31_0	64	0	rw	
GIC_SH_MAP085_VPE31_0	64	0	rw	
GIC_SH_MAP086_VPE31_0	64	0	rw	
GIC_SH_MAP087_VPE31_0	64	0	rw	
GIC_SH_MAP088_VPE31_0	64	0	rw	
GIC_SH_MAP089_VPE31_0	64	0	rw	
GIC_SH_MAP090_VPE31_0	64	0	rw	
GIC_SH_MAP091_VPE31_0	64	0	rw	
GIC_SH_MAP092_VPE31_0	64	0	rw	
GIC_SH_MAP093_VPE31_0	64	0	rw	
GIC_SH_MAP094_VPE31_0	64	0	rw	
GIC_SH_MAP095_VPE31_0	64	0	rw	
GIC_SH_MAP096_VPE31_0	64	0	rw	
GIC_SH_MAP097_VPE31_0	64	0	rw	
GIC_SH_MAP098_VPE31_0	64	0	rw	
GIC_SH_MAP099_VPE31_0	64	0	rw	
GIC_SH_MAP100_VPE31_0	64	0	rw	
GIC_SH_MAP101_VPE31_0	64	0	rw	
GIC_SH_MAP102_VPE31_0	64	0	rw	
GIC_SH_MAP103_VPE31_0	64	0	rw	
GIC_SH_MAP104_VPE31_0	64	0	rw	
GIC_SH_MAP105_VPE31_0	64	0	rw	
GIC_SH_MAP106_VPE31_0	64	0	rw	
GIC_SH_MAP107_VPE31_0	64	0	rw	
GIC_SH_MAP108_VPE31_0	64	0	rw	
GIC_SH_MAP109_VPE31_0	64	0	rw	
GIC_SH_MAP110_VPE31_0	64	0	rw	
GIC_SH_MAP111_VPE31_0	64	0	rw	
GIC_SH_MAP112_VPE31_0	64	0	rw	
GIC_SH_MAP113_VPE31_0	64	0	rw	
GIC_SH_MAP114_VPE31_0	64	0	rw	
GIC_SH_MAP115_VPE31_0	64	0	rw	
GIC_SH_MAP116_VPE31_0	64	0	rw	

GIC.SH_MAP117_VPE31_0	64	0	rw	
GIC.SH_MAP118_VPE31_0	64	0	rw	
GIC.SH_MAP119_VPE31_0	64	0	rw	
GIC.SH_MAP120_VPE31_0	64	0	rw	
GIC.SH_MAP121_VPE31_0	64	0	rw	
GIC.SH_MAP122_VPE31_0	64	0	rw	
GIC.SH_MAP123_VPE31_0	64	0	rw	
GIC.SH_MAP124_VPE31_0	64	0	rw	
GIC.SH_MAP125_VPE31_0	64	0	rw	
GIC.SH_MAP126_VPE31_0	64	0	rw	
GIC.SH_MAP127_VPE31_0	64	0	rw	
GIC.SH_MAP128_VPE31_0	64	0	rw	
GIC.SH_MAP129_VPE31_0	64	0	rw	
GIC.SH_MAP130_VPE31_0	64	0	rw	
GIC.SH_MAP131_VPE31_0	64	0	rw	
GIC.SH_MAP132_VPE31_0	64	0	rw	
GIC.SH_MAP133_VPE31_0	64	0	rw	
GIC.SH_MAP134_VPE31_0	64	0	rw	
GIC.SH_MAP135_VPE31_0	64	0	rw	
GIC.SH_MAP136_VPE31_0	64	0	rw	
GIC.SH_MAP137_VPE31_0	64	0	rw	
GIC.SH_MAP138_VPE31_0	64	0	rw	
GIC.SH_MAP139_VPE31_0	64	0	rw	
GIC.SH_MAP140_VPE31_0	64	0	rw	
GIC.SH_MAP141_VPE31_0	64	0	rw	
GIC.SH_MAP142_VPE31_0	64	0	rw	
GIC.SH_MAP143_VPE31_0	64	0	rw	
GIC.SH_MAP144_VPE31_0	64	0	rw	
GIC.SH_MAP145_VPE31_0	64	0	rw	
GIC.SH_MAP146_VPE31_0	64	0	rw	
GIC.SH_MAP147_VPE31_0	64	0	rw	
GIC.SH_MAP148_VPE31_0	64	0	rw	
GIC.SH_MAP149_VPE31_0	64	0	rw	
GIC.SH_MAP150_VPE31_0	64	0	rw	
GIC.SH_MAP151_VPE31_0	64	0	rw	
GIC.SH_MAP152_VPE31_0	64	0	rw	
GIC.SH_MAP153_VPE31_0	64	0	rw	
GIC.SH_MAP154_VPE31_0	64	0	rw	
GIC.SH_MAP155_VPE31_0	64	0	rw	
GIC.SH_MAP156_VPE31_0	64	0	rw	
GIC.SH_MAP157_VPE31_0	64	0	rw	
GIC.SH_MAP158_VPE31_0	64	0	rw	
GIC.SH_MAP159_VPE31_0	64	0	rw	
GIC.SH_MAP160_VPE31_0	64	0	rw	
GIC.SH_MAP161_VPE31_0	64	0	rw	
GIC.SH_MAP162_VPE31_0	64	0	rw	
GIC.SH_MAP163_VPE31_0	64	0	rw	
GIC.SH_MAP164_VPE31_0	64	0	rw	
GIC.SH_MAP165_VPE31_0	64	0	rw	
GIC.SH_MAP166_VPE31_0	64	0	rw	
GIC.SH_MAP167_VPE31_0	64	0	rw	
GIC.SH_MAP168_VPE31_0	64	0	rw	
GIC.SH_MAP169_VPE31_0	64	0	rw	
GIC.SH_MAP170_VPE31_0	64	0	rw	
GIC.SH_MAP171_VPE31_0	64	0	rw	
GIC.SH_MAP172_VPE31_0	64	0	rw	

GIC.SH_MAP173_VPE31_0	64	0	rw	
GIC.SH_MAP174_VPE31_0	64	0	rw	
GIC.SH_MAP175_VPE31_0	64	0	rw	
GIC.SH_MAP176_VPE31_0	64	0	rw	
GIC.SH_MAP177_VPE31_0	64	0	rw	
GIC.SH_MAP178_VPE31_0	64	0	rw	
GIC.SH_MAP179_VPE31_0	64	0	rw	
GIC.SH_MAP180_VPE31_0	64	0	rw	
GIC.SH_MAP181_VPE31_0	64	0	rw	
GIC.SH_MAP182_VPE31_0	64	0	rw	
GIC.SH_MAP183_VPE31_0	64	0	rw	
GIC.SH_MAP184_VPE31_0	64	0	rw	
GIC.SH_MAP185_VPE31_0	64	0	rw	
GIC.SH_MAP186_VPE31_0	64	0	rw	
GIC.SH_MAP187_VPE31_0	64	0	rw	
GIC.SH_MAP188_VPE31_0	64	0	rw	
GIC.SH_MAP189_VPE31_0	64	0	rw	
GIC.SH_MAP190_VPE31_0	64	0	rw	
GIC.SH_MAP191_VPE31_0	64	0	rw	
GIC.SH_MAP192_VPE31_0	64	0	rw	
GIC.SH_MAP193_VPE31_0	64	0	rw	
GIC.SH_MAP194_VPE31_0	64	0	rw	
GIC.SH_MAP195_VPE31_0	64	0	rw	
GIC.SH_MAP196_VPE31_0	64	0	rw	
GIC.SH_MAP197_VPE31_0	64	0	rw	
GIC.SH_MAP198_VPE31_0	64	0	rw	
GIC.SH_MAP199_VPE31_0	64	0	rw	
GIC.SH_MAP200_VPE31_0	64	0	rw	
GIC.SH_MAP201_VPE31_0	64	0	rw	
GIC.SH_MAP202_VPE31_0	64	0	rw	
GIC.SH_MAP203_VPE31_0	64	0	rw	
GIC.SH_MAP204_VPE31_0	64	0	rw	
GIC.SH_MAP205_VPE31_0	64	0	rw	
GIC.SH_MAP206_VPE31_0	64	0	rw	
GIC.SH_MAP207_VPE31_0	64	0	rw	
GIC.SH_MAP208_VPE31_0	64	0	rw	
GIC.SH_MAP209_VPE31_0	64	0	rw	
GIC.SH_MAP210_VPE31_0	64	0	rw	
GIC.SH_MAP211_VPE31_0	64	0	rw	
GIC.SH_MAP212_VPE31_0	64	0	rw	
GIC.SH_MAP213_VPE31_0	64	0	rw	
GIC.SH_MAP214_VPE31_0	64	0	rw	
GIC.SH_MAP215_VPE31_0	64	0	rw	
GIC.SH_MAP216_VPE31_0	64	0	rw	
GIC.SH_MAP217_VPE31_0	64	0	rw	
GIC.SH_MAP218_VPE31_0	64	0	rw	
GIC.SH_MAP219_VPE31_0	64	0	rw	
GIC.SH_MAP220_VPE31_0	64	0	rw	
GIC.SH_MAP221_VPE31_0	64	0	rw	
GIC.SH_MAP222_VPE31_0	64	0	rw	
GIC.SH_MAP223_VPE31_0	64	0	rw	
GIC.SH_MAP224_VPE31_0	64	0	rw	
GIC.SH_MAP225_VPE31_0	64	0	rw	
GIC.SH_MAP226_VPE31_0	64	0	rw	
GIC.SH_MAP227_VPE31_0	64	0	rw	
GIC.SH_MAP228_VPE31_0	64	0	rw	

GIC.SH_MAP229_VPE31_0	64	0	rw
GIC.SH_MAP230_VPE31_0	64	0	rw
GIC.SH_MAP231_VPE31_0	64	0	rw
GIC.SH_MAP232_VPE31_0	64	0	rw
GIC.SH_MAP233_VPE31_0	64	0	rw
GIC.SH_MAP234_VPE31_0	64	0	rw
GIC.SH_MAP235_VPE31_0	64	0	rw
GIC.SH_MAP236_VPE31_0	64	0	rw
GIC.SH_MAP237_VPE31_0	64	0	rw
GIC.SH_MAP238_VPE31_0	64	0	rw
GIC.SH_MAP239_VPE31_0	64	0	rw
GIC.SH_MAP240_VPE31_0	64	0	rw
GIC.SH_MAP241_VPE31_0	64	0	rw
GIC.SH_MAP242_VPE31_0	64	0	rw
GIC.SH_MAP243_VPE31_0	64	0	rw
GIC.SH_MAP244_VPE31_0	64	0	rw
GIC.SH_MAP245_VPE31_0	64	0	rw
GIC.SH_MAP246_VPE31_0	64	0	rw
GIC.SH_MAP247_VPE31_0	64	0	rw
GIC.SH_MAP248_VPE31_0	64	0	rw
GIC.SH_MAP249_VPE31_0	64	0	rw
GIC.SH_MAP250_VPE31_0	64	0	rw
GIC.SH_MAP251_VPE31_0	64	0	rw
GIC.SH_MAP252_VPE31_0	64	0	rw
GIC.SH_MAP253_VPE31_0	64	0	rw
GIC.SH_MAP254_VPE31_0	64	0	rw
GIC.SH_MAP255_VPE31_0	64	0	rw
GIC.VB_DINT_SEND	64	0	-w
GIC.SH_EJTAG_BRK	64	0	rw
GIC.SH_TEAMID_LO	64	0	rw
GIC.SH_TEAMID_HI	64	0	rw
GIC.SH_TEAMID_EXT	64	0	rw
GIC.SH_DBG_CONFIG	64	0	rw
GIC.SH_DINT_PART	64	0	rw
GIC.SH_DEBUGM_STATUS	64	0	r-
GIC.VPE_CTL	64	2	rw
GIC.VPE_PEND	64	0	r-
GIC.VPE_MASK	64	7f	r-
GIC.VPE_RMASK	64	0	-w
GIC.VPE_SMASK	64	0	-w
GIC.VPE_WD_MAP	64	40000000	rw
GIC.VPE_COMPARE_MAP	64	80000000	rw
GIC.VPE_TIMER_MAP	64	80000005	rw
GIC.VPE_FDC_MAP	64	80000005	rw
GIC.VPE_PERFCTR_MAP	64	80000005	rw
GIC.VPE_SWInt0_MAP	64	80000000	rw
GIC.VPE_SWInt1_MAP	64	80000000	rw
GIC.VPE_OTHER_ADDRESS	64	0	rw
GIC.VPE_IDENT	64	0	r-
GIC.VPE_WD_CONFIG	64	0	rw
GIC.VPE_WD_COUNT	64	0	r-
GIC.VPE_WD_INITIAL	64	0	rw
GIC.VPE.Compare	64	ffffff ffffffff	rw
GIC.VPE.EICSS00	64	0	rw
GIC.VPE.EICSS01	64	0	rw
GIC.VPE.EICSS02	64	0	rw

GIC_VPE.EICSS03	64	0	rw	
GIC_VPE.EICSS04	64	0	rw	
GIC_VPE.EICSS05	64	0	rw	
GIC_VPE.EICSS06	64	0	rw	
GIC_VPE.EICSS07	64	0	rw	
GIC_VPE.EICSS08	64	0	rw	
GIC_VPE.EICSS09	64	0	rw	
GIC_VPE.EICSS10	64	0	rw	
GIC_VPE.EICSS11	64	0	rw	
GIC_VPE.EICSS12	64	0	rw	
GIC_VPE.EICSS13	64	0	rw	
GIC_VPE.EICSS14	64	0	rw	
GIC_VPE.EICSS15	64	0	rw	
GIC_VPE.EICSS16	64	0	rw	
GIC_VPE.EICSS17	64	0	rw	
GIC_VPE.EICSS18	64	0	rw	
GIC_VPE.EICSS19	64	0	rw	
GIC_VPE.EICSS20	64	0	rw	
GIC_VPE.EICSS21	64	0	rw	
GIC_VPE.EICSS22	64	0	rw	
GIC_VPE.EICSS23	64	0	rw	
GIC_VPE.EICSS24	64	0	rw	
GIC_VPE.EICSS25	64	0	rw	
GIC_VPE.EICSS26	64	0	rw	
GIC_VPE.EICSS27	64	0	rw	
GIC_VPE.EICSS28	64	0	rw	
GIC_VPE.EICSS29	64	0	rw	
GIC_VPE.EICSS30	64	0	rw	
GIC_VPE.EICSS31	64	0	rw	
GIC_VPE.EICSS32	64	0	rw	
GIC_VPE.EICSS33	64	0	rw	
GIC_VPE.EICSS34	64	1	rw	
GIC_VPE.EICSS35	64	0	rw	
GIC_VPE.EICSS36	64	0	rw	
GIC_VPE.EICSS37	64	0	rw	
GIC_VPE.EICSS38	64	0	rw	
GIC_VPE.EICSS39	64	0	rw	
GIC_VPE.EICSS40	64	0	rw	
GIC_VPE.EICSS41	64	0	rw	
GIC_VPE.EICSS42	64	0	rw	
GIC_VPE.EICSS43	64	0	rw	
GIC_VPE.EICSS44	64	0	rw	
GIC_VPE.EICSS45	64	0	rw	
GIC_VPE.EICSS46	64	0	rw	
GIC_VPE.EICSS47	64	0	rw	
GIC_VPE.EICSS48	64	0	rw	
GIC_VPE.EICSS49	64	0	rw	
GIC_VPE.EICSS50	64	0	rw	
GIC_VPE.EICSS51	64	0	rw	
GIC_VPE.EICSS52	64	0	rw	
GIC_VPE.EICSS53	64	0	rw	
GIC_VPE.EICSS54	64	0	rw	
GIC_VPE.EICSS55	64	0	rw	
GIC_VPE.EICSS56	64	0	rw	
GIC_VPE.EICSS57	64	0	rw	
GIC_VPE.EICSS58	64	0	rw	



GIC_VPE.EICSS59	64	0	rw	
GIC_VPE.EICSS60	64	0	rw	
GIC_VPE.EICSS61	64	0	rw	
GIC_VPE.EICSS62	64	0	rw	
GIC_VPE.EICSS63	64	0	rw	
GIC_VL.COFFSET	64	0	rw	
GIC_VL.VIRTUAL.VP_NUM	64	0	rw	
GIC_Vx.DINT_PART	64	0	rw	
GIC_Cx.BRK_GROUP	64	0	rw	
GIC_VPE.CTL	64	2	rw	
GIC_VPE.PEND	64	0	r-	
GIC_VPE.MASK	64	7f	r-	
GIC_VPE.RMASK	64	0	-w	
GIC_VPE.SMASK	64	0	-w	
GIC_VPE.WD_MAP	64	40000000	rw	
GIC_VPE.COMPARE_MAP	64	80000000	rw	
GIC_VPE.TIMER_MAP	64	80000005	rw	
GIC_VPE.FDC_MAP	64	80000005	rw	
GIC_VPE.PERFCTR_MAP	64	80000005	rw	
GIC_VPE.SWInt0_MAP	64	80000000	rw	
GIC_VPE.SWInt1_MAP	64	80000000	rw	
GIC_VPE.OTHER_ADDRESS	64	0	rw	
GIC_VPE.IDENT	64	0	r-	
GIC_VPE.WD_CONFIG	64	0	rw	
GIC_VPE.WD_COUNT	64	0	r-	
GIC_VPE.WD_INITIAL	64	0	rw	
GIC_VPE.Compare	64	ffffff ffffff	rw	
GIC_VPE.EICSS00	64	0	rw	
GIC_VPE.EICSS01	64	0	rw	
GIC_VPE.EICSS02	64	0	rw	
GIC_VPE.EICSS03	64	0	rw	
GIC_VPE.EICSS04	64	0	rw	
GIC_VPE.EICSS05	64	0	rw	
GIC_VPE.EICSS06	64	0	rw	
GIC_VPE.EICSS07	64	0	rw	
GIC_VPE.EICSS08	64	0	rw	
GIC_VPE.EICSS09	64	0	rw	
GIC_VPE.EICSS10	64	0	rw	
GIC_VPE.EICSS11	64	0	rw	
GIC_VPE.EICSS12	64	0	rw	
GIC_VPE.EICSS13	64	0	rw	
GIC_VPE.EICSS14	64	0	rw	
GIC_VPE.EICSS15	64	0	rw	
GIC_VPE.EICSS16	64	0	rw	
GIC_VPE.EICSS17	64	0	rw	
GIC_VPE.EICSS18	64	0	rw	
GIC_VPE.EICSS19	64	0	rw	
GIC_VPE.EICSS20	64	0	rw	
GIC_VPE.EICSS21	64	0	rw	
GIC_VPE.EICSS22	64	0	rw	
GIC_VPE.EICSS23	64	0	rw	
GIC_VPE.EICSS24	64	0	rw	
GIC_VPE.EICSS25	64	0	rw	
GIC_VPE.EICSS26	64	0	rw	
GIC_VPE.EICSS27	64	0	rw	
GIC_VPE.EICSS28	64	0	rw	

GIC_VPE.EICSS29	64	0	rw	
GIC_VPE.EICSS30	64	0	rw	
GIC_VPE.EICSS31	64	0	rw	
GIC_VPE.EICSS32	64	0	rw	
GIC_VPE.EICSS33	64	0	rw	
GIC_VPE.EICSS34	64	1	rw	
GIC_VPE.EICSS35	64	0	rw	
GIC_VPE.EICSS36	64	0	rw	
GIC_VPE.EICSS37	64	0	rw	
GIC_VPE.EICSS38	64	0	rw	
GIC_VPE.EICSS39	64	0	rw	
GIC_VPE.EICSS40	64	0	rw	
GIC_VPE.EICSS41	64	0	rw	
GIC_VPE.EICSS42	64	0	rw	
GIC_VPE.EICSS43	64	0	rw	
GIC_VPE.EICSS44	64	0	rw	
GIC_VPE.EICSS45	64	0	rw	
GIC_VPE.EICSS46	64	0	rw	
GIC_VPE.EICSS47	64	0	rw	
GIC_VPE.EICSS48	64	0	rw	
GIC_VPE.EICSS49	64	0	rw	
GIC_VPE.EICSS50	64	0	rw	
GIC_VPE.EICSS51	64	0	rw	
GIC_VPE.EICSS52	64	0	rw	
GIC_VPE.EICSS53	64	0	rw	
GIC_VPE.EICSS54	64	0	rw	
GIC_VPE.EICSS55	64	0	rw	
GIC_VPE.EICSS56	64	0	rw	
GIC_VPE.EICSS57	64	0	rw	
GIC_VPE.EICSS58	64	0	rw	
GIC_VPE.EICSS59	64	0	rw	
GIC_VPE.EICSS60	64	0	rw	
GIC_VPE.EICSS61	64	0	rw	
GIC_VPE.EICSS62	64	0	rw	
GIC_VPE.EICSS63	64	0	rw	
GIC_VL.COFFSET	64	0	rw	
GIC_VL.VIRTUAL_VP_NUM	64	0	rw	
GIC_Vx.DINT_PART	64	0	rw	
GIC_Cx.BRK_GROUP	64	0	rw	
GIC_CounterLoUser	64	0	r-	
GIC_CounterHiUser	64	0	r-	

Table 13.10: Registers at level 2, type:CPU group:GIC

### 13.2.11 Integration\_support

Registers at level:2, type:CPU group:Integration\_support

Name	Bits	Initial-Hex	RW	Description
stop	32	0	rw	write with non-zero to stop processor

Table 13.11: Registers at level 2, type:CPU group:Integration\_support